

Getting from one cell to a readable line


Written 2026-08-19. Architecture study - nothing here is built yet.

Braillix today is **one cell, 68 mm wide**. A single character at a time.

That is fine for showing how a braille cell works. It is not enough to read a sentence, and it cannot show a mathematics symbol at all - Nemeth code writes multiplication and division as **two cells each**, and fractions use opening and closing indicators spanning several cells. Two cells 68 mm apart are not two cells to a reader. They are two separate objects.

This document asks one question: **can Braillix reach a readable line without becoming expensive?**

1. The wall



<i>Cell pitch problem</i>

Standard braille cells sit **6.1-6.5 mm apart**. That single number decides everything, because anything placed at **every** cell has to fit inside it.

Per-cell actuator	Width	Verdict
Piezo bimorph reed	~2 mm	fits - and costs ~\$100/cell
N20 micro gearmotor	10-12 mm	1.9x too wide
28BYJ-48 stepper	28 mm	4.5x too wide
Braillix cam disc	44.4 mm	7.2x too wide
Braillix cell today	68 mm	11x too wide

Only piezo fits - and piezo is precisely why commercial displays cost \$4,000 and up. The cheap motto and one-actuator-per-cell are in direct conflict. That is not a Braillix problem; it is the central problem of the whole field.

Ideas that hit the wall

Two motors in one cell, two letters. The 28BYJ-48's shaft is off-centre, so two cans can interleave - but the motor was never the constraint. Two **cam discs** need about 44 mm between centres. Still 7x too wide. Costs weeks, does not produce a readable line.

Eight motors for eight cells. 8 x 150 of motors is affordable. 8 x 68 mm of box is 544 mm. Geometry kills it, not cost.

N20 gearmotors. Smaller and much faster - but still about 2x too wide, and being DC motors they have no step counting, so each one needs an encoder or hard stops. More parts, more cost, still no.

2. Two things that **are** worth taking from the brainstorm

Splitting the cell across two 8-state discs is a genuinely good idea - just not for scaling. Three dots per disc means 8 states, 45deg per slice, and the cam ramp problem (R-07) disappears:

states	radius	ramp	pressure angle
64 (today)	12.8 mm	1.1deg	78.5deg - unclimbable
8	12.8 mm	40.5deg	7.9deg - comfortable

Two things it does **not** do, both counter-intuitive:

- **It does not make refresh faster.** Rotation time depends on the **angle** travelled, not the number of states. 180deg is 180deg whether that is 32 slices or 4.
- **Shrinking the disc does not help the ramp.** At minimum size the dwell arc equals the foot width and the pressure angle collapses to $\text{atan}(\text{lift} \times \pi / 2 \times \text{foot}) = \mathbf{51.5deg}$, regardless of radius or state count. The disc must be **large relative to its state count**, not small.

3. The architecture that escapes the wall

The travelling cam: one mechanism, many cells

The cam stops being part of a cell. It becomes a setting head that moves along a line of latching pins.

Why this escapes the wall

Each cell holds only 1.7 mm pins — nothing bulky sits at the cell. Actuator count stops scaling with cell count: 4 cells need 2 motors. So do 8. So do 20.

<i>Travelling cam architecture</i>

Stop giving every cell an actuator. Let **one cam head travel along a line of latching pins**.


Each cell then contains nothing but six 1.7 mm pins. Nothing bulky sits at the cell, so standard 6.2 mm pitch becomes achievable - and **the number of motors stops scaling with the number of cells**. Four cells need two motors. So do eight. So do twenty.

This is the same family of approach that lets line-at-a-time displays reach far lower per-cell costs than one-actuator-per-dot designs. Worth researching properly and citing at the panel; do not quote figures you have not checked yourself.

The refresh cycle

Refresh cycle: why a reset bar is unavoidable

A cam can only PUSH. It cannot pull a latched pin back down. So every refresh is: wipe the line, then set it.



Estimated timing

~1.5–2 s per cell (dominated by cam rotation, not traverse). 4 cells $\approx$ 8 s · 8 cells $\approx$ 15 s per line.
Acceptable for reading a maths line you set once. NOT acceptable for continuous scrolling — state this honestly.

<i>Refresh cycle</i>

A cam can only push. It cannot pull a latched pin back down. So every refresh is two phases:

- 1 **Reset** - a bar sweeps the line and pushes every pin flat.
- 2 **Set** - the head visits each cell, the cam rotates to that character's state, the lifted

linkages push the required pins up, and the latch holds them.

Once set, the line holds with **zero power**.

Speed: be honest about this

Per cell	~1.5-2 s, dominated by cam rotation
4 cells	~8 s
8 cells	~15 s

A leadscrew will not work. Even at 8 mm/rev, a 28BYJ-48 needs about 16 s just to traverse four cells. It has to be a **GT2 belt** - a 20-tooth pulley moves 40 mm/rev, roughly 5x faster.

15 s per line is acceptable for a maths line you set once and then read. It is **not** acceptable for continuous scrolling. Say so plainly rather than letting a panel discover it.

4. The one real unknown: the latch

The one real unknown: the latch

Each pin must HOLD its height after the cam head moves on — but still yield to a reading finger.

Target: hold $\approx$ 0.4 N against a reading force of only 5–15 g. Too weak = dots collapse. Too strong = the cam stalls.



Test this on a 4-pin coupon BEFORE anything else is built. It is the single assumption the whole architecture rests on.

<i>Latch options</i>

Everything else here is ordinary mechanism. The latch is the assumption the architecture rests on.

Each pin must **hold about 0.4 N** so a dot does not collapse, while still yielding to a reading finger pressing with only 5-15 g. Too weak and the line sags. Too strong and the cam stalls trying to set it.

	Cost	Notes
Silicone sleeve friction	~?50	A short length of silicone tube per pin. Fully printable, no magnets. Force tuned by interference fit. Start here.
Magnetic detent	~?200	Small magnet per pin plus a steel plate. More repeatable, but 24 magnets to place and align.

Test this first, on a 4-pin coupon Print four pins, four guides and both latch styles. Load them with a gram scale. Do not design a single other part until one of them holds 0.4 N and releases under a fingertip. This is a one-evening test that decides whether the next six weeks are worth starting.

5. What carries over, what is new

Carries over unchanged - this is the strongest argument for the approach:

- the 64-state cam encoding and the DOT_TO_BIT mapping (sim/extract_params.py)
- the cam disc itself (cad/scad/braille_cam.scad) - already ordered in resin
- hall-sensor homing, step counting, shortest-path rotation
- the 3D simulator, which can be extended to show the carriage

New work:

- GT2 belt, pulleys and a carriage - plus one extra motor
- 24 latching pins at 2.5 mm dot / 6.2 mm cell pitch
- a reset bar and its actuation
- re-converged linkages: the current arms fan out to a 4.8 x 5.2 mm cluster, a standard cell needs

2.5 x 2.5 mm

6. Recommendation

Build the single cell first. Do not abandon it.

Nothing in this project has ever been physically assembled - no dot has gone up and come back down. The parts are already paid for and arriving. The single cell is the guaranteed demo, and it settles **R-07** (whether the cam ramp is climbable at all) before that assumption gets replicated across 24 pins.

Then, and only then:

- 1 **Latch coupon.** One evening. Decides everything downstream.
- 2 **Build four cells, not eight.** Half the pins, the same architectural proof - and "it scales by

lengthening the belt" becomes a demonstrated claim instead of a hope.

A note for later

If Brailix is ever commercialised rather than submitted, **check patents in this space first**. There is prior art around micro-motor and cam actuation of braille pins, and at least one open-source project in India was shut down over it. Irrelevant for academic work. Very relevant the day it stops being academic.

Sources for the numbers

Every dimension is read from the CAD, not from memory:

Number	Where from
6.2 mm cell pitch, 2.5 mm dot pitch	braille standard (Library of Congress / Marburg Medium)
44.4 mm cam disc, 68 mm cell	cad/scad/mech_layout.scad, cad/scad/outer_box.scad
pressure angles	computed from pin_lift, track_r, angular_ramp_fraction
Nominal 4096 steps/rev, 64 steps/position; owned motor requires Hall-to-Hall calibration	firmware/breadboard_test/breadboard_test.ino

Number	Where from
traverse timings	28BYJ-48 at 800-1000 steps/s, belt versus leadscrew