

ECE 240 Formula Sheet

By Benjamin Kong & Lora Ma

1. Time-domain signals

A continuous-time signal takes the form

$$x(t + nT) = x(t) \quad n \in \mathbb{Z}.$$

A signal $z(t) = \alpha x(t + aT_1) + \beta x(t + bT_2)$ will be periodic if

$$\frac{T_1}{T_2} = \frac{a}{b}$$

for some $a, b \in \mathbb{Z}$.

Let $x(t)$ be some signal.

- The *energy* for $t \in (-L, L)$ is given by

$$E_{2L} = \int_{-L}^L |x(t)|^2 dt.$$

- The *total energy* is given by

$$E = \lim_{T \rightarrow \infty} \int_{-L}^L |x(t)|^2 dt.$$

- The *average power* is given by

$$P = \lim_{T \rightarrow \infty} \frac{1}{2L} \int_{-L}^L |x(t)|^2 dt.$$

- If $x(t)$ is periodic,

$$P = \frac{1}{T} \int_0^T |x(t)|^2 dt.$$

E finite \rightarrow **Energy signal** $\rightarrow P = 0$.

E infinite and P finite \rightarrow **Power signal**.

Periodic signal \rightarrow **Power signal**.

Let $x(t)$ be some signal.

- A *time shift* is represented by

$$x(t - t_0).$$

- A *reflection* is represented by

$$x(-t).$$

- A signal is *even* if

$$x(-t) = x(t)$$

- and *odd* if

$$x(-t) = -x(t).$$

The *unit step signal* is defined as

$$u(t) = \begin{cases} 1 & t > 0, \\ 0 & t < 0. \end{cases}$$

Note that $u(0) = \frac{1}{2}$.

A *rectangular pulse* is represented as

$$\text{rect}\left(\frac{t}{T}\right) = u\left(t + \frac{T}{2}\right) - u\left(t - \frac{T}{2}\right).$$

A *ramp signal* is represented as

$$r(t) = tu(t) = \begin{cases} t & t \geq 0, \\ 0 & t < 0. \end{cases}$$

The *unit impulse* $\delta(t)$ (Dirac delta function) is defined as

$$\int_{t_1}^{t_2} x(t)\delta(t) dt = x(0) \quad t_1 < 0 < t_2.$$

It has the following properties:

- $\delta(t) = 0$ for $t \neq 0$,

- $\int_{-\infty}^{\infty} \delta(t) dt = 1$,

- $\delta(-t) = \delta(t)$,

- $\delta(0) = \infty$.