

The schematic diagram illustrates the power supply section, featuring two TPS7A2033DBVR regulators (U1 and U2) and a Schottky diode (D3).
 - **U1 (TPS7A2033DBVR)**: This regulator takes VIN_5V as input (pin 1) and provides +3V3_OSC output (pin 5). It is configured with a 1uF capacitor (C3) on the input and its output is connected to +3V3_OSC. The enable pin (pin 3) is connected to VIN_5V, and the non-control pin (pin 4) is marked with an 'X'. The ground pin (pin 2) is connected to ground.
 - **U2 (TPS7A2033DBVR)**: This regulator also takes VIN_5V as input (pin 1) and provides +3V3_CLK output (pin 5). It is configured with a 1uF capacitor (C5) on the input and its output is connected to +3V3_CLK. The enable pin (pin 3) is connected to VIN_5V, and the non-control pin (pin 4) is marked with an 'X'. The ground pin (pin 2) is connected to ground.
 - **Diode D3**: A Schottky diode is connected to the +3V3_CLK output through a 1k resistor (R1). The diode's cathode is connected to ground, and its anode is connected to the output line, which is labeled +3V3_CLK, GRN, and PWR.

NC pins tied to GND (SiTime layout guide: heat path). Pin 1 = OE, 10k pull-up (note 8).

1. U3 S1T5155: water-soluble flux only. No no-clean flux. No ultrasonic or megasonic cleaning (SiTime).
2. Reflow: IPC/JEDEC J-STD-020 profile.
3. SMA J2-J10: vertical THT jacks (132134), hand-solder after reflow.
4. Outputs: J3-J6 10 MHz ~ +7 dBm/50R, J7-J10 PPS 3.3 V CMOS.

[illegible]

Id: 1/1