Automated Layers

Vertigo MK1 Cable Spec

COMPANY: Automated Layers LLC
TITLE: Vertigo MK1 Cable Spec
CABLE SPEC: V03
REV: 03
DATE: 28-April-2026

Wire No.	Qty	Z-Code	Schematic Label	Description, per wire	Interface A	Interface B	Interface A, Abbrev.	Interface B, Abbrev	Length (mm)	Connector Type	Connector Model	Connector (img)	Pin	Description	Color	Gauge	Insulation	Misc. Attributes (I)	Pin	Connector (img)	Connector Type	Connector Model	Misc. Attributes (II)
1	1	Z-01	ACPE~L_TBAC~L3	Power Distribution - AC	AC Power Entry	Terminal Block - AC	ACPE~L	TBAC~L3	240	**Hardware Component 10A Fuse Switch IEC Inlet**		.	.	L	RED	16	UL1007	Flexible Tinned Copper Wire	.		Insulated Ferrule	E1508	Single
2	1	Z-02	ACPE~N_TBAC~N3	Power Distribution - AC	AC Power Entry	Terminal Block - AC	ACPE~N	TBAC~N3	240			.	.	N	White	16	UL1007	Flexible Tinned Copper Wire	.		Insulated Ferrule	E1508	Single
3	1	Z-03	ACPE~G_TBAC~G3	Power Distribution - AC	AC Power Entry	Terminal Block - AC	ACPE~G	TBAC~G3	240			.	.	G	Green / Green w. Yellow Stripe	16	UL1007	Flexible Tinned Copper Wire	.		Insulated Ferrule	E1508	Single
4	1	Z-04	PSU24V~L_TBAC~L1	Power Distribution - AC	PSU24V	Terminal Block - AC	PSU24V~L	TBAC~L1	165	Insulated Terminal	Ring M4		.	L	RED	16	UL1007	Flexible Tinned Copper Wire	.		Insulated Ferrule	E1508	Single
5	1	Z-05	PSU24V~N_TBAC~N1	Power Distribution - AC	PSU24V	Terminal Block - AC	PSU24V~N	TBAC~N1	165	Insulated Terminal	Ring M4		.	N	White	16	UL1007	Flexible Tinned Copper Wire	.		Insulated Ferrule	E1508	Single
6	1	Z-06	PSU24V~G_TBAC~G1	Power Distribution - AC	PSU24V	Terminal Block - AC	PSU24V~G	TBAC~G1	185	Insulated Terminal	Ring M4		.	G	Green / Green w. Yellow Stripe	16	UL1007	Flexible Tinned Copper Wire	.		Insulated Ferrule	E1508	Single
7	1	Z-07	SSR~2_TBAC~L4	Power Distribution - AC	SSR	Terminal Block - AC	SSR~2	TBAC~L4	190	**Hardware Component 7A Fuse**		.	.	.	White	18	UL1007	Flexible Tinned Copper Wire	.		Insulated Ferrule	E1008	Single
8				Power Distribution - AC								.	.	.	Black	18	UL1007	Flexible Tinned Copper Wire	.		Insulated Terminal	Ring M4	Single
9	1	Z-08	TBB~6_TBAC~N4	Power Distribution - AC	Terminal Block - Bed	Terminal Block - AC	TBB~6	TBAC~N4	265	Insulated Ferrule	E1508		.	N	White	16	UL1007	Flexible Tinned Copper Wire	.		Insulated Ferrule	E1508	Single
10	1	Z-09	TBB~5_TBAC~G4	Power Distribution - AC	Terminal Block - Bed	Terminal Block - AC	TBB~5	TBAC~G4	305	Insulated Ferrule	E1508		.	G	Green / Green w. Yellow Stripe	16	UL1007	Flexible Tinned Copper Wire	.		Insulated Ferrule	E1508	Single
11	1	Z-10	TBB~7_SSR~1	Power Distribution - AC	Terminal Block - Bed	SSR	TBB~7	SSR~1	355	Insulated Ferrule	E1508		.	L	RED	16	UL1007	Flexible Tinned Copper Wire	.		Insulated Terminal	Ring M4	Single
12	1	Z-11	TBDC24V[-]_PSU24V[-]	Power Distribution - DC	Terminal Block - DC24	PSU24V	TBDC24V[-]	PSU24V[-]	190	Insulated Ferrule	E1508		.	Gnd	Gray	16	UL1007	Flexible Tinned Copper Wire	.		Insulated Terminal	Ring M4	Single
13	1	Z-12	TBDC24V[+]_PSU24V[+]	Power Distribution - DC	Terminal Block - DC24	PSU24V	TBDC24V[+]	PSU24V[+]	165	Insulated Ferrule	E1508		.	V+	Blue	16	UL1007	Flexible Tinned Copper Wire	.		Insulated Terminal	Ring M4	Single
14	1	Z-13	TBDC24V[-]_MB~PMot[-]	Power Distribution - DC	Terminal Block - DC24	MB - Motor Power	TBDC24V[-]	MB~PMot[-]	150	Insulated Ferrule	E1508		.	Gnd	Gray	16	UL1007	Flexible Tinned Copper Wire	.		Insulated Terminal	Ring M4	Single
15	1	Z-14	TBDC24V[+]_MB~PMot[+]	Power Distribution - DC	Terminal Block - DC24	MB - Motor Power	TBDC24V[+]	MB~PMot[+]	125	Insulated Ferrule	E1508		.	V+	Blue	16	UL1007	Flexible Tinned Copper Wire	.		Insulated Terminal	Ring M4	Single
16	1	Z-15	TBDC24V[-]_MB~P[-]	Power Distribution - DC	Terminal Block - DC24	MB - Power	TBDC24V[-]	MB~P[-]	165	Insulated Ferrule	E1508		.	Gnd	Gray	16	UL1007	Flexible Tinned Copper Wire	.		Insulated Terminal	Ring M4	Single
17	1	Z-16	TBDC24V[+]_MB~P[+]	Power Distribution - DC	Terminal Block - DC24	MB - Power	TBDC24V[+]	MB~P[+]	140	Insulated Ferrule	E1508		.	V+	Blue	16	UL1007	Flexible Tinned Copper Wire	.		Insulated Terminal	Ring M4	Single
18	1	Z-17	TBDC24V[-]_MB~PB[-]	Power Distribution - DC	Terminal Block - DC24	MB - Bed Power	TBDC24V[-]	MB~PB[-]	180	Insulated Ferrule	E1508		.	Gnd	Gray	16	UL1007	Flexible Tinned Copper Wire	.		Insulated Terminal	Ring M4	Single
19	1	Z-18	TBDC24V[+]_MB~PB[+]	Power Distribution - DC	Terminal Block - DC24	MB - Bed Power	TBDC24V[+]	MB~PB[+]	170	Insulated Ferrule	E1508		.	V+	Blue	16	UL1007	Flexible Tinned Copper Wire	.		Insulated Terminal	Ring M4	Single
20	1	Z-19	TBDC24V[-]_TBCAN~3	Power Distribution - DC	Terminal Block - DC24	Terminal Block - CAN	TBDC24V[-]	TBCAN~3	275	Insulated Ferrule	E1508		.	Gnd	Gray	16	UL1007	Flexible Tinned Copper Wire	.		Insulated Ferrule	E1508	Single
21	1	Z-20	TBDC24V[+]_TBCAN~4	Power Distribution - DC	Terminal Block - DC24	Terminal Block - CAN	TBDC24V[+]	TBCAN~4	265	Insulated Ferrule	E1508		.	V+	Blue	16	UL1007	Flexible Tinned Copper Wire	.		Insulated Ferrule	E1508	Single
22	1	Z-21	MB~BO[-]_SSR~4	Signal, SSR Trigger	MB - Bed Out	SSR	MB~BO[-]	SSR~4	280	Insulated Terminal	Ring M4		.	(-)	Gray	16	UL1007	Flexible Tinned Copper Wire	.		Insulated Terminal	Ring M4	Single
23	1	Z-22	MB~BO[+]_SSR~3	Signal, SSR Trigger	MB - Bed Out	SSR	MB~BO[+]	SSR~3	320	Insulated Terminal	Ring M4		.	(+)	Yellow	16	UL1007	Flexible Tinned Copper Wire	.		Insulated Terminal	Ring M4	Single
24	1	Z-23	MB~CAN_TBCAN~1	Signal, CAN H (PD0)	MB - CAN	Terminal Block - CAN	MB~CAN	TBCAN~1	190	JST	XH 2.54 (2P) Plug Housing w. Female Term.		1	CAN H	Yellow	22	UL1007	Flexible Tinned Copper Wire	.		Insulated Ferrule	E0508	Twisted Pair
25			MB~CAN_TBCAN~2	Signal, CAN L (PD1)		Terminal Block - CAN	MB~CAN	TBCAN~2					2	CAN L	Green	22	UL1007	Flexible Tinned Copper Wire	.		Insulated Ferrule	E0508	
26	1	Z-24	MB~BTC_TBB~3	Signal, (THB, PB1)	MB - Bed TC	Terminal Block - Bed	MB~BTC	TBB~3	180	JST	XH 2.54 (2P) Plug Housing w. Female Term.		1	Signal	Yellow	22	UL1007	Flexible Tinned Copper Wire	.		Insulated Ferrule	E0508	Bonded Pair
27			MB~BTC_TBB~4	Signal, (THB, GND)		Terminal Block - Bed	MB~BTC	TBB~4					2	Signal	Yellow	22	UL1007	Flexible Tinned Copper Wire	.		Insulated Ferrule	E0508	
28	1	Z-25	MB~FS_YCAB*PBA~FSA	Signal, (TH3, PA7)	MB - FS	Y Cable	MB~FS	YCAB*PBA~FSA	65	JST	XH 2.54 (2P) Plug Housing w. Female Term.		1	Signal	White	22	UL1007	Stranded Copper Wire	1		JST	XH 2.54 (2P) Receptical w. Male Term.	Single
29				-		-							-	-	-	-	-	-	Jumpered				
30			MB~FS_YCAB*PBA~FSB	Signal, (TH3, GND)		Y Cable	MB~FS	YCAB*PBA~FSB					2	Signal	White	22	UL1007	Stranded Copper Wire	2				
31	1	Z-26	MB~BFan_TBB~1	Power Distribution, (FAN0, PF7), (-)	MB - Fan	Terminal Block - Bed	MB~BFan	TBB~1	185	JST	XH 2.54 (2P) Plug Housing w. Female Term.		1	Gnd	Black	22	UL1007	Stranded Copper Wire	.		Insulated Ferrule	E0508	Bonded Pair
32			MB~BFan_TBB~2	Power Distribution, (FAN0, VF0), (+)		Terminal Block - Bed	MB~BFan	TBB~2					2	V+	Blue	22	UL1007	Stranded Copper Wire	.		Insulated Ferrule	E0508	
33	1	Z-27	MB~FS_PBA~FSA	Signal	YCAB*PB:A~FS:A	Peripheral Block - FS	MB~FS	PBA~FSA	210	JST	XH 2.54 (2P) Plug Housing w. Female Term.		2	Signal	White	22	UL1007	Stranded Copper Wire	2		JST	XH 2.54 (2P) Receptical w. Male Term.	Bonded Pair
34				Signal									1	Signal	Blue	22	UL1007	Stranded Copper Wire	1				
35	1	Z-28	MB~FS_PBA~FSB	Signal	YCAB*PB:A~FS:B	Peripheral Block - FS	MB~FS	PBA~FSB	210	JST	XH 2.54 (2P) Plug Housing w. Female Term.		2	Signal	White	22	UL1007	Stranded Copper Wire	2		JST	XH 2.54 (2P) Receptical w. Male Term.	Bonded Pair
36				Signal									1	Signal	Blue	22	UL1007	Stranded Copper Wire	1				
37	1	Z-29	MB~ESY_PBA~ESY	Signal (M6 Stop, +5V)	MB - YE	Peripheral Block - YE	MB~ESY	PBA~ESY	210	JST	XH 2.54 (3P) Plug Housing w. Female Term.		1	V+	Red	22	UL1007	Stranded Copper Wire	1		JST	XH 2.54 (3P) Receptical w. Male Term.	Bonded Ribbon
38				Signal (M6 Stop, Gnd)									2	Gnd	Black	22	UL1007	Stranded Copper Wire	2				
39				Signal (M6 Stop, PC15)									3	S	Green	22	UL1007	Stranded Copper Wire	3				
40	1	Z-30	TBDC24V[-]_PBA~LLGT	Power Distribution	Terminal Block - DC24	Peripheral Block - LLGT	TBDC24V[-]	PBA~LLGT	295	Insulated Ferrule	E0508		.	Gnd	Black	22	UL1007	Stranded Copper Wire	1		JST	XH 2.54 (3P) Receptical w. Male Term.	Bonded Pair
41			.	.			.	.					-	-	-	-	-	-	.				
42		Z-31	TBDC24V[+]_PBA~LLGT	Power Distribution			TBDC24V[+]	PBA~LLGT		Insulated Ferrule	E0508		.	V+	Blue	22	UL1007	Stranded Copper Wire	3				
43	1	Z-32	MB~LGT_YCAB*PBA~LGTA	Power Distribution, (FAN4, PA4), (-)	MB - LGT	Y Cable	MB~LGT	YCAB*PBA~LGTA	65	JST	XH 2.54 (2P) Plug Housing w. Female Term.		1	Gnd	Black	22	UL1007	Stranded Copper Wire	1		JST	XH 2.54 (3P) Receptical w. Male Term.	Bonded Pair
44													.						.				
45				Power Distribution, (FAN4, VF4), (+)									2	V+	Blue	22	UL1007	Stranded Copper Wire	3				
46		Z-33	MB~LGT_YCAB*PBA~LGTB	Power Distribution, (FAN4, PA4), (-)		Y Cable	MB~LGT	YCAB*PBA~LGTB					1	Gnd	Black	22	UL1007	Stranded Copper Wire	1		JST	XH 2.54 (3P) Receptical w. Male Term.	Bonded Pair
47													.						.				
48				Power Distribution, (FAN4, VF4), (+)									2	V+	Blue	22	UL1007	Stranded Copper Wire	3				
49	1	Z-34	MB~LGT_PBA~LGTA	Power Distribution, (FAN4, PA4), (-)	MB - LGT	Peripheral Block - LGT	MB~LGT	PBA~LGTA	210	JST	XH 2.54 (3P) Plug Housing w. Female Term.		1	Gnd	Black	22	UL1007	Stranded Copper Wire	1		JST	XH 2.54 (3P) Receptical w. Male Term.	Bonded Ribbon
50													2	NC	Green	22	UL1007	Stranded Copper Wire	2				
51				Power Distribution, (FAN4, VF4), (+)									3	V+	Red	22	UL1007	Stranded Copper Wire	3				
52	1	Z-35	MB~LGT_PBA~LGTB	Power Distribution, (FAN4, PA4), (-)	MB - LGT	Peripheral Block - LGT	MB~LGT	PBA~LGTB	210	JST	XH 2.54 (3P) Plug Housing w. Female Term.		1	Gnd	Black	22	UL1007	Stranded Copper Wire	1		JST	XH 2.54 (3P) Receptical w. Male Term.	Bonded Ribbon
53													2	NC	Green	22	UL1007	Stranded Copper Wire	2				
54				Power Distribution, (FAN4, VF4), (+)									3	V+	Red	22	UL1007	Stranded Copper Wire	3				
55	1	Z-36	MB~Mot1_PBA~Mot1	Power Distribution, Motor 1	MB - M1	Peripheral Block - M1	MB~Mot1	PBA~Mot1	430	JST	XH 2.54 (4P) Plug Housing w. Female Term.		1	2B	Red	22	UL1007	Stranded Copper Wire	1		JST	XH 2.54 (4P) Plug Housing w. Female Term.	Bonded Ribbon
56				Power Distribution, Motor 1									2	2A	Blue	22	UL1007	Stranded Copper Wire	2				
57				Power Distribution, Motor 1									3	1A	Green	22	UL1007	Stranded Copper Wire	3				
58				Power Distribution, Motor 1									4	1B	Black	22	UL1007	Stranded Copper Wire	4				
59	1	Z-37	MB~Mot2_PBA~Mot2	Power Distribution, Motor 2	MB - M2	Peripheral Block - M2	MB~Mot2	PBA~Mot2	430	JST	XH 2.54 (4P) Plug Housing w. Female Term.		1	2B	Red	22	UL1007	Stranded Copper Wire	1		JST	XH 2.54 (4P) Plug Housing w. Female Term.	Bonded Ribbon
60				Power Distribution, Motor 2									2	2A	Blue	22	UL1007	Stranded Copper Wire	2				
61				Power Distribution, Motor 2									3	1A	Green	22	UL1007	Stranded Copper Wire	3				
62				Power Distribution, Motor 2									4	1B	Black	22	UL1007	Stranded Copper Wire	4				
63	1	Z-38	MB~Mot3_PBA~Mot3	Power Distribution, Motor 3	MB - M3	Peripheral Block - M3	MB~Mot3	PBA~Mot3	430	JST	XH 2.54 (4P) Plug Housing w. Female Term.		1	2B	Red	22	UL1007	Stranded Copper Wire	1		JST	XH 2.54 (4P) Plug Housing w. Female Term.	Bonded Ribbon
64				Power Distribution, Motor 3									2	2A	Blue	22	UL1007	Stranded Copper Wire	2				
65				Power Distribution, Motor 3									3	1A	Green	22	UL1007	Stranded Copper Wire	3				
66				Power Distribution, Motor 3									4	1B	Black	22	UL1007	Stranded Copper Wire	4				
67	1	Z-39	MB~Mot4_PBA~Mot4	Power Distribution, Motor 4	MB - M4	Peripheral Block - M4	MB~Mot4	PBA~Mot4	430	JST	XH 2.54 (4P) Plug Housing w. Female Term.		1	2B	Red	22	UL1007	Stranded Copper Wire	1		JST	XH 2.54 (4P) Plug Housing w. Female Term.	Bonded Ribbon
68				Power Distribution, Motor 4									2	2A	Blue	22	UL1007	Stranded Copper Wire	2				
69				Power Distribution, Motor 4									3	1A	Green	22	UL1007	Stranded Copper Wire	3				
70				Power Distribution, Motor 4									4	1B	Black	22	UL1007	Stranded Copper Wire	4				
71	1	Z-40	MB~MotA_PBA~MotA	Power Distribution, Motor A	MB - M A	Peripheral Block - M A	MB~MotA	PBA~MotA	430	JST	XH 2.54 (4P) Plug Housing w. Female Term.		1	2B	Red	22	UL1007	Stranded Copper Wire	1		JST	XH 2.54 (4P) Plug Housing w. Female Term.	Bonded Ribbon
72				Power Distribution, Motor A									2	2A	Blue	22	UL1007	Stranded Copper Wire	2				
73				Power Distribution, Motor A									3	1A	Green	22	UL1007	Stranded Copper Wire	3				
74				Power Distribution, Motor A									4	1B	Black	22	UL1007	Stranded Copper Wire	4				
75	1	Z-41	MB~MotB_PBA~MotB	Power Distribution, Motor B	MB - M B	Peripheral Block - M B	MB~MotB	PBA~MotB	430	JST	XH 2.54 (4P) Plug Housing w. Female Term.		1	2B	Red	22	UL1007	Stranded Copper Wire	1		JST	XH 2.54 (4P) Plug Housing w. Female Term.	Bonded Ribbon
76				Power Distribution, Motor B									2	2A	Blue	22	UL1007	Stranded Copper Wire	2				
77				Power Distribution, Motor B									3	1A	Green	22	UL1007	Stranded Copper Wire	3				
78				Power Distribution, Motor B									4	1B	Black	22	UL1007	Stranded Copper Wire	4				
79	1	Z-42	MB~ES1_PBZ~1	Signal (M1 Stop, +5V)	MB - E1	Peripheral Block Z - ES1	MB~ES1	PBZ~1	335	JST	XH 2.54 (3P) Plug Housing w. Female Term.		1	V+	Red	22	UL1007	Stranded Copper Wire	1		JST	XH 2.54 (3P) Receptical w. Male Term.	Bonded Ribbon
80				Signal (M1 Stop, Gnd)									2	Gnd	Black	22	UL1007	Stranded Copper Wire	2				
81				Signal (M1 Stop, PF4)									3	S	Green	22	UL1007	Stranded Copper Wire	3				
82	1	Z-43	MB~ES2_PBZ~2	Signal (M2 Stop, +5V)	MB - E2	Peripheral Block Z - ES2	MB~ES2	PBZ~2	335	JST	XH 2.54 (3P) Plug Housing w. Female Term.		1	V+	Red	22	UL1007	Stranded Copper Wire	1		JST	XH 2.54 (3P) Receptical w. Male Term.	Bonded Ribbon
83				Signal (M2 Stop, Gnd)									2	Gnd	Black	22	UL1007	Stranded Copper Wire	2				
84				Signal (M2 Stop, PF3)									3	S	Green	22	UL1007	Stranded Copper Wire	3				
85	1	Z-44	MB~ES3_PBZ~3	Signal (M3 Stop, +5V)	MB - E3	Peripheral Block Z - ES3	MB~ES3	PBZ~3	335	JST	XH 2.54 (3P) Plug Housing w. Female Term.		1	V+	Red	22	UL1007	Stranded Copper Wire	1		JST	XH 2.54 (3P) Receptical w. Male Term.	Bonded Ribbon
86				Signal (M3 Stop, Gnd)									2	Gnd	Black	22	UL1007	Stranded Copper Wire	2				
87				Signal (M3 Stop, PF2)									3	S	Green	22	UL1007	Stranded Copper Wire	3				
88	1	Z-45	MB~ES4_PBZ~4	Signal (M4 Stop, +5V)	MB - E4	Peripheral Block Z - ES4	MB~ES4	PBZ~4	335	JST	XH 2.54 (3P) Plug Housing w. Female Term.		1	V+	Red	22	UL1007	Stranded Copper Wire	1		JST	XH 2.54 (3P) Receptical w. Male Term.	Bonded Ribbon
89				Signal (M4 Stop, Gnd)									2	Gnd	Black	22	UL1007	Stranded Copper Wire	2				
90				Signal (M4 Stop, PF1)									3	S	Green	22	UL1007	Stranded Copper Wire	3				
91	1	Z-46	TBB~1_WB~FAN[-]	Power Distribution, (FAN0, PF7), (-)	Terminal Block - Bed	Bed Wago Bar	TBB~1	WB~FAN[-]	930	Insulated Ferrule	E0508		.	Gnd	Black	22	UL3135 or equivalent	Silicone, Dynamic Cable	-		Insulated Ferrule	E0508	Bonded Pair
92		Z-47	TBB~2_WB~FAN[+]	Power Distribution, (FAN0, VF0), (+)			TBB~2	WB~FAN[+]	930	Insulated Ferrule	E0508		.	V+	Blue	22	UL3135 or equivalent	Silicone, Dynamic Cable	-		Insulated Ferrule	E0508	
93	1	Z-48	TBB~3_WB~BTC	Signal, (THB, PB1)	Terminal Block - Bed	Bed Wago Bar	TBB~3	WB~BTC	990	Insulated Ferrule	E0508		.	Signal	Yellow	22	UL3135 or equivalent	Silicone, Dynamic Cable	-		Insulated Ferrule	E0508	Bonded Pair
94		Z-49	TBB~4_WB~BTC	Signal, (THB, GND)			TBB~4	WB~BTC	990	Insulated Ferrule	E0508		.	Signal	Yellow	22	UL3135 or equivalent	Silicone, Dynamic Cable	-		Insulated Ferrule	E0508	
95	1	Z-50	TBB~7_WB~L	VAC - L	Terminal Block - Bed	Bed Wago Bar	TBB~7	WB~L	965	Insulated Ferrule	E1008		-	L	White	18	UL3135 or equivalent	Silicone, Dynamic Cable	-		Insulated Ferrule	E1008	Single
96	1	Z-51	TBB~6_WB~N	VAC - N	Terminal Block - Bed	Bed Wago Bar	TBB~6	WB~N	965	Insulated Ferrule	E1008		-	N	White	18	UL3135 or equivalent	Silicone, Dynamic Cable	-		Insulated Ferrule	E1008	Single
97	1	Z-52	TBB~5_WB~G	VAC - G	Terminal Block - Bed	Bed Wago Bar	TBB~5	WB~G	965	Insulated Ferrule	E1008		-	G	Green	18	UL3135 or equivalent	Silicone, Dynamic Cable	-		Insulated Ferrule	E1008	Single
98	1	Z-53	THB~CAN_TBCAN~1	Signal, CAN H (PD0)	Terminal Block - CAN	Toolhead	THB~CAN	TBCAN~1	815	Insulated Ferrule	.		.	High	Yellow	28	UL3135 or equivalent	Silicone, Dynamic Cable	3		XT Bullet	XT30 (2+2) Female	Twisted Pair
99	1	Z-54	THB~CAN_TBCAN~2	Signal, CAN L (PD1)	Terminal Block - CAN	Toolhead	THB~CAN	TBCAN~2	815	Insulated Ferrule	.		.	Low	Green / White	28	UL3135 or equivalent	Silicone, Dynamic Cable	4				
100	1	Z-55	THB~CAN_TBCAN~4	Power Distribution - DC	Terminal Block - CAN	Toolhead	THB~CAN	TBCAN~4	815	Insulated Ferrule	E1008		.	V+	Blue	18	UL3135 or equivalent	Silicone, Dynamic Cable	1				Single
101	1	Z-56	THB~CAN_TBCAN~3	Power Distribution - DC	Terminal Block - CAN	Toolhead	THB~CAN	TBCAN~3	815	Insulated Ferrule	E1008		.	Gnd	Black	18	UL3135 or equivalent	Silicone, Dynamic Cable	2				Single
102	1	Z-57	PBA~LGT_LGT:A	Power Distribution	Peripheral Block - LGT	Light Bar Left	PBA~LGT	LGT:A	610	JST	XH 2.54 (3P) Plug Housing w. Female Term.		1	Gnd	Black	22	UL1007	Stranded Copper Wire	2		JST	XH 2.54 (2P) Plug Housing w. Female Term.	Bonded Ribbon
103				Power Distribution									3	V+	Blue	22	UL1007	Stranded Copper Wire	1				
104	1	Z-58	PBA~LGT_LGT:B	Power Distribution	Peripheral Block - LGT	Light Bar Right	PBA~LGT	LGT:B	545	JST	XH 2.54 (3P) Plug Housing w. Female Term.		1	Gnd	Black	22	UL1007	Stranded Copper Wire	2		JST	XH 2.54 (2P) Plug Housing w. Female Term.	Bonded Ribbon
105				Power Distribution									3	V+	Blue	22	UL1007	Stranded Copper Wire	1				
106	1	Z-59	PBA~LLGT_LGT:LLGT	Power Distribution	Peripheral Block - LLGT	Light Bar Logo	PBA~LLGT	LGT:LLGT	990	JST	XH 2.54 (3P) Plug Housing w. Female Term.		1	Gnd	Black	22	UL1007	Stranded Copper Wire	2		JST	XH 2.54 (2P) Plug Housing w. Female Term.	Bonded Ribbon
107				Power Distribution									3	V+	Blue	22	UL1007	Stranded Copper Wire	1				
108	1	Z-60	PBA~FSA_WFS:A~2/4	Signal	Peripheral Block - Force Sensor	Force Sensor	PBA~FSA	WFS:A~2/4	800	JST	XH 2.54 (2P) Plug Housing w. Female Term.		2	Signal	White	22	UL1007	Stranded Copper Wire	.		Insulated Ferrule	E0508	Bonded Ribbon
109				Signal									1	Signal	Blue	22	UL1007	Stranded Copper Wire	.		Insulated Ferrule	E0508	
110	1	Z-61	PBA~FSB_WFS:B~2/4	Signal	Peripheral Block - Force Sensor	Force Sensor	PBA~FSB	WFS:B~2/4	710	JST	XH 2.54 (2P) Plug Housing w. Female Term.		2	Signal	White	22	UL1007	Stranded Copper Wire	.		Insulated Ferrule	E0508	Bonded Ribbon
111				Signal									1	Signal	Blue	22	UL1007	Stranded Copper Wire	.		Insulated Ferrule	E0508	
112	1	Z-62	PBA~Mot1_Nema17~Mot1	Power Distribution, Motor 1	Peripheral Block - Motor Front	Front Motors	PBA~Mot1	Nema17~Mot1	890	**Hardware Component NEMA 17 (Geared)**			6	2B	Black	.	UL1007	Stranded Copper Wire	1		JST	XH 2.54 (4P) Plug Housing w. Female Term.	.
113				Power Distribution, Motor 1									4	2A	Green	.	UL1007	Stranded Copper Wire	2				
114				Power Distribution, Motor 1									3	1A	Red	.	UL1007	Stranded Copper Wire	4				
115				Power Distribution, Motor 1									1	1B	Blue	.	UL1007	Stranded Copper Wire	3				
116	1	Z-63	PBA~Mot2_Nema17~Mot2	Power Distribution, Motor 2	Peripheral Block - Motor Front	Front Motors	PBA~Mot2	Nema17~Mot2	890	**Hardware Component NEMA 17 (Geared)**			6	2B	Black	.	UL1007	Stranded Copper Wire	1		JST	XH 2.54 (4P) Plug Housing w. Female Term.	.
117				Power Distribution, Motor 2									4	2A	Green	.	UL1007	Stranded Copper Wire	2				
118				Power Distribution, Motor 2									3	1A	Red	.	UL1007	Stranded Copper Wire	4				
119				Power Distribution, Motor 2									1	1B	Blue	.	UL1007	Stranded Copper Wire	3				
120	1	Z-64	PBA~Mot3_Nema17~Mot3	Power Distribution, Motor 2	Peripheral Block - Motor Front	Front Motors	PBA~Mot3	Nema17~Mot3	500	**Hardware Component NEMA 17 (Geared)**			6	2B	Black	.	UL1007	Stranded Copper Wire	1		JST	XH 2.54 (4P) Plug Housing w. Female Term.	.
121				Power Distribution, Motor 2									4	2A	Green	.	UL1007	Stranded Copper Wire	2				
122				Power Distribution, Motor 2									3	1A	Red	.	UL1007	Stranded Copper Wire	4				
123				Power Distribution, Motor 2									1	1B	Blue	.	UL1007	Stranded Copper Wire	3				
124	1	Z-65	PBA~Mot4_Nema17~Mot4	Power Distribution, Motor 2	Peripheral Block - Motor Front	Front Motors	PBA~Mot4	Nema17~Mot4	500	**Hardware Component NEMA 17 (Geared)**			6	2B	Black	.	UL1007	Stranded Copper Wire	1		JST	XH 2.54 (4P) Plug Housing w. Female Term.	.
125				Power Distribution, Motor 2									4	2A	Green	.	UL1007	Stranded Copper Wire	2				
126				Power Distribution, Motor 2									3	1A	Red	.	UL1007	Stranded Copper Wire	4				
127				Power Distribution, Motor 2									1	1B	Blue	.	UL1007	Stranded Copper Wire	3				
128	1	Z-66	PBA~MotA_Nema17G~MotA	Power Distribution, Motor A	Peripheral Block - Motor XY	X-Y Motors	PBA~MotA	Nema17G~MotA	305	**Hardware Component NEMA 17**			6	2B	Black	.	UL1007	Stranded Copper Wire	1		JST	XH 2.54 (4P) Plug Housing w. Female Term.	.
129				Power Distribution, Motor A									4	2A	Green	.	UL1007	Stranded Copper Wire	2				
130				Power Distribution, Motor A									3	1A	Red	.	UL1007	Stranded Copper Wire	3				
131				Power Distribution, Motor A									1	1B	Blue	.	UL1007	Stranded Copper Wire	4