AHU MOTOR STARTER PANEL DESIGN & CONTROL INTERLOCKS:
1. Fully compartmentalized Form 3b motor control center (MCC) housing starters for AHU-01 through AHU-08.
2. Variable Frequency Drives (VFD) equipped with bypass contactors, EMC line filters, and Modbus communication cards.
3. Microprocessor motor protection relays providing thermal overload, single phasing, locked rotor, and earth leakage protection.
4. Safety Interlock 1: Differential pressure switch across supply fan proving airflow before electric heating or cooling is energized.
5. Safety Interlock 2: High static pressure safety cut-out switch opening control circuit if duct static exceeds 750 Pa.
6. Safety Interlock 3: Hardwired dry contact from Fire Alarm Panel immediately opening main contactor upon fire alarm trip.

Starter Tag	AHU Served	Motor Rating	Full Load Amps	VFD Model	MCCB Rating
STR-01	AHU-01 (Assembly Hall North)	22.0 kW (30 HP)	42.0 Amps	Danfoss FC-102	63A 3P 36kA
STR-02	AHU-02 (Assembly Hall South)	22.0 kW (30 HP)	42.0 Amps	Danfoss FC-102	63A 3P 36kA
STR-03	AHU-03 (Speaker Secretariat)	15.0 kW (20 HP)	29.0 Amps	Danfoss FC-102	40A 3P 36kA
STR-04	AHU-04 (Cabinet Room)	15.0 kW (20 HP)	29.0 Amps	Danfoss FC-102	40A 3P 36kA
STR-05	AHU-05 (Press & Media Hall)	11.0 kW (15 HP)	21.5 Amps	Danfoss FC-102	32A 3P 25kA