Sort
abcd
abcd



Replace phone battery easily

Mini Bluetooth Speaker (Advanced)

All rights are reserved inprint - Privacy Policy - Terms of Service

Replace phone battery



Tools Needed:
- Replacement battery (specific to your phone model)
- Small screwdriver set (Phillips or Pentalobe screws)
- Plastic pry tools
- Suction cup tool
- Tweezers
- SIM card ejector tool (optional)
- Heat pad or hairdryer (to soften adhesive)
- Antistatic wristband (optional but recommended)

Step 1: Power Off Your Phone

Before beginning any work, power off your phone to avoid short circuits or electrical shock.

Step 2: Remove the SIM Card Tray (If Applicable)(optional)

Some phones require the SIM card tray to be removed before disassembling. Use the SIM card ejector tool to take it out.

Step 3: Heat the Back Cover (If Necessary)

If your phone has a glued or adhesive-sealed back cover, apply a little heat using a heat pad or a hairdryer. This will soften the adhesive, making it easier to open. Heat for about 30 seconds to 1 minute.

Step 4: Pry Open the Back Cover

Using a plastic pry tool or suction cup, carefully separate the back cover from the phone. Be gentle to avoid cracking the cover or damaging any components. Work your way around the phone, loosening the adhesive, until the back cover is removed.

Step 5: Unscrew the Internal Screws

Most phones will have screws securing the internal components. Using the appropriate screwdriver, remove the screws. Keep track of the different screw sizes and where they belong.

Step 6: Disconnect the Battery Connector

Once the screws are removed, locate the battery connector (usually covered with a small protective plastic cover). Use a plastic tool to gently lift the connector from its port. Be cautious not to damage any connectors or cables.

Step 7: Remove the Old Battery

If the battery is glued in place, use the plastic pry tool or suction cup to gently lift the battery. If there is any resistance, apply a little heat to soften the adhesive further. Once free, carefully remove the old battery.

Step 8: Install the New Battery

Place the new battery into the compartment, aligning it properly. Reconnect the battery's connector to the phone's motherboard. Make sure it's securely connected.

Step 9: Reassemble the Phone

Once the battery is connected, start reassembling the phone. Place the back cover on and gently press it to secure it. If there are screws, replace them in their original spots. If the back cover is glued, make sure it's aligned correctly.

Step 10: Power On the Phone

Turn your phone back on to check that the battery is properly installed. Make sure it is charging and working properly.

Safety Tip: Always make sure the replacement battery is specifically made for your phone model. Using the wrong battery can cause damage to your phone or even cause a fire hazard.
With these steps, you should be able to successfully replace your phone's battery!

All rights are reserved inprint - Privacy Policy - Terms of Service

Mini Bluetooth Speaker



Tools & Materials Required:
- Bluetooth Audio Module (e.g., CSR8635 or BC127)
- Speaker Drivers (typically 3W to 5W)
- Battery (Lithium-ion rechargeable, 3.7V)
- Charging Module (e.g., TP4056 for charging the battery)
- Amplifier Module (e.g., TDA2822 or LM386)
- Power Switch
- Enclosure (can be a small box, plastic, or wood)
- Wire (for connections)
- Soldering Iron & Solder
- Hot Glue Gun or Double-Sided Tape
- Micro-USB Cable (for charging)
- Aux Cable (optional, if you want to include a wired option)
- Resistors and Capacitors (if needed, depending on your circuit)
- Plastic or Wood for Enclosure (can use a project box, old speaker box, or custom-designed case)
- Drill (for making holes for the speaker and controls)

Step 1: Prepare the Speaker Enclosure

- Choose your enclosure: You can use a small plastic or wooden box as the speaker's case. The size of the box should be big enough to fit the speaker, battery, and other components.
- Drill holes: Drill a hole for the speaker driver (front) and for the buttons/charging port (back or side).
- Make space for components: Arrange space for the Bluetooth module, battery, amplifier, and charging circuit inside the enclosure.

Step 2: Wiring the Components

A. Connect the Bluetooth Module:
- Power Supply: Connect the 5V output of the battery charging module to the VCC input on the Bluetooth module.
- Ground Connection: Connect the GND of the Bluetooth module to the battery charging module's GND.
- Audio Output: The Bluetooth module will output audio signals, usually through left (L) and right (R) channels, which need to be connected to the amplifier module.

B. Connect the Amplifier Module:
- Input from Bluetooth Module: Connect the L and R audio output from the Bluetooth module to the input pins of the amplifier module.
- Speaker Output: Connect the output pins from the amplifier module to the speaker driver.
  - For the left and right channels, connect them together if using a single speaker. If using two speakers, ensure each speaker is connected to each respective channel.
- Power Supply for Amplifier: Connect the 5V and GND from the battery module to the amplifier module to power it.

C. Battery & Charging Module:
- Connect the Charging Module to the Battery:
- Connect the B+ and B- from the charging module to the positive and negative terminals of the battery.
- Make sure the input pins of the charging module are connected to the Micro-USB port for charging.

Step 3: Set Up the Control Buttons

- Power Switch: Install a simple ON/OFF switch to control power to the Bluetooth module and the amplifier. You can place this on the side of the enclosure.
- Volume Control: For volume control, you could add a rotary potentiometer or simple push buttons connected to the amplifier's gain control.
- Bluetooth Pairing Button: If needed, you can add a button for Bluetooth pairing, though many Bluetooth modules pair automatically when powered on.

Step 4: Secure the Components Inside the Enclosure

- Position the Speaker Driver: Secure the speaker driver to the front hole you drilled. Use hot glue or double-sided tape for a secure attachment.
- Mount the Bluetooth Module: Place the Bluetooth module, amplifier, and charging circuit inside the enclosure and secure them using glue or mounting tape.
- Wire Management: Organize the wires neatly to prevent them from interfering with the moving parts or causing shorts. Use zip ties or clips to keep wires in place.

Step 5: Final Assembly and Testing

1. Check Connections: Double-check that all connections are correct. Make sure power is properly supplied to each module and that the audio output of the Bluetooth module is correctly wired to the amplifier.
2. Test the Speaker: Power on the device, and pair it with your phone or Bluetooth-enabled device. Play some music to test the audio output. Adjust the volume and check for any distortion or issues with sound.
3. Adjustments: If there are any issues with sound quality (distortion or low volume), check your amplifier and speaker connections. Make sure you're using appropriate components for your power and speaker output.

Step 6: Secure the Enclosure and Finish the Project

- Close the Enclosure: Once everything is working fine, close the enclosure and secure the top part with screws or glue.
- Test Charging: Plug in the charging cable and test the charging function to make sure everything works as expected.

Step 7: Enjoy Your Mini Bluetooth Speaker!

Now you have your own portable Bluetooth speaker! You can customize it further with added features like:
- LED Lights for visual effects.
- Extra Bass by adjusting the amplifier settings.
- Waterproofing for outdoor use.

Caution: Handle all electronic components carefully to avoid short circuits or static damage. Make sure all connections are secure before powering on, and use proper insulation to prevent any accidental contact with wires. Always test the speaker in a safe environment before final assembly to ensure functionality.

All rights are reserved inprint - Privacy Policy - Terms of Service

Welcome!!!

Login

E-mail Address

Password

Login

Register

Name

Enter E-mail Address

Enter Password

Re-Enter Password

Register

All rights are reserved inprint - Privacy Policy - Terms of Service

My Profile

Username : abc
Email Address : abc@gmail.com

Edit Profile

History
Settings
Language
Logout

All rights are reserved inprint - Privacy Policy - Terms of Service

Contact Us

Username

E-mail Address

Enter your message

Submit

All rights are reserved inprint - Privacy Policy - Terms of Service

About Us

Welcome to Evertone Electronic – **your ultimate destination for hands-on guides and creative inspiration to build your own electronic gadgets. Whether you're a hobbyist, beginner, or an experienced engineer, we're here to help you bring your ideas to life through easy-to-follow, step-by-step instructions.**

Our Mission: At Evertone Electronic, our mission is to empower individuals to explore the fascinating world of electronics. We provide the tools, resources, and tutorials to help you learn new skills, solve problems, and create amazing devices from scratch. Whether it's a simple circuit or a more advanced project, we want to spark your creativity and fuel your passion for technology.

What We Offer:
- **Step-by-step guides:** Clear instructions with detailed explanations and visuals to help you successfully complete a variety of electronics projects.
- **Diverse Projects:** From basic circuits to complex microcontroller-driven systems, we cover a wide range of ideas, including home automation, robotics, IoT, and more.
- **Learning Resources:** Access to beginner-friendly materials, component guides, and troubleshooting tips to ensure your success.

All rights are reserved inprint - Privacy Policy - Terms of Service