

P-CHANNEL ENHANCEMENT MODE DMOS TRANSISTOR

Features

- High Input Impedance
- · Fast Switching Speed
- CMOS Logic Compatible Input
- No Thermal Runaway or Secondary Breakdown


Mechanical Data

Case: TO-92, Plastic

• Leads: Solderable per MIL-STD-202,

Method 208

Pin Connection: See DiagramApprox Weight: 0.18 grams



TO-92				
Dim	Min	Max		
Α	4.45	4.70		
В	4.46	4.70		
С	12.7	_		
D	0.41	0.63		
E	3.43	3.68		
G	2.42	2.67		
Н	1.14	1.40		
All Dimensions in mm				

Maximum Ratings @ $T_A = 25$ °C unless otherwise specified

Characteristic	Symbol	Value	Unit
Drain-Source Voltage	-V _{DSS}	60	V
Drain-Gate Voltage	-V _{DGS}	60	V
Gate-Source-Voltage (pulsed)	V_{GS}	±20	V
Drain Current (continuous)	-I _D	250	mA
Power Dissipation @T _C = 25°C (Note 1)	P _d	830	mW
Operating and Storage Temperature Range	T _j , T _{STG}	-55 +150	°C

Inverse Diode @ T_A = 25°C unless otherwise specified

Characteristic	Symbol	Value	Unit
Maximum Forward Current (continuous)	lF	0.15	Α
Forward Voltage Drop (Typ.) @ $V_{GS} = 0$, $I_F = 0.15A$, $T_j = 25$ °C	V _F	0.85	V

Electrical Characteristics @ TA = 25°C unless otherwise specified

Characteristic	Symbol	Min	Тур	Max	Unit	Test Condition
Drain-Source Breakdown Voltage	-V _{(BR)DSS}	60	70	_	V	$I_D = 100 \mu A, V_{GS} = 0$
Gate Threshold Voltage	-V _{GS(th)}	_	1.0	3.0	V	$V_{GS} = V_{DS}, -I_D = 1.0 \text{mA}$
Gate-Body Leakage Current	-I _{GSS}	_	_	20	nA	-V _{GS} = 15V, V _{DS} = 0
Drain-Source Cutoff Current	-I _{DSS}	_	_	0.5	μA	-V _{DS} = 25V, V _{GS} = 0
Drain-Source ON Resistance	r _{DS (ON)}	_	3.5	5.0	Ω	-V _{GS} = 10V, -I _D = 0.2A
Thermal Resistance, Junction to Ambient Air	$R_{\theta JA}$	_	_	150	K/W	Note 1
Forward Transconductance	g FS	_	150	_	mS	$-V_{DS} = 10V, -I_{D} = 0.2A,$ f = 1.0MHz
Input Capacitance	C _{iss}	_	60	_	pF	-V _{DS} = 10V, V _{GS} = 0, f = 1.0MHz
Switching Times Turn On Time Turn Off Time	t _{on} t _{off}		5 25	_	ns	$-V_{GS} = 10V, -V_{DS} = 10V,$ $R_D = 100\Omega$

Notes: 1. Valid provided that leads are kept at ambient temperature at a distance of 2mm from case.

