31 27	26 25	24 20	19 15	14 12	11 7	6 0	
funct7		rs2	rs1	funct3	rd	opcode	R-type
imm[11:0]			rs1	funct3	rd	opcode	I-type
imm[11:5]		rs2	rs1	funct3	imm[4:0]	opcode	S-type
imm[12|10:5]		rs2	rs1	funct3	imm[4:1|11]	opcode	B-type
imm[31:12]					rd	opcode	U-type
imm[20|10:1|11|19:12]					rd	opcode	J-type

RV32I Base Instruction Set

imm[31:12]					rd	0110111	LUI
imm[31:12]					rd	0010111	AUIPC
imm[20|10:1|11|19:12]					rd	1101111	JAL
imm[11:0]			rs1	000	rd	1100111	JALR
imm[12|10:5]		rs2	rs1	000	imm[4:1|11]	1100011	BEQ
imm[12|10:5]		rs2	rs1	001	imm[4:1|11]	1100011	BNE
imm[12|10:5]		rs2	rs1	100	imm[4:1|11]	1100011	BLT
imm[12|10:5]		rs2	rs1	101	imm[4:1|11]	1100011	BGE
imm[12|10:5]		rs2	rs1	110	imm[4:1|11]	1100011	BLTU
imm[12|10:5]		rs2	rs1	111	imm[4:1|11]	1100011	BGEU
imm[11:0]			rs1	000	rd	0000011	LB
imm[11:0]			rs1	001	rd	0000011	LH
imm[11:0]			rs1	010	rd	0000011	LW
imm[11:0]			rs1	100	rd	0000011	LBU
imm[11:0]			rs1	101	rd	0000011	LHU
imm[11:5]		rs2	rs1	000	imm[4:0]	0100011	SB
imm[11:5]		rs2	rs1	001	imm[4:0]	0100011	SH
imm[11:5]		rs2	rs1	010	imm[4:0]	0100011	SW
imm[11:0]			rs1	000	rd	0010011	ADDI
imm[11:0]			rs1	010	rd	0010011	SLTI
imm[11:0]			rs1	011	rd	0010011	SLTIU
imm[11:0]			rs1	100	rd	0010011	XORI
imm[11:0]			rs1	110	rd	0010011	ORI
imm[11:0]			rs1	111	rd	0010011	ANDI
0000000		shamt	rs1	001	rd	0010011	SLLI
0000000		shamt	rs1	101	rd	0010011	SRLI
0100000		shamt	rs1	101	rd	0010011	SRAI
0000000		rs2	rs1	000	rd	0110011	ADD
0100000		rs2	rs1	000	rd	0110011	SUB
0000000		rs2	rs1	001	rd	0110011	SLL
0000000		rs2	rs1	010	rd	0110011	SLT
0000000		rs2	rs1	011	rd	0110011	SLTU
0000000		rs2	rs1	100	rd	0110011	XOR
0000000		rs2	rs1	101	rd	0110011	SRL
0100000		rs2	rs1	101	rd	0110011	SRA
0000000		rs2	rs1	110	rd	0110011	OR
0000000		rs2	rs1	111	rd	0110011	AND
fm	pred	succ	rs1	000	rd	0001111	FENCE
000000000000			00000	000	00000	1110011	ECALL
000000000001			00000	000	00000	1110011	EBREAK

31 27	26 25	24 20	19 15	14 12	11 7	6 0	
funct7		rs2	rs1	funct3	rd	opcode	R-type
imm[11:0]			rs1	funct3	rd	opcode	I-type
imm[11:5]		rs2	rs1	funct3	imm[4:0]	opcode	S-type

RV64I Base Instruction Set (in addition to RV32I)

imm[11:0]		rs1	110	rd	0000011	LWU
imm[11:0]		rs1	011	rd	0000011	LD
imm[11:5]	rs2	rs1	011	imm[4:0]	0100011	SD
000000	shamt	rs1	001	rd	0010011	SLLI
000000	shamt	rs1	101	rd	0010011	SRLI
010000	shamt	rs1	101	rd	0010011	SRAI
imm[11:0]		rs1	000	rd	0011011	ADDIW
0000000	shamt	rs1	001	rd	0011011	SLLIW
0000000	shamt	rs1	101	rd	0011011	SRLIW
0100000	shamt	rs1	101	rd	0011011	SRAIW
0000000	rs2	rs1	000	rd	0111011	ADDW
0100000	rs2	rs1	000	rd	0111011	SUBW
0000000	rs2	rs1	001	rd	0111011	SLLW
0000000	rs2	rs1	101	rd	0111011	SRLW
0100000	rs2	rs1	101	rd	0111011	SRAW

RV32/RV64 *Zifencei* Standard Extension

imm[11:0]	rs1	001	rd	0001111	FENCE.I

RV32/RV64 *Zicsr* Standard Extension

csr	rs1	001	rd	1110011	CSRRW
csr	rs1	010	rd	1110011	CSRRS
csr	rs1	011	rd	1110011	CSRRC
csr	uimm	101	rd	1110011	CSRRWI
csr	uimm	110	rd	1110011	CSRRSI
csr	uimm	111	rd	1110011	CSRRCI

RV32M Standard Extension

0000001	rs2	rs1	000	rd	0110011	MUL
0000001	rs2	rs1	001	rd	0110011	MULH
0000001	rs2	rs1	010	rd	0110011	MULHSU
0000001	rs2	rs1	011	rd	0110011	MULHU
0000001	rs2	rs1	100	rd	0110011	DIV
0000001	rs2	rs1	101	rd	0110011	DIVU
0000001	rs2	rs1	110	rd	0110011	REM
0000001	rs2	rs1	111	rd	0110011	REMU

RV64M Standard Extension (in addition to RV32M)

0000001	rs2	rs1	000	rd	0111011	MULW
0000001	rs2	rs1	100	rd	0111011	DIVW
0000001	rs2	rs1	101	rd	0111011	DIVUW
0000001	rs2	rs1	110	rd	0111011	REMW
0000001	rs2	rs1	111	rd	0111011	REMUW

31 27	26 25	24 20	19 15	14 12	11 7	6 0	
funct7		rs2	rs1	funct3	rd	opcode	R-type

RV32A Standard Extension

00010	aq	rl	00000	rs1	010	rd	0101111	LR.W
00011	aq	rl	rs2	rs1	010	rd	0101111	SC.W
00001	aq	rl	rs2	rs1	010	rd	0101111	AMOSWAP.W
00000	aq	rl	rs2	rs1	010	rd	0101111	AMOADD.W
00100	aq	rl	rs2	rs1	010	rd	0101111	AMOXOR.W
01100	aq	rl	rs2	rs1	010	rd	0101111	AMOAND.W
01000	aq	rl	rs2	rs1	010	rd	0101111	AMOOR.W
10000	aq	rl	rs2	rs1	010	rd	0101111	AMOMIN.W
10100	aq	rl	rs2	rs1	010	rd	0101111	AMOMAX.W
11000	aq	rl	rs2	rs1	010	rd	0101111	AMOMINU.W
11100	aq	rl	rs2	rs1	010	rd	0101111	AMOMAXU.W

RV64A Standard Extension (in addition to RV32A)

00010	aq	rl	00000	rs1	011	rd	0101111	LR.D
00011	aq	rl	rs2	rs1	011	rd	0101111	SC.D
00001	aq	rl	rs2	rs1	011	rd	0101111	AMOSWAP.D
00000	aq	rl	rs2	rs1	011	rd	0101111	AMOADD.D
00100	aq	rl	rs2	rs1	011	rd	0101111	AMOXOR.D
01100	aq	rl	rs2	rs1	011	rd	0101111	AMOAND.D
01000	aq	rl	rs2	rs1	011	rd	0101111	AMOOR.D
10000	aq	rl	rs2	rs1	011	rd	0101111	AMOMIN.D
10100	aq	rl	rs2	rs1	011	rd	0101111	AMOMAX.D
11000	aq	rl	rs2	rs1	011	rd	0101111	AMOMINU.D
11100	aq	rl	rs2	rs1	011	rd	0101111	AMOMAXU.D

31 27	26 25	24 20	19 15	14 12	11 7	6 0	
funct7		rs2	rs1	funct3	rd	opcode	R-type
rs3	funct2	rs2	rs1	funct3	rd	opcode	R4-type
imm[11:0]			rs1	funct3	rd	opcode	I-type
imm[11:5]		rs2	rs1	funct3	imm[4:0]	opcode	S-type

RV32F Standard Extension

imm[11:0]		rs1	010	rd	0000111	FLW
imm[11:5]		rs2	rs1	010	imm[4:0]	0100111	FSW
rs3	00	rs2	rs1	rm	rd	1000011	FMADD.S
rs3	00	rs2	rs1	rm	rd	1000111	FMSUB.S
rs3	00	rs2	rs1	rm	rd	1001011	FNMSUB.S
rs3	00	rs2	rs1	rm	rd	1001111	FNMADD.S
0000000		rs2	rs1	rm	rd	1010011	FADD.S
0000100		rs2	rs1	rm	rd	1010011	FSUB.S
0001000		rs2	rs1	rm	rd	1010011	FMUL.S
0001100		rs2	rs1	rm	rd	1010011	FDIV.S
0101100		00000	rs1	rm	rd	1010011	FSQRT.S
0010000		rs2	rs1	000	rd	1010011	FSGNJ.S
0010000		rs2	rs1	001	rd	1010011	FSGNJN.S
0010000		rs2	rs1	010	rd	1010011	FSGNJX.S
0010100		rs2	rs1	000	rd	1010011	FMIN.S
0010100		rs2	rs1	001	rd	1010011	FMAX.S
1100000		00000	rs1	rm	rd	1010011	FCVT.W.S
1100000		00001	rs1	rm	rd	1010011	FCVT.WU.S
1110000		00000	rs1	000	rd	1010011	FMV.X.W
1010000		rs2	rs1	010	rd	1010011	FEQ.S
1010000		rs2	rs1	001	rd	1010011	FLT.S
1010000		rs2	rs1	000	rd	1010011	FLE.S
1110000		00000	rs1	001	rd	1010011	FCLASS.S
1101000		00000	rs1	rm	rd	1010011	FCVT.S.W
1101000		00001	rs1	rm	rd	1010011	FCVT.S.WU
1111000		00000	rs1	000	rd	1010011	FMV.W.X

RV64F Standard Extension (in addition to RV32F)

1100000		00010	rs1	rm	rd	1010011	FCVT.L.S
1100000		00011	rs1	rm	rd	1010011	FCVT.LU.S
1101000		00010	rs1	rm	rd	1010011	FCVT.S.L
1101000		00011	rs1	rm	rd	1010011	FCVT.S.LU

31 27	26 25	24 20	19 15	14 12	11 7	6 0	
funct7		rs2	rs1	funct3	rd	opcode	R-type
rs3	funct2	rs2	rs1	funct3	rd	opcode	R4-type
imm[11:0]			rs1	funct3	rd	opcode	I-type
imm[11:5]		rs2	rs1	funct3	imm[4:0]	opcode	S-type

RV32D Standard Extension

imm[11:0]		rs1	011	rd	0000111	FLD
imm[11:5]		rs2	rs1	011	imm[4:0]	0100111	FSD
rs3	01	rs2	rs1	rm	rd	1000011	FMADD.D
rs3	01	rs2	rs1	rm	rd	1000111	FMSUB.D
rs3	01	rs2	rs1	rm	rd	1001011	FNMSUB.D
rs3	01	rs2	rs1	rm	rd	1001111	FNMADD.D
0000001		rs2	rs1	rm	rd	1010011	FADD.D
0000101		rs2	rs1	rm	rd	1010011	FSUB.D
0001001		rs2	rs1	rm	rd	1010011	FMUL.D
0001101		rs2	rs1	rm	rd	1010011	FDIV.D
0101101		00000	rs1	rm	rd	1010011	FSQRT.D
0010001		rs2	rs1	000	rd	1010011	FSGNJ.D
0010001		rs2	rs1	001	rd	1010011	FSGNJN.D
0010001		rs2	rs1	010	rd	1010011	FSGNJX.D
0010101		rs2	rs1	000	rd	1010011	FMIN.D
0010101		rs2	rs1	001	rd	1010011	FMAX.D
0100000		00001	rs1	rm	rd	1010011	FCVT.S.D
0100001		00000	rs1	rm	rd	1010011	FCVT.D.S
1010001		rs2	rs1	010	rd	1010011	FEQ.D
1010001		rs2	rs1	001	rd	1010011	FLT.D
1010001		rs2	rs1	000	rd	1010011	FLE.D
1110001		00000	rs1	001	rd	1010011	FCLASS.D
1100001		00000	rs1	rm	rd	1010011	FCVT.W.D
1100001		00001	rs1	rm	rd	1010011	FCVT.WU.D
1101001		00000	rs1	rm	rd	1010011	FCVT.D.W
1101001		00001	rs1	rm	rd	1010011	FCVT.D.WU

RV64D Standard Extension (in addition to RV32D)

1100001	00010	rs1	rm	rd	1010011	FCVT.L.D
1100001	00011	rs1	rm	rd	1010011	FCVT.LU.D
1110001	00000	rs1	000	rd	1010011	FMV.X.D
1101001	00010	rs1	rm	rd	1010011	FCVT.D.L
1101001	00011	rs1	rm	rd	1010011	FCVT.D.LU
1111001	00000	rs1	000	rd	1010011	FMV.D.X

31 27	26 25	24 20	19 15	14 12	11 7	6 0	
funct7		rs2	rs1	funct3	rd	opcode	R-type
rs3	funct2	rs2	rs1	funct3	rd	opcode	R4-type
imm[11:0]			rs1	funct3	rd	opcode	I-type
imm[11:5]		rs2	rs1	funct3	imm[4:0]	opcode	S-type

RV32Q Standard Extension

imm[11:0]		rs1	100	rd	0000111	FLQ
imm[11:5]		rs2	rs1	100	imm[4:0]	0100111	FSQ
rs3	11	rs2	rs1	rm	rd	1000011	FMADD.Q
rs3	11	rs2	rs1	rm	rd	1000111	FMSUB.Q
rs3	11	rs2	rs1	rm	rd	1001011	FNMSUB.Q
rs3	11	rs2	rs1	rm	rd	1001111	FNMADD.Q
0000011		rs2	rs1	rm	rd	1010011	FADD.Q
0000111		rs2	rs1	rm	rd	1010011	FSUB.Q
0001011		rs2	rs1	rm	rd	1010011	FMUL.Q
0001111		rs2	rs1	rm	rd	1010011	FDIV.Q
0101111		00000	rs1	rm	rd	1010011	FSQRT.Q
0010011		rs2	rs1	000	rd	1010011	FSGNJ.Q
0010011		rs2	rs1	001	rd	1010011	FSGNJN.Q
0010011		rs2	rs1	010	rd	1010011	FSGNJX.Q
0010111		rs2	rs1	000	rd	1010011	FMIN.Q
0010111		rs2	rs1	001	rd	1010011	FMAX.Q
0100000		00011	rs1	rm	rd	1010011	FCVT.S.Q
0100011		00000	rs1	rm	rd	1010011	FCVT.Q.S
0100001		00011	rs1	rm	rd	1010011	FCVT.D.Q
0100011		00001	rs1	rm	rd	1010011	FCVT.Q.D
1010011		rs2	rs1	010	rd	1010011	FEQ.Q
1010011		rs2	rs1	001	rd	1010011	FLT.Q
1010011		rs2	rs1	000	rd	1010011	FLE.Q
1110011		00000	rs1	001	rd	1010011	FCLASS.Q
1100011		00000	rs1	rm	rd	1010011	FCVT.W.Q
1100011		00001	rs1	rm	rd	1010011	FCVT.WU.Q
1101011		00000	rs1	rm	rd	1010011	FCVT.Q.W
1101011		00001	rs1	rm	rd	1010011	FCVT.Q.WU

RV64Q Standard Extension (in addition to RV32Q)

1100011	00010	rs1	rm	rd	1010011	FCVT.L.Q
1100011	00011	rs1	rm	rd	1010011	FCVT.LU.Q
1101011	00010	rs1	rm	rd	1010011	FCVT.Q.L
1101011	00011	rs1	rm	rd	1010011	FCVT.Q.LU

Table 24.2: Instruction listing for RISC-V

Table 24.3 lists the CSRs that have currently been allocated CSR addresses. The timers, counters, and floating-point CSRs are the only CSRs defined in this specification.

Number	Privilege	Name	Description
Floating-Point Control and Status Registers			
0x001	Read/write	fflags	Floating-Point Accrued Exceptions.
0x002	Read/write	frm	Floating-Point Dynamic Rounding Mode.
0x003	Read/write	fcsr	Floating-Point Control and Status Register (frm + fflags).
Counters and Timers			
0xC00	Read-only	cycle	Cycle counter for RDCYCLE instruction.
0xC01	Read-only	time	Timer for RDTIME instruction.
0xC02	Read-only	instret	Instructions-retired counter for RDINSTRET instruction.
0xC80	Read-only	cycleh	Upper 32 bits of cycle, RV32I only.
0xC81	Read-only	timeh	Upper 32 bits of time, RV32I only.
0xC82	Read-only	instreth	Upper 32 bits of instret, RV32I only.

Table 24.3: RISC-V control and status register (CSR) address map.