

Ê PHASOR TEMPLATES (Air: ε_r=μ_r=1)

Wavenumber per medium *nonmag.*

$k_i = \frac{\omega \sqrt{\epsilon_{r,i}}}{c}$ (rad/m) $\Rightarrow k_2 = k_1 \sqrt{\epsilon_{r,2}/\epsilon_{r,1}}$

Direction table $u \in \{x, y, z\} = \text{axis perp. to boundary}$

Inc dir	Inc	Refl	Trans
+û	$e^{-jk_1 u}$	$e^{+jk_1 u}$	$e^{-jk_2 u}$
-û	$e^{+jk_1 u}$	$e^{-jk_1 u}$	$e^{+jk_2 u}$

+û direction ⇔ Med 2 at u ≥ 0. Reflected sign flips, transmitted matches incident.

General template (incident has pol. ê, amplitude a₀):

$\hat{\mathbf{E}}^i = a_0 \hat{e} e^{\mp j k_1 u}$ (incident wave, Med 1)

$\hat{\mathbf{E}}^r = \Gamma a_0 \hat{e} e^{\pm j k_1 u}$ (reflected wave, Med 1)

$\hat{\mathbf{E}}^t = \tau a_0 \hat{e} e^{\mp j k_2 u}$ (transmitted wave, Med 2)

(lossy med 2: replace $e^{\mp j k_2 u}$ with $e^{\mp \alpha_2 u} e^{\mp j \beta_2 u}$)

Total in medium 1: $\mathbf{E}_1 = \mathbf{E}^i + \mathbf{E}^r$.

ê by polarization *plug into templates above*

Pol.	ê	Note
Lin. x̂	x̂	E _y = 0
Lin. ŷ	ŷ	E _x = 0
Lin. at 45°	(x̂ + ŷ)/√2	in phase
RHC	x̂ - j ŷ	δ = -π/2
LHC	x̂ + j ŷ	δ = +π/2
General	a _x x̂ + a _y e ^{jδ} ŷ	elliptical

Γ, τ act on ê unchanged. Only swap the polarization, not the formulas.

POWER REFLECTION & TRANSMISSION

% reflected *always*

$\%P_r = 100 |\Gamma|^2$

% transmitted *η-ratio matters!*

$\%P_t = 100 |\tau|^2 \frac{\eta_1}{\eta_2}$

Check: %P_r + %P_t = 100.

If medium 2 is denser (η₂ < η₁), |τ| > 1 but %P_t < 100% because of the η₁/η₂ factor.

LOSSY MEDIA — 5 CASES

Loss tangent $\epsilon' = \epsilon_r \epsilon_0, \epsilon_0 \approx 1/(36\pi \times 10^9)$

$\frac{\epsilon''}{\epsilon'} = \frac{\sigma}{\omega \epsilon_r \epsilon_0}$

Type	σ/ωε	ηc, α, β
Lossless	0	η = η ₀ /√ε _r exact; α = 0, β = ω√ε _r /c
Low-loss	< 10 ⁻²	$\frac{\eta_0}{\sqrt{\epsilon_r}} \approx \frac{\eta_0}{\sqrt{\epsilon_r}} \left(1 + j \frac{\sigma}{2\omega\epsilon'}\right); \alpha \approx \frac{\sigma\eta_0}{2\sqrt{\epsilon_r}}, \beta \approx \frac{\omega\sqrt{\epsilon_r}}{c}$
Quasi-cond.	10 ⁻² – 10 ²	exact: (η/√X) e ^{jθ} η, see below
Good cond.	> 10 ²	η _c ≈ (1+j)√π f μ σ; α ≈ β ≈ √π f μ σ
Magnetic	any	keep full √μ _r /ε _r η ₀

For Γ/τ: drop j correction; use η₀/√ε_r. Magnetic: keep μ_r.

Exact (quasi-cond) $X = \sqrt{1 + (\epsilon''/\epsilon')^2}$

$\alpha = \omega \sqrt{\frac{\mu \epsilon'}{2}} \sqrt{X - 1}$

$\beta = \omega \sqrt{\frac{\mu \epsilon'}{2}} \sqrt{X + 1}$

$\theta_\eta = \frac{1}{2} \arctan \frac{\sigma}{\omega \epsilon'}$

SNELL'S LAW — OBLIQUE INCIDENCE

Single boundary *angles from normal*

$\sin \theta_2 = \sin \theta_1 \sqrt{\frac{\epsilon_{r1}}{\epsilon_{r2}}} = \sin \theta_1 \frac{n_1}{n_2}$

Multilayer chain *stack of slabs 1 → 2 → 3 → 4*

$\sin \theta_{i+1} = \sin \theta_i \sqrt{\frac{\epsilon_{r,i}}{\epsilon_{r,i+1}}}$

Air–slabs–air *shortcut outer media identical*

$\theta_{\text{exit}} = \theta_{\text{incident}}$

Snell only sets angles. Reflection/transmission magnitudes need Fresnel coefficients (parallel vs perpendicular).

LATERAL DISPLACEMENT

Beam offset through N slabs thickness t_i, refracted angle inside slab i

Slab-indexed θ_i = angle inside slab i

$d = \sum_{i=1}^N t_i \tan \theta_i$

Angle-indexed (HW3 P3 style) θ₁ = incident, θ_{i+1} = inside slab i

$d = \sum_{i=1}^N t_i \tan \theta_{i+1}$

Same physics, different numbering. In HW3 P3: slab 1 contributes t₁ tan θ₂, slab 2 contributes t₂ tan θ₃. The angle in the formula is always the one the ray makes inside that slab.

Air–slab–air: exit angle returns to θ₁ but is laterally shifted by d.

TABLE 8-2 — Γ, τ, R, T SUMMARY

Med. 1 (z < 0) incident side; Med. 2 (z ≥ 0) transmitted.

Shorthand: c_i = cos θ_i, c_t = cos θ_t.

	Normal (θ _i = 0)	⊥ pol	∥ pol
Γ refl. wave	$\frac{\eta_2 - \eta_1}{\eta_2 + \eta_1}$	$\frac{\eta_2 c_i - \eta_1 c_t}{\eta_2 c_i + \eta_1 c_t}$	$\frac{\eta_2 c_t - \eta_1 c_i}{\eta_2 c_t + \eta_1 c_i}$
τ trans. wave	$\frac{2\eta_2}{\eta_2 + \eta_1}$	$\frac{2\eta_2 c_i}{\eta_2 c_i + \eta_1 c_t}$	$\frac{2\eta_2 c_t}{\eta_2 c_t + \eta_1 c_i}$
τ rel.	τ = 1 + Γ	τ _⊥ = 1 + Γ _⊥	τ _∥ = (1 + Γ _∥) $\frac{c_i}{c_t}$
R refl. pwr	Γ ²	Γ _⊥ ²	Γ _∥ ²
T trans. pwr	τ ² $\frac{\eta_1}{\eta_2}$	τ _⊥ ² $\frac{\eta_1 c_t}{\eta_2 c_i}$	τ _∥ ² $\frac{\eta_1 c_t}{\eta_2 c_i}$
R + T total	T = 1 - R	T _⊥ = 1 - R _⊥	T _∥ = 1 - R _∥

Notes: sin θ_t = √μ₁ε₁/μ₂ε₂ sin θ_i; nonmag. ⇒ η₂/η₁ = n₁/n₂.

Intrinsic impedance η_i *plug into table above*

$\eta_i = \sqrt{\frac{\mu_r}{\epsilon_r}} \eta_0 \xrightarrow{\mu_r=1} \frac{\eta_0}{\sqrt{\epsilon_{r,i}}} \text{ (}\Omega\text{)} \quad \eta_0 = 120\pi \approx 377 \Omega$

Default μ_r = 1 (air, dielectric). Use μ_r ≠ 1 only if problem says “ferromagnetic”/iron/ferrite/etc.

Low-loss correction η_c σ/(ωε) ≪ 1

$\eta_c \approx \sqrt{\frac{\mu}{\epsilon'}} \left(1 + j \frac{\sigma}{2\omega\epsilon'}\right) \xrightarrow{\text{drop } j} \frac{\eta_0}{\sqrt{\epsilon_r}}$

For Γ/τ just use η₀/√ε_r. The j term is for |η_c|, θ_η. See LOSSY MEDIA — 5 CASES for all regimes.

RECTANGULAR WAVEGUIDE — MODES

TE mode E_z = 0, H_z ≠ 0

TM mode H_z = 0, E_z ≠ 0

Dimensions a × b with a > b along x̂, ŷ; wave in ẑ.

E_x form (TE) *read m, n from arguments*

$E_x \propto \cos\left(\frac{m\pi x}{a}\right) \sin\left(\frac{n\pi y}{b}\right) \sin(\omega t - \beta z)$

coef. on x = mπ/a; coef. on y = nπ/b.

Identify TE_{m,n} vs TM_{m,n} *cos/sin pattern of E_x is identical for both!*

1. Read the problem statement (e.g. “a TE wave” → TE).

2. If m = 0 or n = 0 in the mode label ⇒ must be TE (TM forbids 0).

3. Source field H_z(x, y) given ⇒ TE. Source field E_z(x, y) given ⇒ TM.

TE allows at least one of m, n ≥ 1 (other can be 0). TM needs both m, n ≥ 1. That’s why TE₁₀ exists but TM₁₀ doesn’t.

TABLE 8-3 — FULL FIELD COMPONENTS

Shorthand: C_X = cos $\frac{m\pi x}{a}$, S_X = sin $\frac{m\pi x}{a}$, C_Y = cos $\frac{n\pi y}{b}$, S_Y = sin $\frac{n\pi y}{b}$. All fields carry an e^{-jβz} factor (omitted below). k_c² = (mπ/a)² + (nπ/b)².

TE mode *generator: Ĥ_z*

$\hat{H}_z = H_0 C_X C_Y$

$\hat{E}_x = \frac{j\omega\mu}{k_c^2} \left(\frac{n\pi}{b}\right) H_0 C_X S_Y$

$\hat{E}_y = -\frac{j\omega\mu}{k_c^2} \left(\frac{m\pi}{a}\right) H_0 S_X C_Y$

$\hat{E}_z = 0, \quad \hat{H}_x = -\hat{E}_y/Z_{TE}, \quad \hat{H}_y = \hat{E}_x/Z_{TE}$

TM mode *generator: Ê_z*

$\hat{E}_z = E_0 S_X S_Y$

$\hat{E}_x = -\frac{j\beta}{k_c^2} \left(\frac{m\pi}{a}\right) E_0 C_X S_Y$

$\hat{E}_y = -\frac{j\beta}{k_c^2} \left(\frac{n\pi}{b}\right) E_0 S_X C_Y$

$\hat{H}_z = 0, \quad \hat{H}_x = -\hat{E}_y/Z_{TM}, \quad \hat{H}_y = \hat{E}_x/Z_{TM}$

TEM (plane wave) for reference: Ê_x = E₀ e^{-jβz}, Ĥ_y = Ê_x/η, f_c N/A, k = ω√μ̵.

CUTOFF FREQUENCY

f_{m,n} *m, n integers ≥ 0 (not both zero)*

$f_{mn} = \frac{u_{p0}}{2} \sqrt{\left(\frac{m}{a}\right)^2 + \left(\frac{n}{b}\right)^2} \text{ (Hz)}$

Common cutoffs (a > b)

Quantity	Formula
u _{p0}	c/√ε _r (hollow: u _{p0} = c)
TE ₁₀	u _{p0} /(2a) (dominant)
TE ₀₁	u _{p0} /(2b)
TE ₂₀	u _{p0} /a = 2f ₁₀
TE ₁₁ , TM ₁₁	$\frac{u_{p0}}{2} \sqrt{1/a^2 + 1/b^2}$

Propagation requires f > f_{m,n}.

ε_r FROM DISPERSION

Given ω, β, mode (m, n)

$\epsilon_r = \frac{c^2}{\omega^2} \left[\beta^2 + \left(\frac{m\pi}{a}\right)^2 + \left(\frac{n\pi}{b}\right)^2 \right]$

Sanity: β in rad/m, a, b in m, ω in rad/s.

WAVE IMPEDANCE & H_y

$Z_{TE} = \frac{\eta}{\sqrt{1 - (f_c/f)^2}} \text{ (}\Omega\text{)} \quad Z_{TM} = \eta \sqrt{1 - (f_c/f)^2}$

$\eta = \frac{\eta_0}{\sqrt{\epsilon_r}} \quad H_y = \frac{E_x}{Z_{TE}} \text{ (TE mode)}$

Z_{TE} > η always (denominator < 1); Z_{TM} < η.

GROUP VELOCITY & TRAVEL TIME

$u_g = u_{p0} \sqrt{1 - (f_{mn}/f)^2} \text{ (m/s)}$

$u_p = \frac{u_{p0}}{\sqrt{1 - (f_{mn}/f)^2}} \text{ (m/s)} \Rightarrow u_p u_g = u_{p0}^2 \text{ (m}^2\text{/s}^2\text{)}$

t = L/u_g (s) *travel time through guide of length L*

Higher modes have lower u_g ⇒ they arrive later. Group delay spread = sum over excited modes.

BOUNDARY

η₁, η₂ — imp. (Ω)

Γ — refl. coeff (unitless)

τ = 1 + Γ — trans. coeff

k_i = ω√ε_{r,i}/c (rad/m)

α₂, β₂ — if med 2 lossy

z = 0 — boundary plane

η₀ = 120π ≈ 377 Ω

SNELL / OBLIQUE

θ_i, θ_t — angles from normal

n_i = √ε_{r,i} — index of refr.

t_i — slab thickness (m)

d — lateral disp. (m)

plane of inc. = plane of k̂ + normal

⊥: E ⊥ this plane

∥: E ∥ this plane

WAVEGUIDE

a, b — wide, narrow dim. (m); a > b

m, n — mode indices (int.)

f_{mn} — cutoff (Hz)

μ — prop. const (rad/m)

Z_{TE}/Z_{TM} — wave imp. (Ω)

E_x, H_y — field comps (V/m, A/m)

η = η₀/√ε_r

VELOCITIES

u_{p0} = c/√ε_r — bulk phase vel.

u_p = u_{p0}/√1 - (f_c/f)²

u_g = u_{p0}√1 - (f_c/f)²

u_p u_g = u_{p0}²

t = L/u_g — travel time

c = 3 × 10⁸ m/s

POWER & UNITS

%P_r = 100|Γ|²

%P_t = 100|τ|² η₁/η₂

%P_r + %P_t = 100

σ (S/m), ε (F/m), μ (H/m)

ε₀ = 8.85 × 10⁻¹² F/m

μ₀ = 4π × 10⁻⁷ H/m

1/(36π) × 10⁻⁹ ≈ ε₀