

Login name: twallema Password: XXXXXXXXXXXXXXXXX

Processor: Intel Core i7-14700 (8P @ 2.1 GHz + 12E @ 1.5 GHz)

Network card name: wlx984827ebfcf4

How to safely reboot this device?

```
sudo systemctl stop actions.runner.BentoLab-DiseaseDynamics.twallema-gh-runner.service
```

```
sudo reboot
```

How to check the status of the GH runner?

```
sudo systemctl status actions.runner.BentoLab-DiseaseDynamics.twallema-gh-runner.service
```

How to restart the GH runner after an incorrect reboot?

```
cd /home/twallema/actions-runner
```

```
sudo ./svc.sh uninstall
```

```
sudo ./svc.sh install
```

```
sudo ./svc.sh start
```

The procedure is successful if the service is active and the output says: "Listening for jobs"

How to connect this machine to eduroam?

```
Sudo nmcli connection add type wifi ifname wlx984827ebfcf4 con-name eduroam ssid eduroam -- wifi-sec.key-mgmt wpa-eap 802-1x.eap peap 802-1x.phase2-auth mschapv2 802-1x.identity "<netID>@cornell.edu" 802-1x.password "<password>"
```