PS/2 Keyboard · Scan Code Set 2

US QWERTY • All byte values are hexadecimal • Ordered by make code

Standard keys · 0x01–0x3C

Key	Make · pressed	Break · released
F9	0x01	0xF0, 0x01
F5	0x03	0xF0, 0x03
F3	0x04	0xF0, 0x04
F1	0x05	0xF0, 0x05
F2	0x06	0xF0, 0x06
F12	0x07	0xF0, 0x07
F10	0x09	0xF0, 0x09
F8	0x0A	0xF0, 0x0A
F6	0x0B	0xF0, 0x0B
F4	0x0C	0xF0, 0x0C
Tab	0x0D	0xF0, 0x0D
` (back tick)	0x0E	0xF0, 0x0E
Left Alt	0x11	0xF0, 0x11
Left Shift	0x12	0xF0, 0x12
Left Control	0x14	0xF0, 0x14
Q	0x15	0xF0, 0x15
1	0x16	0xF0, 0x16
Z	0x1A	0xF0, 0x1A
S	0x1B	0xF0, 0x1B
A	0x1C	0xF0, 0x1C
W	0x1D	0xF0, 0x1D
2	0x1E	0xF0, 0x1E
C	0x21	0xF0, 0x21
X	0x22	0xF0, 0x22
D	0x23	0xF0, 0x23
E	0x24	0xF0, 0x24
4	0x25	0xF0, 0x25
3	0x26	0xF0, 0x26
Space	0x29	0xF0, 0x29
V	0x2A	0xF0, 0x2A
F	0x2B	0xF0, 0x2B
T	0x2C	0xF0, 0x2C
R	0x2D	0xF0, 0x2D
5	0x2E	0xF0, 0x2E
N	0x31	0xF0, 0x31
B	0x32	0xF0, 0x32
H	0x33	0xF0, 0x33
G	0x34	0xF0, 0x34
Y	0x35	0xF0, 0x35
6	0x36	0xF0, 0x36
M	0x3A	0xF0, 0x3A
J	0x3B	0xF0, 0x3B
U	0x3C	0xF0, 0x3C

PS/2 Keyboard · Scan Code Set 2

US QWERTY • All byte values are hexadecimal • Ordered by make code

Standard keys · 0x3D–0x83

Key	Make · pressed	Break · released
7	0x3D	0xF0, 0x3D
8	0x3E	0xF0, 0x3E
,	0x41	0xF0, 0x41
K	0x42	0xF0, 0x42
I	0x43	0xF0, 0x43
O	0x44	0xF0, 0x44
0 (zero)	0x45	0xF0, 0x45
9	0x46	0xF0, 0x46
.	0x49	0xF0, 0x49
/	0x4A	0xF0, 0x4A
L	0x4B	0xF0, 0x4B
;	0x4C	0xF0, 0x4C
P	0x4D	0xF0, 0x4D
-	0x4E	0xF0, 0x4E
'	0x52	0xF0, 0x52
[	0x54	0xF0, 0x54
=	0x55	0xF0, 0x55
CapsLock	0x58	0xF0, 0x58
Right Shift	0x59	0xF0, 0x59
Enter	0x5A	0xF0, 0x5A
]	0x5B	0xF0, 0x5B
\	0x5D	0xF0, 0x5D
Backspace	0x66	0xF0, 0x66
Keypad 1	0x69	0xF0, 0x69
Keypad 4	0x6B	0xF0, 0x6B
Keypad 7	0x6C	0xF0, 0x6C
Keypad 0	0x70	0xF0, 0x70
Keypad .	0x71	0xF0, 0x71
Keypad 2	0x72	0xF0, 0x72
Keypad 5	0x73	0xF0, 0x73
Keypad 6	0x74	0xF0, 0x74
Keypad 8	0x75	0xF0, 0x75
Escape	0x76	0xF0, 0x76
NumberLock	0x77	0xF0, 0x77
F11	0x78	0xF0, 0x78
Keypad +	0x79	0xF0, 0x79
Keypad 3	0x7A	0xF0, 0x7A
Keypad -	0x7B	0xF0, 0x7B
Keypad *	0x7C	0xF0, 0x7C
Keypad 9	0x7D	0xF0, 0x7D
ScrollLock	0x7E	0xF0, 0x7E
F7	0x83	0xF0, 0x83

PS/2 Keyboard · Scan Code Set 2

US QWERTY • All byte values are hexadecimal • Ordered by make code

Extended keys · 0xE0 prefix

Key	Make · pressed	Break · released
Multimedia: WWW search	0xE0, 0x10	0xE0, 0xF0, 0x10
Right Alt	0xE0, 0x11	0xE0, 0xF0, 0x11
Right Control	0xE0, 0x14	0xE0, 0xF0, 0x14
Multimedia: Previous track	0xE0, 0x15	0xE0, 0xF0, 0x15
Multimedia: WWW favourites	0xE0, 0x18	0xE0, 0xF0, 0x18
Left GUI	0xE0, 0x1F	0xE0, 0xF0, 0x1F
Multimedia: WWW refresh	0xE0, 0x20	0xE0, 0xF0, 0x20
Multimedia: Volume down	0xE0, 0x21	0xE0, 0xF0, 0x21
Multimedia: Mute	0xE0, 0x23	0xE0, 0xF0, 0x23
Right GUI	0xE0, 0x27	0xE0, 0xF0, 0x27
Multimedia: WWW stop	0xE0, 0x28	0xE0, 0xF0, 0x28
Multimedia: Calculator	0xE0, 0x2B	0xE0, 0xF0, 0x2B
Apps	0xE0, 0x2F	0xE0, 0xF0, 0x2F
Multimedia: WWW forward	0xE0, 0x30	0xE0, 0xF0, 0x30
Multimedia: Volume up	0xE0, 0x32	0xE0, 0xF0, 0x32
Multimedia: Play/pause	0xE0, 0x34	0xE0, 0xF0, 0x34
ACPI: Power	0xE0, 0x37	0xE0, 0xF0, 0x37
Multimedia: WWW back	0xE0, 0x38	0xE0, 0xF0, 0x38
Multimedia: WWW home	0xE0, 0x3A	0xE0, 0xF0, 0x3A
Multimedia: Stop	0xE0, 0x3B	0xE0, 0xF0, 0x3B
ACPI: Sleep	0xE0, 0x3F	0xE0, 0xF0, 0x3F
Multimedia: My computer	0xE0, 0x40	0xE0, 0xF0, 0x40
Multimedia: Email	0xE0, 0x48	0xE0, 0xF0, 0x48
Keypad /	0xE0, 0x4A	0xE0, 0xF0, 0x4A
Multimedia: Next track	0xE0, 0x4D	0xE0, 0xF0, 0x4D
Multimedia: Media select	0xE0, 0x50	0xE0, 0xF0, 0x50
Keypad Enter	0xE0, 0x5A	0xE0, 0xF0, 0x5A
ACPI: Wake	0xE0, 0x5E	0xE0, 0xF0, 0x5E
End	0xE0, 0x69	0xE0, 0xF0, 0x69
Cursor left	0xE0, 0x6B	0xE0, 0xF0, 0x6B
Home	0xE0, 0x6C	0xE0, 0xF0, 0x6C
Insert	0xE0, 0x70	0xE0, 0xF0, 0x70
Delete	0xE0, 0x71	0xE0, 0xF0, 0x71
Cursor down	0xE0, 0x72	0xE0, 0xF0, 0x72
Cursor right	0xE0, 0x74	0xE0, 0xF0, 0x74
Cursor up	0xE0, 0x75	0xE0, 0xF0, 0x75
Page down	0xE0, 0x7A	0xE0, 0xF0, 0x7A
Page up	0xE0, 0x7D	0xE0, 0xF0, 0x7D

Special sequences

Print Screen pressed: `0xE0, 0x12, 0xE0, 0x7C`

Print Screen released: `0xE0, 0xF0, 0x7C, 0xE0, 0xF0, 0x12`

Pause pressed: `0xE1, 0x14, 0x77, 0xE1, 0xF0, 0x14, 0xF0, 0x77`

No Pause release sequence was supplied in the source table.