Additional Information

This notice includes information related to your product. Please read this sheet carefully and retain for your reference.

1. Jumper Setting

In normal use, the V9958 video board requires a jumper between pins 9 and 11 of J2.

The included pin header has this jumper pre-installed for you.

This jumper is not required if external hardware is being used to provide video sync information.

In cases where a daughterboard is being connected to J2 and external sync is not being used, this connection should be made on the daughterboard (or, for example, a jumper may be provided for this purpose).

2. Use with revision 1.2 mainboard

In order to use your r1.1 V9958 video display board with the revision 1.2 main board, you will need to solder a jumper wire between pin 14 of IC2 and pin 57 (DTACK) of the main J1 connector.

When looking at the solder-side of the board, pin 57 of J1 is fourth-from right on the bottom row.

See the below (rather untidy) image: