

Heights 6 Radio Communications

Set up the BTECH UV-PRO for **Heights 6**, then make short, disciplined calls.

! WARNING — URGENT ACTION

Life safety comes first. Call 911 when available for an immediate threat. Do not delay evacuation, enter a hazard, or rely on this radio as your only way to summon help.

PROGRAM HEIGHTS 6

† LOCAL INFORMATION — VERIFY BEFORE APPROVAL

Name: Heights 6 | **Radio:** BTECH UV-PRO

RX: 462.38750 MHz / DCS 331N | **TX:** 467.38750 MHz / DCS 331N

Repeater site: KOCE-TV transmitter site, 16711 E Skyline Dr, La Habra Heights, CA 90631

- 1 Connect.** Open the UV-PRO app on the paired phone, select the correct radio, and read its channel list.
- 2 Create.** Select an unused memory, name it **Heights 6**, and use separate RX and TX fields.
- 3 Enter the values exactly:** RX 462.38750 MHz and TX 467.38750 MHz. Do not reverse them.
- 4 Set both DCS/DQT fields to 331, normal (N).** Do not select inverted/reverse polarity.
- 5 Write and verify.** Synchronize, reconnect, and confirm the name and four values. Do not change other fields.

△ CAUTION — PREVENT HARM

If the app does not clearly show separate RX/TX frequencies and DCS values, stop and ask the radio lead. Never transmit on an unknown channel.

CHECK THE RADIO BEFORE DUTY

- ☐ Battery charged; spare or cable ready
- ☐ Antenna secure; volume audible
- ☐ **Heights 6** selected; callsign known
- ☐ Push-to-talk protected from accidental use
- ☐ Receive checked; transmit only if authorized

BEFORE A NET BEGINS

Monitor first. To reach a member, say their callsign, then yours: **“145, 238.”** Wait for “238, go ahead.” Use plain language and confirmed facts.

Identification: use your three-digit callsign. Address city personnel by title (for example, **Public Works** or **Fire Chief**). Follow instructions for any required station ID.

SOURCES

La Habra Heights Fire Watch operational brief, received September 24, 2026. Verify the workflow against current BTECH UV-PRO documentation.

Heights 6 Radio Communications — continued

On a directed net, listen, wait to be recognized, and report only the essential facts.

! WARNING — URGENT ACTION

Emergency traffic has priority. At a break, say “**Emergency traffic**” and your callsign, then release push-to-talk and wait. Do not interrupt routine traffic.

DIRECTED-NET PROCEDURE

- 1 Listen.** Do not answer another station's call or transmit during a Net Control update.
- 2 Call:** “Net Control, [callsign].” Release and wait. If unanswered, pause and try once more.
- 3 Wait.** After “[callsign], go ahead,” press, pause, and give one concise report.
- 4 Report** location, observation and time, threats, action taken, and help needed. Label rumor as rumor.
- 5 Confirm.** Read back critical details. End with your callsign and resume monitoring.

NET CONTROL UPDATES

- **High activity:** every 15 minutes—:00, :15, :30, :45
- **Quieter:** every 30 minutes—:00, :30
- **Stand-down:** every 60 minutes—:00

Hold routine calls when an update is due.

GOOD RADIO HABITS

- Think first; press, pause, and speak clearly.
- Give streets, addresses, landmarks, and directions.
- Say “affirmative” or “negative” when clarity matters.
- Do not share sensitive details, speculate, or argue.

SAMPLE EXCHANGES

Routine report

145: “Net Control, 145.”

Net Control: “145, go ahead.”

145: “Skyline at Cypress: light gray smoke north, first seen two minutes ago. No flame visible. 145.”

Net Control: “145, observe safely and report changes.”

145: “Observe safely. 145.”

Emergency traffic

238: “Emergency traffic, 238.”

Net Control: “All stations hold. 238, go ahead.”

238: “Arcing line across East Road at 17000. Road blocked; people moving back. Request response. 238.”

Net Control: “238, keep everyone clear; response requested.”

238: “Keep clear. 238.”

CLOSING OR LEAVING THE NET

Do not leave silently. Ask to check out or report a radio change. Note final instructions. After duty, report problems, recharge, and do not alter Heights 6.

SOURCES

— Fire Watch operational brief, received September 24, 2026. Draft; verify against current BTECH documentation.