

CROSSSAFE · DESIGN DECISIONS REGISTER

CrossSafe design decisions register

Design Molecule Lab · designmolecule.com

DOCUMENT CONTROL

Document ID	CRS-DEC-001	Version	0.1
Status	Draft	Date	2026-09-30
Author	Amish Chadha	License	CERN-OHL-S-2.0
Project TRL	TRL 3 Proof of concept		
Repository	github.com/BoujeeEnjinia1701/crosssafe		
Source	docs/06-design-decisions.md @ uncommitted		

REVISION HISTORY

Version	Date	Author	Change
0.1	2026-09-30	Amish Chadha	Register opened with the open decisions from the review note, CRS-DDR-001 to CRS-DDR-003 and the build plan work

CrossSafe design decisions register

Every design decision still to be made, and every decision made, in one place. Each decision is argued in full in its decision record under `docs/decisions/` ; this register is the index Amish works from. The build plan (`docs/05-build-plan.md`) describes the design as it stands and does not list open decisions.

■ Open decisions

#	Decision needed	Options	Recommendation	Affects in the build	Source
1	Budget for the existing-pole prototype: the parts added to make the design buildable take it to \$360.00, \$10.00 over budget_usd (\$350), so R15 is not met on paper (\$720.00 per crossing against \$700)	(a) raise budget_usd to \$375; (b) find \$10.00 of savings now; (c) keep \$350 and accept R15 not met until prices are quoted at TRL 4	(a)	Parts list only; the build is the same	CRS-DDR-003, A1; CRS-CAL-001 v0.3, [H1] to [H3]
2	Accept the design for construction changes P1 to P11 (keyed saddles and bands for every part on the pole, sign nearer the pole, folded light bar, mounting plate, radar arm, welded panel bracket and rails, gland layout, anti-rotation bolt through the sign)	(a) accept; (b) ask for a different arrangement of any of them	(a)	The whole build plan	CRS-DDR-003, Table 1 and A3
3	Panel mount on existing poles that the post-top socket does not fit (poles other than about 114 mm, poles that are taller or carry a luminaire)	(a) reducing sleeves for 76 and 89 mm poles; (b) a side-of-pole panel arm on two more saddles; (c) limit the existing-pole kit to free-topped poles of about 114 mm	(b), designed once the pilot site's poles are known; the prototype uses (c)	Panel bracket (section 3.8) for site kits; not the prototype	CRS-DDR-003, A2
4	Sign rotation on existing poles under about 70 mm, where keyed saddles alone do not hold the 175 N·m gust torsion (R9 at risk)	(a) a third saddle and band at the sign on poles under 76 mm; (b) limit the existing-pole range to 76 mm and up; (c) a through-bolt where the pole owner allows drilling	(a)	One more saddle and band on small poles; not the prototype (114.3 mm post)	CRS-DDR-002, N1
5	Pilot partner, site and jurisdiction, including a road authority willing to review the design	Not yet named	None yet; no preference stated	Antenna band, sign design and colour, flash pattern, mounting heights, whether the pilot light is allowed	CRS-DDR-001, O1; CRS-DDR-002
6	Visors and bezels on the LED heads (in the renders, not in the model)	(a) add them to the model and the wind area; (b) leave them out	(a): they cut sun phantom on the lenses	Head modules bought with visors; light bar wind area	REVIEW 2026-09-26, item 2
7			(a)	Sun shield (section 3.9)	

#	Decision needed	Options	Recommendation	Affects in the build	Source
	Louvre slots in the sun shield walls (in the renders, not in the model)	(a) keep as appearance only until the shield is measured; (b) adopt now		stays plain sheet	REVIEW 2026-09-26, item 3
8	Sign colour shown in the renders (fluorescent yellow-green)	(a) show it in renders and leave the colour to the road authority; (b) another colour	(a)	Sign sheeting is bought to the local design	REVIEW 2026-09-26, item 4
9	Small appearance differences in the renders (pilot light housing 36 mm, saddle flange at the sign, band screw housings turned away)	(a) accept as appearance detail; (b) bring the renders into line with the model	(a); the renders are stale anyway after item 2	None	REVIEW 2026-09-26, item 5

■ To confirm when parts are bought

#	What to confirm	Why it matters	Source
1	The enclosure model: its internal plate and boss positions, its lug kit, and that the lid is on the 260 x 300 face away from the back	They set the internal plate layout, the lug holes in the mounting plate and the shield fit	CRS-DDR-003, P4
2	The solar panel frame has a flat back lip at least 15 mm wide on its long edges	The rails bolt through it	CRS-DDR-003, P8
3	Each LED head's flange covers a 128 x 50 mm window, its body is no deeper than 25 mm, and its screw pattern	They set the light bar windows and leave 16 mm between facing heads	CRS-DDR-003, P3
4	The push-button station fixes to a flat face with two bolts 40 mm apart (or an adaptor plate is needed)	It bolts to a saddle's two tapped holes	CRS-DDR-003, P9
5	The radar housing's two base screws are 50 mm apart and the PIR's neck is 12 mm or less	They set the radar arm's holes	CRS-DDR-003, P7
6	The battery, charger and controller board fit the sizes in the build plan (151 x 95 x 98, 40 x 90 x 60, 180 x 100 mm)	The internal layout and the battery strap are drawn to them	CRS-DDR-003, P4
7	The band and buckle reach 1,000 N of tension with the banding tool, and the keyed saddle's grip friction is about 0.4	CRS-CAL-001 assumes both for the sign torsion	CRS-CAL-001, [G6c]
8	The test post's top is square and open (or capped flush) so the bracket cap sits on it	The socket's cap rests on the pole's top edge	CRS-DDR-003, P8

■ Decisions made

Date	Decision	Decided by	Record
2026-09-25	TRL 2 review items D1 to D9: <code>budget_usd</code> covers one assembly on an existing pole; PIR gating of the radar; existing poles first and a 114.3 x 3.6 mm post where a new one is needed; FHWA IA-21 baseline; button plus passive detection; LoRa side-to-side link; FieldNode radio core with CrossSafe's own 12 V power; pedestrian pilot light where allowed; no change to the pitch	Amish: "i accept all your recommendations, go with them across all repos."	CRS-DDR-001, CRS-DDR-002
2026-09-25	\$750 site-trial budget for a two-sided crossing, to apply when a site trial starts (on hold with TRL 4); <code>budget_usd</code> stays \$350	Amish, same instruction	CRS-DDR-002, O2
2026-09-25	Ventilated sun shield on the enclosure (E1); anti-rotation bolt on new posts and keyed saddles on existing poles (E2); timed installation trial, on hold with TRL 4 (E3)	Amish, same instruction	CRS-DDR-002
2026-09-26	CrossSafe chosen for the first batch of product renders	Amish	REVIEW 2026-09-26
2026-09-30	Build plan format approved; open decisions kept in this register, not in the build plan	Amish: "this is the correct build plan ... this is a good quality document format. Extend this across all the other repos"	This register; CRS-BLD-001
2026-09-30	Make the design physically buildable while drawing the build plan	Amish: "If you are realising that the design cannot be built as per concept - fix the design assumptions to match and be physically feasible as you draw the illustrations."	CRS-DDR-003 (changes open for his review, open decision 2)