

H2BENCH · DESIGN PRECIS

H2Bench design precis

Open Hardware Portfolio · amishchadha.com

DOCUMENT CONTROL

Document ID	HBN-PRC-001	Version	0.3
Status	Draft	Date	2026-09-25
Author	Amish Chadha	License	CERN-OHL-S-2.0
Project TRL	TRL 3 Proof of concept		
Repository	github.com/BoujeeEnjinia1701/h2bench		
Source	docs/02-concept.md @ 8f87588		

REVISION HISTORY

Version	Date	Author	Change
0.3	2026-09-25	Amish Chadha	TRL 3 update; choices adopted for TRL 3 (HBN-DDR-001), numbers checked in HBN-CAL-001, parametric model and HBN-DWG-001, vent needle valve, media refreshed
0.2	2026-09-25	Amish Chadha	Populate to TRL 2 (architecture, first-order numbers, design choices, safety, media)
0.1	2026-09-25	Amish Chadha	Initial scaffold


H2Bench design precis

■ Summary

H2Bench is a teaching bench that turns about 21 Wh of electricity into about 4.5 L of usable hydrogen in an 18 min fill, holds it in a 2 L tank at up to 300 kPa gauge, and returns about 5 Wh through a 12 W class fuel cell over about 29 min. Every stage is metered, so students measure a round-trip efficiency of about 25 % (estimate, HHV basis) from their own data and see where the other 75 % goes. The bench sits on an existing lab table under a canopy hood and runs only while the portfolio's H2Guard detector, extraction fan and interlock are active. All figures are checked in the calculation note HBN-CAL-001; they are paper estimates, not measurements.

H2Bench

CONCEPT, NOT FOR FABRICATION



Grey: Lab table (existing), Person, 1.75 m (scale) for scale

Figure 1. H2Bench on an existing lab table with a 1.75 m person for scale. Energy flows left to right: power supply, water, electrolyzer, gas treatment, buffer tank, regulator, fuel cell and lamp. Massing-plus model from `cad/src/model.py`.

■ How it works

A lesson runs in two halves.

1. **Fill (about 18 min).** The bench power supply (4) drives the PEM electrolyzer stack (6) in constant-current mode at about 9 A and 7.8 V. Deionized water from the reservoir (5) is split: oxygen vents into the hood, and hydrogen passes through the separator and drier (7), the check valve and flame arrestor (8), and into the buffer tank (9). The electrolyzer pushes the tank from 70 to 300 kPa gauge on its own; there is no compressor. Students log current, voltage, tank pressure and temperature, and compute the hydrogen made from the gas law and from Faraday's law. The difference is the Faraday efficiency.
2. **Discharge (about 29 min).** The solenoid valve and regulator (11) feed the fuel cell (12) at about 50 kPa gauge. The fuel cell runs the electronic load and lamp (13) at about 1.5 A. Students log power out and tank pressure fall, and plot the fuel cell's polarization curve by stepping the load.

The meters and logger (14) record every quantity at 1 Hz to a CSV file. The H2Guard sensor at the high point of the canopy hood (15) watches for hydrogen; on alarm it cuts the power supply output, closes the tank solenoid and runs the extraction fan at full speed.

H2Bench: energy per lesson cycle, HHV basis (estimates, HBN-CAL-001)

CONCEPT, NOT FOR FABRICATION




Figure 2. Energy per lesson cycle, HHV basis, from HBN-CAL-001. All values are paper estimates: electrolyzer 72.2 % (voltage efficiency 75.9 %, Faraday efficiency 95 %), 2 % lost to leaks and venting in storage, fuel cell 35.5 % net (0.60 V per cell, 95 % fuel utilization, 0.9 W fan and controls).

■ Main components

Table 1. Main components. Numbers match `bom/bom.csv` and Figure 3.

No.	Component	Function	Key figure (estimate)
1	Bench deck and extrusion frame	Carries everything, sits on the lab table	900 x 450 mm
2	Instrument back panel	Printed energy-chain schematic; carries the meters	570 mm tall
3	Canopy hood, duct and posts	Collects rising hydrogen at one point for sensing and extraction	100 mm duct
4	Bench DC power supply	Constant-current drive for the electrolyzer	0 to 30 V, 0 to 10 A
5	DI water reservoir and deionizer	Feed water at 1 μ S/cm or less	About 3.4 g water used per fill
6	PEM electrolyzer stack	Splits water; pressurizes the tank	4 cells, about 70 W, about 250 mL/min H ₂
7	Gas and water separator, drier	Returns water; dries the hydrogen	Silica gel with indicator
8	Check valve and flame arrestor	Stops backflow and flame propagation into the stack	7 kPa cracking pressure
9	Hydrogen buffer tank with guard	Stores the lesson's hydrogen	2 L, 300 kPa gauge working, rated 1 MPa or more
10	Tank manifold	Pressure and temperature for the gas law; relief; gauge; vent needle valve	Relief at 350 kPa gauge; vent in 3 min or more
11	Regulator and solenoid valve	Feeds the fuel cell; closes on alarm or power loss	About 50 kPa gauge out
12	PEM fuel cell	Converts hydrogen back to electricity	12 W class, 13 cells, 154 mL/min H ₂ supplied
13	Electronic load and lamp	Steps the load for polarization curves; shows the output	0 to 3 A
14	Meters, logger and display	Three power monitors, pressure and temperature, CSV at 1 Hz	± 1 % power
15	H2Guard sensor, controller and fan	Detection, extraction and interlock (H2Guard project)	See H2Guard

H2Bench: exploded view

CONCEPT, NOT FOR FABRICATION

- 1 Bench deck and extrusion frame
- 2 Instrument back panel
- 3 Canopy hood, duct and posts
- 4 Bench DC power supply, 0 to 30 V, 10 A
- 5 DI water reservoir and deionizer
- 6 PEM electrolyzer stack, about 70 W
- 7 Gas and water separator, drier
- 8 Check valve and flame arrestor
- 9 Hydrogen buffer tank, 2 L, with guard
- 10 Tank manifold: sensors, relief, gauge
- 11 Regulator and solenoid valve
- 12 PEM fuel cell, 12 W class
- 13 Electronic load and lamp
- 14 Meters, logger and display
- 15 H2Guard sensor, controller and fan




Figure 3. Exploded view with BOM numbers.

H2Bench: cutaway on the gas train centreline

CONCEPT, NOT FOR FABRICATION




Figure 4. Section on the gas train centreline, looking from the front. Left to right: power supply (4), electrolyzer (6) with its four membrane electrode assemblies between titanium plates, separator and drier (7), check valve and flame arrestor (8), buffer tank (9) shown hollow inside its rod guard with the manifold (10) and the relief line rising to the canopy, regulator and solenoid (11) and fuel cell (12).

The general arrangement, with the main dimensions and interfaces, is drawing HBN-DWG-001 Rev P1 ([cad/drawings/HBN-DWG-001.pdf](#)); STEP and STL exports are in [cad/step/](#) and [cad/stl/](#).

■ First-order numbers

The numbers below are checked in HBN-CAL-001 ([docs/04-calcs/01-sizing.md](#)), which also holds the assumptions and the results table against every requirement.

Table 2. Energy and gas per lesson cycle (HBN-CAL-001).

Quantity	Value	Assumption
Electrolyzer input	70.2 W for 17.7 min, 20.8 Wh	4 cells, 1.95 V per cell, 9 A
Hydrogen produced	0.189 mol, 4.5 L at 20 °C, 15.0 Wh (HHV); 256 mL/min	Faraday efficiency 95 %; HHV 285.8 kJ/mol
Electrolyzer efficiency	72.2 % (HHV)	Voltage efficiency $1.48 \text{ V} / 1.95 \text{ V} = 75.9 \%$
Compression penalty	17.4 mV per cell, under 1 %	Electrochemical, 1 to 4 bar absolute on the H2 side
Tank content at 300 kPa gauge	0.33 mol, 7.9 L at 20 °C, 0.66 g (8.5 L with the lines)	2.000 L at 401 kPa absolute, 20 °C; 0.15 L outside the tank
Inventory at the relief setting	9.6 L; 10.5 L at full relief lift on a 15 °C day	Relief 350 kPa gauge, 10 % overpressure at full lift
Usable swing	300 down to 70 kPa gauge, 0.189 mol	Regulator needs about 20 kPa headroom above the fuel cell supply
Storage loss	About 2 %, 0.3 Wh	Leaks, purge of the lines; to be measured
Fuel cell output	11.7 W gross, 10.8 W net, for 29.0 min, 5.2 Wh; 154 mL/min supplied	13 cells at 0.60 V and 1.5 A; 95 % utilization; 0.9 W fan and controls
Fuel cell efficiency	35.5 % net (HHV), 42.0 % (LHV)	Consistent with the 40 % system efficiency listed for the 12 W class (Fuel Cell Store)
Round trip	25.1 % (HHV)	Just below the 27.4 to 48 % range in OIES (2025) , as expected at 12 W scale with a dead-end fuel cell
Heat released	About 20 W at the electrolyzer, about 19 W at the fuel cell	Losses in Figure 2 divided by run time
Oxygen vented	2.3 L per fill	Half the hydrogen moles
Total release into a 30 m³ room	0.032 % by volume, 0.8 % of the 4 % lower flammable limit	Relief-set inventory, well mixed
Venting 300 to 20 kPa gauge	5.9 L over 3.0 min through the needle valve; peak 0.35 % by volume at the duct	60 m³/h hood extraction
Stored pressure energy	646 J (776 J at the relief setting)	Isentropic expansion of 2 L to 101 kPa absolute
Stored chemical energy	About 94 kJ (HHV), 80 kJ (LHV)	0.33 mol
Hydrogen measurement	±1.5 % per fill; each stage efficiency within ±1.8 %	0.25 % FS transducer on 600 kPa, ±1 K, tank volume calibrated by water fill to ±1 %
Envelope and mass	900 x 450 x 755 mm; 25.2 kg (22.2 kg without the supply)	<code>cad/src/model.py</code> ; mass estimate in HBN-CAL-001
Parts cost	\$865, or \$800 without the bench supply	<code>bom/bom.csv</code> ; H2Guard excluded

The numbers show that one 90 min lesson holds a full cycle with 13 min to spare (R2), the round trip lands where published studies say it should, and students can measure each stage to better than $\pm 2\%$, so the bench teaches the right lesson. They also show two requirements not met, cost (R14) and hydrogen purity at the fuel cell (R9), and four at risk: inventory at full relief lift (R5), the H2Guard interlock (R8), electrolyzer back-pressure (R10) and mass (R13).

■ Key design choices

Choices 1 to 7 are **adopted as recommended for TRL 3 under Amish's 2026-09-25 instruction, open for his review** (HBN-DDR-001). Choices 8 and 9 remain **proposed, awaiting Amish**.

1. **Storage: rigid 2 L buffer tank at up to 300 kPa gauge.** Adopted for TRL 3 (HBN-DDR-001 item 1). Options were: (a) rigid tank, pressurized by the electrolyzer; (b) metal hydride canister (stores more at lower pressure, but slow, costly and hides the gas law); (c) near-atmospheric gasbag or water-displacement gas holder with a small pump to feed the fuel cell. (a) was chosen because the fuel cell needs about 45 to 55 kPa gauge supply ([Fuel Cell Store](#)) and pressure and temperature give students a direct measurement of the hydrogen. Condition: the electrolyzer must hold the back-pressure, 357 kPa over its oxygen side at the relief setting (R10, HBN-CAL-001); if not, fall back to (c).
2. **PEM electrolysis with deionized water, not alkaline.** Adopted for TRL 3 (item 2). Alkaline cells are cheaper but need potassium hydroxide, a caustic electrolyte.
3. **Generic 12 W class fuel cell rather than a branded stack.** Adopted for TRL 3 (item 3). A branded 12 W stack lists at \$482 to \$576; a generic stack is estimated at about \$250, with a published polarization curve and a purity tolerance as purchase conditions; branded as the fallback.
4. **Measure hydrogen by pressure, volume and temperature, not by a mass flow meter.** Adopted for TRL 3 (item 4). It is cheaper, and the gas law is itself a lesson. A mass flow meter could be an upgrade for university labs.
5. **Bench power supply in constant-current mode as the source.** Adopted for TRL 3 (item 5). A small solar panel could be added later to show renewable-to-hydrogen; not in the first version.
6. **H2Guard as a hard dependency, costed in its own project and shipped with the bench.** Adopted for TRL 3 (item 6). The bench cannot run without it.
7. **Tank kept above about 20 kPa gauge between lessons** so air cannot enter; a new or opened tank is purged with hydrogen by pressure cycling before first use (three fill and vent cycles to 300 kPa gauge reduce the air fraction to about 1.6 %). Adopted for TRL 3 (item 7).
8. **Canopy hood with a single high point** so the sensor sees any leak first and the fan extracts it. Proposed, awaiting Amish (HBN-DDR-001 item 11); it is the working design in the model.
9. **Budget.** Proposed, awaiting Amish (HBN-DDR-001 item 9): the parts cost is \$865 against the \$450 in `project.yaml`; about \$850 was recommended at TRL 2.

Engineering proposals from HBN-CAL-001, awaiting Amish (HBN-DDR-001 item 13): set the relief valve at 325 kPa gauge so the inventory stays under 10 L even at full lift; add a 310 kPa gauge cut of the supply so the relief valve is a backup only; set the vent needle valve for 3 min or more; add a plug-in 30 mA RCD (BOM line 18).

■ Safety

Safety: Hydrogen is flammable in air from about 4 to 74 % by volume and ignites with about 0.02 mJ, far less than most fuels; its flame is hard to see in daylight ([US DOE](#)). H2Bench is a research and teaching prototype, not certified laboratory equipment. Run it only under supervision, only with the H2Guard detector, fan and interlock active and tested, and never near open flames, heaters or sparking tools.

Safety: The tank and lines are under pressure (up to 300 kPa gauge, relief at 350 kPa gauge). Use only vessels and fittings rated 1 MPa or more and rated for hydrogen; never use plastic bottles. Keep the tank inside its guard, pipe the relief valve and manual vent into the hood, and never open a fitting while the system is pressurized.

Safety: Vent slowly through the needle valve (3 min or more from 300 to 20 kPa gauge). A faster vent can raise the concentration at the duct past H2Guard's warning level (HBN-CAL-001 section 7).

Safety: Keep air out of the tank. A hydrogen and air mixture inside a closed vessel can burn or detonate. Purge a new or opened tank with hydrogen by pressure cycling, and never vent it below about 20 kPa gauge.

Safety: The oxygen outlet of the electrolyzer must vent to the hood, away from the hydrogen outlet, so oxygen and hydrogen can never mix in a line.

Safety: The bench power supply is mains powered. Use a supply with a protective earth, keep the mains lead off the wet deck, and fit a residual-current device (RCD or GFCI) on the bench socket. Water and electricity share the deck; keep the reservoir below and away from the supply.

Safety: The electrolyzer and fuel cell stacks run warm (about 20 W of heat each) and the fuel cell's maximum stack temperature is about 55 °C. Allow cooling before handling.

■ Open questions

- [] Can a generic electrolyzer stack at this size hold 357 kPa on the hydrogen side over the oxygen side, the relief setting plus the check valve (R10, HBN-CAL-001)?
- [] What hydrogen purity reaches the fuel cell after the separator and drier, and does the chosen fuel cell tolerate it (R9)?
- [] H2Guard alarm set point and response time; how the interlock reaches the power supply output and the solenoid (R8).
- [] Tank: aluminium or stainless; which certified vessel type is easiest for schools to approve?
- [] Is a 300 kPa gauge tank acceptable to school safety officers, or is option (c) (near-atmospheric storage with a pump) needed?
- [] Which curriculum and age group to align the first worksheets with?
- [] How to bring the cost toward \$450, or whether the recommended \$850 applies (HBN-DDR-001 item 9).
- [] Which H2Guard output breaks the 9 A supply line, and at what voltage the tank solenoid runs (H2Guard uses a 24 V valve; R8).

Concept media: [blueprint sheet](#), [interactive 3D model](#).