BUILD PLAN SKETCH, PLAN NOT YET BUILT

HeatMap Node · github.com/BoujeeEnjinia1701/heatmap-node

REV	DESCRIPTION	DATE	BY
P1	Making sketch for the prototype build plan	2026-10-02	AC



TOP VIEW

Scale 1:5; looking down (along -Z)



FRONT VIEW

Scale 1:5; looking at the front (along +Y)

RIGHT VIEW

Scale 1:5; looking at the right side (along -X)

WHERE IT GOES

This part in colour, its neighbours in grey

HOW TO MAKE IT AND HOW IT FITS

A channel 120 wide, 180 tall and 40 deep, bent from one 3 mm sheet blank.
The web is the flat back the arm bears on; the two flanges point at the pole.
Blank about 120 x 250 mm; the bending shop sets the length for its bend allowance so the web is 180 outside and each flange stands 40 out.
Before bending, cut a 120 degree V in each end of the blank (the flange): 110.9 wide at the free edge, point 32 in from the edge (8 from the web).
Web holes: four 6.6 mm, 35 each side of centre, 25 above and below the middle (65 and 115 up from the bottom edge).
Band slots: four 3 x 16 mm, 55 each side of centre, centred 20 from the top and bottom edges. Chain drill 3 mm and file square.
Bend both flanges 90 degrees the same way, inside radius about 3 mm.
Deburr; push rubber edge trim over both V edges (it takes 1.5 mm).
Check: on a 114 mm tube both V edges touch the tube through the trim.

HEATMAP NODE

github.com/BoujeeEnjinia1701/heatmap-node

HeatMap Node arm saddle: making sketch

DRAWING NO.	REV	SHEET	SIZE
HMN-DWG-101	P1	1 of 1	ANSI B

SCALE	UNITS	PROJECTION	DATE	DRAWN
1:5	mm		2026-10-02	Amish Chadha

MATERIAL / NOTES

Aluminium sheet 3 mm, 5052-H32

Licensed CERN-OHL-S-2.0 · Design Molecule Lab · designmolecule.com

Generated from cad/src; do not edit by hand