

MACHINEPULSE · CALCULATION

MachinePulse sizing calculations

Design Molecule Lab · designmolecule.com

DOCUMENT CONTROL

Document ID	MPL-CAL-001	Version	0.4
Status	Draft	Date	2026-10-02
Author	Amish Chadha	License	CERN-OHL-S-2.0
Project TRL	TRL 3 Proof of concept		
Repository	github.com/BoujeeEnjinia1701/machinepulse		
Source	docs/04-calcs/01-sizing.md @ uncommitted		

REVISION HISTORY

Version	Date	Author	Change
0.4	2026-10-02	Amish Chadha	R4 restated by Amish on 2026-10-02; requirement table and summary count updated (2 at risk, 4 met by design)
0.3	2026-10-01	Amish Chadha	Constructable design (MPL-DDR-003); mass, mount resonance, magnet margins and cost re-run; budget treated as a value-engineering target
0.2	2026-09-25	Amish Chadha	Recommendations accepted by Amish (DDR-002)
0.1	2026-09-25	Amish Chadha	First issue for TRL 3 (current and CT window, current and energy error budgets, vibration noise, bandwidth and mount resonance, magnet holding, probe error, pod temperature, power, data and storage, cost)

MachinePulse sizing calculations

On paper, MachinePulse meets twelve of its seventeen requirements (nine by calculation, three by design), has three at risk, misses one, and its estimated cost is over the value-engineering target. Version 0.4 records R4 restated by Amish on 2026-10-02 as a relative energy trend, met by design, so thirteen are met (four by design) and two are at risk; the figures below are unchanged. Version 0.3 re-runs the numbers for the constructable design of MPL-DDR-003 (a separate boss on a set screw, a carrier board on stand-offs, a third gland, a grommet, a light pipe and a made probe clip): the pod is 24 g heavier, so the mount resonance and the magnet margins fall slightly, the thermal results are unchanged, and the parts cost rises to \$83.50, \$2.50 over the \$81 value-engineering target. Version 0.2 applied the decisions Amish made on 2026-09-25 (MPL-DDR-002): high-temperature pot magnets rated 120 °C replace the standard 80 °C grade, the budget rises from \$80 to \$81 to pay for them, and R8 is restated with a 4 °C tolerance from 85 to 100 °C. As a result R8 and R12 move from at risk to met by calculation. The miss is R10: on many machines the current transformer (CT) can only go round a single insulated conductor inside a terminal box or panel, which needs a qualified person and isolation. The three at risk are current accuracy at the bottom of the CT range (R3), energy per shift (R4) and the magnet mount's resonance inside the vibration band (R5). Cost (R16) is reported against the value-engineering target: \$83.50 against \$81, \$2.50 over. Several TRL 2 figures change. Data per day is about 1.15 MB, not 0.4 MB, because a full-resolution spectrum is 7.4 kB, not 1 kB. The magnet mount resonates at about 0.89 to 1.78 kHz rather than being usable to 2 kHz. Energy error with a fixed power factor is about 26 %, not 20 %; with a load-dependent power factor curve it falls to 8.5 % RSS. The box on its own would survive an 80 °C frame; the limit that TRL 2 put at 60 °C was set by the standard magnets at about 81 °C, not by the enclosure, and with the high-temperature magnets it moves to the accelerometer at about 110 °C. The calculations add four details within the adopted design: a CT bias of 1.50 V instead of 1.65 V, clamp diodes on the CT input, a ± 16 g accelerometer range, and 5 mm nylon stand-offs between the sensor block and the box floor. Every number in this note is printed by `docs/04-calcs/sizing.py`; the tag in brackets, for example [D7], is the line of that script's output that carries it.

Safety: These are first-principles estimates for a paper proof of concept. They are not a substitute for bench measurements, an electrical safety review of the CT installation or pull tests on real frames. See MPL-PRC-001, Safety.

■ Scope and method

The note checks every requirement in MPL-REQ-001 v0.4 against the design in MPL-PRC-001 v0.4 and the parametric model `cad/src/model.py`. The script imports the model's `PARAMS`, `derived()` and part solids, so the magnet spacing, block, stand-off gap, box and part volumes used here are the ones in the STEP files and in drawing MPL-DWG-001. It also reads `bom/bom.csv` and `budget_usd` in `project.yaml`. Run it from the repo root with `python docs/04-calcs/sizing.py`.

The design case is a 7.5 kW, 400 V three-phase induction motor (IEC 132 frame class, 130 mm frame radius) in a workshop at 40 °C, with the pod on the top line of the frame and the CT on one phase conductor where it leaves the terminal box.

Status terms used in Table 4: **met by calculation** (the estimate meets the target with the stated assumptions), **met by design** (a design feature meets it; no number to compute), **at risk** (the central estimate meets the target but the worst case or a key untested assumption does not, or the margin is nil), and **not met**.

■ Assumptions

Table 1. Main assumptions.

Area	Assumption	Basis
Motor	7.5 kW, 400 V, efficiency 0.88, power factor 0.84 at full load	Typical nameplate values
CT	SCT-013 class, voltage output, 1 V RMS at rated current, 13 mm aperture; ratio nonlinearity 1 % after calibration	Typical of the family; to confirm
ADC	ESP32-S3 ADC at 12 dB attenuation treated as linear from 0.10 to 2.90 V; residual error after two-point calibration equal to 3 mV on a 1 s RMS value; noise 3 LSB RMS	Assumed; the S3 ADC's nonlinearity is the main current risk and must be measured
Other current errors	Burden and reference drift 1 %; calibration clamp meter 1 %; conductor position 1 %	Assumed
Energy	Supply voltage within ± 5 % of nominal; power factor from a nameplate-based curve within ± 6 % running and ± 25 % at idle; phase imbalance 3 %	Assumed
Accelerometer	IIS3DWB class: 75 $\mu\text{g}/\text{VHz}$, 26.667 kHz output rate, ± 16 g range (ST); ADXL345 class fallback taken as about 400 $\mu\text{g}/\text{VHz}$	Datasheet figure for the first; order of magnitude for the second
Mount stiffness	Contact stiffness per magnet 2.0×10^7 N/m on flat clean steel, 0.5×10^7 N/m on a painted curved frame	Assumed; to be measured
Magnets	32 mm pot magnet, 290 N rated pull on thick flat steel; pull falls as $F_0 / (1 + g / 0.5 \text{ mm})^2$ with gap g ; 0.2 mm paint; friction 0.25; full pull needs about 4 mm of steel; high-temperature grade rated 120 °C (mag_t_max in the model; standard N grade, 80 °C, kept for comparison); pull falls 0.12 %/K	Typical catalog values; gap law assumed
Probe	DS18B20 within 0.5 °C from -10 to 85 °C, taken as 2 °C above 85 °C; 0.5 mm thermal pad at 3 W/mK over 6 x 20 mm plus 1 K/W for clip and sleeve; 10 W/m ² K on the sleeve; 0.005 W/K down the lead	Datasheet figure below 85 °C; the rest assumed
Thermal	ABS box continuous-use limit 70 °C; controller module rated 85 °C (no octal PSRAM) with an 8 K local rise; accelerometer rated 105 °C; outside surfaces 8 to 10 W/m ² K, inside 4 to 5 W/m ² K; magnet contact 750 W/m ² K over half the face on paint	Assumed; check against the chosen box and module datasheets
Power	Wi-Fi connected with modem sleep 80 mA at 3.3 V; 40 mA more for 5 s a minute during the burst; linear regulator from 5 V; adapter 70 % efficient at this load	As at TRL 2; to be measured
Data	Summary 200 B a minute; spectrum every 15 min, three axes, one byte per bin; 15 % protocol overhead; 4 MB of flash for the offline queue	Design choices

■ A. Motor current and CT window (R1, R3)

- **Design motor.** Full-load current is 14.6 A, 49 % of a 30 A CT [A1]. Small and large machines need other CTs: 0.37 kW single-phase draws 3.3 A and 1.5 kW three-phase 3.4 A, both suited to a 5 A CT; 15 kW draws 28.0 A and

needs a 50 A CT [A2]. The voltage-output range therefore runs from 5 to 60 A. The 100 A SCT-013-000 is a current-output type and is excluded, so the TRL 2 key figure "5 to 100 A" is corrected.

- **ADC window.** At full range the CT gives 1.414 V peak. About the TRL 2 bias of 1.65 V it would reach 3.064 V, 0.164 V above the linear window [A4]. A 1.50 V bias spans 0.086 to 2.914 V [A3], which clips the peak by 1 % and costs 0.12 % of RMS at 100 % of range [A5]. The interface board bias moves to 1.50 V.
- **Starting current.** About six times full load (88 A) gives 4.14 V peak at the ADC pin [A6]. A series resistor and clamp diodes on the CT input are added to the interface board (BOM line 7); run-state logic ignores the clipped start.

■ B. Current error, run state and run time (R1, R2, R3)

Table 2. Current error budget [B1].

Point in the CT range	ADC term	RSS	Worst-case sum	R3 target
10 %	3.0 %	3.6 %	7.0 %	5 %
49 % (design motor)	0.6 %	2.1 %	4.6 %	5 %
100 %	0.3 %	2.0 %	4.3 %	5 %

- **R3 is at risk.** The RSS error meets 5 % across the range, but the worst case at 10 % of range is 7.0 %, and the ADC term rests on an assumed 3 mV residual. Choosing the CT so that normal load sits above about 30 % of its range (section A) keeps the design motor at 4.6 % worst case. Under MPL-DDR-002 (N3) the target is kept and the ADC residual is the first thing to measure at TRL 4.
- **Run state.** A 1 s RMS window holds 2,000 samples, 50 whole cycles at 50 Hz and 60 at 60 Hz, so the state updates every second [B3]. ADC noise reads as about 0.07 A at zero current on a 30 A CT, well below a 0.5 A off threshold [B2]. R1 is met by calculation.
- **Run time.** The worst-case edge error of 1 s is 1.00 % of a 100 s run and 0.17 % of a 10 min run; it reaches 3.33 % only for 30 s runs, where random edge errors over a week largely cancel [B4]. R2 is met by calculation for runs of 100 s or longer even in the worst case.

■ C. Energy per shift from one CT (R4)

- **Example shift.** Three hours idling at 40 % of full-load current and power factor 0.20, then five hours at 80 % and 0.81, use 35.3 kWh [C1].
- **Fixed power factor (the TRL 2 method).** Using the nameplate 0.84 throughout gives 44.3 kWh, 26 % high, because idle current is mostly magnetizing current [C2].
- **Load-dependent power factor.** With a power factor curve built from the nameplate and the measured no-load current, the error terms are current 2.1 %, voltage 5 %, power factor 5.8 % and imbalance 3 % [C3], for 8.5 % RSS and 16.0 % worst case [C4]. R4 is therefore at risk rather than not met. The curve is adopted in the gateway software design.
- **Voltage reference.** Measuring voltage and power factor on one phase would give 4.3 % RSS for about \$10 more [C5], which would take the parts to \$91.00 [J2]. Not adopted; see the review note.

■ D. Vibration sensing (R5, R6, R7)

- **Noise (R6).** Integrating 75 $\mu\text{g}/\text{VHz}$ as velocity over 10 to 1,000 Hz gives 0.037 mm/s RMS, a factor of 2.7 inside the 0.1 mm/s target. An ADXL345-class fallback at about 400 $\mu\text{g}/\text{VHz}$ gives 0.20 mm/s and would miss R6 [D1].
- **Range and sampling.** Decimating the 26.7 kHz stream by eight gives 3,333 Hz with a 1,667 Hz Nyquist limit, and 13,333 samples per axis in a 4 s burst; quantization at ± 16 g adds only 3.5 $\mu\text{g}/\text{VHz}$ [D2]. The ± 2 g range assumed at TRL 2 would clip: 11 mm/s at 500 Hz is already 5.0 g peak [D3].
- **Memory.** The raw burst at full rate is 640 kB and does not fit the ESP32-S3's 512 kB of internal SRAM; decimating as the FIFO is read keeps 80 kB, plus a 66 kB FFT buffer [D5].
- **Resolution (R7).** An 8,192-point FFT at 3,333 Hz gives 0.407 Hz bins (0.61 Hz Hann noise bandwidth), against 0.5 Hz; the 1x line of a 1,450 rpm motor is at 24.17 Hz [D4]. R7 is met by calculation.
- **Mount resonance (R5).** The constructable pod weighs 319 g [D6] (295 g in v0.2, before the carrier board, sockets, glands, pillars and fixings of MPL-DDR-003), all carried by the two magnet contacts. On flat clean steel it resonates at about 1,783 Hz, so readings are 10 % high by 535 Hz; on a painted 130 mm radius frame it resonates at about 892 Hz, 10 % high by 267 Hz and 3 dB high by 481 Hz [D7]. The sensor covers the 10 to 1,000 Hz band, but the mount does not measure it flat. Overall velocity on most machines is dominated by running-speed components well below 267 Hz, so the effect on the ISO 20816 value is usually small; bearing and gear content near the top of the band will be overstated. R5 is at risk; under MPL-DDR-002 (N3) the target is kept, the mount resonance is the first thing to measure at TRL 4, and a flat steel saddle for curved frames is the option to consider then. The TRL 2 statement "usable to about 2 kHz" is withdrawn.

■ E. Magnet holding (R11)

- **Pull.** Through 0.2 mm of paint a magnet keeps about 51 % of its rated pull on a flat frame and 33 % on a 130 mm radius frame, because the face touches only along a line [E1]. The pair gives 296 N flat and 191 N curved, against 15.6 N at 5 g [E2].
- **Margins.** Pull-off margin is 12.2 on the curved frame. Slip governs: 0.25 friction gives a margin of 3.0 curved and 4.7 flat [E3]. At 80 °C the magnets lose about 7 % of their pull and the curved slip margin falls to 2.8 [G5]. Tipping across a curved frame, with the contact lever taken as a quarter of the magnet diameter, has a margin of 3.5 [E4]. R11 is met by calculation, with the pull-gap law and friction still to be checked by a pull test.
- **Aluminium frames.** Steel pads 3 mm thick keep about 75 % of rated pull (435 N, slip margin 7.0) [E5]. Thin 1 mm pads would keep about 25 % (slip margin 2.3) [E6], so BOM line 11 now specifies 35 mm by 3 mm discs.

■ F. Surface temperature probe (R8)

- **Contact error.** With a thermal pad and the sleeve cooled by air and its lead, the probe reads 1.06 K low on an 80 °C frame and 1.19 K low at 85 °C, for totals of 1.56 K and 1.69 K with the sensor tolerance [F1]. R8 is met to 85 °C.
- **Above 85 °C.** At 100 °C the contact error is 1.59 K and the sensor tolerance outside its ± 0.5 °C band is taken as 2 °C, for 3.59 K [F1]. Against the original 2 °C target over 0 to 100 °C this was at risk. R8 as restated under MPL-DDR-002 (2 °C to 85 °C, 4 °C from 85 to 100 °C) is met by calculation, with 0.31 K in hand at 85 °C and 0.41 K at 100 °C.

■ G. Pod temperature on a hot frame (R12)

- **Network.** The model has three nodes (block, box floor, inside air) between the frame and the room. Conductances are 0.547 W/K from frame to block through the magnets, 0.137 W/K from block to floor with the floor sitting on the block, 0.0229 W/K across the 5 mm stand-off gap, 0.030 W/K from floor to inside air and 0.052 W/K through walls and lid; 0.42 W of electronics heat is released inside [G1].
- **Results at an 80 °C frame and 40 °C air.** With the floor on the block (the TRL 2 arrangement), the floor reaches 67.2 °C and the controller module about 63.7 °C. With 5 mm nylon stand-offs the floor falls to 53.9 °C and the module to about 58.9 °C; the magnets sit at about 78.7 °C and the block and accelerometer at 77.4 °C [G2].

Table 3. Frame temperature at which each limit is reached, 40 °C air [G3].

Arrangement	N-grade magnets 80 °C (superseded)	High-temperature magnets 120 °C	ABS floor 70 °C	Accelerometer 105 °C	Module 85 °C
Floor on the block (TRL 2)	82.0 °C	124.1 °C	84.2 °C	112.0 °C	163.1 °C
5 mm nylon stand- offs	81.3 °C	122.7 °C	134.7 °C	109.6 °C	Not reached

- **Finding.** The box alone would take an 80 °C frame, with only 4 K in hand; the stand-offs add a large margin for the box and module for \$1.00 and are adopted within decision D7. With standard N-grade magnets the magnets set the limit, with only 1.3 K to spare at 80 °C. Under MPL-DDR-002 the design uses high-temperature pot magnets rated 120 °C, which reach their limit only at a 122.7 °C frame. The accelerometer now sets the limit, at a 109.6 °C frame, 29.6 K above the target, so R12 is met by calculation.
- **Module choice.** ESP32-S3 module variants with octal PSRAM are rated to 65 °C and would have only 6.1 K of margin even with stand-offs [G4]. BOM line 3 now specifies a module without octal PSRAM, rated to 85 °C.

■ H. Power

- **Average.** About 84.7 mA at 3.3 V (Wi-Fi modem sleep 80 mA, burst processing 3.3 mA averaged, sensors and LED), or 84.8 mA and 0.42 W from 5 V [H1]. The TRL 2 figure of about 0.5 W stands.
- **At the wall.** With a 70 % efficient adapter, 0.61 W, or 5.3 kWh a year, not the 4.4 kWh stated at TRL 2; the regulator dissipates 0.14 W inside the box [H2].
- **Peak.** Wi-Fi transmit peaks near 0.35 A, 1.75 W from the adapter, within its 1 A rating [H3].

■ I. Data, delivery and offline store (R9, R15)

- **Spectrum size.** Keeping 0.407 Hz bins up to 1 kHz needs 2,458 bins per axis; at one byte per bin for three axes plus a header, each spectrum is 7.4 kB, not the 1 kB assumed at TRL 2 [I1].
- **Daily volume.** Summaries are 0.29 MB and spectra 0.71 MB a day, or 1.15 MB with protocol overhead, an average of 0.11 kbit/s [I2]. This is trivial for Wi-Fi and for a TwinKit gateway. R9 is met by calculation.
- **Delivery.** A summary reaches the broker within about 66 s of the start of its minute, against 120 s [I5].
- **Offline store (R15).** The 4 MB queue holds 13.9 days of summaries alone, or 4.0 days of summaries and spectra [I3]. The queue keeps summaries first and drops the oldest spectra when full. R15 is met by calculation. Flash wear is negligible: each 4 kB sector is erased once per 14 days of offline running [I4].

■ J. Cost (R16)

Value-engineering target: USD 81 (`budget_usd` , a hypothetical control target, not a limit). Estimated cost of the constructable design: USD 83.50 (USD 2.50 over the target) from the 14-line BOM [J1]. Making the design constructable added \$2.50: the third gland and the M16 gland (\$0.50), the carrier board's sockets, terminals and light pipe (\$1.00), the made probe clip with its magnets in place of a bought clip (\$0.50 net) and the grommet, set screw and carrier fixings (\$0.50) (MPL-DDR-003). A three-CT variant would cost \$103.50 and a voltage reference \$93.50 [J2]. Prices are indicative, not quotes. R16 is reported as over the value-engineering target by \$2.50; the build stays hand tools, a drill press and perfboard, with no custom PCB.

■ Results against every requirement

Table 4. Requirement status from this note.

ID	Requirement	Target	Value from this note	Status
R10	Install without opening live enclosures	Pod and probe in 10 min without tools; CT on an accessible insulated conductor	Pod and probe need no tools; the CT needs a single insulated conductor, often only inside a terminal box or panel	Not met
R3	Measure load current	Within 5 % of reading, 10 % to 100 % of range	RSS 3.6 % at 10 %, 2.1 % at 49 %; worst case 7.0 % at 10 % [B1]	At risk
R4	Estimate energy per shift	Relative energy trend per shift, kWh reported as an estimate (restated by Amish, 2026-10-02; was within 10 % of a reference meter)	8.5 % RSS, 16.0 % worst case with a PF curve; 26 % with a fixed PF [C2, C4]	Met by design as restated
R5	Measure vibration	Velocity RMS, 10 to 1,000 Hz, three axes	Sensor covers the band; mount resonance 892 to 1,783 Hz, +10 % from 267 Hz on a curved frame [D7]	At risk
R16	Low cost and buildable	Parts against the \$81 value-engineering target; hand tools; no custom PCB	\$83.50, over the target by \$2.50 [J1]; hand tools, drill press and perfboard	Over the value-engineering target
R1	Detect run state	Off, idle, running at 1 s resolution	1 s RMS windows; 0.07 A zero reading against a 0.5 A threshold [B2, B3]	Met by calculation
R2	Log run time	Within 1 % over a week	1.00 % worst case on 100 s runs, 0.17 % on 10 min runs [B4]	Met by calculation
R6	Low vibration noise floor	0.1 mm/s RMS or better	0.037 mm/s [D1]	Met by calculation
R7	Resolve running-speed peaks	0.5 Hz bins or finer to 1 kHz	0.407 Hz [D4]	Met by calculation
R8	Measure frame temperature	Within 2 °C to 85 °C; within 4 °C from 85 to 100 °C	1.56 K at 80 °C, 1.69 K at 85 °C, 3.59 K at 100 °C [F1]	Met by calculation
R9	Report often enough	Summary each minute, spectrum each 15 min, within 2 min	1.15 MB/day; 66 s worst delivery [I2, I5]	Met by calculation
R11	Stay attached	No slip at 5 g on a painted cast frame; aluminium option	Slip margin 3.0 (2.8 at 80 °C); 3 mm pads 7.0 [E3, E5, G5]	Met by calculation
R12	Tolerate hot frames	Frames up to 80 °C in 40 °C air	Box and module pass with stand-offs; 120 °C magnets reach their limit at a 122.7 °C frame; accelerometer limit at 109.6 °C [G3]	Met by calculation
R15	Store data when offline	7 days of summaries	13.9 days [I3]	Met by calculation
R13	Workshop protection	IP54 or better	IP54 box, three IP68 glands (one cable each), silicone grommet round the boss, sealed light pipe	Met by design
R14	Keep data local	TwinKit or any MQTT broker; no cloud	MQTT on the local network	Met by design

ID	Requirement	Target	Value from this note	Status
R17	Safe by design	Low voltage in the pod; certified adapter; voltage-output CT; no link to controls	Unchanged; CT input now clamped [A6]	Met by design

Summary (v0.4, after R4 was restated by Amish on 2026-10-02): 1 not met, 2 at risk, 9 met by calculation, 4 met by design, 1 (R16) reported against the value-engineering target, none left unverifiable at TRL 3. R13's IP rating and the at-risk items need bench evidence that belongs to TRL 4, which is on hold.

■ Checks against the TRL 2 figures

Table 5. TRL 2 figures that change.

Quantity	TRL 2	This note
Pod size and mass	100 x 68 x 58 mm, 0.35 kg	100 x 68 x 63 mm (137 mm over glands), 0.32 kg [D6]
CT variants	5 to 100 A	5 to 60 A voltage output [A2]
Current accuracy	About 3 %	2.1 % RSS at the design point, 3.6 % at 10 % of range [B1]
Energy accuracy	About 20 %	26 % fixed PF; 8.5 % RSS with a PF curve [C2, C4]
Magnet mount	Usable to about 2 kHz	Resonance 892 to 1,783 Hz [D7]
Magnet margin	About 6 times	Pull-off 12.2, slip 3.0 [E3]
Data volume	About 0.4 MB/day	1.15 MB/day [I2]
Offline store	About 10 days	13.9 days of summaries, 4.0 days with spectra [I3]
Frame temperature limit	About 60 °C (box)	About 81 °C with N-grade magnets; 109.6 °C (accelerometer) with the 120 °C magnets [G3]
Annual energy	About 4.4 kWh	5.3 kWh at the wall [H2]
Parts cost	About \$79	\$83.50 against an \$81 value-engineering target [J1]