

MOTIONCORE · CALCULATION NOTE

MotionCore sizing calculations

Open Hardware Portfolio · amishchadha.com

DOCUMENT CONTROL

Document ID	MTC-CAL-001	Version	0.1
Status	Draft	Date	2026-09-25
Author	Amish Chadha	License	CERN-OHL-S-2.0
Project TRL	TRL 3 Proof of concept		
Repository	github.com/BoujeeEnjinia1701/motioncore		
Source	docs/04-calcs/01-sizing.md @ 2f82c33		

REVISION HISTORY

Version	Date	Author	Change
0.1	2026-09-25	Amish Chadha	First TRL 3 sizing note (currents, fuses and leads, thermal, e-stop timing, precharge, speed sensing, reaction times, CAN and bus voltage, size, mass, cost) against the TRL 3 decisions in MTC-DDR-001

MotionCore sizing calculations

On paper, MotionCore meets nine of its fourteen requirements. **R12 is not met**: the module weighs about 1.94 kg against 1.5 kg, because the finned enclosure that is also the heat sink weighs about 1.0 kg on its own. R2 and R9 are **at risk** in the heavy case: at 350 W on an 8S LiFePO4 pack the case reaches about 58.5 °C against 60 °C, and reasonable changes to the controller assumptions push it to 65 to 71 °C. R10 is **at risk** because the XT90 power socket is not sealed, and R11 (fit time) cannot be verified at TRL 3. The reference case is comfortable: about 50 °C on the case, 6.9 A from a SwapCell pack, e-stop power removal within 67 ms worst case, and a MotionCore kit cost of \$265 against the \$300 budget, with the \$70 reference motor costed to each host.

Every number here is printed by `docs/04-calcs/sizing.py` (run from the repo root: `python docs/04-calcs/sizing.py`), which also writes `docs/04-calcs/results.csv`. The script reads the enclosure dimensions from `cad/src/model.py` and the costs from `bom/bom.csv`. All values are first-principles estimates; nothing is measured.

■ 1. Assumptions

Table 1. Inputs. All are assumptions for a paper design; part-specific values are to be confirmed from datasheets once parts are chosen.

Input	Value	Basis
Reference pack	SwapCell 13S lithium-ion, 46.8 V nominal, 39.0 to 54.6 V, 110 mΩ, 20 A continuous, 35 A for 10 s	SwapCell interface v0.3 (SWC-PRC-001 v0.3)
CargoMule pack	12S LiFePO ₄ , 38.4 V nominal, 30.0 to 43.8 V, about 60 mΩ, 15 A host limit	CargoMule precis (CGM-PRC-001); resistance assumed
Heavy-case pack	8S LiFePO ₄ , 25.6 V nominal, 20.0 to 29.2 V, about 30 mΩ	PalletPilot and StepClimber class; resistance assumed
Motor efficiency	80 % at rated load, 75 % at 750 W for 10 s	Typical small geared hub
Phase to bus current ratio	1.2 (winding matched to the host's speed)	Assumption; 2.0 checked as a sensitivity
Controller losses	3.9 mΩ per phase (MOSFET 2.4 mΩ hot, shunt 0.5 mΩ, copper 1.0 mΩ); 100 ns switching edges at 30 kHz; 1.5 W fixed	Typical VESC-class 75 V stage
Power path in the module	Contactor 0.5 mΩ, internal leads 1.5 mΩ, XT90 pair 0.6 mΩ, fuse 3.5 mΩ (20 A) or 1.5 mΩ (40 A)	Typical parts
Auxiliary supply	Coil 4.0 W at 12 V, supervisor 0.6 W, buck efficiency 85 %	Typical sealed 100 A contactor without economizer
Enclosure	220 x 140 x 60 mm body, 3 mm walls, 3 mm lid, 22 fins 4 x 14 x 48 mm; clear anodized, ε 0.80, solar absorptance 0.35	<code>cad/src/model.py</code>
Convection	Vertical plates $h = 1.42 (\Delta T/L)^{0.25}$, lid $h = 1.32 (\Delta T/L)^{0.25}$, fin faces 0.8 of a free plate; underside ignored	Simplified laminar correlations for still air
Contactor coil	36 Ω, 0.30 H, releases at 10 % of rated current; 10 ms armature travel; 5 ms arc	Assumed; release time 50 ms or less is a selection criterion
Bus capacitance	1,000 μF; precharge 100 Ω	To confirm from the chosen controller
Speed sensor	8 magnets; 2 % period jitter from magnet placement	Concept (MTC-PRC-001)
Ambient	40 °C, shaded	MTC-REQ-001 R9

■ 2. Operating points (R1, R2)

The controller is more efficient than the blanket 95 % assumed at TRL 2, so the pack supplies about 322 W, not 333 W, in the reference case. At the reference point about 5.7 W goes to the auxiliary supply and power path, 3.9 W to the controller and 62.5 W to motor and gear losses (Figure 4 in MTC-PRC-001).

Table 2. Operating points. Currents at nominal and minimum pack voltage.

Case	Pack power	Current, nominal V	Current, minimum V	Controller loss	Controller efficiency
Reference: 250 W, SwapCell	322 W	6.9 A at 46.8 V	8.3 A at 39.0 V	3.9 W	98.8 %
CargoMule: 250 W, 12S LFP	323 W	8.4 A at 38.4 V	10.8 A at 30.0 V	4.3 W	98.7 %
Heavy: 350 W, 8S LFP	453 W	17.7 A at 25.6 V	22.9 A at 20.0 V	9.0 W	98.0 %
500 W, 8S LFP (information)	648 W	25.3 A at 25.6 V	32.9 A at 20.0 V	15.5 W	97.6 %

For 750 W over 10 s at nominal voltage, the pack current is 21.9 A on SwapCell (inside its 35 A, 10 s limit) and 40.9 A on 8S LiFePO₄. CargoMule's own 15 A pack limit caps its peak at about 414 W of shaft power: this is a host setting, which the supervisor respects, not a MotionCore limit. The supervisor sets the controller's battery current limit to the lower of the host setting and the pack's allowed discharge current in PACK_LIMITS.

All three host packs fall inside 20 to 58 V; the controller is a 75 V class and the auxiliary buck accepts 18 to 75 V, so **R1 is met by design review**. R2 is met electrically; its heavy case depends on R9 and is **at risk**.

■ 3. Fuses, contactor and leads

The fuse must carry 1.25 times the continuous current at minimum pack voltage and hold the 10 s peak at no more than 110 % of its rating, which a blade fuse carries without opening.

Table 3. Fuse check.

Pack	Continuous at minimum V	10 s peak	Fuse needed	Fitted	Prospective short circuit
SwapCell	8.3 A	21.9 A	19.9 A	20 A	about 470 A
CargoMule	10.8 A	15.0 A (host limit)	13.6 A	20 A	about 663 A
8S LiFePO ₄	22.9 A	40.9 A	37.2 A	40 A	about 856 A

The 20 A and 40 A fuses proposed at TRL 2 hold, although the 20 A fuse has little margin for a SwapCell host that uses the full 750 W peak. The fuse must be rated for **58 V DC or more** with at least **1 kA** breaking capacity; common 32 V automotive fuses are not suitable. The contactor carries at most about 41 A for 10 s against its 100 A rating; the selection criterion that matters is breaking at least 50 A at 60 V DC.

Pack leads of 2.5 mm² over 1.5 m each way drop 0.14 V and lose 1.0 W in the reference case. In the heavy case at 20 V they drop 0.47 V and lose 10.8 W (3.1 % of shaft power); 4 mm² leads cut this to 0.30 V and 6.7 W, so 24 V hosts get 4 mm² pack leads (bom/bom.csv item 13).

■ 4. Thermal (R9)

The enclosure has 0.0308 m² of lid, 0.0454 m² of walls and 0.0338 m² of fin faces. At the heavy point the heat-transfer coefficients are about 6.5 W/m²K on the walls, 5.6 on the fins, 6.7 on the lid and 6.4 for radiation, giving a conductance of about 1.17 W/K (the TRL 2 estimate was 1.3 W/K). Heat is taken at minimum pack voltage, where the current is highest.

Table 4. Case and MOSFET temperatures at 40 °C ambient, shaded.

Case	Heat in the module	Case surface	MOSFET junction
Reference, 250 W on SwapCell	10.0 W	50.2 °C	about 52 °C
CargoMule, 250 W	11.2 W	51.2 °C	about 54 °C
Heavy, 350 W on 8S LFP	20.1 W	58.5 °C	about 67 °C
500 W on 8S LFP (information)	32.7 W	67.9 °C	about 84 °C

The derate to 350 W at 24 V (MTC-DDR-001 item 9) is needed: 500 W misses the 60 °C target by about 8 K. At 350 W the margin is only 1.5 K and depends on the controller assumptions:

- Phase current twice the bus current (a motor running well below its base speed, as a walk-behind host with a fast winding would): 37.2 W, **71.0 °C**.
- Twice the phase resistance (budget controller MOSFETs): 28.9 W, **65.1 °C**.
- Sun on the lid (information; R9 assumes shade): 10.8 W absorbed, 59.1 °C in the reference case and 66.5 °C in the heavy case.

The auxiliary supply is about 54 % of the reference-case heat, mostly the contactor coil. A coil economizer that holds the contactor at about 1 W would lower the heavy case to 16.5 W and 55.7 °C. **R9 is met in the reference case and at risk in the heavy case.**

■ 5. Emergency stop timing (R3)

Channel A of the e-stop opens the contactor coil circuit directly. With a 24 V Zener across the coil, the coil current decays from 333 mA to its release point in 2.9 ms ($\tau = 8.3$ ms); a plain diode takes 15.5 ms. Adding 10 ms for contact opening and bounce, 10 ms for armature travel, 5 ms of arc and 2.2 ms during which the bus capacitors (0.69 J) keep the motor running gives about **30 ms modeled** with the Zener and 43 ms with a plain diode.

The worst case uses the release time the contactor must meet as a selection criterion (50 ms or less with its suppressor): $10 + 50 + 5 + 2.2 \approx \mathbf{67\ ms}$, inside the 100 ms of R3. In 67 ms a host at 25 km/h travels about 47 cm and a walk-behind machine at 1.5 m/s about 10 cm (69 cm and 15 cm in the full 100 ms). No firmware is in this path, so R3 holds with both processors failed. **R3 is met on paper.** R4 (no automatic restart) is met by circuit review: the coil loop can close only after the key is cycled, and the supervisor closes its switch only at zero throttle with the brakes released and no fault.

■ 6. Precharge (R8)

With 100 Ω and 1,000 μF the time constant is 100 ms. The supervisor closes the contactor after six time constants (0.6 s) and only if the controller reports a bus voltage of at least 90 % of the pack voltage, which catches a shorted bus or a missing capacitor bank. The residual difference at closure is 0.07 to 0.14 V, and the closure inrush is 1.0 A (SwapCell), 1.2 A (CargoMule) and 1.3 A (8S LiFePO₄), under the 5 A target. Peak precharge current is 0.55 A at 54.6 V, and the resistor absorbs 1.49 J per start. Into a shorted bus it would dissipate 30 W; a 1 s timeout limits that to 30 J, which a 10 W aluminum-clad resistor survives. **R8 is met.** The TRL 2 figure of 0.5 s (five time constants) left up to 8 A at closure on a low-resistance LiFePO₄ pack, so the closure point moves to 0.6 s.

■ 7. Speed sensing and reaction times (R5 to R7)

Table 5. Speed sensor pulse rates with eight magnets.

Wheel	At 1.5 m/s	At 25 km/h
20 in, 1.57 m (CargoMule)	7.6 pulses/s (131 ms period)	35.4 pulses/s (28 ms)
700C or 28 in, 2.15 m (SunSpoke)	5.6 pulses/s (179 ms)	25.8 pulses/s (39 ms)
200 mm hub, 0.63 m (walk-behind)	19.0 pulses/s (52 ms)	88.2 pulses/s (11 ms)

Counting pulses over 0.5 s is too coarse at walking pace (one count is 26 % of the reading). The supervisor therefore times each period with a 1 MHz timer (resolution about 0.0035 % at 25 km/h); magnet placement jitter of about 2 % leaves a fivefold margin to the 10 % overspeed threshold. Overspeed held for 0.5 s opens the contactor in about 0.70 s at 1.5 m/s and 0.60 s at 25 km/h on a 20 in wheel, including one pulse period and the 67 ms contactor budget. **R6 is met on paper.** The wheel circumference and magnet count are configuration values; a wrong value moves the limit, so they belong on the fault chart.

Timing budgets: a brake switch sets the controller command to zero in about 75 ms (10 ms debounce, 5 ms loop, 10 ms CAN, 50 ms current ramp), inside 200 ms (**R5 met on paper**). A lost controller heartbeat takes about 170 ms (100 ms timeout plus loop, CAN and ramp), and the contactor is opened as well; a BMS fault, which SwapCell and CellGuard send on change, takes about 80 ms (**R7 met on paper**).

■ 8. CAN buses and bus voltage

The supervisor uses two CAN buses: an internal bus to the controller at 500 kbit/s (the VESC default) and an external bus to the SwapCell pack or CellGuard BMS at the SwapCell rate of 250 kbit/s. The internal bus carries five controller status frames at 50 Hz and commands at 100 Hz, about 11.2 % load. The external bus carries the pack's frames (1.8 %, SWC-CAL-001) plus the supervisor's HOST_HEARTBEAT and a status frame at 10 Hz each, about 2.9 % in total. Keeping the buses apart means the pack never sees controller traffic and no VESC setting has to change.

As a SwapCell host, the supervisor sends HOST_HEARTBEAT as host type 0 (vehicle) and requests mode 2 (discharge). The controller's battery regeneration current is set to zero unless the host enables regeneration, in which case the supervisor requests mode 4 with a host charge limit, as SwapCell interface v0.3 item C allows.

Regeneration at 10 A into a full SwapCell pack raises its terminals to about 55.9 V, inside 58 V. If the contactor opens while the controller is regenerating, the bus rises at about 10 V/ms. With the controller's overvoltage fault set to 60 V, the energy left in the phase inductance (0.12 J) lifts the bus to about 62.0 V, inside the 75 V rating. A direct-drive motor pushed faster than its no-load speed is the remaining risk: its back-EMF stays under 75 V only up to 1.29 times the no-load speed at 58 V, so direct-drive hosts need a speed limit below that or a bus clamp.

■ 9. Size and mass (R12)

The module envelope from the model is 243 x 168 x 66 mm, inside 250 x 170 x 70 mm. The enclosure metal weighs about 1.01 kg (body shell 0.58 kg, fins 0.16 kg, lid 0.26 kg), and the parts inside and on the panel about 0.93 kg, so the module weighs about **1.94 kg against 1.5 kg: R12 is not met.** The TRL 2 estimate of 1.3 kg left out most of the enclosure metal. Thinner walls and lid (2 mm) and 3 mm fins bring it to about 1.63 kg, still over. The kit weighs about 5.3 kg with the reference motor and 2.9 kg without it. The options are listed in [docs/REVIEW.md](#) as proposed, awaiting Amish.

■ 10. Cost (R14)

Under the redefined budget (MTC-DDR-001 item 1) the \$300 covers the MotionCore kit, items 2 to 14 of `bom/`
`bom.csv` : **\$265, a margin of \$35**. The reference hub motor (item 1, \$70) is costed to each host, which brings a complete kit with motor to \$335. The supervisor rose from \$22 to \$30 to carry a second CAN transceiver and the 18 to 75 V auxiliary buck, and the pads and consumables from \$6 to \$8. All prices are indicative. **R14 is met on indicative prices.**

■ 11. Results against requirements

Table 6. Requirement status (not met and at risk first).

ID	Value	Target	Status
R12	243 x 168 x 66 mm; 1.94 kg	250 x 170 x 70 mm; 1.5 kg	Not met (mass)
R2	250 W: 6.9 A; 350 W: 17.7 A; 750 W for 10 s: 21.9 A (SwapCell), 40.9 A (8S LFP)	250 W reference; 350 W heavy; 750 W for 10 s	At risk (heavy case thermal, R9)
R9	50.2 °C reference; 58.5 °C heavy (65 to 71 °C in sensitivity cases)	60 °C at 40 °C ambient	At risk
R10	XT90 not sealed; M12 and motor plug sealed when mated; vibration not analyzed	IP65; survive vibration	At risk
R11	Interface v0.1 adopted and drawn (MTC-DWG-001); fit time needs a timed fit	One keyed set; fit in 2 h	Not verifiable at TRL 3
R1	Three host packs inside 20 to 58 V; 75 V controller; 18 to 75 V auxiliary buck	20 to 58 V; 75 V transients	Met (design review)
R3	67 ms worst case, 30 ms modeled; no firmware in the path	100 ms	Met (paper)
R4	Key reset; supervisor enable conditions	No automatic restart	Met (design review)
R5	75 ms	200 ms	Met (paper)
R6	Period method; 5x margin over jitter; trip 0.60 to 0.70 s	10 % for 0.5 s	Met (paper)
R7	170 ms worst	200 ms	Met (paper)
R8	0.55 A peak; 1.3 A at closure; ready in 0.6 s	Under 5 A; 1 s	Met
R13	MIT supervisor on its own processor; unmodified GPL-3.0 VESC firmware; CAN link only	Open hardware and firmware	Met (design review); formal license review open
R14	\$265 for items 2 to 14	\$300	Met (indicative prices)

■ 12. Checks against earlier documents

The TRL 2 figures in MTC-PRC-001 v0.2, MTC-REQ-001 v0.2 and the README were checked against this script and corrected in v0.3: pack power 333 W to 322 W; reference current 7.1 A to 6.9 A; CargoMule current 9.3 A at 36 V to 8.4 A at 38.4 V (CargoMule uses a 12S LiFePO4 pack); controller loss 16 W to 3.9 W; reference case temperature 55

°C to 50 °C; 500 W case 67 °C to 68 °C (now information only); heavy case now 350 W and 58.5 °C; e-stop time about 60 ms to 67 ms worst case; precharge closure 0.5 s to 0.6 s; module envelope 250 x 170 x 66 mm to 243 x 168 x 66 mm; module mass 1.3 kg to 1.94 kg; kit mass 4.4 kg to 5.3 kg; cost \$325 for the full kit to \$265 for the MotionCore kit plus \$70 for the reference motor (\$335 with motor). The speed-sensor pulse rates (7.5 and 35 pulses per second) and the precharge peak (0.55 A, 1.5 J) stand.

Safety: These are paper estimates for a module that switches a lithium pack able to deliver several hundred amperes into a short and drives moving machinery. They do not replace a circuit review, datasheet checks or testing of the safety functions. Nothing may be built or energized from this note; building and testing are TRL 4 work and on hold by Amish's instruction.