

NOISEMAP · CALCULATION NOTE

NoiseMap sizing calculations

Design Molecule Lab · designmolecule.com

DOCUMENT CONTROL

Document ID	NSM-CAL-001	Version	0.3
Status	Draft	Date	2026-10-01
Author	Amish Chadha	License	CERN-OHL-S-2.0
Project TRL	TRL 3 Proof of concept		
Repository	github.com/BoujeeEnjinia1701/noisemap		
Source	docs/04-calcs/01-sizing.md @ uncommitted		

REVISION HISTORY

Version	Date	Author	Change
0.3	2026-10-01	Amish Chadha	Mechanics, mass and cost re-run for the constructable design (NSM-DDR-003); FieldNode core at FND-CAL-001 v0.3; budget treated as a value-engineering target
0.2	2026-09-25	Amish Chadha	Recommendations accepted by Amish (DDR-002); pocketed V-blocks and saddle, corrected V-block geometry, R10 at 3.5 kg, interval rule for R12, level-based wind flag
0.1	2026-09-25	Amish Chadha	First issue for TRL 3 (measuring range, frequency response, reflections and accuracy, processing and power, energy, record format, airtime, privacy capacity, wind and rain flagging, mechanics, mass, cost)

NoiseMap sizing calculations

On paper, NoiseMap meets eight of its fifteen requirements (four by calculation, four by design), has three at risk, misses none and leaves four that only tests can settle. Under NSM-DDR-002 R10 is relaxed to 3.5 kg. With the design made constructable (NSM-DDR-003: sawn and drilled V-blocks, a bent sheet arm saddle with two bands, fixings throughout, and the FieldNode core without its small-pole V-blocks and bands), the node weighs **3.45 kg against 3.5 kg (R10)**, a margin of only 0.05 kg. An automatic interval rule at slow data rates brings R12 within fair use at every spreading factor. Energy is not a concern: the design load is 12.2 mW, 12 % of FieldNode's 100 mW allowance, which gives 53 days without sun and keeps the node in credit even on the hot clear days that stop FieldNode charging. The measuring range reaches 35 dBA with no margin on the ICS-43434 (34.9 dBA) and with 7 dB of margin on the IM72D128 (27.9 dBA), and tops out at 113 dBA. Accuracy (R3) is at risk: an assumed uncertainty budget gives ± 2.9 dB, and a facade behind the pole can add up to 2.4 dB before a site correction. Under NSM-DDR-001 D1 the \$100 `budget_usd` applies to the NoiseMap parts; it is a value-engineering target, not a limit. The constructable NoiseMap parts are estimated at \$72.00, \$28.00 under the target; the full node with the FieldNode core is \$211.00.

Every number in this note is printed by `docs/04-calcs/sizing.py` (run from the repo root: `python docs/04-calcs/sizing.py`), which also writes `docs/04-calcs/results.csv`. The tag in brackets, for example [A1], is the line of the script's output that carries the number. The script imports `PARAMS`, `derived()` and the part volumes from `cad/src/model.py`, reads `bom/bom.csv` and `budget_usd` in `project.yaml`, and takes FieldNode energy figures from FND-CAL-001 v0.1 and its mass from FND-CAL-001 v0.3.

Safety: These are first-principles estimates for a paper proof of concept. They do not show that the pole mounting, the lithium iron phosphate cell or the installation is safe. Clamp preload, arm fixing and the cell's charge lockout must be checked on hardware before any node is installed. See NSM-PRC-001, Safety.

■ Assumptions

Table 1. Main assumptions.

Area	Assumption	Basis
ICS-43434	65 dB SNR, sensitivity -26 dBFS at 94 dB SPL, 120 dB SPL overload, response 60 Hz to 20 kHz, listed end of life; supply 0.49 mA	TDK product page (TDK InvenSense); current is a typical class value, not checked
IM72D128	72 dB(A) SNR, PDM output, IP57 at part level; overload and roll-off taken equal to the ICS-43434; supply 1.0 mA	DNMS README (DNMS); overload, roll-off and current not checked
Range criteria	Lower limit where self-noise adds 1 dB; 10 dB crest factor above the rms level for traffic, horns and sirens	Screening values
Response limits	± 2.5 dB at 63 Hz and ± 5 dB at 8 kHz, taken as the class 2 limits; low-frequency corner spread ± 20 %	Approximate; the IEC 61672-1 table was not re-checked in this session
Processing	48 kHz; seven biquads (A 3, C 2, low-frequency equalizer 1, wind band 1) at 14 cycles each; four channels at 6 cycles; 10 cycles overhead; 48 MHz clock; 120 μ A/ MHz running, 1.6 mA asleep with DMA running	STM32L4 class typical figures; to confirm on the chosen board
FieldNode core	4.0 mWh/day core; 15.36 Wh usable; 70 % at -20 °C, 80 % at end of life; rail 90 %; controller 8 mA awake, woken for each 12-byte frame at 9,600 baud plus 5 ms	FND-CAL-001 v0.1; the wake overhead is assumed
Energy chain	6 W panel, 1.5 peak sun hours (NoiseMap design case), 0.80 derating, charger 0.85, cell 0.95	NSM-REQ-001 Table 2; FND-CAL-001
Radio	22-byte record plus 13 bytes of LoRaWAN overhead; 125 kHz, CR 4/5, 8-symbol preamble, explicit header, CRC; 96 uplinks a day	LoRaWAN defaults
Speech codec	Codec 2 runs at 700 to 3,200 bit/s	Rowetel, Codec 2
Reflections	Incoherent addition; facade energy reflection 0.9; lanes 5 and 10 m from the microphone	Screening values
Wind	35 m/s gust, 1.225 kg/m ³ ; Cd 1.2 on tubes, 0.5 on the foam sphere; 6063-T5 class E = 69 GPa, yield 145 MPa; band preload 1,000 N and friction 0.2; turbulence intensity 0.2 at 4 m	Handbook ranges; preload as FND-CAL-001
Mass	Aluminium 2.70, stainless steel 7.90, ASA 1.07, nylon 1.15, foam 0.030 g/cm ³ from model volumes (printed parts counted solid); boards 15 g, cable 90 g, ties, tape and small parts 30 g; FieldNode base node 2.45 kg (FND-CAL-001 v0.3) less its small-pole V-blocks and 80 g of bands, which a street pole node leaves off (NSM-DDR-003)	Estimates

■ A. Measuring range (R4)

- **Self-noise and lower limit.** The ICS-43434 has 29.0 dBA of self-noise, so a 35 dBA street reads 0.97 dB high; the 1 dB lower limit is **34.9 dBA**, with no margin on the 35 dBA target. The IM72D128 has 22.0 dBA of self-noise and a lower limit of **27.9 dBA** [A1].

- **Noise-floor subtraction** helps only as far as the self-noise is known: with the ICS-43434 at 35 dBA, an error of ± 1 dB in the stored self-noise leaves the result between 34.71 and 35.22 dBA [A2]. The adapter board of D3 lets a quiet-street node use the IM72D128.
- **Upper limit.** The ICS-43434 reaches full scale at 120 dB SPL rms for a sine, 123 dB peak [A3]. With a 10 dB crest factor the highest rms level measured cleanly is **113 dB**, against the 110 dBA target. The TRL 2 figure of 115 dBA ignored crest factor. The IM72D128 overload point was not checked and is taken as the same.
- **R4 is at risk** with the ICS-43434 and met on paper with the IM72D128.

■ B. Frequency response (R5)

- **Low frequencies.** Treating the 60 Hz lower limit as a first-order corner, the microphone is down 0.9 dB at 125 Hz, 2.8 dB at 63 Hz and 6.7 dB at 31.5 Hz [B1]. A fixed digital equalizer in the head restores this; if the corner varies by ± 20 % between parts, the residual is ± 0.8 dB at 63 Hz and about ± 1.4 dB at 31.5 Hz [B2], inside the ± 2.5 dB taken as the class 2 limit at 63 Hz. The equalizer adds 6.7 dB of gain at 31.5 Hz, where A weighting is -39.4 dB, so LAeq self-noise barely changes; LReq self-noise rises at low frequencies [B2b].
- **Acoustic port.** The 3 mm port through the 2 mm top plate and a 3 x 0.5 mm front cavity (the gasket gap between plate and microphone board) resonate at **36.2 kHz**, adding 0.44 dB at 8 kHz undamped [B3]. A tenfold larger cavity would resonate at 10.4 kHz and add 7.9 dB at 8 kHz [B3b], so the cavity must stay small. These dimensions are parameters in `cad/src/model.py`.
- **R5 is at risk.** The hydrophobic membrane, the windscreen and diffraction round the 40 mm head all shape the response above about 2 kHz, and none can be calculated with confidence on paper.

■ C. Reflections and accuracy (R3)

- **Pole.** A 114.3 mm pole 0.45 m behind the microphone reflects 6.0 % of the direct energy back to it, adding 0.25 dB [C1]. The FieldNode core sits in the pole's shadow on the far side.
- **Facades.** A facade behind the pole adds more (Table 2) [C2]. At 1 to 2 m the bias is 1.1 to 2.4 dB, which approaches the whole ± 2 dB of R3.

Table 2. Level added by a facade behind the microphone (energy reflection 0.9).

Facade distance	Lane 5 m, point source	Lane 5 m, traffic line	Lane 10 m, point source	Lane 10 m, traffic line
1 m	+1.6 dB	+2.2 dB	+2.1 dB	+2.4 dB
2 m	+1.1 dB	+1.8 dB	+1.6 dB	+2.2 dB
5 m	+0.4 dB	+1.1 dB	+0.9 dB	+1.6 dB
10 m	+0.2 dB	+0.7 dB	+0.4 dB	+1.1 dB

- **Uncertainty budget.** With assumed standard uncertainties of 0.4 dB for the calibrator, 0.5 dB for drift between checks, 0.5 dB for the windscreen, 0.7 dB for the response residual and 1.0 dB for reflections after a site correction, the combined value is 1.47 dB and the expanded value ($k = 2$) **2.9 dB** against ± 2 dB [C3], [C3b]. **R3 is at risk.** The side-by-side comparison of D7 is what sets the site correction; only it can show whether R3 is met.

■ D. Processing and power (R7)

- **Processor load.** Seven biquads and four channels take 132 cycles per sample: 6.34 million cycles a second, 13.2 % of a 48 MHz core. At 32 kHz this falls to 4.22 million [D1]. The TRL 2 question on sample rate therefore does not affect power much; 48 kHz stays.
- **Current.** Running 13.2 % of the time at 5.76 mA and sleeping with DMA at 1.6 mA, the processor averages **2.15 mA** [D2]. The TRL 2 assumption was 5 mA.
- **Node load.** With the ICS-43434 the head takes 9.7 mW from the cell and the node 10.3 mW; with the IM72D128 the head takes 11.5 mW and the node **12.2 mW** (0.292 Wh a day), the design value. Waking the FieldNode controller for each one-second frame costs 0.46 mW, more than the 0.17 mW of the rest of the core [D3]. With the TRL 2 processor current and a 1 mA microphone the upper bound is 22.6 mW (0.543 Wh a day) [D4]. The design load is 12 % of FieldNode's 100 mW design allowance [D5].

■ E. Energy (R7)

- **Harvest.** At 1.5 peak sun hours the cell stores 5.81 Wh a day, 20 times the design load and 11 times the upper bound; FieldNode's worst month (2 h) gives 7.75 Wh [E1].
- **Autonomy.** At the design load one cell lasts **53 days** without sun, 37 days at -20 °C and 42 days at end of life; the upper bound, cold and aged, still gives 16 days [E2], against 14.
- **Hot weather.** FieldNode's hot clear day without a shield stores 0.8 Wh (clean) or 0.3 Wh (dusty) because the cell is above its 45 °C charge limit most of the day. NoiseMap draws 0.29 Wh at the design load, so it stays in credit, marginally when dusty; at the upper bound (0.54 Wh) a dusty node would lose charge [E3]. The FieldNode sun shield decision (FieldNode review item 4) matters little to NoiseMap.
- **R7 is met on paper.**

■ F. Record, radio and privacy (R1, R2, R6, R12)

- **Record.** Fifteen 1-minute LAeq bytes, LAeq,15min, LAFmax, LAFmin, L10, L90, LCEq and a status byte make **22 bytes**; one byte at 0.5 dB steps spans 20.0 to 147.5 dB [F1]. The status byte carries the wind flag and the count of flagged minutes. R2 is met by design.
- **Airtime (Table 3).** At SF9 each uplink takes 246.8 ms, 23.7 s a day. At SF10 the 35-byte frame takes 493.6 ms and 47.4 s a day, over The Things Network's 30 s [F2]. A stored record sent later carries a 4-byte time stamp (267.3 ms at SF9) [F2b]. The EU868 1 % duty cycle is met at every spreading factor.
- **Interval rule (NSM-DDR-002, item 04).** The core keeps 15 minutes at SF7 to SF9 and lengthens the interval automatically at slower data rates to the shortest that fits 30 s a day: 24 min at SF10 (29.6 s a day, 60 records), 48 min at SF11 (29.6 s, 30 records) and 87 min at SF12 (30.0 s, 16 records). The record stays 22 bytes; its fifteen sub-interval LAeq values then each span 1.6, 3.2 or 5.8 minutes [F2c]. **R12 is met on paper** with this rule, which follows FieldNode's own interval item.

Table 3. Time on air for a 22-byte record (35 bytes on air) at 125 kHz [F2].

Spreading factor	Per uplink	Per day at 15 min	Shortest interval within 30 s/day	EU868 1 % off-time
SF7	77.1 ms	7.4 s	4 min	8 s
SF8	143.9 ms	13.8 s	7 min	14 s
SF9	246.8 ms	23.7 s	12 min	24 s
SF10	493.6 ms	47.4 s	24 min	49 s
SF11	987.1 ms	94.8 s	48 min	98 s
SF12	1,810.4 ms	173.8 s	87 min	179 s

- **Time stamps.** The core stamps each record from LoRaWAN network time (DeviceTimeReq), which is well within 2 s; R6 is met by design.
- **What the links could carry (R1).** Raw audio is 1.152 Mbit/s. The UART carries 7,680 bit/s of payload, 150 times too slow for raw audio, and the level frames use 1.25 % of it. A speech codec such as Codec 2 needs 700 to 3,200 bit/s, which the cable could carry [F3]. The radio could carry 21.4 kbit a day at SF9 under fair use, about 31 s of 700 bit/s speech, or 1.97 Mbit a day at SF7 under the 1 % duty cycle alone, about 47 min [F4]. The physical links do not rule out leaking speech, so, as D2 states, privacy rests on the open head firmware, read-out protection and a published build hash. R1 is met by design on that basis.

■ G. Wind and rain flagging (R11)

- **Wind.** Turbulence at 4 m makes pressure fluctuations of about 1 Pa rms at 2 m/s, 6 Pa at 5 m/s and 25 Pa at 10 m/s at an unscreened microphone (94, 110 and 122 dB), mostly below 20 Hz [G1]. The foam windscreen removes much of this, but what reaches the microphone scales roughly with the fourth power of wind speed: from 2 to 5 m/s it rises by 15.9 dB, and 1 m/s near 5 m/s is 3.2 dB [G2]. A Z-weighted band below 40 Hz, computed in the head, and its one-second spread therefore separate windy minutes sharply from traffic once a threshold is set. The threshold cannot be computed; it needs a field comparison with an anemometer.
- **Rain.** Rain on the foam gives broadband impulses that level statistics do not reliably separate from street noise. The method is a server-side flag from the nearest public weather station or radar rainfall, which needs no hardware.
- **Wind sensor option, not adopted.** A cup anemometer with a pulse output on FieldNode's second port would cost about \$25 and weigh about 0.15 kg (indicative, unchecked), bringing the NoiseMap parts to \$97.00 and the node to 3.60 kg, over R10 [I3]. Under NSM-DDR-002 (item O3) the level-based flag is the method, so no anemometer is fitted.
- **R11 is not verifiable at TRL 3.** The method is chosen; the threshold needs a field comparison with an anemometer, which is TRL 4 work and on hold.

■ H. Mechanics (R10)

- **Mass.** The FieldNode base node is 2.45 kg; a street pole node leaves off its V-blocks (0.144 kg) and bands (0.08 kg), which gives 2.23 kg. To that the arm saddle, tube, flange and fixings add 0.391 kg, the arm bands and lanyard 0.129 kg, the head housing, cap and bolts 0.108 kg, the boards 0.015 kg, the windscreen and spike 0.023 kg, the cable and gland 0.099 kg, the street pole V-blocks and screws 0.314 kg, their bands 0.114 kg, and ties and small parts 0.030 kg [H1]: **3.45 kg against the relaxed 3.5 kg, so R10 is met on paper**, with 0.05 kg of

margin [H2]. Sawing the V-blocks from 16 mm bar rather than 20 mm and drilling four 14 mm holes in each saves 0.144 kg [H2b].

- **History.** Version 0.2 also gave 3.45 kg, with machined, pocketed 110 x 60 x 40 mm V-blocks, a pocketed saddle, one arm band and the 2.41 kg FieldNode core with its small-pole parts left in. The constructable design (NSM-DDR-003) adds a second arm band, a tube flange, a head cap, a gland and fixings, and leaves the FieldNode small-pole parts off; the two roughly balance.
- **Wind on the arm.** At 35 m/s (750 Pa) the 383 mm arm takes 8.6 N, the head tube 3.8 N and the windscreen 2.4 N [H3]. The arm root sees 4.01 N·m from wind and 0.83 N·m from weight, 4.10 N·m combined; the 25 x 2 mm tube (770 mm³ section modulus) is stressed to 5.3 MPa, a factor of 27 on yield [H4]. The tip moves 0.26 mm in the gust.
- **Vibration.** The arm and head have a first mode near 70 Hz. Vortex shedding matches it at about 8.8 m/s across the arm and 14.1 m/s across the head [H5]. Stresses are low, but vibration at those speeds would add structure-borne noise at the microphone, and those intervals are windy enough to be flagged anyway.
- **Clamp.** The arm saddle now has two bands. Wind twists it about the pole with 4.86 N·m against 45.7 N·m of friction (factor 9.4), and the arm and head pull it down with 6.5 N against 800 N [H6]. Both depend on the assumed 1,000 N preload per band.
- **Pole load.** The node adds about 96 N at 3.5 to 4 m in a 35 m/s gust (81 N from FieldNode) [H7], which the pole owner should check.
- **Fit.** On a 60 mm pole the V contacts sit 21.2 mm either side of the centre line and on a 140 mm pole 49.5 mm, inside both the V-blocks' 106 mm mouth and the saddle's 109 mm mouth; poles up to 141 mm keep their contacts 3 mm inside both [H8], [H8b]. The street pole bands need about 369 to 558 mm. The fit to 60 to 140 mm poles is met by design; the 45 min installation time can only be timed.

■ I. Cost (R13)

The BOM has 14 lines, all priced. Lines 1 to 6, the FieldNode core, total \$139.00, the base node figure in the FieldNode BOM after its own design for construction (FND-DDR-003); lines 7 to 14, the NoiseMap parts, total **\$72.00** [I1]. Value-engineering target: USD 100 (`budget_usd` , a hypothetical control target, not a limit). Estimated cost of the constructable design: USD 72.00 for the NoiseMap parts (USD 28.00 under the target); the full node is USD 211.00 [I2]. **R13 is met on paper.** The constructable design added \$10.00 to the NoiseMap parts (two-band saddle and tube flange \$6.00, cable gland \$1.00, fixings and lanyard \$2.00, head cap \$1.00) and the FieldNode core rose from \$126.00 to \$139.00 under FND-DDR-003.

■ L. Results against every requirement

Table 4. Requirement status (weakest first) [L].

ID	Requirement	Value	Target	Status
R3	Accuracy	Expanded uncertainty 2.9 dB (assumed terms); facade bias up to +2.4 dB before site correction	±2 dB, 40 to 100 dBA	At risk
R4	Measuring range	ICS-43434 34.9 to 113 dBA; IM72D128 27.9 to 113 dBA	35 to 110 dBA	At risk (no margin with ICS-43434)
R5	Frequency weighting	-2.8 dB at 63 Hz before equalizing, ±0.8 dB after; port resonance 36 kHz	Class 2 limits, 63 Hz to 8 kHz	At risk (membrane, windscreen, head)
R8	Ingress and weather	FieldNode IP65; head skirt, membrane, bored windscreen	IP65; driving rain; -20 to +50 °C	Not verifiable at TRL 3
R9	Calibration check	Calibrator fits the head with the windscreen off; offset stored in the head	10 min or less	Not verifiable at TRL 3
R11	Contaminated data	Level-based wind flag; server rain flag	Flag wind above 5 m/s and heavy rain	Not verifiable at TRL 3 (method chosen; threshold on hold with TRL 4)
R14	Service life	ASA, yearly windscreen, FieldNode cell swap	5 years	Not verifiable at TRL 3
R10	Installation and mass	3.45 kg constructable design; arm factor 27 on yield; clamp twist factor 9.4; fits 60 to 140 mm poles	3.5 kg or less; 35 m/s gusts; two people, 45 min	Met on paper on mass (margin 0.05 kg); wind met on paper; time not verifiable at TRL 3
R12	Radio use	15 min at SF7 to SF9 (23.7 s/day at SF9); 24, 48 and 87 min at SF10 to SF12 (at most 30.0 s/day)	1 % duty cycle; 30 s/day	Met on paper (interval rule)
R7	Energy	5.81 Wh/day stored against 0.29 Wh/day; 53 days without sun (16 cold, aged, upper bound)	Neutral at 1.5 h; 14 days	Met on paper
R13	Parts cost	NoiseMap parts \$72.00; full node \$211.00	NoiseMap parts at or under the \$100 value-engineering target	Met on paper (USD 28.00 under the target)
R1	Privacy	No storage or radio in the head; firmware sends levels only	Levels only; published build hash	Met by design (rests on firmware)
R2	Reported metrics	22 bytes per 15 min	Metric set per D5	Met by design
R6	Time stamps	LoRaWAN network time	Within 2 s of UTC	Met by design
R15	Openness	Repo licenses; method and format here	All published	Met by design

Counts [L2]: 0 not met, 3 at risk, 4 not verifiable at TRL 3, 4 met on paper, 4 met by design.

■ Checks against the TRL 2 figures

TRL 2 claim (NSM-PRC-001 v0.2)	This note	Action
Range about 35 to 115 dBA	34.9 (27.9 with IM72D128) to 113 dBA	Precis and README updated
Processor about 5 mA; head 18 mW; node 21 mW, 0.51 Wh/day	2.15 mA; head 9.7 to 11.5 mW; node 12.2 mW, 0.29 Wh/day (22.6 mW upper bound)	Precis, README and flow updated
Autonomy about 30 days	53 days (37 at -20 °C)	Updated
Winter harvest about 5.8 Wh/day	5.81 Wh/day	Stands
Airtime about 24 s/day at SF9; 47 s at SF10	23.7 s and 47.4 s	Stands
Mass about 2.3 kg; R10 met	3.45 kg for the constructable design against the relaxed 3.5 kg (v0.2: 3.45 kg pocketed; v0.1: 3.32 kg, with the V-blocks wrongly modeled as flat plates)	Updated per NSM-DDR-002 and NSM-DDR-003
Wind load on the panel about 50 N	52.2 N (FND-CAL-001); 16 N more on the arm and head	Updated
Cost about \$171 (core \$119, NoiseMap \$52)	\$211.00 (core \$139.00, NoiseMap \$72.00 with the adapter and construction parts)	BOM, precis and README updated
Microphone 0.45 m from the pole; arm about 400 mm	0.45 m; arm tube 383 mm between the flange socket and the head socket	Stands
Cable "far too slow" for audio	Too slow for raw audio, fast enough for a speech codec	Precis wording follows D2