

POTHOLELOG · CALCULATION

PotholeLog sizing calculations

Design Molecule Lab · designmolecule.com

DOCUMENT CONTROL

Document ID	PHL-CAL-001	Version	0.5
Status	Draft	Date	2026-10-02
Author	Amish Chadha	License	CERN-OHL-S-2.0
Project TRL	TRL 3 Proof of concept		
Repository	github.com/BoujeeEnjinia1701/potholelog		
Source	docs/04-calcs/01-sizing.md @ uncommitted		

REVISION HISTORY

Version	Date	Author	Change
0.5	2026-10-02	Amish Chadha	Approved follow-ups carried out: status light pipes and LEDs, breather vent and nameplate label (BOM lines 14 to 16) added to the model and BOM; mass, fixings, stiffness and cost re-run; R15 moves from met on paper to not met (\$2.50 over the target)
0.4	2026-10-02	Amish Chadha	Requirement table wording for R13 and R14 follows the decisions of 2026-10-02; no result changed
0.3	2026-10-01	Amish Chadha	Design made constructable (PHL-DDR-003); mass, fixings, plate stiffness and cost re-run; budget treated as a value-engineering target
0.2	2026-09-25	Amish Chadha	Recommendations accepted by Amish (DDR-002)
0.1	2026-09-25	Amish Chadha	First issue for TRL 3 (vehicle and road model, roughness signal and calibration, pothole detection, location, storage and upload, power and transients, hold-up, environment, plate stiffness, installation, cost)

PotholeLog sizing calculations

On paper, PotholeLog meets seven of its sixteen requirements (three by calculation, four by design), has six at risk, cannot show two at TRL 3 and misses one (R15, cost, \$2.50 over the value-engineering target since the parts adopted on 2026-10-02). Version 0.2 applies Amish's 2026-09-25 decisions (PHL-DDR-002). Version 0.1 found two misses. First, a bus tyre largely bridges the R1 reference pothole (50 mm deep, 300 mm long), so a floor-mounted logger sees it clearly only at low speed: in the quarter-car model the impact stands above ordinary road vibration up to about 20 km/h on a fair road (IRI 4) and about 50 km/h on a good one (IRI 2), and not at 80 km/h. R5's defect-detection range is now restated as 10 to 30 km/h, relying on repeat slow passes near stops and junctions; it is met on good roads and misses by a hair (margin 0.97) at 30 km/h on fair ones, so R5 moves from not met to at risk, and R1 stays at risk. Second, the 9 to 36 V converter was exceeded by a suppressed load dump on a 24 V vehicle. The BOM now carries a 60 V-rated converter, which clears the 58 V load dump and the 58.1 V TVS clamp by 1.9 V; the TVS pulse energy is unverified, so R9 moves from not met to at risk. Version 0.3 re-runs the mass, fixing, stiffness and cost lines for the constructable design of PHL-DDR-003, which adds a carrier plate for the modules and a box fixing kit: the logger is now 0.43 kg, the plate's first mode 168 Hz (still above the 150 Hz target) and the estimated cost \$74.00, \$1.00 under the \$75 value-engineering target. Version 0.5 adds the status light pipes and LEDs, the breather vent and the nameplate label that Amish adopted on 2026-10-02: the logger is 0.44 kg, the first mode stays at 168 Hz and the estimated cost is \$77.50, \$2.50 over the target, so R15 moves from met on paper to not met. The roughness function itself looks sound: the signal is 12 times the sensor noise at 20 km/h on a smooth road, and a synthetic calibration against IRI gives r^2 of 0.93 from one pass and 0.99 from five. Every number in this note is printed by `docs/04-calcs/sizing.py`; the tag in brackets, for example [C2], is the line of that script's output that carries it.

Safety: These are first-principles estimates for a paper proof of concept. They are not a survey method, an automotive electrical approval or a mounting approval. Outputs must not drive contract acceptance or safety decisions without validation against a calibrated reference. See PHL-PRC-001, Safety.

■ Scope and method

The note checks every requirement in PHL-REQ-001 v0.5 against the design in PHL-PRC-001 v0.5, the constructable design of PHL-DDR-003 and the parametric model `cad/src/model.py`. The script imports the model's `PARAMS`, derived dimensions and part volumes, so the plate, hole pattern, enclosure and masses used here are the ones in the STEP files and in drawing PHL-DWG-001. It also reads `bom/bom.csv` and `budget_usd` in `project.yaml`. Run it from the repo root with `python docs/04-calcs/sizing.py`.

The vehicle is a linear quarter-car model of one side of a 12 m city bus's rear axle: sprung body, unsprung axle and twin tyres. Random road profiles follow the ISO 8608 spectral shape and are solved in the frequency domain; their IRI comes from the standard golden-car model at 80 km/h, following World Bank Technical Paper 46. A single pothole is enveloped by a rigid tyre circle and solved in the time domain. The logger reads the body's vertical acceleration at the floor centerline above the axle.

■ Assumptions

Table 1. Main assumptions.

Area	Assumption	Basis
Vehicle	Per side: sprung mass 4,500 kg (3,500 empty to 5,250 laden), unsprung 500 kg; body frequency 1.2 Hz with 20 % damping (air suspension); twin tyres 1.8 MN/m; tyre radius 0.52 m; wheelbase 6 m	Typical 12 m city bus; to confirm with the pilot fleet
Road	ISO 8608 displacement spectrum with slope 2 (1.8 to 2.2 for the calibration study), 0.01 to 10 cycles/m, 250 mm moving average as the tyre patch	ISO 8608 shape; the classes are mapped to IRI in [A2]
Logger position	Floor centerline above the axle sees half of a one-sided input (bounce only) and 0.87 of the single-track random input (left and right tracks correlated at 0.5)	Assumed; roll and pitch are not modeled
Sensor	400 Hz output, ± 16 g, noise about 100 $\mu\text{g}/\sqrt{\text{Hz}}$; roughness metric band 0.5 to 20 Hz	LSM6DSO class; to confirm from the datasheet
Detection	A pothole is detected when its floor peak exceeds the level that ordinary roughness crosses once per km (Rice formula, Gaussian roughness); lateral wander σ 250 mm; twin-tyre width 0.6 m	Assumed; real roads have joints, covers and bumps that are not Gaussian
Location	M10-class GNSS, open-sky CEP 1.5 m; σ 3 m per axis suburban, 10 m in dense urban streets with errors 0.5 correlated between passes; PPS time-stamping to 10 ms	Class figures; urban values assumed
Data	6 axes x 16 bit at 400 Hz; 40 B GNSS record at 10 Hz; 8 B time stamp per 100 samples; 10 to 12 h of driving and 200 km a day; 500 events a day; 32 GB card with 94 % usable	As at TRL 2, with the record layout now defined
Power	3.3 V loads 91 mA (ESP32-S3 60 mA at 240 MHz with radio off, board 10 mA, GNSS 10 mA, card 10 mA average, IMU 1 mA); linear regulator on the board from 5 V; 85 % converter efficiency; Wi-Fi adds 150 mA while uploading	Typical module figures; to confirm by measurement later
Transients	Suppressed load dump of 35 V (12 V systems) and 58 V (24 V systems), as understood from ISO 16750-2 test B	To confirm from the standard
Hold-up	1 F, 5.0 V rail less a 0.3 V diode, regulator dropout floor 3.6 V; capacitance 70 % at end of life and at -20 °C; 1 s to flush and close files	Typical supercapacitor data; worst-case card write latency
Structure	Aluminum E = 70 GPa; plate on four corner bolts with nothing beneath, half the width effective; 20 g crash pulse, M6 property class 8.8	Conservative screening values, not a vehicle-code check

■ A. Road and vehicle model

- **Vehicle.** The bus corner has a 1.2 Hz body mode (256 kN/m, 13.6 kN·s/m) and a 10.2 Hz wheel-hop mode [A1].
- **Road classes on the IRI scale.** ISO 8608 classes A, B, C and D come out at 2.17, 4.35, 8.69 and 17.38 m/km [A2]. IRI scales with the square root of the spectrum level, so IRI 2, 4 and 6 m/km correspond to $G_d(n_0)$ of 13.6, 54.2 and $122.0 \times 10^{-6} \text{ m}^3$ [A3]. In this note "IRI 2" stands for a good urban road and "IRI 4" for a fair one.

■ B. Roughness signal and calibration (R3, R5)

- **Noise.** The IMU's noise over the 0.5 to 20 Hz band is 4.3 mm/s² RMS, and one count at ± 16 g is 4.8 mm/s² [B1].
- **Signal.** The floor RMS acceleration in that band rises with IRI and with speed [B2]:

Table 2. Floor RMS acceleration in the 0.5 to 20 Hz band, m/s² [B2].

IRI	10 km/h	20 km/h	30 km/h	50 km/h	80 km/h
1 m/km	0.031	0.051	0.066	0.089	0.114
2 m/km	0.062	0.102	0.133	0.178	0.228
4 m/km	0.123	0.204	0.266	0.356	0.456
6 m/km	0.185	0.306	0.398	0.533	0.684

- **Low speed.** On a smooth road (IRI 1) the signal is 7 times the noise at 10 km/h and 12 times at 20 km/h [B3]. The 20 km/h floor of the roughness range in R5 is supported; the sensor is not the limit.
- **Speed.** At IRI 2 the RMS at 80 km/h is 2.23 times the 20 km/h value; even normalized by the square root of speed it varies 1.31 to 1 over 10 to 80 km/h [B4]. The metric must be calibrated per speed band, as TRL 2 assumed.
- **Scatter.** A 100 m segment at 50 km/h holds 7.2 s of data. With an effective bandwidth of 3.33 Hz, one RMS estimate scatters by 14 %, falling to 6 % averaged over five passes [B5].
- **Calibration.** For 40 synthetic sections from IRI 1 to 8 m/km with spectral slopes from 1.8 to 2.2, a straight-line fit of IRI on floor RMS gives r^2 of 0.998 with expected values, 0.934 from one pass and 0.992 from five passes, with a slope of 11.1 m/km per m/s^2 [B6]. This supports the response-type method and the R3 target of r^2 0.8, but only a calibration on real reference sections can verify R3.
- **Load.** From empty to laden, the floor RMS changes from 1.07 to 0.96 of its mid-load value with air suspension, and from 1.22 to 0.89 with steel springs [B7]. Buses with air suspension need no load correction beyond this ± 7 %; refuse trucks on steel springs need a load flag or calibration by load state.

■ C. Pothole detection (R1, R2, R5, R6)

- **The tyre bridges the hole.** A 1,040 mm tyre can drop only 22.1 mm into a 300 mm long pothole, however deep it is, and the loaded tyre's contact patch is about 337 mm long [C1]. A bus sees the R1 reference pothole as a 22 mm dip.
- **Floor peak against background.** The floor peak from the reference pothole falls with speed while ordinary road vibration rises:

Table 3. Reference pothole (50 mm deep, 300 mm long) against a threshold that ordinary roughness crosses once per km [C2], [K1].

Speed	Floor peak	Threshold, IRI 2	Margin, IRI 2	Threshold, IRI 4	Margin, IRI 4
10 km/h	1.35 m/s^2 (0.138 g)	0.24 m/s^2	5.64	0.48 m/s^2	2.82
20 km/h	1.20 m/s^2	0.40 m/s^2	3.03	0.79 m/s^2	1.51
30 km/h	0.98 m/s^2	0.51 m/s^2	1.94	1.01 m/s^2	0.97
50 km/h	0.71 m/s^2	0.66 m/s^2	1.07	1.32 m/s^2	0.54
80 km/h	0.48 m/s^2	0.82 m/s^2	0.59	1.64 m/s^2	0.30

Margins below 1 (bold) mean the pothole is lost in ordinary road vibration.

- **Relaxing the threshold does not rescue high speed.** Allowing 10 background crossings per km, which clustering over repeat passes could tolerate, raises the IRI 4 margins only to 1.17 at 30 km/h and 0.66 at 50 km/h [C2b]. A band-pass detector tuned to the wheel-hop band gave similar margins in a side check, so the limit is physical, not the choice of filter.
- **Longer potholes are found at all speeds.** A 50 mm deep pothole 600 mm long lets the tyre reach the bottom and gives margins of 5.28 at 10 km/h, 2.63 at 50 km/h and 1.67 at 80 km/h on an IRI 4 road [C2c].
- **Wheel path.** The twin tyres hit a 300 mm pothole centered in the wheel path on 93 % of passes, and on at least one of three passes 99.96 % of the time [C3]. The limit is detection per hit, not the chance of a hit.
- **R1 is at risk and R5 is not met.** In urban service a bus often passes a spot at 20 km/h or less, near stops and junctions, and R1 allows three passes, so R1 may still be met on streets with low speeds; it cannot be shown without field data. The original R5 defect-detection range of 10 to 80 km/h was not met for the reference pothole at 30 km/h and above on fair roads, or at 80 km/h on good ones. Under PHL-DDR-002 (N2) the range is restated as 10 to 30 km/h. Across that band the lowest margin is 1.94 on IRI 2 roads and 0.97 at 30 km/h on IRI 4 roads, or 1.17 allowing 10 background crossings per km [K2]. R5 is at risk rather than not met.
- **Range and sampling (R6).** The floor peak is at most 0.14 g, far inside ± 16 g. An axle mount would see about 9 g in this linear model, 65 times more, with water and stones [C4], which supports the floor mount (D3). Sampling at 400 Hz keeps 99 % or more of the floor peak; samples are 35 mm apart at 50 km/h and 56 mm at 80 km/h, giving 9 and 5 samples across the pothole [C5].
- **Two axles.** The front and rear axle impacts arrive 0.72 s apart at 30 km/h and 0.43 s at 50 km/h [C6]. Pairing them confirms an event and fixes which axle hit it.
- **R2 cannot be shown at TRL 3.** Joints, drain covers and speed bumps are not Gaussian roughness, and they are the likely false reports. Only a field check of reported clusters can verify R2.

■ D. Location (R4)

Table 4. 95 % location radius [D1].

Setting	σ per axis	One pass	10-pass cluster
Open sky	1.3 m	3.1 m	1.0 m
Suburban	3.0 m	7.3 m	2.3 m
Dense urban	10.0 m	24.5 m	18.2 m (errors correlated)

- **Timing.** With PPS, a 10 ms IMU-to-GNSS error is 0.22 m at 80 km/h; using message times alone, 100 ms is 2.2 m. Fixes are 2.2 m apart at 10 Hz and 80 km/h [D2]. BOM item 8 now calls for a PPS output.
- **Axle.** An event attributed to the wrong axle is misplaced by the 6 m wheelbase [D3]; axle pairing (section C) removes this.
- **R4 is at risk.** The 10 m target is met in open and suburban streets but not in dense urban streets, where multipath errors repeat from pass to pass and do not average out. Map matching to the street centerline is the likely fix and is a later software task.

■ E. Storage and upload (R7, R8)

- **Raw data.** 5.23 kB/s, or 188 MB per 10 h day and 226 MB per 12 h day [E1]. A 32 GB card holds 160 days at 10 h or 133 days at 12 h [E2], far beyond the 30 days of R7. Over five years the card is written 14 times over (412 GB) [E3], well within a high-endurance card's rating. **R7 is met on paper.**
- **Summaries.** A 48 B segment record and a 32 B event record give 112 kB a day for 200 km and 500 events [E4]. The pass time is kept only in the operator's copy (R13).
- **Upload.** At 2 Mbit/s effective at the edge of depot coverage the upload takes 8.4 s, most of it connecting; a day of raw data would take 13 min, so raw data stays on the card [E5]. The hold-up capacitor can power Wi-Fi for only 2.3 s [G3], so the upload runs while the ignition is on: on arrival at the depot or at the next start. **R8 is met on paper** for vehicles in daily service that spend at least about 10 s with the ignition on within depot Wi-Fi.

■ F. Power and transients (R9)

- **Running power.** The 3.3 V loads draw 91 mA, which is 0.45 W at 5 V through the board's linear regulator and 0.54 W from the vehicle [F1]: 45 mA at 12 V, 22 mA at 24 V and 59 mA at 9 V, well within the 2 A fuse [F2]. Uploading raises this to 1.42 W for about 8 s a day; a 10 h day uses 5.4 Wh [F3]. The running target of under 1 W is met; the brief upload peak exceeds it. With an ignition-switched feed there is no draw with the ignition off. The TRL 2 estimate of 0.7 W was conservative and is revised to 0.54 W.
- **Transients.** Under PHL-DDR-002 (N1) the converter is rated 60 V (v0.1 used a 36 V part). Normal 12 V (9 to 16 V) and 24 V (18 to 32 V) supplies and both suppressed load dumps, 35 V on 12 V systems and 58 V on 24 V systems, are within the 60 V input [F4]. The SMBJ36A-class TVS clamps at up to 58.1 V, which the 60 V converter clears by 1.9 V [F5]. The TVS conducts during a 24 V load dump, and a pulse lasting hundreds of milliseconds may overheat it; only a bench test can show that it survives. **The transient part of R9 is at risk** for 24 V vehicles, rather than not met. A surge-stopper front end remains the fuller fix and was not chosen.

■ G. Hold-up (R10)

- **Hold-up time.** 1 F from 4.7 V to 3.6 V stores 4.57 J, which lasts 10.0 s new and 7.0 s at 70 % capacitance; closing files needs about 1 s, a factor of 7 [G1]. The TRL 2 estimate of about 9 s stands for a new capacitor. **R10 is met on paper.** The controller should start shutdown only after about 2 s of low input, so engine cranking dips are ridden through rather than logged as a stop.
- **Charging.** Through 10 Ω the capacitor reaches 95 % in 30 s; the 0.5 A charge peak is within the 1 A converter [G2].

■ H. Environment and fixings (R11)

- **Self-heating.** 0.54 W over 339 cm² of box raises the inside by 2.0 K, so at +70 °C ambient the parts see about 72 °C [H1]. The GNSS, IMU, converter and a high-endurance card are commonly rated to 85 °C, but many supercapacitors are rated to 70 °C and some ESP32-S3 module variants (those with octal PSRAM) are rated to 65 °C. BOM items 5, 6 and 10 now state the grades needed. Parked in the sun with the ignition off, the logger sees only storage temperature.
- **Mass.** The plate is 187 g, the polycarbonate enclosure with its moulded lid-screw pillars 143 g, the modules on their carrier 90 g (of which the aluminium carrier is 24 g and its standoffs, screws and tape 21 g) the gland 12 g, and the light pipes, vent and label adopted on 2026-10-02 8 g: 0.44 kg for the logger, 0.58 kg with the 2 m lead and fixings [H2]. The TRL 2 estimate of 0.4 kg is close.

- **Fixings.** A 20 g crash pulse puts 86 N on the plate, 22 N per M6 bolt against about 9.6 kN of shear capacity, and 46 N on the four M4 hex standoffs that hold the box to the plate [H3]. Strength is not a concern; loosening under long-term vibration is, and only a test can show that locking nuts suffice.
- **R11 is at risk:** the temperature margin depends on part grades, and vibration and loosening cannot be verified at TRL 3.

■ I. Plate stiffness and installation (R12)

- **Stiffness.** Spanning 140 mm between corner bolts with nothing beneath, on half its width, the 4 mm plate has a stiffness of 359 kN/m under a moving mass of 323 g and a first mode of 168 Hz; on full-width supports it is 237 Hz [I1]. A 3.7 mm plate would just reach 150 Hz on the conservative model [I2], so the 4 mm plate keeps a small margin. The bracket part of R12 is met on paper. The mode sits near the 200 Hz Nyquist limit, so the IMU's internal low-pass filter should be set well below 200 Hz. A thin floor panel has its own lower modes, so the plate should bolt to a crossmember, seat rail or other stiff structure.
- **Installation time.** The tasks add up to 30 min, exactly the R12 limit [I3]. Tool clearance around the bolts is tight: the hole centers are 10 mm beyond the box end walls, leaving about 2 mm for a 10 mm socket [I4]; a ring spanner or a thin-wall socket is needed, and the build plan uses a ring spanner on the assembled logger. **R12 is at risk** on installation time.

■ J. Cost (R15)

Value-engineering target: USD 75 (`budget_usd` , a hypothetical control target, not a limit). Estimated cost of the constructable design: USD 77.50 from the 16-line BOM (USD 2.50 over the target) [J1]. The 60 V converter added about \$2 under PHL-DDR-002 (N1), the carrier plate and box fixing kit added for construction (PHL-DDR-003) add \$3.50, and the status light pipes and LEDs (\$1.00), breather vent (\$2.00) and nameplate label (\$0.50) adopted by Amish on 2026-10-02 add \$3.50 [J2]. **R15 is not met:** the estimate is over the target. The savings listed in the design decisions register (PHL-DEC-001) could close the gap; `budget_usd` is unchanged. The LTE-M option would bring the cost to \$98 to \$108 [J2], over the target; it is not in the BOM.

■ K. Results against every requirement

Table 5. Requirement status from this note.

ID	Requirement	Value	Target	Status
R5	Work across normal fleet speeds	Roughness signal 12 x noise at 20 km/h; lowest defect margin in 10 to 30 km/h 1.94 on IRI 2 and 0.97 on IRI 4 [K2]	Roughness 20 to 80 km/h; defects 10 to 30 km/h (PHL-DDR-002, N2)	At risk (30 km/h on fair roads)
R9	Run from vehicle power	0.54 W running, 1.42 W for 8 s uploading; 24 V suppressed load dump 58 V and TVS clamp 58.1 V against a 60 V converter [F4], [F5]	9 to 36 V, under 1 W, ISO 16750-2 transient levels	At risk (1.9 V margin; TVS pulse energy unverified)
R1	Detect potholes	Margin above 1 up to 20 km/h on IRI 4 and 50 km/h on IRI 2; 93 % of passes hit	80 % found within 3 passes	At risk; field data needed
R4	Locate defects	95 % radius 2.3 m suburban, 18.2 m dense urban (10 passes)	10 m, correct street	At risk
R11	Survive the vehicle environment	About 72 °C inside at +70 °C; crash factor 448; breather vent equalizes pressure	-20 to +70 °C, IP65, no loosening	At risk (part grades; vibration unverifiable)
R12	Install quickly and safely	30 min; plate first mode 168 Hz	30 min; above 150 Hz	At risk (install time at the limit)
R2	Keep false reports low	Not computable from Gaussian roughness	10 % or fewer false clusters	Not verifiable at TRL 3
R3	Report roughness per segment	Synthetic r^2 0.93 from one pass, 0.99 from five	r^2 0.8 against reference IRI	Not verifiable at TRL 3 (supported on paper)
R7	Store data on the vehicle	133 to 160 days on 32 GB	30 days	Met on paper
R8	Get data off the vehicle	112 kB in 8.4 s with the ignition on in depot Wi-Fi	Within 24 h, no staff action	Met on paper (vehicles in daily service)
R10	Shut down cleanly	7.0 s hold-up at end of life, 1 s needed	No corruption on power loss	Met on paper
R15	Low cost and buildable	\$77.50	\$75 value-engineering target	Not met (\$2.50 over the target)
R6	Sample fast enough	400 Hz, ± 16 g, 10 Hz GNSS; peak 0.14 g	400 Hz, ± 8 g, 5 Hz	Met by design
R13	Protect privacy	No camera or microphone; pass times kept by the operator only; dates published only when pooled	Road-level data only	Met by design
R14	Open outputs	CSV and GeoJSON per the CityTwin export (D6)	Readable by CityTwin and GIS	Met by design (CityTwin fetches from the operator's server)
R16	Fit the fleet types in this build	Buses and refuse trucks on 9 to 36 V power (D1)	Buses and refuse trucks; bicycles deferred	Met by design (bicycle variant deferred)

Counts: 1 not met (R15), 6 at risk, 2 not verifiable at TRL 3, 3 met on paper, 4 met by design (v0.4: 0 not met, 4 met on paper; v0.1: 2 not met, 4 at risk).

■ Checks against the TRL 2 figures

Table 6. TRL 2 figures checked.

TRL 2 claim (PHL-PRC-001 v0.2)	This note	Action
About 35 mm sample spacing at 50 km/h	35 mm [C5]	Stands
About 9 samples across a 300 mm pothole at 50 km/h, about 4 at 80 km/h	9 and 5 [C5]	Precis updated (5)
Raw data about 5.2 kB/s, 190 MB a day	5.23 kB/s, 188 MB per 10 h day [E1]	Stands
About 5 months on 32 GB	160 days at 10 h, 133 days at 12 h [E2]	Stands
About 0.1 MB of summaries a day	112 kB [E4]	Stands
About 0.7 W, about 60 mA at 12 V	0.54 W, 45 mA at 12 V [F1], [F2]	Precis updated
About 9 s hold-up	10.0 s new, 7.0 s at end of life [G1]	Precis updated
About 0.4 kg	0.44 kg; 0.58 kg with lead and fixings [H2]	Updated for the constructable design (PHL-DDR-003) and the parts adopted on 2026-10-02
About \$69	\$77.50 with the 60 V converter, the construction parts and the parts adopted on 2026-10-02 [J1]	Updated under PHL-DDR-002, PHL-DDR-003 and PHL-DEC-001
9 to 36 V input covers 12 V and 24 V vehicles	Not for 24 V load dump with the 36 V part; within 60 V [F4]	60 V converter decided (PHL-DDR-002, N1)
Detection margin "thin at high speed"	Lost at 30 km/h and above (IRI 4) or 80 km/h (IRI 2) for the reference pothole [K1]	R5 range restated as 10 to 30 km/h (PHL-DDR-002, N2); at risk