


REV	DESCRIPTION	DATE	BY
P1	Making sketch for the prototype build plan	2026-10-01	AC



TOP VIEW

Scale 1:1; looking down (along -Z)



FRONT VIEW

Scale 1:1; looking at the front (along +Y)

RIGHT VIEW

Scale 1:1; looking at the right side (along -X)



WHERE IT GOES

This part in colour, its neighbours in grey

HOW TO MAKE IT AND HOW IT FITS

Cut two 80 mm lengths of 4 mm 316 rod; square the top ends.

Grind a point on the other end: about 4 mm long, tip about 0.6 mm.

Abrade the top 15 mm, tin it with stainless-steel flux and solder a

0.25 mm² wire to it (or crimp in a 4 mm splice); wash off the flux.

Slide a 5 mm length of 4 mm heat-shrink to sit just below the fin foot

(15 to 20 mm from the top end) and shrink it.

Fit: top 15 mm in the foot grooves, 24 mm apart, set in epoxy when the

halves are glued; 5 mm sleeved, then 60 mm bare below the foot.

Check: bare length 60 mm on each rod (it sets the EC cell constant);

no flux left on the bare length.

ROOTMESH

github.com/BoujeeEnjinia1701/rootmesh

RootMesh EC electrode (make 2): making sketch

DRAWING NO.

RMS-DWG-103

REV

P1

SHEET

1 of 1

SIZE

ANSI B

SCALE

1:1

UNITS

mm

PROJECTION



DATE

2026-10-01

DRAWN

Amish Chadha

MATERIAL / NOTES

316 stainless steel rod, 4 mm diameter