

SLOPEWATCH · REQUIREMENTS

SlopeWatch requirements

Design Molecule Lab · designmolecule.com

DOCUMENT CONTROL

Document ID	SLW-REQ-001	Version	0.4
Status	Draft	Date	2026-09-25
Author	Amish Chadha	License	CERN-OHL-S-2.0
Project TRL	TRL 3 Proof of concept		
Repository	github.com/BoujeeEnjinia1701/slopedwatch		
Source	docs/03-requirements.md @ 50ddcd2		

REVISION HISTORY

Version	Date	Author	Change
0.4	2026-09-25	Amish Chadha	Recommendations accepted by Amish (DDR-002)
0.3	2026-09-25	Amish Chadha	TRL 3 status from SLW-CAL-001; R11 redefined to SlopeWatch-specific parts (SLW-DDR-001 D1); reference-site layout and FieldNode port assumptions stated
0.2	2026-09-25	Amish Chadha	First measurable requirements for TRL 2, with status against the concept estimates
0.1	2026-09-25	Amish Chadha	Initial scaffold

SlopeWatch requirements

These are first-pass requirements for one monitored site. Five of the thirteen are met on paper by calculation and two by design; four are at risk and two can only be shown in the field (SLW-CAL-001 v0.2, Table 3). None is now unmet. R11 is met because Amish decided on 2026-09-25 (SLW-DDR-002) that the reference site mounts the node on an existing pole, with a new mast as a site option: the SlopeWatch-specific parts cost \$245 against \$250, and \$269 where a new mast is needed. R11 was redefined under SLW-DDR-001 D1 (the FieldNode core is costed in the FieldNode project), now also decided by Amish. Targets are still proposals, not yet validated with users, and will be revised after co-design sessions (see SLW-PRB-001). "Met on paper" means shown by calculation, not by test.

The **reference site** is a slope or dump face up to about 50 m wide with three tilt stakes 10 m apart on the fall line, one crack gauge across a tension crack at the crest, and the FieldNode core and alert unit on an existing pole or building 15 m beyond the toe, within 60 m of cable, with the keyed silence switch on its own post about 5 m from the siren. Where no pole exists, the optional mast (BOM line 8) takes its place (SLW-DDR-002).

Table 1. SlopeWatch requirements for one site.

ID	Requirement	Target	Verification (TRL 3 or later)	Status at TRL 3 (SLW-CAL-001)
R1	Measure surface tilt	Resolution 0.01 degrees or finer; range ± 30 degrees or more on two axes	Datasheet and calculation; later bench tilt table	Met on paper: 0.0055 degree step and ± 90 degrees in the sensor's mode 1 (modes 3 and 4 stop at ± 10 degrees)
R2	Limit false tilt from temperature	Apparent tilt change from the daily soil temperature cycle 0.02 degrees or less per day, and 0.002 degrees per hour or less, without software correction	Thermal calculation; later chamber test (CalRig)	Met on paper with the capsule 0.4 m deep: 0.0092 degrees per day and 0.0012 degrees per hour in wet soil; not met at the TRL 2 depth of 0.3 m in wet soil
R3	Measure crack opening	Range 100 mm or more; resolution 0.1 mm; re-settable in the field without tools beyond a spanner	Datasheet and design review	Met by design (datasheet class); precaution rate taken over 24 h because of the gauge's own thermal swing
R4	Sample and report often enough to see acceleration	Every sensor read every 10 min or faster; uplink every 60 min in the normal state and every 10 min in the precaution or warning state	Firmware sketch review; airtime calculation	Met on paper: 0.30 % of time at SF12 against the 1 % EU868 limit; a site that runs at SF12 uses a TwinKit gateway rather than The Things Network (SLW-DDR-002)
R5	Local alarm without a network	Siren and beacon start within 60 s of a warning condition, driven by the on-site node alone	Design review; later bench test	Met by design: about 13 s
R6	Remote alert	At least two named people notified by SMS or app within 5 min of a warning, where gateway and mobile coverage exist	Latency calculation; later end-to-end test	At risk: 1.6 min at the first try, 4.6 min at SF12 with one lost uplink; no remote alert at a site without a gateway
R7	Alarm audible where people work	65 dB(A) or more at 100 m from the mast in open ground	Spreading-loss calculation; later field measurement	At risk: 65.5 to 68.5 dB(A) in open ground; not met near running machinery. The keyed switch now sits about 5 m from the mast, at about 95 dB(A) instead of 105 dB(A) (SLW-DDR-002)
R8	Energy autonomy	5 days with no sun, including one 30 min alarm, on the FieldNode cell	Energy calculation	Met on energy (7.3 Wh of 13.1 Wh at -10 °C, with the precaution beacon at 1 % duty or less, decided in SLW-DDR-002); at risk on the FieldNode 12 V rail current (0.45 A, no rating stated; FieldNode asked to rate it at 0.5 A or more, SLW-DDR-002)
R9	Survive burial and weather	Capsule and stake head IP67 and buried to 0.4 m; node IP65; operate -10 to 50 °C; cable in conduit rated for burial and UV	Datasheets and design review	At risk: SlopeWatch parts met by choice of parts; the FieldNode enclosure exceeds 60 °C in 45 °C sun (FND-CAL-001)
R10	Installable by a small team	Each stake installed by two trained people with hand tools (post-hole	Method review; later timed trial	Not verifiable at TRL 3: 43 min estimated, at the limit

ID	Requirement	Target	Verification (TRL 3 or later)	Status at TRL 3 (SLW-CAL-001)
		auger or driven pilot, hand-mixed grout) in 45 min or less; no work below an actively moving face		
R11	Affordable	Parts specific to SlopeWatch for one reference site (node on an existing pole) \$250 or less, excluding the FieldNode core (costed in the FieldNode project), any LoRaWAN gateway and the optional mast, which is a site option (SLW-DDR-002)	Priced BOM (bom/bom.csv)	Met on paper: \$245; \$269 at a site that needs the optional mast
R12	Open, local data	90 days or more of raw readings kept on the node; open CSV export; works with any LoRaWAN server	Storage calculation and design review	Met on paper: 363 kB for 90 days on 16 MB of flash
R13	Trustworthy alarms	No more than one false warning per site per year, and a documented statement of the failure modes the system cannot detect	Field trial with partner	Not verifiable at TRL 3; statement in SLW-PRC-001

■ Assumptions

- Tilt thresholds of 0.01 degrees per hour (precaution) and 0.1 degrees per hour (warning) follow Uchimura et al. (2015); site-specific thresholds must be set with a geotechnical engineer after a baseline period.
- The FieldNode core provides about 19 Wh of LiFePO₄ storage (3.2 V, 6 Ah), switched 3.3, 5 and 12 V rails on two M12 5-pin ports (one rail per port), SPI flash and a LoRaWAN radio, as described in FND-PRC-001 and FND-REQ-001 v0.3. SlopeWatch uses one port at 5 V for the sensor bus and the other at 12 V for the alert unit.
- Siren sound level 110 dB(A) at 1 m, from typical 12 V piezo sirens; spherical spreading with air absorption and 0 to 3 dB of ground attenuation (SLW-CAL-001, section E).
- Soil temperature ranges and properties as in SLW-CAL-001, Table 1.
- Stake spacing and site layout will change after co-design; R11 is stated for the reference site only.
- Network rule (SLW-DDR-002): a site whose uplinks need SF12 uses its own gateway (TwinKit), because hourly uplinks at SF12 take 43.5 s a day, over The Things Network's 30 s fair-use allowance.