

Fourier Towers: Finite Heisenberg Symmetry, Cocycle Phases, and Clifford Decompositions

Driss Boutat
INSA Centre Val de Loire

Abstract

We introduce the Fourier Tower framework for the analysis of solvable finite groups and symmetry-adapted quantum circuits.

The central principle is that nonabelian structure may be decomposed into interacting local abelian Fourier layers coupled through permutations, cocycle phases, and symplectic interactions.

We develop this viewpoint explicitly for the finite Heisenberg group, where noncommutativity is encoded by a central cocycle and naturally produces controlled phase interactions after Fourier transformation.

This perspective connects Fourier analysis on solvable groups with:

- Heisenberg and Weyl symmetries,
- projective representations,
- Clifford circuits,
- stabilizer propagation,
- and discrete phase-space geometry.

We further propose a speculative Fourier Tower decomposition principle for Clifford circuits in terms of local Fourier layers, symplectic propagation, and cocycle phase corrections.

Possible links with discrete Wigner methods, classical shadow tomography, and hierarchical quantum propagation schemes are also discussed.

1 Introduction

Fourier analysis on finite groups plays a fundamental role in harmonic analysis, representation theory, quantum computation, and signal processing.

For abelian groups, the Fourier transform decomposes functions into independent frequency modes. For nonabelian groups, however, the situation becomes substantially more complicated because irreducible representations are matrix-valued and interact through noncommutative structure.

Several approaches have been developed to study nonabelian Fourier transforms, including:

- fast Fourier transforms on finite groups,
- Bratteli-diagram decompositions,
- induced representation methods,
- orbit methods,

- and quantum Fourier transforms for hidden subgroup problems.

The purpose of the present work is to explore a complementary viewpoint adapted to solvable and hierarchical group structures.

The central idea is that many nonabelian systems may be decomposed into interacting local abelian Fourier layers associated with a solvable tower

$$\{e\} = G_0 \triangleleft G_1 \triangleleft \cdots \triangleleft G_n = G.$$

Within this framework:

- local Fourier transforms describe abelian quotient layers,
- nonabelianity appears through controlled permutations and cocycle interactions,
- and quantum phase structure emerges from central extensions and projective representations.

The finite Heisenberg group provides the key example because its noncommutative structure is entirely encoded by a cocycle over a symplectic phase space.

This naturally connects the Fourier Tower viewpoint with:

- Weyl operators,
- Clifford circuits,
- stabilizer quantum mechanics,
- discrete Wigner representations,
- and symplectic quantum computation.

The goal of this article is partly expository and partly exploratory.

On the expository side, we give explicit Fourier Tower constructions and circuit interpretations.

On the exploratory side, we propose possible links between Fourier Towers and:

- Clifford decomposition algorithms,
- cocycle-based phase propagation,
- symmetry-adapted stabilizer dynamics,
- classical shadow tomography,
- and hierarchical phase-space inference methods.

2 Fourier Towers, Heisenberg Symmetry, and Quantum Phase Geometry

2.1 General Philosophy

The Fourier Tower framework is based on the principle that many nonabelian structures may be decomposed into interacting local abelian Fourier layers.

Given a solvable tower

$$\{e\} = G_0 \triangleleft G_1 \triangleleft \cdots \triangleleft G_n = G,$$

with abelian quotients

$$Q_i = G_i/G_{i-1},$$

one constructs local Hilbert spaces

$$\mathcal{H}_i = \mathbb{C}[Q_i],$$

together with local Fourier transforms

$$F_{\text{loc}} = \bigotimes_i F_{Q_i}.$$

The nonabelian structure then appears through interactions between the local Fourier sectors. These interactions may take several forms:

- controlled permutations,
- cocycle-induced phases,
- symplectic couplings,
- or projective phase corrections.

Thus the guiding principle becomes

$\text{nonabelianity} = \text{interaction between local Fourier layers.}$

2.2 The Finite Heisenberg Group

The finite Heisenberg group over the finite field

$$\mathbb{F}_p$$

is

$$H_p = \left\{ \begin{pmatrix} 1 & a & c \\ 0 & 1 & b \\ 0 & 0 & 1 \end{pmatrix} : a, b, c \in \mathbb{F}_p \right\}.$$

Equivalently, elements are triples

$$(a, b, c), \quad a, b, c \in \mathbb{F}_p.$$

The multiplication law is

$$(a, b, c)(a', b', c') = (a + a', b + b', c + c' + ab').$$

The inverse is

$$(a, b, c)^{-1} = (-a, -b, -c + ab).$$

2.3 Central Extension Structure

The center of the group is

$$Z(H_p) = \{(0, 0, c) : c \in \mathbb{F}_p\} \cong \mathbb{Z}_p.$$

Moreover,

$$H_p/Z(H_p) \cong \mathbb{Z}_p \times \mathbb{Z}_p.$$

Thus the Heisenberg group fits into the central extension

$$1 \rightarrow \mathbb{Z}_p \rightarrow H_p \rightarrow \mathbb{Z}_p \times \mathbb{Z}_p \rightarrow 1.$$

The nonabelianity is entirely encoded by the cocycle

$$\omega((a, b), (a', b')) = ab'.$$

Without this cocycle term, the group would simply be the abelian group

$$\mathbb{Z}_p^3.$$

2.4 Symplectic Structure

The quotient space

$$H_p/Z(H_p) \cong \mathbb{F}_p^2$$

carries a natural symplectic form:

$$\Omega((a, b), (a', b')) = ab' - ba'.$$

This antisymmetric form measures the failure of commutativity.

Indeed,

$$(a, b, c)(a', b', c') \neq (a', b', c')(a, b, c)$$

precisely because of the central correction

$$ab' - ba'.$$

Thus the Heisenberg group may be viewed as

a central extension of a symplectic vector space.

This is the finite analogue of classical phase space in quantum mechanics.

2.5 Projective Representations and Cocycle Geometry

The cocycle

$$\omega((a, b), (a', b')) = ab'$$

defines a projective phase correction.

Instead of an ordinary representation satisfying

$$\rho(x)\rho(y) = \rho(xy),$$

one obtains a projective representation

$$\rho(x)\rho(y) = \omega(x, y)\rho(x + y).$$

Thus the cocycle measures the obstruction to strict commutativity.

The Fourier Tower therefore naturally connects with:

- projective representation theory,
- group cohomology,
- and quantum phase geometry.

2.6 Local Fourier Layers

The natural Hilbert space is

$$\mathbb{C}[H_p] \cong \mathbb{C}[\mathbb{Z}_p] \otimes \mathbb{C}[\mathbb{Z}_p] \otimes \mathbb{C}[\mathbb{Z}_p].$$

The three registers correspond to:

- the first quotient coordinate,
- the second quotient coordinate,
- the central phase coordinate.

Let

$$\omega_p = e^{2\pi i/p}.$$

The Fourier transform on

$$\mathbb{Z}_p$$

is

$$F_p|x\rangle = \frac{1}{\sqrt{p}} \sum_{k=0}^{p-1} \omega_p^{kx} |k\rangle.$$

Thus the local Fourier layer is

$$F_{\text{loc}} = F_p \otimes F_p \otimes F_p.$$

2.7 Cocycle-Induced Phase Interaction

The multiplication law contains the cocycle correction

$$c \mapsto c + ab'.$$

After Fourier transformation of the central layer, translations become phases. Consequently,

$$c + ab'$$

becomes the phase factor

$$\omega_p^{ab'}.$$

At the quantum level, the cocycle interaction becomes

$$|a\rangle|b\rangle|c\rangle \mapsto \omega_p^{ab} |a\rangle|b\rangle|c\rangle.$$

Thus the Fourier Tower transform is

$$F_{\mathcal{T}} = C_{\omega}(F_p \otimes F_p \otimes F_p),$$

where

$$C_{\omega} = \sum_{a,b} \omega_p^{ab} |a, b\rangle \langle a, b| \otimes I.$$

Theorem 1 (Fourier Tower Decomposition for the Finite Heisenberg Group). *Let*

$$H_p \cong (\mathbb{Z}_p \times \mathbb{Z}_p) \times_{\omega} \mathbb{Z}_p$$

be the finite Heisenberg group with cocycle

$$\omega((a, b), (a', b')) = ab'.$$

Then Fourier transformation of the central layer converts the cocycle contribution into a diagonal phase interaction.

Equivalently, the Fourier Tower transform may be written schematically as

$$F_{\mathcal{T}} = C_{\omega}(F_p \otimes F_p \otimes F_p),$$

where

$$C_{\omega} = \sum_{a, b \in \mathbb{F}_p} \omega_p^{ab} |a, b\rangle \langle a, b| \otimes I$$

is a cocycle-controlled phase operator.

Here the phase term ab represents the effective cocycle interaction obtained after Fourier transformation of the central layer and identification of the translated central coordinate with its Fourier dual variable.

Thus the nonabelian structure of H_p is represented in Fourier space by cocycle-induced phase geometry.

Proof. The multiplication law in H_p is

$$(a, b, c)(a', b', c') = (a + a', b + b', c + c' + ab').$$

The term ab' defines the cocycle contribution in the central coordinate.

Applying the Fourier transform to the central $\mathbb{Z}_p$ -layer converts translations

$$c \mapsto c + t$$

into phase multiplications


$$|k\rangle \mapsto \omega_p^{kt} |k\rangle.$$

Therefore the cocycle correction ab' becomes the phase

$$\omega_p^{ab'}.$$

Hence the transformed interaction is diagonal and is represented by the controlled phase operator C_{ω} . □

2.8 Circuit for the Heisenberg Fourier Tower



2.9 Connection with Weyl Operators

Define the generalized Pauli operators

$$X|x\rangle = |x+1\rangle,$$

and

$$Z|x\rangle = \omega_p^x|x\rangle.$$

They satisfy the Heisenberg commutation relation

$$ZX = \omega_p XZ.$$

This is the finite-dimensional analogue of the canonical commutation relation in quantum mechanics.

The finite Heisenberg Fourier Tower therefore connects naturally with:

- Weyl operators,
- stabilizer quantum mechanics,
- Clifford circuits,
- discrete phase-space methods,
- and symplectic quantum computation.

2.10 Fourier Transform as Symplectic Rotation

The Fourier transform exchanges translation and phase operators:

$$FXF^{-1} = Z, \quad FZF^{-1} = X^{-1}.$$

This operation corresponds to the symplectic transformation

$$(q, p) \mapsto (p, -q).$$

Thus:

Fourier transform = symplectic rotation.

2.11 The CNOT Gate as a Symplectic Fourier Coupling

The controlled-NOT gate (CNOT or CX) is defined by

$$CX|a, b\rangle = |a, a+b\rangle, \quad a, b \in \mathbb{Z}_2.$$

The first qubit acts as a control layer, while the second qubit is translated conditionally. The action of CX is linear over the finite phase space

$$\mathbb{F}_2^2.$$

Indeed, at the level of computational coordinates,

$$(a, b) \mapsto (a, a+b),$$

which corresponds to the linear shear

$$L_{\text{CX}} = \begin{pmatrix} 1 & 0 \\ 1 & 1 \end{pmatrix}.$$

At the level of Pauli–Weyl phase space, this linear shear extends to a symplectic transformation preserving the commutation relations.

Thus the CNOT gate naturally acts as a symplectic propagation operator between Fourier layers.

2.11.1 Pauli Propagation

Let

$$X|x\rangle = |x+1\rangle, \quad Z|x\rangle = (-1)^x|x\rangle.$$

Under conjugation by CX, the Pauli operators transform as

$$X \otimes I \mapsto X \otimes X,$$

$$I \otimes X \mapsto I \otimes X,$$

$$Z \otimes I \mapsto Z \otimes I,$$

and

$$I \otimes Z \mapsto Z^{-1} \otimes Z.$$

Therefore CX preserves the Pauli–Heisenberg structure and acts as a Clifford transformation.

2.11.2 Fourier Tower Interpretation

Within the Fourier Tower framework, the CX gate may be interpreted as:


symplectic coupling between local Fourier layers.

The first qubit carries the control Fourier sector, while the second qubit undergoes conditional translation.

After Fourier transformation, conditional translations become conditional phase interactions.

Thus CX represents the basic linear propagation mechanism underlying Clifford circuits and stabilizer evolution.

2.11.3 Circuit Interpretation



The Fourier layers construct local phase-space coordinates, while the controlled translation implements symplectic propagation between layers.

2.12 Fourier Tower Representation of the Toffoli Gate

The Toffoli gate is

$$U = \text{CCX},$$

defined by

$$\text{CCX}|a, b, c\rangle = |a, b, c \oplus ab\rangle.$$

The target register carries the translation symmetry

$$\mathbb{Z}_2.$$

Define

$$X|c\rangle = |c \oplus 1\rangle.$$

Then

$$U = |0, 0\rangle\langle 0, 0| \otimes I + |0, 1\rangle\langle 0, 1| \otimes I + |1, 0\rangle\langle 1, 0| \otimes I + |1, 1\rangle\langle 1, 1| \otimes X.$$

The Fourier transform on the target layer is

$$F_{\text{loc}} = I \otimes I \otimes H.$$

Using

$$HXH = Z,$$

we obtain

$$F_{\text{loc}} U F_{\text{loc}}^{-1} = \text{CCZ}.$$

Hence

$$\text{CCZ}|a, b, c\rangle = (-1)^{abc}|a, b, c\rangle.$$

Thus Fourier conjugation transforms controlled translations into controlled phases.

This realizes explicitly the principle

$$\boxed{\text{translation symmetry} \longrightarrow \text{phase symmetry.}}$$

Thus Fourier conjugation transforms controlled translations into controlled phases.

In contrast with the CX gate, whose action is linear and symplectic, the Toffoli gate introduces the quadratic interaction term

$$ab.$$

From the Fourier Tower viewpoint, this corresponds to a higher-order phase coupling between Fourier layers.

Schematically,

$$\boxed{\text{CX} \longrightarrow \text{linear symplectic propagation,}}$$

while

$$\boxed{\text{Toffoli} \longrightarrow \text{nonlinear cocycle-like phase interaction.}}$$

This suggests that non-Clifford gates may correspond to higher-order phase geometries extending the symplectic structure of Clifford circuits.

2.13 Toward Clifford Decomposition and Quantum Phase Geometry

The Heisenberg Fourier Tower suggests a broader interpretation.

Clifford circuits preserve Weyl operators under conjugation and therefore preserve the underlying symplectic geometry.

Consequently, Clifford operations may be viewed as:

- local Fourier transforms,
- quadratic phase interactions,
- and symplectic couplings between Fourier layers.

The Fourier Tower viewpoint suggests the following hierarchical computational structure:

$$\boxed{\text{local Fourier layers} \longrightarrow \text{phase-space encoding} \longrightarrow \text{cocycle-induced entangling phases} \longrightarrow \text{symplectic propagation}}$$

In this interpretation, local Fourier transforms construct phase-space coordinates, cocycle interactions generate nonabelian phase entanglement, and symplectic transformations propagate the resulting quantum geometry.

This viewpoint indicates that certain classes of quantum circuits may admit a natural decomposition into harmonic, cohomological, and symplectic layers.

The previous examples therefore motivate the organizational principle

$$\text{local Fourier transforms} + \text{phase interactions} + \text{symplectic propagation},$$

which may provide a natural extension of the Fourier Tower framework to general Clifford circuits and stabilizer dynamics.

3 Toward Fourier Tower Decompositions of Clifford Circuits

The finite Heisenberg example suggests a possible extension of the Fourier Tower framework to Clifford circuits.

Clifford circuits are precisely the circuits that preserve Pauli–Weyl operators under conjugation. Therefore they naturally act on the finite Heisenberg group and on its symplectic quotient.

3.1 Pauli–Heisenberg Structure

For a qudit of prime dimension p , define

$$X|x\rangle = |x+1\rangle, \quad Z|x\rangle = \omega_p^x|x\rangle,$$

where

$$\omega_p = e^{2\pi i/p}.$$

These satisfy

$$ZX = \omega_p XZ.$$

For n qudits, Pauli–Weyl operators are indexed by vectors

$$v = (q, p) \in \mathbb{F}_p^{2n}.$$

The commutation relation is controlled by the symplectic form

$$\Omega(v, w) = q \cdot p' - p \cdot q'.$$

Thus the Pauli group is a central extension

$$1 \rightarrow U(1) \rightarrow \mathcal{P}_n \rightarrow \mathbb{F}_p^{2n} \rightarrow 1.$$

The cocycle of this extension records the phase appearing when Pauli operators are multiplied.

3.2 Clifford Circuits as Symplectic Transformations

A Clifford unitary U satisfies

$$U\mathcal{P}_nU^{-1} = \mathcal{P}_n.$$

Equivalently, for every Pauli operator $W(v)$,

$$UW(v)U^{-1} = \lambda(v)W(Sv),$$

where:

- $S \in Sp(2n, \mathbb{F}_p)$ is a symplectic matrix,
- $\lambda(v) \in U(1)$ is a phase factor.

Thus every Clifford circuit has two components:

Clifford = symplectic action + cocycle phase correction.

This is exactly the type of structure captured by a Fourier Tower.

3.3 Fourier Tower Viewpoint

In the Fourier Tower interpretation, the Pauli–Heisenberg group is decomposed into:

local translation layers + local phase layers + central cocycle layer.

The Fourier transform exchanges translation and phase:

$$FXF^{-1} = Z, \quad FZF^{-1} = X^{-1}.$$

Thus a Clifford circuit may be decomposed into:

- local Fourier transforms,
- controlled additions,
- quadratic phase gates,
- and cocycle-induced central phases.

Schematically,

$$U_{\text{Cliff}} = C_\omega F_{\text{tower}} S_{\text{symp}},$$

where:

- S_{symp} encodes the symplectic transformation,
- F_{tower} performs local Fourier changes of basis,
- C_ω records cocycle phase corrections.

3.4 Intertwining Interpretation

The cocycle interaction operator may also be interpreted as an intertwining operator between local Fourier representations and the global nonabelian action.

Indeed, the local Fourier decomposition produces independent abelian Fourier sectors

$$\bigotimes_i \mathbb{C}[\widehat{Q_i}],$$

while the cocycle and symplectic interactions couple these sectors into a coherent global representation.

From this viewpoint, the Fourier Tower transform

$$F_{\mathcal{T}} = C_{\omega} F_{\text{loc}}$$

acts as a twisted intertwiner between:

- local abelian harmonic modes,
- and the global nonabelian symmetry representation.

This interpretation is closely related to:

- induced representations,
- projective representation theory,
- Mackey-type constructions,
- and the Weil representation of finite symplectic groups.

3.5 Symmetry-Adapted Stabilizer Propagation

A stabilizer state is determined by an abelian subgroup

$$\mathcal{S} \subset \mathcal{P}_n.$$

Under a Clifford circuit,

$$\mathcal{S} \mapsto U \mathcal{S} U^{-1}.$$

In the Fourier Tower picture, this propagation can be described layer by layer:

stabilizer generators $\longrightarrow$ Fourier sectors $\longrightarrow$ symplectic propagation $\longrightarrow$ cocycle phase correction.

Thus stabilizer propagation becomes a hierarchical Fourier process.

The advantage of this viewpoint is that it separates:

- the abelian Fourier data,
- the symplectic movement of generators,
- and the phase correction coming from the central extension.

3.6 Cocycle-Based Phase Decomposition

Let

$$W(v)W(w) = \omega_p^{\beta(v,w)}W(v+w),$$

where $\beta(v, w)$ is a cocycle.

The antisymmetric part of β gives the symplectic form:

$$\Omega(v, w) = \beta(v, w) - \beta(w, v).$$

A Clifford circuit preserves Ω , but may change the cocycle representative by a phase coboundary. Thus the phase part of a Clifford circuit may be interpreted as a cocycle transformation:

$$\beta \mapsto \beta + d\phi.$$

This suggests a decomposition principle:

Clifford phase structure = cocycle data + coboundary correction.

In circuit terms:

- linear symplectic maps correspond to Clifford permutations of Pauli labels,
- quadratic phase gates correspond to cocycle corrections,
- Fourier gates exchange translation and phase layers.

3.7 Prototype Algorithmic Decomposition

A possible Fourier Tower decomposition algorithm for a Clifford circuit is:

1. Encode Pauli generators as vectors

$$v_i \in \mathbb{F}_p^{2n}.$$

2. Compute the induced symplectic matrix

$$S \in Sp(2n, \mathbb{F}_p).$$

3. Decompose S into elementary symplectic operations:

$$S = S_k \cdots S_2 S_1.$$

4. Interpret each elementary symplectic operation as a Fourier Tower gate:

- Fourier transform,
- shear,
- controlled addition,
- phase gate.

5. Track the cocycle phase accumulated at each step.

6. Reconstruct the Clifford circuit as

$$U = C_\omega U_k \cdots U_2 U_1.$$

Thus the Clifford circuit is decomposed into:

local Fourier layers + symplectic propagation + cocycle phase correction.

3.8 Interpretation

This viewpoint suggests that Fourier Towers may provide a natural harmonic language for Clifford circuits.

The finite Heisenberg group supplies the algebraic foundation:

Pauli group = central extension of phase space.

The Clifford group supplies the symmetry:

Clifford group = automorphisms of the Heisenberg structure.

The Fourier Tower supplies the decomposition:

Clifford circuit = layered Fourier propagation with cocycle phases.

This provides a possible bridge between:

- finite group Fourier analysis,
- stabilizer quantum mechanics,
- symplectic linear algebra,
- and quantum circuit decomposition.

3.9 Possible Connections with Phase-Space Quantum Methods

The Fourier Tower viewpoint also suggests possible connections with several modern approaches to quantum information and quantum simulation.

Although the following remarks are partly speculative, they indicate that the Fourier Tower framework may provide a common algebraic language for phase-space based quantum methods.

3.9.1 Discrete Wigner Representations

Finite-dimensional quantum systems are often described using discrete phase spaces

$$\mathbb{F}_p^{2n},$$

equipped with a symplectic structure.

In discrete Wigner theory, quantum states are represented by quasiprobability distributions on this finite phase space.

The finite Heisenberg group plays a central role because its generalized Pauli operators generate translations in discrete phase space.

For a single qudit, the operators

$$X|x\rangle = |x+1\rangle, \quad Z|x\rangle = \omega_p^x|x\rangle$$

generate the finite Heisenberg algebra

$$ZX = \omega_p XZ.$$

The Fourier Tower construction naturally decomposes these operators into:

- local Fourier layers,
- cocycle phase corrections,
- and controlled symplectic interactions.

From this viewpoint, the cocycle

$$\omega((a, b), (a', b')) = ab'$$

may be interpreted as the discrete symplectic area responsible for phase-space interference.

Thus the Fourier Tower may provide a structured decomposition of discrete Wigner dynamics into local Fourier propagation together with cocycle-induced phase geometry.

3.9.2 Symplectic Structure and Clifford Circuits

Clifford circuits act naturally on generalized Pauli operators through symplectic transformations.

Indeed, the Clifford group is generated by unitary operators preserving the Heisenberg commutation relations.

At the level of phase space, Clifford operations correspond to matrices

$$M \in \text{Sp}(2n, \mathbb{F}_p).$$

The Fourier transform itself corresponds to a symplectic rotation exchanging position and momentum coordinates.

Since the Fourier Tower separates:

- local Fourier transforms,
- permutation couplings,
- and cocycle phase interactions,

it suggests a possible decomposition principle for Clifford circuits:

$$\text{Clifford circuit} = \text{local Fourier layers} + \text{symplectic couplings} + \text{cocycle phases}.$$

This viewpoint may provide an alternative algebraic description of stabilizer propagation and Clifford simulation.

3.9.3 Symmetry-Adapted Stabilizer Propagation

Stabilizer states are usually propagated through Clifford circuits using symplectic linear algebra over finite fields.

Within the Fourier Tower framework, one may instead organize stabilizer propagation according to the tower structure of the underlying symmetry group.

In this interpretation:

- local stabilizer sectors correspond to local Fourier layers,
- nonabelian corrections appear as controlled permutations,
- and cocycle interactions generate phase entanglement between layers.

This suggests the possibility of:

symmetry-adapted stabilizer propagation.

Rather than evolving a stabilizer state globally, one would propagate:

1. local Fourier sectors,
2. local cocycle phases,
3. and inter-layer coupling data.

Such a decomposition could potentially simplify simulation for systems possessing hierarchical symmetry structures.

3.9.4 Classical Shadow Tomography

Classical shadow tomography estimates many observables from randomized measurements.

Many shadow protocols rely on random Clifford operations or randomized Pauli measurements.

Since the Fourier Tower framework naturally decomposes Clifford-like transformations into structured Fourier and cocycle components, one may speculate that:

- shadow measurements could be organized layer-by-layer,
- local Fourier sectors could be sampled independently,
- and cocycle phases could encode inter-sector correlations.

This suggests a possible “Fourier Tower shadow representation” in which measurement complexity is reduced by exploiting solvable or hierarchical symmetry decompositions.

3.9.5 Phase-Space Sampling and Quantum Bayesian Propagation

The tower decomposition also resembles hierarchical probabilistic propagation schemes.

Indeed:

- local Fourier layers behave like local frequency variables,
- cocycle phases encode compatibility constraints,
- and controlled couplings propagate correlations between layers.

This structure is reminiscent of:

- factor graphs,
- belief propagation,
- tensor-network message passing,
- and Bayesian updating procedures.

From this viewpoint, the Fourier Tower may potentially provide:

a hierarchical phase-space propagation formalism.

In such a framework:

- local Fourier sectors carry partial probabilistic information,
- cocycle phases encode geometric consistency conditions,
- and inter-layer couplings propagate quantum correlations.

Although these ideas remain speculative, they suggest that Fourier Towers may connect:

harmonic analysis, symplectic geometry, stabilizer quantum mechanics,

and

hierarchical quantum inference methods.

A Relation with Existing Mathematical and Quantum Frameworks

Several components of the Fourier Tower framework are closely related to well-established mathematical structures.

In particular:

- The use of local Fourier decompositions over solvable towers is related to classical finite-group harmonic analysis and fast Fourier transforms on groups.
- The finite Heisenberg group, Weyl operators, and the relation

$$ZX = \omega_p XZ$$

are standard structures in finite-dimensional quantum mechanics and stabilizer theory.

- The symplectic action of Clifford circuits on Pauli–Weyl operators is well known in stabilizer quantum computation.
- The interpretation of noncommutativity through cocycles and projective representations belongs to classical group cohomology and central extension theory.
- Discrete Wigner methods, phase-space quantum mechanics, and symplectic finite geometry are already highly developed subjects.

The speculative aspect of the present work is therefore not the existence of these individual structures themselves, but rather the proposal that they may be organized under a common “Fourier Tower” viewpoint based on:

local Fourier layers + cocycle phase interactions + symplectic propagation.

In particular, the possible connections with:

- Clifford decomposition algorithms,
- symmetry-adapted stabilizer propagation,
- classical shadow tomography,
- and hierarchical phase-space inference,

remain exploratory and are proposed here mainly as conceptual directions for further investigation.

B References

References

- [1] P. Diaconis, *Group Representations in Probability and Statistics*, Institute of Mathematical Statistics, 1988.
- [2] A. Terras, *Fourier Analysis on Finite Groups and Applications*, Cambridge University Press, 1999.
- [3] J.-P. Serre, *Linear Representations of Finite Groups*, Springer, 1977.
- [4] G. W. Mackey, *Induced Representations of Groups and Quantum Mechanics*, Benjamin, 1968.
- [5] G. Karpilovsky, *Projective Representations of Finite Groups*, Marcel Dekker, 1985.
- [6] G. B. Folland, *Harmonic Analysis in Phase Space*, Princeton University Press, 1989.
- [7] R. Howe, “On the Role of the Heisenberg Group in Harmonic Analysis,” *Bulletin of the American Mathematical Society*, Vol. 3, No. 2, 1980.
- [8] D. Gross, “Hudson’s Theorem for Finite-Dimensional Quantum Systems,” *Journal of Mathematical Physics*, 49, 082105 (2008).
- [9] M. Nielsen and I. Chuang, *Quantum Computation and Quantum Information*, Cambridge University Press, 2000.
- [10] D. Gottesman, *Stabilizer Codes and Quantum Error Correction*, PhD thesis, Caltech, 1997.
- [11] S. Aaronson and D. Gottesman, “Improved Simulation of Stabilizer Circuits,” *Physical Review A*, 70, 052328 (2004).
- [12] S. Bravyi and D. Maslov, “Hadamard-Free Circuits Expose the Structure of the Clifford Group,” *IEEE Transactions on Information Theory*, 67(7), 4546–4563 (2021).
- [13] H.-Y. Huang, R. Kueng, and J. Preskill, “Predicting Many Properties of a Quantum System from Very Few Measurements,” *Nature Physics*, 16, 1050–1057 (2020).
- [14] D. M. Appleby, “SIC-POVMs and the Extended Clifford Group,” *Journal of Mathematical Physics*, 46, 052107 (2005).
- [15] V. Veitch, C. Ferrie, D. Gross, and J. Emerson, “Negative Quasi-Probability as a Resource for Quantum Computation,” *New Journal of Physics*, 14, 113011 (2012).