

HSRP and EtherChannel lab exercise

In this lab exercise you will have to configure Hot Standby Router Protocol (HSRP) and an EtherChannel between 2 switches. All basic configuration of the devices has been completed and does not have to be done.

1. On R0:
 - a. On interface G0/1 enable HSRP in group 1.
 - b. Set the virtual IP address to both of the PC's default gateway address.
 - c. Set the priority value to be 10 more than the default value.
 - d. Enable pre-emption.
2. On R1:
 - a. On interface G0/2 enable HSRP in group 1.
 - b. Set the virtual IP address to both of the PC's default gateway address.
 - c. Leave the default priority value.
3. From PC0 ping its default gateway. This should work.
4. Disable interface G0/1 on R0 and do it again. What do you expect to happen?
5. Check the HSRP status on R1.
6. Enable interface G0/1 on R0 and check the HSRP status on R1 again.
7. On SW1:
 - a. Create an EtherChannel on interfaces F0/1 and F0/2. The protocol used must be a Cisco standard.
 - b. Configure it as a trunk port.
8. On SW2:
 - a. Create an EtherChannel on interfaces F0/1 and F0/1. The protocol used must be a Cisco standard.
 - b. Configure it as a trunk port.
9. Check the created port channel interface on SW1. What information are you able to see?