

Multitech Micro Professor MPF-III Keyboard Matrix

Row	Col.	Row Pin	Col. Bus	R6	Normal Code	Shift Code	Key
0	7	P2.0	DB7	39	00	00	CTRL (modifier)
0	6	P2.0	DB6	38	00	00	(no code: NumLk/PB?)
0	5	P2.0	DB5	37	00	00	CAPS LOCK (modifier)
0	4	P2.0	DB4	36	00	00	(no code: NumLk/PB?)
0	3	P2.0	DB3	35	23	2B	F12
0	2	P2.0	DB2	34	20	2A	F11
0	1	P2.0	DB1	33	1D	29	F10
0	0	P2.0	DB0	32	1C	28	F9
1	7	P2.1	DB7	4F	1B	3F	F8
1	6	P2.1	DB6	4A	1A	3B	F7
1	5	P2.1	DB5	45	19	37	F6
1	4	P2.1	DB4	40	18	33	F5
1	3	P2.1	DB3	3B	17	2F	F4
1	2	P2.1	DB2	36	16	2B	F3
1	1	P2.1	DB1	31	15	27	F2
1	0	P2.1	DB0	30	14	26	F1
2	7	P2.2	DB7	2F	03	8B	kp7/CLRS
2	6	P2.2	DB6	2E	04	8D	kp9/HOME
2	5	P2.2	DB5	2D	1F	99	kp-/LIST
2	4	P2.2	DB4	2C	06	83	kp+/RUN
2	3	P2.2	DB3	2B	01	85	kp1/CLRL
2	2	P2.2	DB2	2A	02	87	kp3/CPES
2	1	P2.2	DB1	29	00	84	kp0/INSC
2	0	P2.2	DB0	28	05	A4	kp./DELC
3	7	P2.3	DB7	3F	6B	8C	kp8(up)
3	6	P2.3	DB6	3B	58	88	Bksp/kp4(<-)
3	5	P2.3	DB5	37	89	89	5/kp5
3	4	P2.3	DB4	33	5F	8A	kp6(->)
3	3	P2.3	DB3	2F	62	86	kp2(dn)
3	2	P2.3	DB2	2B	53	53	BREAK
3	1	P2.3	DB1	27	5D	5D	HALT
3	0	P2.3	DB0	26	7D	7D	Return

4	7	P2.4	DB7	25	58	58	Bksp/kp4(<-)
4	6	P2.4	DB6	24	FF	FF	DEL
4	5	P2.4	DB5	23	A7	83	=
4	4	P2.4	DB4	22	C3	FD	]
4	3	P2.4	DB3	21	D2	FE	`
4	2	P2.4	DB2	20	99	DF	-/kp-
4	1	P2.4	DB1	1F	C1	FB	[
4	0	P2.4	DB0	1E	75	70	'
5	7	P2.5	DB7	2F	AF	BF	/
5	6	P2.5	DB6	2C	8F	8E	;
5	5	P2.5	DB5	29	A4	B3	./kpDEL
5	4	P2.5	DB4	26	8E	9B	,
5	3	P2.5	DB3	23	6E	6E	Space
5	2	P2.5	DB2	20	C2	FC	\
5	1	P2.5	DB1	1D	59	59	TAB
5	0	P2.5	DB0	1C	77	77	ESC
6	7	P2.6	DB7	1B	0A	0A	(empty)
6	6	P2.6	DB6	1A	F1	B7	q
6	5	P2.6	DB5	19	D3	9D	a
6	4	P2.6	DB4	18	FA	C0	z
6	3	P2.6	DB3	17	F7	BD	w
6	2	P2.6	DB2	16	F3	B9	s
6	1	P2.6	DB1	15	F8	BE	x
6	0	P2.6	DB0	14	D7	A1	e
7	7	P2.7	DB7	1F	0A	0A	(empty)
7	6	P2.7	DB6	1D	D6	A0	d
7	5	P2.7	DB5	1B	D5	9F	c
7	4	P2.7	DB4	19	F2	B8	r
7	3	P2.7	DB3	17	D8	A2	f
7	2	P2.7	DB2	15	F6	BC	v
7	1	P2.7	DB1	13	F4	BA	t
7	0	P2.7	DB0	12	D9	A3	g
8	7	P1.0	DB7	11	0A	0A	(empty)
8	6	P1.0	DB6	10	D4	9E	b

8	5	P1.0	DB5	0F	F9	BF	y
8	4	P1.0	DB4	0E	DA	A4	h
8	3	P1.0	DB3	0D	E0	C2	n
8	2	P1.0	DB2	0C	F5	BB	u
8	1	P1.0	DB1	0B	DC	A6	j
8	0	P1.0	DB0	0A	DF	B5	m
9	7	P1.1	DB7	0F	0A	0A	(empty)
9	6	P1.1	DB6	0E	DB	A5	i
9	5	P1.1	DB5	0D	DD	A7	k
9	4	P1.1	DB4	0C	EF	CF	o
9	3	P1.1	DB3	0B	DE	A8	l
9	2	P1.1	DB2	0A	F0	B6	p
9	1	P1.1	DB1	09	84	77	0
9	0	P1.1	DB0	08	8D	76	9
10	7	P1.2	DB7	07	8C	78	8
10	6	P1.2	DB6	06	8B	74	7
10	5	P1.2	DB5	05	8A	D1	6
10	4	P1.2	DB4	04	89	73	5/kp5
10	3	P1.2	DB3	03	88	72	4
10	2	P1.2	DB2	02	87	71	3
10	1	P1.2	DB1	01	86	9C	2
10	0	P1.2	DB0	00	85	6F	1