

JNCRADIO MC-750 PORTABLE HF GP ANTENNA

<https://chelegance.com/product/jncradio-mc-750-100-watts-portable-hf-gp-antenna/>



1-1. DESCRIPTION & SPECIFICATION

MC-750 is a 7-50MHz, 100-WATT GP antenna designed for portable applications.

For Frequencies above 14MHz it is used as a full size (1/4 wavelength) antenna. And a coil is used for 7MHz.

All the components are packed with a 65CMX9CMX7CM carry bag which makes it very easy to be carried by operators for field operation.

| | |
|-----------------|---------------|
| FREQUENCY RANGE | 7MHz-50MHz |
| POWER | 100 WATTS PEP |
| IMPEDANCE | 50 OHMS |
| COUNTERPOISE | 4 X 3.5M |
| WEIGHT(KG) | 1.8 |
| DIMENSION(CM) | 65X9X7 |

//WARNING: Do not power the antenna more than its PEP power ratings.

1-2. PART LIST

- 1 X GROUND ROD(ANT BASE ATTACHED)
- 1 X 7MHZ COIL
- 1 X 50CM ANT ARM
- 1 X 5.2M WHIP
- 4 X COUNTERPOISE WIRES(radials)
- 1 X WIRE COLLECTOR BOARD
- 1 X CARRY BAG

1-3. INSTALLATION GUIDE

- Connect the 50CM antenna arm to the ground rod(antenna based attached)
- Insert the ground rod to the ground, the deeper the better.
- Insert the 4 counterpoise wires into the 4 *holes* to the antenna base, spread the counterpoises to different angles



- If you want to use 7MHz band, connect the 7MHz coil to the antenna arm. If not, skip this step.
- Connect the 5.2M whip to the antenna arm(top of the 7MHz coil if you want to operate on 7MHz)

There are reference marking points printed on the whip antenna. Adjust the length of the whip to meet your desired frequency according to the reference marking points. *(All sections above the mark needs to be fully extended and all sections fully collapsed.. 7MHz band need to have the supplied coil used as mentioned above)*



- Although there are reference points, you might still need to do fine adjustments to the length of the whip antenna until you get a sensible VSWR readings(From an in/external VSWR meter, VNA or antenna analyzer).

1-4. RECOMMENDATIONS ON ACCESSORIES

- It's recommended to have antenna analyzer or VNA to be able to read the parameters of the antenna set up.
- Of course it will be great if you have an antenna tuner

Reach out to us if you have any problems: support@chelegance.com

HAVE FUN WITH MC-750, 73!