

minutes slices of the motion videos. This config option was renamed from `max_movie_time` to `max_mpeg_time` in motion. If you use the motion-mm1 build, this one will work. If you get an error 'Unknown config option "max_mpeg_time"' either change this one to `max_movie_time` or make sure to really use the motion-mm1 build as shown above.

Hide Copy Code

`max_mpeg_time 600`

As some media players like VLC are unable to play the recorded movies, we've changed the codec to `msmpeg4`. Then, the movies play correctly in all players:

Hide Copy Code

`ffmpeg_video_codec msmpeg4`

Enable access to the live stream from anywhere. Otherwise only localhost (= the Raspberry device) would be allowed to access the live stream:

Hide Copy Code

`stream_localhost off`

If you want to protect the live stream with a username and password, you should enable this:

Hide Copy Code

`stream_auth_method 2`

`stream_authentication SOMEUSERNAME:SOMEPASSWORD`

All configuration parameters are explained in detail in the motion config documentation.

After your changes to the `motion.conf`, reboot the Raspberry:

Hide Copy Code

`sudo reboot`

Après avoir rebooté, vérifiez la division de la caméra

After the reboot, the red light of the camera module should be turned on, which shows that motion currently is using the camera to detect any movement.

À l'allumage !