

# AVM TR-064 – First Steps

*Supported by AVM*

Author: AVM GmbH

Date: 2022-11-18

## Content

1	<a href="#">Introduction</a>	8
2	<a href="#">Device Discovery</a>	8
2.1.1	<a href="#">Remark</a>	8
3	<a href="#">Service Discovery</a>	8
3.1	<a href="#">Manual Discovery</a>	8
4	<a href="#">Security</a>	8
4.1	<a href="#">Authentication</a>	9
4.1.1	<a href="#">Remarks</a>	9
4.1.2	<a href="#">Content Level Authentication</a>	9
4.2	<a href="#">Encryption</a>	10
4.2.1	<a href="#">Remark</a>	10
4.3	<a href="#">Two-Factor-Authentication</a>	11
5	<a href="#">Discovery and Communication</a>	11
5.1	<a href="#">Device Description</a>	12
6	<a href="#">Actions</a>	12
6.1	<a href="#">Actions and User Rights</a>	12
6.1.1	<a href="#">Service DeviceInfo</a>	14
6.1.2	<a href="#">Service DeviceConfig</a>	14
6.1.3	<a href="#">Service Layer3Forwarding</a>	14
6.1.4	<a href="#">Service LANConfigSecurity</a>	15
6.1.5	<a href="#">Service ManagementServer</a>	15
6.1.6	<a href="#">Service Time</a>	15
6.1.7	<a href="#">Service UserInterface</a>	16
6.1.8	<a href="#">Service LANHostConfigManagement</a>	16
6.1.9	<a href="#">Service LANEthernetInterfaceConfig</a>	16
6.1.10	<a href="#">Service Hosts</a>	17
6.1.11	<a href="#">Service WANCommonInterfaceConfig</a>	17
6.1.12	<a href="#">Service WANDSLInterfaceConfig</a>	18
6.1.13	<a href="#">Service WANDSLLinkConfig</a>	18
6.1.14	<a href="#">Service WANEthernetLinkConfig</a>	18
6.1.15	<a href="#">Service WANPPPConnection</a>	18
6.1.16	<a href="#">Service WANIPConnection</a>	19
6.1.17	<a href="#">Service WLANConfiguration</a>	20
6.1.18	<a href="#">Service X_VoIP</a>	21
6.1.19	<a href="#">Service X_AVM-DE_Storage</a>	22
6.1.20	<a href="#">Service X_AVM-DE_WebDAVClient</a>	22
6.1.21	<a href="#">Service X_AVM-DE_UPnP</a>	23
6.1.22	<a href="#">Service X_AVM-DE_OnTel</a>	23

6.1.23	<a href="#">Service X_AVM-DE_TAM</a>	24
6.1.24	<a href="#">Service X_AVM-DE_RemoteAccess</a>	24
6.1.25	<a href="#">Service X_AVM-DE_MyFritz</a>	24
6.1.26	<a href="#">Service X_AVM-DE_Speedtest</a>	25
6.1.27	<a href="#">Service X_AVM-DE_AppSetup</a>	25
6.1.28	<a href="#">Service X_AVM-DE_Homeplug</a>	25
6.1.29	<a href="#">Service X_AVM-DE_Homeauto</a>	25
6.1.30	<a href="#">Service X_AVM-DE_Dect</a>	26
6.1.31	<a href="#">Service X_AVM-DE_Filelinks</a>	26
6.1.32	<a href="#">Service X_AVM-DE_USPController</a>	26
6.1.33	<a href="#">Service X_AVM-DE_Auth</a>	26
6.1.34	<a href="#">Service X_AVM-DE_HostFilter</a>	27
6.1.35	<a href="#">Service X_AVM-DE_Media</a>	27
6.1.36	<a href="#">Service X_AVM-DE_WANMobileConnection</a>	27
7	<a href="#">State Variables</a>	28
7.1	<a href="#">Compatibility with clients</a>	28
8	<a href="#">Support for Multiple Clients and Parallel Access</a>	28
9	<a href="#">Transactions</a>	29
9.1	<a href="#">Usage of Transactions</a>	29
10	<a href="#">Examples</a>	29
10.1	<a href="#">SSDP request from application</a>	29
10.2	<a href="#">SSDP response from CPE</a>	29
10.3	<a href="#">Service description request from application</a>	30
10.4	<a href="#">Service description response from CPE</a>	30
10.5	<a href="#">SOAP Request with Action GetSecurityPort</a>	31
10.6	<a href="#">SOAP Response for Action GetSecurityPort</a>	32
10.7	<a href="#">Content Level Authentication</a>	33
10.7.1	<a href="#">Initial Client Request</a>	33
10.7.2	<a href="#">Server Response to Initial Client Request</a>	33
10.7.3	<a href="#">Client Request with Authentication</a>	34
10.7.4	<a href="#">Server Response for successful Authentication</a>	34
11	<a href="#">Appendix</a>	35
11.1	<a href="#">References</a>	35

## History

Date	Version	Changes
2010-06-17	1	Initial version
2010-06-18	2	Minor changes
2010-06-21	3	4.1 Authorization, actions GetSecurityPort and DialNumber
2010-07-09	4	Added chapter 6 Actions
2010-08-31	5	Added chapter 7 State Variables Added reference to UPnP specification
2011-02-25	6	Added chapter Transactions
2011-03-03	7	Added chapter Support for Multiple Clients and Parallel Access with transactions or multiple session IDs
2011-12-05	8	Changed chapter Authorization to Authentication Added sub chapter Content Level Authentication
2011-12-21	9	Changed examples for Content Level Authentication
2012-11-06	10	Added chapter 6.1 Actions and User Rights . Change list of action allowed without authentication in chapter 4.1 Authentication .
2012-11-07	11	LanConfigSecurity:GetInfoEx () without authentication ManagementServer:GetInfo () without authentication Layer3Forwarding:SetDefaultConnectionService () with configuration rights.
2012-12-03	12	Description of authentication for multi user configurations. X_AVM-DE_GetAnonymousLogin () X_AVM-DE_GetCurrentUser ()
2013-01-23	13	Changed chapter 4.1.1 Remarks to clarify service behaviour for unauthorized requests.
2013-03-25	14	Details for content level authentication.
2013-04-02	15	Spelling Added actions in chapter 6.1.25 Service X_AVM-DE_MyFritz .
2013-08-20	16	Added action and changed right for all actions in chapter 6.1.10 Service Hosts .
2013-08-23	17	Changed right for GetInfo in chapter 6.1.25 Service X_AVM-DE_MyFritz .
2013-08-26	18	Add action in chapter 6.1.17 Service WLANConfiguration : X_AVM-DE_GetWLANExtInfo  Corrections 6.1.17 Service WLANConfiguration : X_AVM_DE_SetStickSurfEnable → X_AVM-

		DE_SetStickSurfEnable  Corrections 6.1.18 Service X_VoIP : X_AVM_DE_*VoIPAccount → X_AVM-DE_*VoIPAccount X_AVM_DE_GetClient* → X_AVM-DE_GetClient* X_AVM_DE_SetClient* → X_AVM-DE_SetClient* X_AVM_DE_DeleteClient → X_AVM-DE_DeleteClient X_AVM_DE_GetClients → X_AVM-DE_GetClients X_AVM_DE_GetNumbers → X_AVM-DE_GetNumbers X_AVM_DE_GetNumberOfNumbers → X_AVM-DE_GetNumberOfNumbers
2014-05-26	19	Added actions to service Hosts in chapter 6.1.10 Service Hosts : X_AVM-DE_GetAutoWakeOnLANByMACAddress, X_AVM-DE_SetAutoWakeOnLANByMACAddress, X_AVM-DE_SetHostNameByMACAddress, X_AVM-DE_WakeOnLANByMACAddress
2015-02-06	20	Added service X_AVM-DE_Speedtest in chapter 6.1.26 Service X_AVM-DE_Speedtest .
2015-03-17	21	Added missing services and actions to chapter 6.1 Actions and User Rights . Change needed rights for many actions. Sort actions per service in alphabetical order.
2015-06-02	22	UserInterface:GetInfo change Right C => C or A Added Service: X_AVME_DE_Homeauto in chapter 6.1 Actions and User Rights
2015-06-05	23	Added New Service: X_AVME_DE_Dect in chapter 6.1 Actions and User Rights
2015-06-10	24	Added missing actions UserInterface:X_AVM_DE_GetInfo UserInterface:X_AVM_DE_SetConfig
2015-07-17	25	Added missing action Service X_AVM-DE_AppSetup: SetAppMessageReceiver
2015-08-31	26	Change rights for UserInterface:GetInfo
2015-10-01	27	Add action SetFTPServerWAN to service 6.1.19 Service X_AVM-DE_Storage .
2015-11-19	28	Corrected actions for service DeviceConfig Layer3Forwarding: Entries => Entry UserInterface: X_AVM-DE_DoPrepareCGI WANCommonInterfaceConfig: X_AVM-DE_GetOnlineMonitor WLANConfiguration: X_AVM-DE_WLANGetNightControl => X_AVM-DE_GetNightControl X_AVM-DE_OnTel: GetDeflection, GetDeflections, GetInfoByIndex, GetNumberOfDeflections X_AVM-DE_Filelink added

		X_AVM-DE_Homeplug X_AVM-DE_StorageService: SetUserConfig
2016-06-29	29	Changed required rights for action GetDDNSInfo
2017-01-09	30	Add description to chapter 4.1.2 Content Level Authentication . Change several actions in chapter 6.1 Actions and User Rights : Add - Hosts:X_AVM-DE_GetHostListPath Add - Hosts:X_AVM-DE_GetSpecificHostEntryByIP Add - WLANConfiguration:X_AVM-DE_GetSpecificAssociatedDeviceInfoByIP Add - X_AVM-DE_AppSetup:ResetEvent Add - X_AVM-DE_FileLinks:GetFileLinkListPath Add - X_AVM-DE_Storage:RequestFTPServerWAN Add - X_AVM-DE_TAM:GetList Add - X_VoIP:X_AVM-DE_GetClientByClientId Add - X_VoIP:X_AVM-DE_SetClient4 Chg - Time:GetInfo Chg - X_AVM-DE_AppSetup:GetInfo Chg - X_AVM-DE_AppSetup:RegisterApp Del - WANIPConnection:X_SetDNSServers Del - WANPPPConnection:X_SetDNSServers
2017-06-02	31	Add PhoneRight and HomeautoRight for Actions GetNumberOfDectEntries, GetGenericDectEntry, GetSpecificDectEntry
2017-06-06	32	Change rights for Actions - SetEnable - X_AVM-DE_GetWPSInfo - X_AVM-DE_SetWPSInfo in WLANConfiguration
2017-11-22	33	Add Action SetEnable in Service RemoteAccess
2018-08-15	34	Updating to state of other tr064-service documents and adding some Two-Factor-Authentication information. Changed referred IP address. Added table for required rights for the service X_AVM- DE_Auth. LanConfigSecurity:GetInfo need authentication and is removed from list in section 4.1.  Add X_VoIP:X_AVM-DE_GetVoIPCommonAreaCode Add X_VoIP:X_AVM-DE_GetVoIPCommonCountryCode Add X_VoIP:X_AVM-DE_SetDelayedCallNotification Add X_VoIP:X_AVM-DE_SetVoIPCommonAreaCode Add X_VoIP:X_AVM-DE_SetVoIPCommonCountryCode Add WANDSLInterfaceConfig:X_AVM-DE_GetDSLDiagnoseInfo Add Hosts:X_AVM-DE_GetMeshListPath Add X_AVM-DE_OnTel:GetPhonebookEntryUID

		Add X_AVM-DE_OnTel:DeletePhonebookEntryUID Add X_AVM-DE_AppSetup:GetAppMessageFilter Add X_AVM-DE_AppSetup:SetAppMessageFilter Add X_AVM-DE_AppSetup:SetAppVPNwithPFS Add X_AVM-DE_Homeauto:GetInfo Add X_AVM-DE_Dect:GetDectListPath Add X_AVM-DE_Auth:GetInfo Add X_AVM-DE_Auth:GetState Add X_AVM-DE_Auth:SetConfig Add WLANConfiguration:X_AVM-DE_SetWLANGlobalEnable  Del X_AVM-DE_GetGenericHostEntryExt Del X_AVM-DE_GetSpecificHostEntryExt
2019-01-07	35	Changed needed rights for WLANConfiguration:GetWLANExtInfo X_AVM-DE_Storage:GetInfo
2019-01-15	36	Changed needed rights for UserInterface:X_AVM-DE_DoUpdate
2019-02-08	37	Add Service X_AVM-DE_AppSetup:GetAppRemoteInfo
2019-03-01	38	Changed needed rights for actions of WLANConfiguration service: GetBeaconType GetSecurityKeys GetSSID SetSecurityKeys X_AVM-DE_GetWPSInfo X_AVM-DE_SetWPSConfig
2019-12-12	39	New Service X_AVM-DE_HostFilter added.
2020-01-09	40	New Action added WLANConfiguration:X_AVM-DE_GetWLANConnectionInfo
2020-02-27	41	New action added LANConfigSecurity:X_AVM-DE_GetUserList
2020-06-23	42	New actions added X_AVM-DE_Hostfilter:DisallowWANAccessByIP, X_AVM-DE_Hostfilter:GetWANAccessByIP X_AVM-DE_OnTel:GetCallBarringEntry X_AVM-DE_OnTel:GetCallBarringEntryByNum X_AVM-DE_OnTel:GetCallBarringList X_AVM-DE_OnTel:SetCallBarringEntry X_AVM-DE_OnTel>DeleteCallBarringEntryUID WANDSLInterfaceConfig:X_AVM-DE_GetDSLInfo X_VoiP:X_AVM-DE_GetAlarmClock X_VoiP:X_AVM-DE_GetNumberOfAlarmClocks X_VoiP:X_AVM-DE_SetAlarmClockEnable
2021-01-20	43	New actions added DeviceConfig:X_AVM-DE_GetSupportDataInfo, DeviceConfig:X_AVM-DE_SendSupportData

2021-07-07	44	New actions added WANCommonInterfaceConfig:WanCommonInterfaceConfig_GetActiveProvider, X_VoIP:X_AVM-DE_GetVoIPStatus, Hosts:X_AVM-DE_SetPrioritizationByIP Changed needed rights for action of WANCommonInterfaceConfig: GetCommonLinkProperties
2021-07-12	45	Added a new chapter describing the device description and some contents of the UpnP root device description
2021-09-29	46	New action added DeviceConfig:X_AVM-DE_SetSupportDataEnable New user rights for Hosts:X_AVM-DE_SetPrioritizationByIP: App, Phone
2021-11-22	47	New user rights for DeviceConfig: X_AVM-DE_GetSupportDataEnable Hosts: X_AVM-DE_GetFriendlyName and X_AVM-DE_SetFriendlyName X_VoIP: X_AVM-DE_GetVoIPAccounts X_AVM-DE_OnTel: DeleteDeflection and SetDeflection X_AVM-DE_RemoteAccess: SetLetsEncryptEnable X_AVM-DE_MyFritz: SetMyFRITZ
2022-01-19	48	New user rights for X_AVM-DE_Speedtest: GetStatistics and ResetStatistics
2022-02-22	49	Changed rights for UserInterface:X_AVM-DE_GetInfo, Hosts:X_AVM-DE_GetAutoWakeOnLANByMACAddress and X_AVM-DE_SetAutoWakeOnLANByMACAddress Required rights explained in subdocuments
2022-02-22	50	Added new service X_AVM-DE_Media with actions and user rights
2022-06-13	51	Added new service X_AVM-DE_USPController with actions and user rights
2022-10-13	52	Added new service X_AVM-DE_WANMobileConnection with actions and user rights  Added actions X_AVM-DE_GetInfo, X_AVM-DE_SetFriendlyNameByIP and X_AVM-DE_SetFriendlyNameByMAC for service Hosts Added actions X_AVM-DE_GetWLANDeviceListPath, and X_AVM-DE_SetWPSEnable for service WLANConfiguration Added action GetBoxSenderId for service X_AVM-DE_AppSetup  Marked action SetDefaultWEPKeyIndex and GetDefaultWEPKeyIndex as removed
2022-11-10	53	Added new Actions GetAccessTechnology, SetAccessTechnology, GetBandCapabilities, GetEnabledBandCapabilities and SetEnabledBandCapabilities for Service X_AVM-DE_WANMobileConnection
2022-11-18	54	Added new actions GetPreferredAccessTechnology and SetPreferredAccessTechnology for Service X_AVM-DE_WANMobileConnection

## 1 Introduction

This document gives a short overview about the TR-064 protocol implementation in AVM devices. Especially the discovery of IP addresses, ports, TR-064 devices and services. Next chapter explains the usage of the security options.

In addition some example messages between the management application and the CPE are listed to see some details.

For details please refer the TR-064 document at

<http://www.broadband-forum.org/technical/download/TR-064.pdf>.

## 2 Device Discovery

To be able to communicate with a TR-064 device from AVM, the following steps have to be done.

A complete description can be found in chapter 3.2.2 *SSDP Search on Start-up of CPE Management Application* in the [TR064] specification.

- 1 SSDP Discovery using M-SEARCH
- 2 Retrieval of device description file(s) using HTTP GET
  - 2.1 The content of the SSDP discover response message has to be parsed to get the valid URL for downloading the service description.
- 3 Be aware of the lease time for every announcement. If an announcement is not re-sent prior to the expire of the lease, the service discovery has to be restarted by the application.

### 2.1.1 Remark

In the [TR064] specification chapter 3.2.1 *SSDP Advertisement on Start-up of CPE Device*, the CPE MUST send broadcast SSDP advertisement (NOTIFY) messages. AVM devices do not do this, to avoid being shown in Microsoft Windows UPnP/ network devices list by default.

## 3 Service Discovery

For the individual services several separate description files can be retrieved.

The URLs are given in the central service description.

An URL can be combined by taking the IP address and the port from the SSDP discovery response message (LOCATION header) and the value in a XML tag SCPDURL.

### 3.1 Manual Discovery

If a TR-064 client tries to detect an AVM TR-064 service manually, the following steps can be used.

- DNS resolution of fritz.box
- HTTP GET request to <http://192.168.178.1:49000/tr64desc.xml>
- HTTPS GET request to <https://192.168.178.1:49443/tr64desc.xml>

## 4 Security

TR-064 offers authorization and encryption to make safe communication. Furthermore some actions with potential to be the target of fraud attacks are protected via Two-Factor-Authentication.



## 4.1 Authentication

In the [TR064] specification, chapter 4.2 *Authentication*, the default usernames and factory default passwords are described.

AVM CPEs have the following implementation.

- If an individual username and a password is configured via WebGUI or TR-064, a configured username and password have to be used for password-protected actions.

It is recommended to always use a configured username and password.

The following actions do not need authorization:

- DeviceInfo:GetSecurityPort
- WLANConfiguration:X\_SetHighFrequencyBand
- LanConfigSecurity:X\_AVM-DE\_GetAnonymousLogin
- If only a password is configured via WebGUI or TR-064, a matching username is used internally.
  - It is not recommended to use only a password without a configured username.
  - If no configured username is used the following action shows which internal user is used instead:  
LanConfigSecurity:X\_AVM-DE\_GetCurrentUser
- If no individual password is configured, TR-064 does not require a password or username.

The following action is protected and not available without an individual password:

  - DialNumber

The default authentication mechanism is HTTP authentication using digest (MD5 hashes). Alternatively an authentication on content level is supported.

### 4.1.1 Remarks

The username dsIf-reset is not supported.

The TR-064 service may use HTTP status code 503 (service unavailable) instead of 401 (unauthorized) if too many unauthenticated requests from one client are made.

### 4.1.2 Content Level Authentication

In addition to HTTP digest authentication which is supported by many libraries another alternative authentication is available.

The Content Level Authentication is based on the idea of SOAP extension for basic and digest authentication described in [SOAPAUTH01].

The client may either use the HTTP authentication mechanisms or use the content level authentication for SOAP actions that require authorization.

To access URLs with HTTP GET or HTTP POST a TR-064 URL session ID has to be retrieved first.

The TR-064 URL session ID is part of the URLs for phone book and call list.

For further requests like:

- phone book images,
- fax messages or
- answering machine messages

the SOAP action DeviceConfig::X\_AVM-DE\_CreateUrlSID () has to be invoked.

See the example for the authentication in the chapter 10.7 Content Level Authentication .

The client has to insert a SOAP header in the content to initiate the content level

authentication.

The server responses an initial request with content level authentication contains a nonce value, the realm and a SOAP fault with a number and a text.

The client needs the nonce value, username, realm and password to calculate the digest hash.

A client side nonce is supported as optional parameter, too.

The following calculation and example values are taken from the examples in chapter 10.7 Content Level Authentication .

Variable	Value	Remark
uid	admin	
pwd	gurkensalat	
realm	F!Box SOAP-Auth	Not writeable.
sn	F758BE72FB999CEA	
response	b4f67585f22b0af7c4615db5a18faa14	

The calculation is similar to chapter 4.3 Digest Computation in [SOAPAUTH01].

`response = MD5( concat(secret, ":", sn) )`

when only client authentication is required.

Where:

- **secret** (string) represents the hex encoding of the digest  
`secret = MD5( concat(uid, ":", realm, ":", pwd) )`
- **uid** (string) represents the User ID.
- **realm** (string) represents the Realm name.
- **pwd** (string) represents the password.
- **sn** (string) represents the nonce serving as the challenge from the server to the client.

## 4.2 Encryption

The TR-064 specification chapter 4.4 *Encryption* describes the possibilities for encryption. To make it more easy for applications the port can be retrieved using a special SOAP action.

The service type urn:dslforum-org:service:DeviceInfo:1 offers the action GetSecurityPort where the used port value can be retrieved.

Example messages for a request and a response with the security port can be found in the examples chapter.

### 4.2.1 Remark

In the [TR064] specification, SSL encryption is recommended only for some SOAP actions. The support for access over an encrypted HTTPS link is not specified in details. Therefore AVM decided to use the explained action GetSecurityPort.

### 4.3 Two-Factor-Authentication

Some actions are protected via Two-Factor-Authentication (2FA) to prevent remote config changes. Even when credentials are known, the physical presence is needed to confirm changes on the AVM CPE device configuration. For more information see X\_Auth service documentation.

## 5 Discovery and Communication

Base on the message flow in the [TR064] specification, the following interaction sequence is expected by the CPE.




Figure 1: CPE Discovery and Communications base on the [TR064] specification

## 5.1 Device Description

The TR-064 root device description on FRITZ!OS devices is delivered as response of search request with M-SEARCH.

A typical response will contain the following URL:

<http://192.168.178.1:49000/tr64desc.xml>

The UPnP Device Architecture 1.1 and 2.0 describe the protocol in details.

A client CAN (re-)identify a FRITZ!OS device by its MAC address.

The MAC address is part of the UUID and serialNumber.

Some more contents of the UPnP root device description can be found in the table below.

XML Tag	Description
UDN	UUID with default MAC as last part, to used for (re-) identification of a FRITZ!OS device by its MAC
serialNumber	Device MAC address
serviceType	URN with service name and ID
serviceId	URN with service ID
controlURL	Path to be used for TR-064 SOAP actions
SCPDURL	URL path to TR-064 service SCPD

UUID = Universally Unique Identifier

URN = Uniform Resource Name

## 6 Actions

Actions may change in their lifetime. The names of actions are kept unchanged as long as possible, but the arguments may change if needed.

The number of arguments may differ and the meaning of a state variable may change.

To detect such a change, it is recommended to parse all SCPDXML files after attaching to a device.

In general actions return 402 if the number of arguments for an action is not as expected or an unexpected argument is used.

If an unknown action is used the returned code is 401. This return code is used for obsoleted actions, too.

### 6.1 Actions and User Rights

The following user rights are supported:

- no rights
- configuration
- phone contents and phone configuration
- NAS contents and NAS configuration

User rights for configuration include user rights for phone contents and phone configuration.

The user rights may be limited to LAN or granted to LAN and WAN access.

There are some more settings for user rights:

- access from LAN only with authentication
- access from LAN without authentication

- no configured user and no configured password

Every action has needed user rights. The following user rights mappings to SOAP actions shall give an overview. Every action without explicit “required rights” field in subdocuments needs config rights.

C – Configuration

A – restricted configuration for applications

P – Phone contents and phone configuration

N – NAS contents and NAS configuration

H – Home automation contents and configuration

- – No rights

If a user is not authenticated, 401 (“Unauthorized”) will be returned.

If a user is authenticated but has not the needed rights, 606 (“Action not authorized”) will be returned. If an action needs 2FA, the status code 866 (“second factor authentication required”), 867 (“second factor authentication blocked”) or 868 (“second factor authentication busy”) will be returned and the 2FA procedure, as described in X\_Auth service description, has to be passed.

### 6.1.1 Service DeviceInfo

Action	User Rights
GetDeviceLog	C
GetInfo	C
GetSecurityPort	-
SetProvisioningCode	C

### 6.1.2 Service DeviceConfig

Action	User Rights
ConfigurationFinished	C
ConfigurationStarted	C
FactoryReset	C
GetPersistentData	C
Reboot	C
SetPersistentData	C
X_AVM-DE_CreateUrlSID	C or A or P or N or H
X_AVM-DE_GetConfigFile	C
X_AVM-DE_SetConfigFile	C
X_GenerateUUID	C
X_AVM-DE_GetSupportDataInfo	C or A or P or N or H
X_AVM-DE_SendSupportData	C or A or P or N or H
X_AVM-DE_GetSupportDataEnable	-
X_AVM-DE_SetSupportDataEnable	C

### 6.1.3 Service Layer3Forwarding

Action	User Rights
AddForwardingEntry	C
DeleteForwardingEntry	C
GetDefaultConnectionService	C
GetForwardNumberOfEntries	C
GetGenericForwardingEntry	C
GetSpecificForwardingEntry	C
SetDefaultConnectionService	C
SetForwardingEntryEnabled	C

### 6.1.4 Service LANConfigSecurity

Action	User Rights
GetInfo	-
SetConfigPassword	C or A or P or N or H
X_AVM-DE_GetAnonymousLogin	-
X_AVM-DE_GetCurrentUser	C or A or P or N or H
X_AVM-DE_GetUserList	-

### 6.1.5 Service ManagementServer

Action	User Rights
GetInfo	C
SetConnectionRequestAuthentication	C
SetManagementServerPassword	C
SetManagementServerURL	C
SetManagementServerUsername	C
SetPeriodicInform	C
SetUpgradeManagement	C
X_AVM-DE_GetTR069FirmwareDownloadEnabled	C
X_AVM-DE_SetTR069FirmwareDownloadEnabled	C
X_SetTR069Enable	C

### 6.1.6 Service Time

Action	User Rights
GetInfo	C or A or P or N or H
SetNTPServers	C

### 6.1.7 Service UserInterface

Action	User Rights
GetInfo	-
X_AVM-DE_CheckUpdate	C
X_AVM-DE_DoUpdate	C or -, depending on configuration
X_AVM-DE_DoPrepareCGI	C
X_AVM-DE_DoManualUpdate	C
X_AVM-DE_GetInternationalConfig	C
X_AVM-DE_SetInternationalConfig	C
X_AVM-DE_GetInfo	-
X_AVM-DE_SetConfig	C

### 6.1.8 Service LANHostConfigManagement

Action	User Rights
GetAddressRange	C
GetDNSServers	C
GetInfo	C
GetIPInterfaceNumberOfEntries	C
GetIPRoutersList	C
GetSubnetMask	C
SetAddressRange	C
SetDHCPSEnable	C
SetIPInterface	C
SetIPRouter	C
SetSubnetMask	C

### 6.1.9 Service LANEthernetInterfaceConfig

Action	User Rights
GetInfo	C
GetStatistics	C
SetEnable	C



### 6.1.10 Service Hosts

Action	User Rights
GetGenericHostEntry	-
GetHostNumberOfEntries	-
GetSpecificHostEntry	-
X_AVM-DE_GetAutoWakeOnLANByMACAddress	-
X_AVM-DE_GetChangeCounter	-
X_AVM-DE_GetFriendlyName	-
X_AVM-DE_GetHostListPath	C or A or P
X_AVM-DE_GetInfo	-
X_AVM-DE_GetMeshListPath	C or P or A
X_AVM-DE_GetSpecificHostEntryByIP	C or A or P
X_AVM-DE_HostDoUpdate	C or A
X_AVM-DE_HostsCheckUpdate	C or A
X_AVM-DE_SetAutoWakeOnLANByMACAddress	-
X_AVM-DE_SetFriendlyName	C or A or P or N or H
X_AVM-DE_SetFriendlyNameByIP	C or A
X_AVM-DE_SetFriendlyNameByMAC	C or A
X_AVM-DE_SetHostNameByMACAddress	C
X_AVM-DE_SetPrioritizationByIP	C or A or P
X_AVM-DE_WakeOnLANByMACAddress	-

### 6.1.11 Service WANCommonInterfaceConfig

Action	User Rights
GetCommonLinkProperties	C or P or A or N or H
GetTotalBytesReceived	C
GetTotalBytesSent	C
GetTotalPacketsReceived	C
GetTotalPacketsSent	C
X_AVM-DE_GetActiveProvider	C or P or A
X_AVM-DE_SetWANAccessType	C
X_AVM-DE_GetOnlineMonitor	C

**6.1.12 Service WANDSLInterfaceConfig**

Action	User Rights
GetInfo	C
GetStatisticsTotal	C
X_AVM-DE_GetDSLDiagnoseInfo	-
X_AVM-DE_GetDSLInfo	-

**6.1.13 Service WANDSLLinkConfig**

Action	User Rights
GetATMEncapsulation	C
GetAutoConfig	C
GetDestinationAddress	C
GetDSLLinkInfo	C
GetInfo	C
GetStatistics	C
SetATMEncapsulation	C
SetDestinationAddress	C
SetDSLLinkType	C
SetEnable	C

**6.1.14 Service WANEthernetLinkConfig**

Action	User Rights
GetEthernetLinkStatus	C

**6.1.15 Service WANPPPConnection**

Action	User Rights
AddPortMapping	C
DeletePortMapping	C
ForceTermination	C
GetConnectionType	C
GetConnectionTypeInfo	C
GetExternalIPAddress	C
GetGenericPortMappingEntry	C
GetInfo	C
GetLinkLayerMaxBitRates	C

GetNATRSIPStatus	C
GetPortMappingNumberOfEntries	C
GetSpecificPortMappingEntry	C
GetStatusInfo	C
GetUserName	C
RequestConnection	C
SetConnectionTrigger	C
SetIdleDisconnectTime	C
SetPassword	C
SetRouteProtocolRx	C
SetUserName	C
X_AVM-DE_GetAutoDisconnectTimeSpan	C
X_AVM-DE_SetAutoDisconnectTimeSpan	C
X_GetDNSServers	C

### 6.1.16 Service WANIPConnection

Action	User Rights
AddPortMapping	C
DeletePortMapping	C
ForceTermination	C
GetConnectionType	C
GetConnectionTypeInfo	C
GetExternalIPAddress	C
GetGenericPortMappingEntry	C
GetInfo	C
GetNATRSIPStatus	C
GetPortMappingNumberOfEntries	C
GetSpecificPortMappingEntry	C
GetStatusInfo	C
RequestConnection	C
SetConnectionTrigger	C
SetIdleDisconnectTime	C
SetRouteProtocolRx	C
X_GetDNSServers	C

### 6.1.17 Service WLANConfiguration

Action	User Rights
GetBasBeaconSecurityProperties	C
GetBeaconAdvertisement	C
GetBeaconType	C or A
GetBSSID	C
GetChannelInfo	C
GetDefaultWEPKeyIndex (removed)	C
GetGenericAssociatedDeviceInfo	C or A or P
GetInfo	C or A or P
GetPacketStatistics	C
GetSecurityKeys	A
GetSpecificAssociatedDeviceInfo	C or A or P
GetSSID	A
GetStatistics	C
GetTotalAssociations	C or A or P
SetBasBeaconSecurityProperties	C
SetBeaconAdvertisement	C
SetBeaconType	C
SetChannel	C
SetConfig	C
SetDefaultWEPKeyIndex (removed)	C
SetEnable	C or A
SetSecurityKeys	C for normal AP, A for guest AP
SetSSID	C
X_AVM-DE_GetIPTVOptimized	C
X_AVM-DE_GetNightControl	-
X_AVM-DE_GetSpecificAssociatedDeviceInfoByIp	C or A or P
X_AVM-DE_GetWLANConnectionInfo	-
X_AVM-DE_GetWLANDeviceListPath	C or A or P
X_AVM-DE_GetWLANExtInfo	C or A
X_AVM-DE_GetWLANHybridMode	C
X_AVM-DE_GetWPSInfo	C or A
X_AVM-DE_SetIPTVOptimized	C

X_AVM-DE_SetStickSurfEnable	C
X_AVM-DE_SetWLANGlobalEnable	C or A
X_AVM-DE_SetWLANHybridMode	C
X_AVM-DE_SetWPSEnabledConfig	C or A
X_AVM-DE_SetWPSEnabled	C or A
X_SetHighFrequencyBand (removed)	-

### 6.1.18 Service X\_VoIP

Action	User Rights
GetExistingVoIPNumbers	P
GetInfo	P
GetInfoEx	P
GetMaxVoIPNumbers	P
GetVoIPCommonAreaCode	P
GetVoIPCommonCountryCode	P
GetVoIPEnableAreaCode	P
GetVoIPEnableCountryCode	P
SetConfig	P
SetVoIPCommonAreaCode	P
SetVoIPCommonCountryCode	P
SetVoIPEnableAreaCode	P
SetVoIPEnableCountryCode	P
X_AVM-DE_AddVoIPAccount	P
X_AVM-DE_DeleteClient	P
X_AVM-DE_DelVoIPAccount	P
X_AVM-DE_DialGetConfig	P
X_AVM-DE_DialHangup	P
X_AVM-DE_DialNumber	P
X_AVM-DE_DialSetConfig	P
X_AVM-DE_GetAlarmClock	P
X_AVM-DE_GetClient	P
X_AVM-DE_GetClient2	P
X_AVM-DE_GetClient3	P
X_AVM-DE_GetClientByClientId	A or P

X_AVM-DE_GetClients	P
X_AVM-DE_GetNumberOfAlarmClocks	P
X_AVM-DE_GetNumberOfClients	P
X_AVM-DE_GetNumberOfNumbers	P
X_AVM-DE_GetNumbers	P
X_AVM-DE_GetPhonePort	P
X_AVM-DE_GetVoIPAccount	P
X_AVM-DE_GetVoIPAccounts	P or A
X_AVM-DE_GetVoIPCommonAreaCode	P
X_AVM-DE_GetVoIPCommonCountryCode	P
X_AVM-DE_GetVoIPStatus	P or A
X_AVM-DE_SetAlarmClockEnable	P
X_AVM-DE_SetClient	P
X_AVM-DE_SetClient2	P
X_AVM-DE_SetClient3	P
X_AVM-DE_SetClient4	P
X_AVM-DE_SetDelayedCallNotification	P
X_AVM-DE_SetVoIPCommonAreaCode	P
X_AVM-DE_SetVoIPCommonCountryCode	P

### 6.1.19 Service X\_AVM-DE\_Storage

Action	User Rights
GetInfo	C or A
GetUserInfo	C
RequestFTPServerWAN	A or N only but not C
SetFTPServer	C
SetFTPServerWAN	C
SetSMBServer	C
SetUserConfig	C

### 6.1.20 Service X\_AVM-DE\_WebDAVClient

Action	User Rights
GetInfo	C
SetConfig	C

**6.1.21 Service X\_AVM-DE\_UPnP**

Action	User Rights
GetInfo	C
SetConfig	C

**6.1.22 Service X\_AVM-DE\_OnTel**

Action	User Rights
AddPhonebook	P
DeleteByIndex	P
DeleteCallBarringEntryUID	P
DeleteDeflection	P
DeletePhonebook	P
DeletePhonebookEntry	P
DeletePhonebookEntryUID	P
GetCallBarringEntry	P
GetCallBarringEntryByNum	P
GetCallBarringList	P
GetCallList	P
GetDECTHandsetInfo	P
GetDECTHandsetList	P
GetDeflection	P
GetDeflections	P
GetInfo	P
GetInfoByIndex	P
GetNumberOfDeflections	P
GetNumberOfEntries	P
GetPhonebook	P
GetPhonebookEntry	P
GetPhonebookEntryUID	P
GetPhonebookList	P
SetCallBarringEntry	P
SetConfig	P
SetConfigByIndex	P
SetDECTHandsetPhonebook	P
SetDeflection	P

SetDeflectionEnable	P
SetEnable	P
SetEnableByIndex	P
SetPhonebookEntry	P
SetPhonebookEntryUID	P

### 6.1.23 Service X\_AVM-DE\_TAM

Action	User Rights
DeleteMessage	P
GetInfo	P
GetList	A or P
GetMessageList	P
MarkMessage	P
SetEnable	P

### 6.1.24 Service X\_AVM-DE\_RemoteAccess

Action	User Rights
GetDDNSInfo	C or A or P or N or H
GetDDNSProviders	C
GetInfo	C or A or P or N or H
SetConfig	C
SetDDNSConfig	C
SetEnable	C
SetLetsEncryptEnable	C or A

### 6.1.25 Service X\_AVM-DE\_MyFritz

Action	User Rights
DeleteServiceByIndex	C or A or P
GetInfo	C or A or P or N or H
GetNumberOfServices	C or A or P
GetServiceByIndex	C or A or P
SetServiceByIndex	C or A or P
SetMyFRITZ	C or A



**6.1.26 Service X\_AVM-DE\_Speedtest**

Action	User Rights
GetInfo	C
GetStatistics	C
ResetStatistics	C
SetConfig	C

**6.1.27 Service X\_AVM-DE\_AppSetup**

Action	User Rights
GetAppMessageFilter	C or A or P or N or H
GetAppRemoteInfo	C or A
GetBoxSenderId	C or A or P or N or H
GetConfig	C or A or P or N or H
GetInfo	-
RegisterApp	C or P or N or H but not A
ResetEvent	C
SetAppMessageFilter	C or A or P or N or H
SetAppMessageReceiver	C or A or P or N or H
SetAppVPN	C
SetAppVPNwithPFS	C

**6.1.28 Service X\_AVM-DE\_Homeplug**

Action	User Rights
DeviceDoUpdate	C or A
GetGenericDeviceEntry	C or A
GetNumberOfDeviceEntries	C or A
GetSpecificDeviceEntry	C or A

**6.1.29 Service X\_AVM-DE\_Homeauto**

Action	User Rights
GetGenericDeviceInfos	C or H
GetInfo	C or H
GetSpecificDeviceInfos	C or H
SetDeviceName	C or A
SetSwitch	C or H

**6.1.30 Service X\_AVM-DE\_Dect**

Action	User Rights
DectDoUpdate	C or A
GetDectListPath	C or A
GetGenericDectEntry	C or A or P or H
GetNumberOfDectEntries	C or A or P or H
GetSpecificDectEntry	C or A or P or H

**6.1.31 Service X\_AVM-DE\_Filelinks**

Action	User Rights
DeleteFilelinkEntry	C or N
GetFileLinkListPath	C or N
GetGenericFilelinkEntry	C or N
GetNumberOfFilelinkEntries	C or N
GetSpecificSpecificEntry	C or N
NewFilelinkEntry	C or N
SetFilelinkEntry	C or N

**6.1.32 Service X\_AVM-DE\_USPController**

Action	User Rights
AddUSPContoller	C
DeleteUSPControllerByIndex	C
GetInfo	C or A or P or N or H
GetUSPControllerByIndex	C
GetUSPContollerNumberOfEntries	C
GetUSPMyFRITZEnable	C or A
SetUSPControllerEnableByIndex	C
SetUSPMyFRITZEnable	C or A or P or N or H

**6.1.33 Service X\_AVM-DE\_Auth**

Action	User Rights
GetInfo	C or A or P or N or H
GetState	C or A or P or N or H
SetConfig	C or A or P or N or H

**6.1.34 Service X\_AVM-DE\_HostFilter**

Action	User Rights
DisallowWANAccessByIP	C or A
MarkTicket	C or A
GetTicketIDStatus	C or A
DiscardAllTickets	C or A
GetWANAccessByIP	C or A

**6.1.35 Service X\_AVM-DE\_Media**

Action	User Rights
GetDVBCEnable	-
GetInfo	-
GetSearchProgress	-
SetDVBCEnable	C or A
StationSearch	C or A

**6.1.36 Service X\_AVM-DE\_WANMobileConnection**

Action	User Rights
GetAccessTechnology	C or A
GetBandCapabilities	C or A
GetEnabledBandCapabilities	C or A
GetInfo	C or A
GetInfoEx	C or A
GetPreferredAccessTechnology	C or A
SetAccessTechnology	C or A
SetEnabledBandCapabilities	C or A
SetPIN	C or A
SetPreferredAccessTechnology	C or A
SetPUK	C or A

## 7 State Variables

The vendor specific state variables with the format X\_<VENDOR>\_StateVariable use the following string for compatibility reasons.

AVM-DE

e.g. X\_AVM-DE\_Password

This string is not conform to the UPnP specification [UPNP11], that does not allow a – in the name of a state variable.

### 7.1 Compatibility with clients

At least one client has compatibility problems with these names of state variables.

Herqq UPnP <http://www.herqq.org>

## 8 Support for Multiple Clients and Parallel Access

There are two features that support parallel access of multiple TR-064 clients to one TR-064 service.

The first feature is the usage of transactions which is described in chapter 9 Transactions and the second feature are multiple internal session IDs.

These internal session IDs are used as parameters for URL access. The action GetCallList () returns such an URL for example.

## 9 Transactions

To support TR-064 access for several clients in parallel the [TR064] specification recommends the usage of transactions.

The description of the transactions is described in the chapter 6.3 Transactional Approach and in the chapter 6.5.2 DeviceConfig in [TR064] .

Some message examples can be found on the page 87 and following pages.

### 9.1 Usage of Transactions

Transactions cover the execution of SOAP actions without interruption by other TR-064 clients.

To begin a transaction the SOAP action DeviceConfig::ConfigurationStarted has to be used.

To end a transaction the SOAP action DeviceConfig::ConfigurationFinished has to be used.

The following sequence of SOAP actions is recommended for the communication with the AVM TR-064 service.

1. DeviceConfig::X\_GenerateUUID
2. DeviceConfig::ConfigurationStarted
3. One or more SOAP actions to be protected against parallel access.
4. DeviceConfig::ConfigurationFinished

A transaction permits to successfully execute SOAP actions for its duration.

A transaction times out 45 seconds after DeviceConfig::ConfigurationStarted was called, if the client does not call DeviceConfig::ConfigurationFinished to handle connection loss between TR-064 client and server and similar failures.

## 10 Examples

The following examples show unencrypted communication between a TR-064 enabled CPE and a TR-064 application.

### 10.1 SSDP request from application

Multicast HTTP message from application.

```
M-SEARCH * HTTP/1.1
HOST: 239.255.255.250:1900
MAN: "ssdp:discover"
MX: 5
ST: urn:dslforum-org:device:InternetGatewayDevice:1
```

### 10.2 SSDP response from CPE

Unicast HTTP response message from CPE to application.

```
HTTP/1.1 200 OK
LOCATION: http://192.168.178.1:49000/tr64desc.xml
SERVER: FRITZBOX UPnP/1.0 AVM FRITZ!Box Fon WLAN 7270 v3 74.04.85
CACHE-CONTROL: max-age=1800
EXT:
ST: urn:dslforum-org:device:InternetGatewayDevice:1
USN: uuid:739f2409-bccb-40e7-8e6c-0024FE6E00C3::urn:dslforum-
org:device:InternetGatewayDevice:1
```

### 10.3 Service description request from application

Unicast HTTP GET request message from application to CPE using values of SSDP discovery response message LOCATION header.

```
GET /tr64desc.xml HTTP/1.1
HOST: 192.168.178.1:49000
CONNECTION: Close
USER-AGENT: AVM UPnP/1.0 Client 1.0
```

### 10.4 Service description response from CPE

Unicast HTTP response message (trimmed) from CPE to application.

```
HTTP/1.0 200 OK
Content-Length: 10327
Content-Type: text/xml
Date: Thu, 17 Jun 2010 11:35:47 GMT
Last-Modified: Thu, 17 Jun 2010 10:33:08 GMT
Mime-Version: 1.0
```

```
<?xml version="1.0"?>
<root xmlns="urn:dslforum-org:device-1-0">
  <specVersion>
    <major>1</major>
    <minor>0</minor>
  </specVersion>
  <device>

<deviceType>urn:dslforum-org:device:InternetGatewayDevice:1</deviceType>
  <friendlyName>FRITZBOX UPnP/1.0 AVM FRITZ!Box Fon WLAN 7270 v3
74.04.85</friendlyName>
  <manufacturer>AVM</manufacturer>
  <manufacturerURL>www.avm.de</manufacturerURL>
  <modelDescription>FRITZ!Box Fon WLAN 7270 v3</modelDescription>
  <modelName>FRITZ!Box Fon WLAN 7270 v3</modelName>
  <modelNumber> - avm</modelNumber>
  <modelURL>www.avm.de</modelURL>
  <UDN>uuid:739f2409-bccb-40e7-8e6c-0024FE6E00C3</UDN>
  <iconList>
    <icon>
      <mimetype>image/gif</mimetype>
      <width>118</width>
      <height>119</height>
      <depth>8</depth>
      <url>/ligd.gif</url>
    </icon>
  </iconList>
  <serviceList>
    <service>
      <serviceType>urn:dslforum-org:service:DeviceInfo:1</serviceType>
      <serviceId>urn:DeviceInfo-com:serviceId:DeviceInfo1</serviceId>
      <controlURL>/upnp/control/deviceinfo</controlURL>
      <eventSubURL>/upnp/control/deviceinfo</eventSubURL>
      <SCPDURL>/deviceinfoSCPD.xml</SCPDURL>
    </service>
```

```

...
</serviceList>
<deviceList>
  <device>
    <deviceType>urn:dslforum-org:device:LANDevice:1</deviceType>
    <friendlyName>LANDevice - FRITZ!Box Fon WLAN 7270 v3</friendlyName>
    <manufacturer>AVM</manufacturer>
    <manufacturerURL>www.avm.de</manufacturerURL>
    <modelDescription>LANDevice - FRITZ!Box Fon WLAN 7270
v3</modelDescription>
    <modelName>LANDevice - FRITZ!Box Fon WLAN 7270 v3</modelName>
    <modelName> - avm</modelName>
    <modelURL>www.avm.de</modelURL>
    <UDN>uuid:75802409-bccb-40e7-8e6b-0024FE6E00C3</UDN>
    <UPC>AVM TR-064</UPC>
    <serviceList>
      <service>

<serviceType>urn:dslforum-org:service:WLANConfiguration:1</serviceType>
      <serviceId>urn:WLANConfiguration-com:serviceId:WLANConfiguration1</
serviceId>
      <controlURL>/upnp/control/wlanconfig1</controlURL>
      <eventSubURL>/upnp/control/wlanconfig1</eventSubURL>
      <SCPDURL>/wlanconfigSCPD.xml</SCPDURL>
    </service>
    ...
  </serviceList>
</device>
...
</deviceList>
<presentationURL>http://fritz.box</presentationURL>
</device>
</root>

```

### 10.5 SOAP Request with Action GetSecurityPort

Unicast SOAP message from application to CPE using values from SCPD description file and SSDP discovery response message.

POST /upnp/control/deviceinfo HTTP/1.1

HOST: 192.168.178.1:49000

CONTENT-LENGTH: 267

CONTENT-TYPE: text/xml; charset="utf-8"

SOAPACTION: "urn:dslforum-org:service:DeviceInfo:1#GetSecurityPort"

USER-AGENT: AVM UPnP/1.0 Client 1.0

```

<?xml version="1.0"?>
<s:Envelope xmlns:s="http://schemas.xmlsoap.org/soap/envelope/"
s:encodingStyle="http://schemas.xmlsoap.org/soap/encoding/">
  <s:Body><u:GetSecurityPort xmlns:u="urn:dslforum-
org:service:DeviceInfo:1"></u:GetSecurityPort>
  </s:Body>
</s:Envelope>

```

## 10.6 SOAP Response for Action GetSecurityPort

Unicast SOAP message from CPE to application.

HTTP/1.1 200 OK

DATE: Thu, 17 Jun 2010 11:53:59 GMT

SERVER: FRITZBOX UPnP/1.0 AVM FRITZ!Box Fon WLAN 7270 v3 74.04.85

CONNECTION: keep-alive

CONTENT-LENGTH: 324

CONTENT-TYPE: text/xml; charset="utf-8"

EXT:

```
<?xml version="1.0"?>
<s:Envelope xmlns:s="http://schemas.xmlsoap.org/soap/envelope/"
s:encodingStyle="http://schemas.xmlsoap.org/soap/encoding/"><s:Body>
<u:GetSecurityPortResponse xmlns:u="urn:dslforum-
org:service:DeviceInfo:1">
<NewSecurityPort>49443</NewSecurityPort>
</u:GetSecurityPortResponse>
</s:Body> </s:Envelope>
```



## 10.7 Content Level Authentication

The used values are listed below.

Variable	Value	Remark
Username	admin	
Password	gurkensalat	
Realm	F!Box SOAP-Auth	Not writeable.
Nonce	F758BE72FB999CEA	
Auth	b4f67585f22b0af7c4615db5a18faa14	
Nonce (next value)	0B9813494DD27C93	

### 10.7.1 Initial Client Request

```
<?xml version="1.0" encoding="utf-8"?>
<s:Envelope s:encodingStyle="http://schemas.xmlsoap.org/soap/encoding/"
xmlns:s="http://schemas.xmlsoap.org/soap/envelope/" >
  <s:Header>
    <h:InitChallenge
      xmlns:h="http://soap-authentication.org/digest/2001/10/"
      s:mustUnderstand="1">
      <UserID>admin</UserID>
    </h:InitChallenge >
  </s:Header>
  <s:Body>
    <u:GetHostNumberOfEntries xmlns:u="urn:dslforum-org:service:Hosts:1">
    </u:GetHostNumberOfEntries>
  </s:Body>
</s:Envelope>
```

### 10.7.2 Server Response to Initial Client Request

```
<?xml version="1.0" encoding="utf-8"?>
<s:Envelope s:encodingStyle="http://schemas.xmlsoap.org/soap/encoding/"
xmlns:s="http://schemas.xmlsoap.org/soap/envelope/" >
  <s:Header>
    <h:Challenge
      xmlns:h="http://soap-authentication.org/digest/2001/10/"
      s:mustUnderstand="1">
      <Status>Unauthenticated</Status>
      <Nonce>F758BE72FB999CEA</Nonce>
      <Realm>F!Box SOAP-Auth</Realm>
    </h:Challenge>
  </s:Header>
  <s:Body>
    <s:Fault>
      <errorCode>503</errorCode>
      <errorDescription>Auth. failed</errorDescription>
    </s:Fault>
  </s:Body>
</s:Envelope>
```

### 10.7.3 Client Request with Authentication

```
<?xml version="1.0" encoding="utf-8"?>
<s:Envelope s:encodingStyle="http://schemas.xmlsoap.org/soap/encoding/"
xmlns:s="http://schemas.xmlsoap.org/soap/envelope/" >
  <s:Header>
    <h:ClientAuth
      xmlns:h="http://soap-authentication.org/digest/2001/10/"
      s:mustUnderstand="1">
      <Nonce>F758BE72FB999CEA</Nonce>
      <Auth>b4f67585f22b0af7c4615db5a18faa14</Auth>
      <UserID>admin</UserID>
      <Realm>F!Box SOAP-Auth</Realm>
    </h:ClientAuth>
  </s:Header>
  <s:Body>
    <u:GetHostNumberOfEntries xmlns:u="urn:dslforum-org:service:Hosts:1">
    </u:GetHostNumberOfEntries>
  </s:Body>
</s:Envelope>
```

### 10.7.4 Server Response for successful Authentication

```
<?xml version="1.0" encoding="utf-8"?>
<s:Envelope s:encodingStyle="http://schemas.xmlsoap.org/soap/encoding/"
xmlns:s="http://schemas.xmlsoap.org/soap/envelope/" >
  <s:Header>
    <h:NextChallenge
      xmlns:h="http://soap-authentication.org/digest/2001/10/"
      s:mustUnderstand="1">
      <Status>Authenticated</Status>
      <Nonce>0B9813494DD27C93</Nonce>
      <Realm>F!Box SOAP-Auth</Realm>
    </h:NextChallenge>
  </s:Header>
  <s:Body>
    <u:GetHostNumberOfEntriesResponse
      xmlns:u="urn:dslforum-org:service:Hosts:1">
      <HostNumberOfEntries>42</HostNumberOfEntries>
    </u:GetHostNumberOfEntriesResponse>
  </s:Body>
</s:Envelope>
```

## **11 Appendix**

### ***11.1 References***

TR064: DSL Forum, LAN-Side DSL CPE Configuration, 2004

SOAPAUTH01: Robert Cunnings, Rich Salz, SOAP Extensions: Basic and Digest Authentication draft-cunnings-salz-soap-auth-00.txt, 2001,

<https://datatracker.ietf.org/doc/html/draft-cunnings-salz-soap-auth-00>

UPNP11: UPnP Forum, UPnP Device Architecture version 1.1, 2008