

C5 Series Stainless Steel Photoelectric Sensors



M5 (5 mm) stainless steel - DC

- 14 models available
- Diffuse and through-beam styles
- Long operating distances
- Compact stainless steel housing
- Scratch resistant and easy to clean glass lens
- Axial cable or M8 quick-disconnect models
- Complete overload protection
- IP67 rated



C5 Series M5 Photoelectric Sensors Selection Chart									
Part Number		Price	Sensing Range	Output State	Logic	Connection	Wiring	Dimensions	Characteristic Curves
Diffuse									
C5D-AN-1A		<--->	50mm (1.97in) ¹	N.O.	NPN	2m (6.5') axial cable	Diagram 1	Figure 1	Chart 1
C5D-AP-1A		<--->			PNP	2m (6.5') axial cable	Diagram 2	Figure 1	Chart 1
C5D-AN-1F		<--->			NPN	M8 (8mm) connector	Diagram 1	Figure 2	Chart 1
C5D-AP-1F		<--->			PNP	M8 (8mm) connector	Diagram 2	Figure 2	Chart 1
C5D-AN-2A		<--->	10mm (0.40in)		NPN	2m (6.5') axial cable	Diagram 1	Figure 1	Chart 3
C5D-AP-2A		<--->			PNP	2m (6.5') axial cable	Diagram 2	Figure 1	Chart 3
C5D-AN-3A		<--->	20mm (0.79in) ¹		NPN	2m (6.5') axial cable	Diagram 1	Figure 1	Chart 4
C5D-AP-3A		<--->			PNP	2m (6.5') axial cable	Diagram 2	Figure 1	Chart 4
Through-beam*									
C5R-AN-1A	Receiver	<--->	250mm (9.84in)	N.O.	NPN	2m (6.5') axial cable	Diagram 1	Figure 1	Chart 2
C5R-AP-1A	Receiver	<--->			PNP	2m (6.5') axial cable	Diagram 2	Figure 1	Chart 2
C5R-AN-1F	Receiver	<--->			NPN	M8 (8mm) connector	Diagram 1	Figure 2	Chart 2
C5R-AP-1F	Receiver	<--->			PNP	M8 (8mm) connector	Diagram 2	Figure 2	Chart 2
C5E-ON-1A	Emitter	<--->		Receiver dependent	Receiver dependent	2m (6.5') axial cable	Diagram 3	Figure 1	Chart 2
C5E-ON-1F	Emitter	<--->				M8 (8mm) connector	Diagram 3	Figure 2	Chart 2
¹ With 100x100mm white matte paper									

¹ With 100x100mm white matte paper

*Purchase one receiver and one emitter for a complete set.

Wiring diagrams

Diagram 1

NPN output




Diagram 2

PNP output





Diagram 3


Emitter



Emitter test input (<4V: OFF/ >8V or open: ON) 0.5mA

Connector

M8 Connector



Warning: These products are not safety sensors and are not suitable for use in personal safety applications.

Switching Element Function

	Thru-beam and Reflective Models	Diffuse Reflective Models
Light on	N.C.	N.O.
Dark on	N.O.	N.C.