SIA CODES 03-29-05

CODE	DESCRIPTION	CODE	DESCRIPTION	CODE	DESCRIPTION	CODE	DESCRIPTION	CODE	DESCRIPTION
AN	ANALOG RESTORAL	EA	EXIT ALARM	KT	HEAT TROUBLE	RN	REMOTE RESET	XJ	RF RCVR TAMPER RST
AR	AC RESTORAL	EE	EXIT_ERROR	KU	HEAT UNBYPASS	RO	RELAY OPEN	XL	LOW RF SIGNAL
AS	ANALOG SERVICE	ER	EXPANSION RESTORAL	L_	LISTEN IN + SECONDS	RP	AUTOMATIC TEST	XM	MISSING ALRM-X POINT
AT	AC TROUBLE	ET	EXPANSION TROUBLE	LB	LOCAL PROG. BEGIN	RR	RESTORE POWER	XQ	RF INTERFERENCE
BA	BURGLARY ALARM	EX	EXTRNL DEVICE STATE	LD	LOCAL PROG. DENIED	RS	REMOTE PROG. SUCCESS	XR	TRANS. BAT. RESTORAL
BB	BURGLARY BYPASS	EZ	MISSING ALARM-EXT ER	LE	LISTEN IN ENDED	RT	DATA LOST	XS	RF RECEIVER TAMPER
BC	BURGLARY CANCEL	FA	FIRE ALARM	LF	LISTEN IN BEGIN	RU	REMOTE PROG. FAIL	XT	TRANS. BAT. TROUBLE
BD	SWINGER TROUBLE	FB	FIRE BYPASS	LR	PHONE LINE RESTORAL	RX	MANUAL TEST	XW	FORCED POINT
BE	SWINGER TRBL RESTORE	FC	FIRE CANCEL	LS	LOCAL PROG. SUCCESS	RY	TEST OFF NORMAL	XX	FAIL TO TEST
BH	BURG ALARM RESTORE	FH	FIRE ALARM RESTORE	LT	PHONE LINE TROUBLE	SA	SPRINKLER ALARM	YA	BELL FAULT
BJ	BURG TROUBLE RESTORE	FI	FIRE TEST BEGIN	LU	LOCAL PROG. FAIL	SB	SPRINKLER BYPASS	YB	BUSY SECONDS
BM	BURG ALARM CROSS PNT	FJ	FIRE TROUBLE RESTORE	LX	LOCAL PROG. ENDED	SH	SPRKLR ALARM RESTORE	YC	COMMUNICATIONS FAIL
BR	BURGLARY RESTORAL	FK	FIRE TEST END	MA	MEDICAL ALARM	SJ	SPRKLR TRBL RESTORE	YD	RCV LINECARD TROUBLE
BS	BURGLARY SUPERVISORY	FM	FIRE ALARM CROSS PNT	MB	MEDICAL BYPASS	SR	SPRINKLER RESTORAL	YE	RCV LINECARD RESTORE
BT	BURGLARY TROUBLE	FR	FIRE RESTORAL	MH	MEDIC ALARM RESTORE	SS	SPRINKLER SUPERVISRY	YF	PARA CHECKSUM FAIL
BU	BURGLARY UNBYPASS	FS	FIRE SUPERVISORY	MJ	MEDICAL TRBL RESTORE	ST	SPRINKLER TROUBLE	YG	PARAMETER CHANGED
BV	BURGLARY VERIFIED	FT	FIRE TROUBLE	MR	MEDICAL RESTORAL	SU	SPRINKLER UNBYPASS	YH	BELL RESTORED
BX	BURGLARY TEST	FU	FIRE UNBYPASS	MS	MEDICAL SUPERVISORY	TA	TAMPER ALARM	YI	OVERCURRENT TROUBLE
BZ	MISSING SUPERVISION	FX	FIRE TEST	MT	MEDICAL TROUBLE	TB	TAMPER BYPASS	YJ	OVERCURRENT RESTORE
CA	AUTOMATIC CLOSING	FY	MISSING FIRE TROUBLE	MU	MEDICAL UNBYPASS	TC	ALL POINTS TESTED	YK	COMM. RESTORAL
CD	CLOSING DELINQUENT	FZ	MISSING FIRE SPRV	NA	NO ACTIVITY	TE	TEST END	YM	SYSTEM BATT MISSING
CE	CLOSING EXTEND	GA	GAS ALARM	NC	NETWORK CONDITION	TH	TAMPER ALRM RESTORE	YN	INVALID REPORT
CF	FORCED CLOSING	GB	GAS BYPASS	NF	FORCED PERIMETER ARM	TJ	TAMPER TRBL RESTORE	YO	UNKNOWN MESSAGE
CG	CLOSE AREA	GH	GAS ALARM RESTORE	NL	PERIMETER ARMED	TP	WALK TEST POINT	YP	PWR SUPPLY TROUBLE
CI	FAIL TO CLOSE	GJ	GAS TROUBLE RESTORE	NR	NETWORK RESTORAL	TR	TAMPER RESTORAL	YQ	PWR SUPPLY RESTORE
CJ	LATE CLOSE	GR	GAS RESTORAL	NS	ACTIVITY RESUMED	TS	TEST START	YR	SYSTEM BAT. RESTORAL
CK	EARLY CLOSE	GS	GAS SUPERVISORY	NT	NETWORK FAILURE	TT	TAMPER TROUBLE	YS	COMMUNICATIONS TRBL
CL	CLOSING REPORT	GT	GAS TROUBLE	OA	AUTOMATIC OPENING	TU	TAMPER UNBYPASS	YT	SYSTEM BAT. TROUBLE
CM	MISSING AL-RECNT CLS	GU	GAS UNBYPASS	OC	CANCEL REPORT	TX	TEST REPORT	YW	WATCHDOG RESET
CP	AUTOMATIC CLOSING	GX	GAS TEST	OG	OPEN AREA	UA	UNTYPED ZONE ALARM	YX	SERVICE REQUIRED
CR	RECENT CLOSING	HA	HOLDUP ALARM	OH	EARLY TO OPN FROM AL	UB	UNTYPED ZONE BYPASS	YY	STATUS REPORT
CS	CLOSE KEY SWITCH	HB	HOLDUP BYPASS	OI	FAIL TO OPEN	UH	UNTYPD ALARM RESTORE	YZ	SERVICE COMPLETED
CT	LATE TO OPEN	HH	HOLDUP ALARM RESTORE	OJ	LATE OPEN	UJ	UNTYPED TRBL RESTORE	ZA	FREEZE ALARM
CW	WAS FORCE ARMED	HJ	HOLDUP TRBL RESTORE	OK	EARLY OPEN	UR	UNTYPED ZONE RESTORE	ZB	FREEZE BYPASS
CZ	POINT CLOSING	HR	HOLDUP RESTORAL	OL	LATE TO OPEN FROM AL	US	UNTYPED ZONE SUPRVRY	ZH	FREEZE ALARM RESTORE
DA	CARD ASSIGNED	HS	HOLDUP SUPERVISORY	OP	OPENING REPORT	UT	UNTYPED ZONE TROUBLE	ZJ	FREEZE TRBL RESTORE
DB	CARD DELETED	HT	HOLDUP TROUBLE	OR	DISARM FROM ALARM	UU	UNTYPED ZONE UNBYPSS	ZR	FREEZE RESTORAL
DC	ACCESS CLOSED	HU	HOLDUP UNBYPASS	OS	OPEN KEY SWITCH	UX	UNDEFINED ALARM	ZS	FREEZE SUPERVISORY
DD	ACCESS DENIED	IA	EQPMT FAIL CONDITION	OT	LATE TO CLOSE	UY	UNTYPED MISSING TRBL	ZT	FREEZE TROUBLE
DE	REQUEST TO ENTER	IR	EQPMT FAIL RESTORE	OZ	POINT OPENING	UZ	UNTYPED MISSING ALRM	ZU	FREEZE UNBYPASS
DF	DOOR FORCED	JA	USER CODE TAMPER	PA	PANIC ALARM	VI	PRINTER PAPER IN		
DG	ACCESS GRANTED	JD	DATE CHANGED	PB	PANIC BYPASS	VO	PRINTER PAPER OUT		
DH	DOOR LEFT OPEN-RSTRL	JH	HOLIDAY CHANGED	PH	PANIC ALARM RESTORE	VR	PRINTER RESTORE		
DJ	DOOR FORCED-TROUBLE	JK	LATCHKEY ALERT	PJ	PANIC TRBL RESTORE	VT	PRINTER TROUBLE		
DK	ACCESS LOCKOUT	JL	LOG THRESHOLD	PR	PANIC RESTORAL	VX	PRINTER TEST		
DL	DOOR LEFT OPEN-ALARM	JO	LOG OVERFLOW	PS	PANIC SUPERVISORY	VY	PRINTER ONLINE		
DM	DOOR LEFT OPEN-TRBL	JP	USER ON PREMISES	PT	PANIC TROUBLE	VZ	PRINTER OFFLINE		
DN	DOOR LEFT OPEN	JR	SCHEDULE EXECUTED	PU	PANIC UNBYPASS	WA	WATER ALARM		
DO	ACCESS OPEN	JS	SCHEDULE CHANGED	QA	EMERGENCY ALARM	WB	WATER BYPASS		
DP	ACCESS DENIED-BAD TM	JT	TIME CHANGED	QB	EMERGENCY BYPASS	WH	WATER ALARM RESTORE		
DQ	ACCESS DENIED-UN ARM	JV	USER CODE CHANGED	QH	EMRGCY ALARM RESTORE	WJ	WATER TRBL RESTORE		
DR	DOOR RESTORAL	JX	USER CODE DELETED	QJ	EMRGCY TRBL RESTORE	WR	WATER RESTORAL		
DS	DOOR STATION	JY	USER CODE ADDED	QR	EMERGENCY RESTORAL	WS	WATER SUPERVISORY		
DT	ACCESS TROUBLE	JZ	USER LEVEL SET	QS	EMRGCY SUPERVISORY	WT	WATER TROUBLE		
DU	DEALER ID#	KA	HEAT ALARM	QT	EMERGENCY TROUBLE	WU	WATER UNBYPASS		
DV	ACCESS DENIED-UN ENT	KB	HEAT BYPASS	QU	EMERGENCY UNBYPASS	XA	EXTRA ACCNT REPORT		
DW	ACCESS DENIED-INTRLK	KH	HEAT ALARM RESTORE	RA	RMOTE PROG CALL FAIL	XE	EXTRA POINT		
DX	REQUEST TO EXIT	KJ	HEAT TROUBLE RESTORE	RB	REMOTE PROG. BEGIN	XF	EXTRA RF POINT		
DY	DOOR LOCKED	KR	HEAT RESTORAL	RC	RELAY CLOSE	XH	RF INTERFERENCE RST		
DZ	ACCESS CLOSED STATE	KS	HEAT SUPERVISORY	RD	REMOTE PROG. DENIED	XI	SENSOR RESET		