



MGMT VPN & UTM (1800F)

CSPRJTASK0017297

Jaimie Prinse
11-6-2026

1 Contents

2	Preparation.....	2
2.1	Objective	2
2.2	Scope.....	2
2.3	Planning	2
2.4	Risk & Impact	3
3	Implementation.....	4
3.1.1	Required steps	4
3.1.2	VPN	4
3.1.3	Policies & UTM.....	5
3.1.4	Routing	6
3.1.5	Testing	6
4	Estimated time	7
5	Annex 1 – General Terms and Conditions	Fout! Bladwijzer niet gedefinieerd.

2 Preparation

2.1 Objective

This change will migrate 2 Axians management VPN's from their current 500E cluster to the new 1800F cluster. The approach is to create 2 new management VPN tunnels on the 1800F, update the relevant routing and firewall policies to ensure uninterrupted management access. Once the new VPNs have been successfully tested and verified, the old VPN tunnels on the 500E firewall will be decommissioned.

2.2 Scope

- Creating new management VPN tunnels on the target firewall (BOEMAA-DC-CL, 1800F).
 - For MGMT and Staging
- Creating UTM profiles & groups
- Updating routing & policy configuration to allow management/staging traffic.
- Enable UTM profiles on 1800F policies, and disable UTM on 500E policies
- Testing management/staging functionality.
- Disable the VPN tunnels and related routes/policies on the source firewall (Boels_Datacenter, 500E).

2.3 Planning

The date and time of execution for this change are shown in the table below:

Components	Date	Time	Remote/On-site	Type	Cluster
Boels-Datacenter(500E)	TBD	TBD	Remote		✓
Boels-DC-CL(1800F)	TBD	TBD	Remote		✓

2.4 Risk & Impact

There is always a risk that a problem may occur after loading new firmware.

Risk: probability (**low**) × impact (**high**).

Risiko & Impact			
Probability	☒	1	(almost) Impossible
<i>Is there a reasonable chance that something could go wrong?</i>	☐	2	Unlikely, but possible
	☐	3	(very) Likely
Frequency	☒	1	(almost) Never
<i>How often does a similar change fail?</i>	☐	2	Sometimes
	☐	3	(almost) Always
Severity	☐	1	(almost) No effect
<i>What is the severity of the disruption if this change goes wrong?</i>	☒	2	Normal, manageable and solvable
	☐	3	High, P1 incident
Security Impact	☒	1	None/Low
<i>Does the change have an impact on the customer's security?</i>	☐	2	Medium
	☐	3	High
Description: New VPN configuration			

Impact:

This will only affect our management connection to the Boels environment. We have a alternate SSLVPN that provides us access to the devices we are changing, therefore we can always restore the original VPN & UTM configuration.

Risk of this change: **Low**

3 Implementation

3.1.1 Required steps

- Create new VPN tunnel configuration on 1800F and Axians MGMT firewalls (x2)
- Create firewall policies for necessary traffic
- Create static routing
- Test connectivity
 - o RADIUS login test
 - o Access to all mgmt. VIP's
 - FMG
 - FAZ
 - NAC nodes (x4)
 - Monitoring servers
 - RDS environment
 - Staging environment

3.1.2 VPN

VPN configuration will be copied from 500E to 1800F via Fortimanager.
Ip address the new VPN's will be using is: 45.14.0.4

VPN Ipsec configuration:

```
config vpn ipsec phase1-interface
  edit "Axians-Staging"
    set type dynamic
    set interface "vlink1001"
    set ike-version 2
    set peertype one
    set net-device disable
    set proposal aes256-sha256
    set localid "boels-dc-stg"
    set dpd on-idle
    set dhgrp 21
    set peerid "ax-cap-stg"
    set psksecret ENC
    set dpd-retrycount 5
  next
end

config vpn ipsec phase2-interface
  edit "Axians-Staging"
    set phaseiname "Axians-Staging"
    set proposal aes256-sha256
    set dhgrp 21
    set keylifeseconds 3600
  next
end

config vpn ipsec phase1-interface
  edit "Axians-Mgmt"
    set type dynamic
    set interface "vlink1001"
    set ike-version 2
    set peertype one
    set net-device disable
    set proposal aes256-sha256
    set localid "boels-dc"
    set dpd on-idle
    set dhgrp 21
    set peerid "ax-mgmt"
    set psksecret ENC
    set dpd-retrycount 5
  next
end

config vpn ipsec phase2-interface
  edit "Axians-Mgmt"
    set phaseiname "Axians-Mgmt"
    set proposal aes256-sha256
    set dhgrp 21
    set keylifeseconds 3600
  next
end
```

3.1.3 Policies & UTM

Corresponding policies have been created for the new ADOM, and prepared in the policy package for the 1800F.

UTM profiles and corresponding groups have been cloned to the new ADOM, and added to the policies in the policy package.

When the package is installed, the policies & UTM settings will be activated. Below a overview of the necessary policies.

Policy configuration:

axians-devtest-zone → axians-zone									
42	h_10.191.242.254	h_10.0.63.10 h_10.0.63.70	always	ALL	✓ ACCEPT	IPPool_172.30.47.202	✓ NAT	Standard	gutm-f-internal
axians-devtest-zone → dc-zone									
43	h_10.191.242.254	h_192.168.18.37	always	ALL ICMP UDP/18121	✓ ACCEPT		Disabled	Standard	gutm-f-internal
axians-zone → dc-zone									
7	all	axians-cmk02 axians-duo-monitoring	always	ALL	✓ ACCEPT		✓ NAT	Standard	utm-flow-internal-monitor
72	all	axians-automation-server axians-cmk02	always	ALL	✓ ACCEPT		✓ NAT	Standard	utm-flow-internal-monitor
16	all	axians-1800F axians-fortinac	always	ALL	✓ ACCEPT	Axians-Fortinac-Pool	✓ NAT	Standard	utm-flow-internal-monitor
73	all	axians-fortinac2	always	ALL	✓ ACCEPT	Axians-Fortinac-Pool	✓ NAT	Standard	utm-flow-internal-monitor
75	all	h_10.10.100.100 h_10.10.100.31	always	ALL	✓ ACCEPT		✓ NAT	Standard	utm-flow-internal-monitor
82	all	h_192.168.18.0/24 h_192.168.20.0/24	always	ALL	✓ ACCEPT		✓ NAT	Standard	utm-flow-internal-monitor
axians-zone → remote-loc-zone									
26	all	temp-vip-cradepoint	always	ALL	✓ ACCEPT		Disabled	Standard	no-inspection
10	all		always	ALL	✓ ACCEPT		Disabled	Standard	utm-flow-internal-monitor

UTM configuration:

Name	Security Profiles
gutm-f-internal	- AV gsp-av-f-dflt - IPS gsp-ips-dflt - SSL gcertificate-inspection - PRCT gdefault
utm-f-mobile-internal	- AV gsp-av-f-dflt - DNS gsp-dns-botnet - IPS gsp-ips-dflt - SSL gcertificate-inspection - PRCT gdefault
utm-flow-internal-monitor	- AV sp-av-flow-monitor - IPS gsp-ips-monitor - SSL certificate-inspection - PRCT gdefault
utm-flow-outgoing-monitor	- AV sp-av-monitor - APP gsp-ac-monitor - IPS gsp-ips-monitor - SSL certificate-inspection

3.1.4 Routing

Routing configuration:

```
config router static
edit 0
set dst 172.17.18.0 255.255.255.0
set device "axians-sec"
next
edit 0
set dst 10.0.63.10 255.255.255.255
set device "axians-sec"
next
edit 0
set dst 10.192.142.90 255.255.255.255
set device "axians-sec"
next
edit 0
set dst 10.0.63.70 255.255.255.255
set device "axians-sec"
next
edit 0
set dst 10.0.63.80 255.255.255.255
set device "axians-sec"
next
edit 0
set dst 100.80.82.251 255.255.255.255
set device "axians-sec"
next
edit 0
set dst 100.80.82.252 255.255.255.255
set device "axians-sec"
next
edit 0
set dst 100.66.0.251 255.255.255.255
set device "axians-sec"
next
edit 0
set dst 100.66.0.252 255.255.255.255
set device "axians-sec"
next
edit 0
set dst 100.72.61.0 255.255.255.0
set device "axians-oc"
next
edit 0
set dst 100.72.254.0 255.255.255.0
set device "axians-oc"
next
edit 0
set dst 100.82.78.0 255.255.255.0
set device "axians-oc"
next
end
```

3.1.5 Testing

Action	Who	Succesfull
Radius authentication test	Axians	☐
FMG connectivity test	Axians	☐
FAZ connectivity test	Axians	☐
NAC connectivity test	Axians	☐
Monitoring test (CMK & LM)	Axians	☐
RDS connectivity test	Axians	☐
Staging connectivity test	Axians	☐
Total time ca.	Axians	☐

11-6-2026 | CSPrJTASK0017297 | MGMT VPN & UTM (1800F)

Axians Rivium Boulevard 41, NL-2909 LK Capelle aan den IJssel
T +31 (0) 88 988 96 00, www.axians.nl

4 Estimated time

Action	Who	Time	Executed
Preliminary investigation	Axians	1:00	☒
Change coordination	Axians	1:00	☒
Draft Implementation plan & Risk analysis	Axians	1:00	☒
Implement configuration	Axians	2:00	☒
Test and troubleshoot configuration	Axians	1:00	☒
Total time ca.	Axians	6:00	☒

*Invoicing will be based on post-calculation and the actual hours worked, applying both to additional work and to any reduction in hours performed. The total time for this work will be allocated to the FG70G project.