

Comprehensive Technical & HR Interview Walkthrough

Master Question & Answer Runbook tailored for UAE Enterprise IT Support, Desktop Engineering, and Network Administration roles.

CCNA Certified (#CSCO15240575)
Location: Baniyas West, Abu Dhabi, UAE

+91 8113832017 |
athulkrishna.os.work@gmail.com
athulkrishna-it.netlify.app

PART 1: HR SCREENING & UAE IN-COUNTRY AVAILABILITY

Q1: 'Walk me through your background and technical experience.'

Optimal Answer: 'I am a CCNA-certified IT Support Engineer with over 4 years of hands-on technical experience across desktop troubleshooting, component-level laptop servicing, Cisco LAN/WLAN networking, CCTV security infrastructure, and PowerShell automation. At Grand Infotech, I managed daily IT service operations handling 30+ repair and support tickets per week while maintaining a sub-24-hour SLA resolution time. I also built automation tools like *Nexus Prime* which cut PC provisioning from 45 minutes down to 8 minutes, and *Helios Tracker* which automated WhatsApp customer notifications for 500+ service jobs. Most recently at Wings IT Solutions, I deployed 16-channel 4K IP CCTV surveillance grids and enterprise VPN routers. I am currently located here in Baniyas West, Abu Dhabi and am ready for immediate onboarding in Abu Dhabi or Dubai.'

■ WHAT RECRUITERS LOOK FOR

Recruiters look for: A crisp 60-90 second summary highlighting CCNA certification, quantifiable achievements (SLA <24h, 82% time reduction), and clear in-country availability in the UAE.

Q2: 'Why are you specifically targeting IT Support roles in the UAE?'

Optimal Answer: 'The UAE is a global technology and business hub characterized by rapid digital infrastructure expansion and world-class enterprise standards. I want to bring my combination of CCNA-certified networking, hardware bench diagnostics, and PowerShell automation to fast-paced corporate environments here. Having already arrived in Abu Dhabi, I have pre-aligned my technical portfolio, deployment playbooks, and certifications to UAE industry requirements and am fully prepared for immediate in-person technical interviews and on-site onboarding.'

Q3: 'What is your current visa status, availability to join, and salary expectations?'

Optimal Answer: 'I am currently residing in Baniyas West, Abu Dhabi on a valid Visit Visa with verified original credentials and my official CCNA certificate, and can join immediately without any notice period constraints (0 days notice). My visa allows for an immediate in-country employment visa issuance. Regarding salary, based on current UAE market standards for CCNA-certified IT Support Specialists with 4+ years of hands-on experience, I am targeting an all-inclusive range of AED 5,500 to AED 8,000 per month depending on the full compensation structure, medical insurance, and career growth prospects.'

■ UAE RECRUITER TIP

Salary Tip: Always quote an 'all-inclusive monthly figure in AED'. Mentioning zero notice period and immediate onboarding availability makes you 3x more attractive to UAE recruiters.

PART 2: CORE HARDWARE DIAGNOSTICS & DESKTOP SUPPORT (TIER 1 & 2)

Q4: 'A laptop power LED turns on, but there is no display and fans don't spin (No POST). How do you troubleshoot?'

Optimal Answer: 'I follow a structured physical-to-component triage methodology:'

- **Hard Reset & Power Drain:** Disconnect AC adapter, unplug internal battery connector, and hold power button for 30 seconds to discharge residual flea power from motherboard capacitors.
- **Memory & Slot Isolation:** Remove RAM sticks, clean gold contact pins using isopropyl alcohol, and test booting with a single verified RAM stick in Slot 1, then Slot 2.
- **CMOS / RTC Reset:** Disconnect the CMOS coin cell / RTC battery for 5 minutes to restore BIOS/UEFI settings to factory defaults.
- **Display & Motherboard Rails:** Connect to an external HDMI monitor to rule out a faulty LCD ribbon cable or bad panel. If still No POST, inspect motherboard DC-in power jack and primary 19V / 3.3V / 5V power rails using a digital multimeter to detect short circuits.'

Q5: 'How do you troubleshoot recurring Windows 11 BSOD crashes (e.g., CRITICAL_PROCESS_DIED or MEMORY_MANAGEMENT)?'

Optimal Answer: 'I isolate software corruption from hardware faults systematically.'

- **Crash Dump Analysis:** Inspect Minidump files (`C:\Windows\Minidump`) using WinDbg or BlueScreenView to identify the exact faulting driver (.sys) or kernel module.
- **OS Integrity Checks:** Boot into Safe Mode or Windows Terminal (Admin) and run DISM /Online /Cleanup-Image /RestoreHealth followed by sfc /scannow to repair damaged system binaries.
- **Hardware Memory & Storage Stress Testing:** Run Windows Memory Diagnostic or MemTest86 for RAM errors. Use CrystalDiskInfo / SMART diagnostics to check NVMe SSD health and bad sectors.
- **Clean Driver Rollback:** If triggered by recent updates, perform clean GPU/Chipset driver reinstallation using DDU (Display Driver Uninstaller) or rollback device drivers in Device Manager.'

Q6: 'What is your component-level servicing procedure for laptop thermal throttling and fan failure'

Optimal Answer: 'From my practical training at L-One Chip Level Solutions: I disassemble the chassis following manufacturer service manuals, disconnect the battery, and remove the copper heat pipe assembly. I clean off hardened factory thermal compound using 99% isopropyl alcohol and lint-free wipes. I clean out dust buildup from fan blades and radiator exhaust fins, lubricate bearings if applicable, and apply high-conductivity thermal paste (e.g. Arctic MX-4) using the pea method. I also replace degraded thermal pads on VRM MOSFETs and VRAM chips to prevent thermal throttling.'

PART 3: ENTERPRISE NETWORKING & CCNA INFRASTRUCTURE

Q7: 'A user workstation gets an IP of 169.254.45.12 and cannot access network shares or internet. What does this mean and how do you fix it'

Optimal Answer: 'An IP in the 169.254.0.0/16 range is an Automatic Private IP Addressing (APIPA) address, which indicates the client failed to reach a DHCP server.'

- **Step 1 (Physical & NIC):** Verify link status LEDs on NIC and wall jack. Run ncpa.cpl to confirm Ethernet adapter is enabled.
- **Step 2 (DHCP Lease Renewal):** Run ipconfig /release and ipconfig /renew in Command Prompt to attempt re-negotiating DORA (Discover, Offer, Request, Acknowledge).
- **Step 3 (VLAN & Port Check):** Log into the Cisco managed switch. Verify switchport status ('show ip int brief'), confirm port is in UP/UP state, and check VLAN assignment ('show mac address-table').
- **Step 4 (DHCP Scope Exhaustion / Relay):** Check the DHCP Server / Router to ensure the IP scope is not 100% exhausted and DHCP Relay ('ip helper-address') is operational across subnets.'

Q8: 'How do you design and configure VLANs on a Cisco switch to isolate Corporate, CCTV, and Guest Wi-Fi'

Optimal Answer: 'I implement logical segmentation at Layer 2 to improve security and contain broadcast domains:'

- **VLAN Creation:** Create VLAN 10 (Corporate Data - 192.168.10.0/24), VLAN 20 (IP CCTV - 192.168.20.0/24), and VLAN 30 (Guest Wi-Fi - 172.16.30.0/24).
- **Access Port Assignment:** Assign endpoint ports: switchport mode access and switchport access vlan 10 (or 20 for PoE camera ports).
- **Trunking:** Configure uplink ports connected to routers/firewalls as 802.1Q trunks: switchport mode trunk and switchport trunk allowed vlan 10,20,30.
- **Inter-VLAN Security:** Implement Router-on-a-Stick sub-interfaces or Layer 3 switch SVIs with Access Control Lists (ACLs) to block Guest Wi-Fi and CCTV traffic from accessing Corporate subnet resources.'

Q9: 'Walk me through your systematic 7-step OSI network troubleshooting workflow for "No Internet".'

Optimal Answer: 'I diagnose from Layer 1 upward:'

1. **Physical (L1):** Verify RJ45 cable click, patch cord continuity, and green link LED lights.
2. **Data Link (L2):** Run getmac / ncpa.cpl to ensure NIC is functional and negotiation speed is 1Gbps Full-Duplex.
3. **Network (L3):** Run ipconfig /all to check IP, Subnet Mask, and Gateway. Ping loopback ping 127.0.0.1 to test TCP/IP stack.
4. **Gateway Reachability:** Ping Default Gateway ping 192.168.1.1. If gateway responds, local LAN is intact.
5. **WAN / Internet Reachability:** Ping public IP ping 8.8.8.8 or 1.1.1.1 to test ISP WAN connectivity.
6. **DNS Resolution:** Run nslookup google.com. If public IP pings but domain fails, flush DNS (ipconfig /flushdns) or update DNS forwarders to 1.1.1.1 / 8.8.8.8.
7. **Application & Proxy (L7):** Check Windows Proxy settings (inetctl.cpl) and firewall rules blocking port 80/443.'

Q10: 'What is the difference between T568A and T568B structured cabling, and how do you verify a new Cat6 run'

Optimal Answer: 'T568A and T568B define the color-code pinouts for RJ45 connectors. In commercial enterprise networking, **T568B** is the dominant industry standard with the color order: **1: White-Orange, 2: Orange, 3: White-Green, 4: Blue, 5: White-Blue, 6: Green, 7: White-Brown, 8: Brown**. For straight-through patch cables, both ends use T568B. At Wings IT Solutions, I routed structured Cat6 cables through conduits, punched down keystone jacks on 24-port patch panels using punch-down impact tools, and certified every run using digital RJ45 cable continuity testers to check for open pairs, crossed wires, and split pairs before connecting to PoE switches.'

PART 4: ACTIVE DIRECTORY & SCRIPTED AUTOMATION

Q11: 'How do you domain-join a Windows 11 workstation and troubleshoot "Domain Controller cannot be contacted".'

Optimal Answer: 'To domain-join: First configure the client Ethernet adapter' ■ Primary DNS server to point directly to the Active Directory Domain Controller IP (not public 8.8.8.8 or router IP). Open sysdm.cpl, select Change, enter the Domain FQDN (e.g. corp.contoso.com), and provide Domain Administrator credentials. If DC cannot be contacted: 1) Verify DNS resolution using nslookup _ldap._tcp.dc._msdcs.corp.contoso.com; 2) Test ICMP and LDAP port 389 reachability via Test-NetConnection -ComputerName dc01 -Port 389; 3) Verify workstation time is synchronized within 5 minutes of the DC (Kerberos authentication requirement).'

Q12: 'Explain your custom automation tool Nexus Prime and its operational impact.'

Optimal Answer: 'At Grand Infotech, manual onboarding of new client machines took ~45 minutes per PC (installing Chrome, Office, PDF readers, drivers, and debloating Windows). I authored **Nexus Prime**, a modular PowerShell 7 automation suite orchestrating the Windows Package Manager (WinGet CLI). It executes silent unattended installations with parameters like --silent --accept-package-agreements --accept-source-agreements, applies registry optimizations to disable telemetry services, sets timezone and regional settings, and installs enterprise drivers. This slashed deployment time by 82%, from 45 minutes to under 8 minutes per PC across 100+ rollouts.'

■ COMPETITIVE EDGE

Interviewer Impression: Emphasizing PowerShell automation separates you from 95% of standard desktop technicians who only use manual GUI setups.

Q13: 'A user reports Outlook is stuck on "Disconnected" or continuously prompting for passwords. How do you resolve it.'

Optimal Answer: '1) Close Outlook and navigate to Windows Credential Manager ('control keymgr.dll') to clear cached user credentials under Generic Credentials. 2) Verify network connectivity, DNS resolution, and check user account status in Active Directory (ensure account is not locked out or expired). 3) Start Outlook in Safe Mode ('outlook.exe /safe') to isolate corrupt third-party add-ins. 4) If the mail profile is corrupt, create a new Outlook profile via Control Panel Mail ('control mlcfg32.cpl') and rebuild the mailbox OST file.'

PART 5: PHYSICAL INFRASTRUCTURE & IP CCTV SURVEILLANCE

Q14: 'How do you calculate storage and power requirements for a 16-channel 4K IP Camera CCTV deployment.'

Optimal Answer: 'At Wings IT Solutions, I performed standard capacity budgeting:'

- **Storage Calculation:** For 16x 4K (8MP) cameras at 15 FPS using H.265+ high-efficiency compression, each stream consumes ~4 Mbps bitrate. Daily total = 16 cameras * (4 Mbps / 8 * 3600 * 24) = ~691 GB/day. For 30 days of continuous recording, storage requirement = ~20.7 TB (configured with 4x 8TB Surveillance HDDs in RAID 5).
- **PoE Power Budgeting:** 16x PoE cameras consuming ~12W each require 192W total power. I specify a 24-port Gigabit PoE+ Switch (IEEE 802.3at) with at least a 250W–300W total power budget to prevent voltage drop and ensure camera IR night-vision stability.'

PART 6: BEHAVIORAL SCENARIOS & HIGH-PRESSURE SITUATIONS (STAR)

Q15: 'Tell me about a high-pressure IT emergency and how you handled it.'

STAR Response:

- **Situation:** An accounting client experienced complete network connectivity failure across 8 accounting terminals 3 hours before the VAT filing deadline.
- **Task:** Restore network access to the centralized database server immediately with zero data loss.
- **Action:** I arrived on-site within 20 minutes. I inspected the network switch rack and discovered a Layer 2 broadcast storm caused by a user plugging both ends of an Ethernet patch cable into two wall jacks. I immediately isolated and disconnected the looped port, verified spanning tree protocol (STP) state, restarted the local server database service, and verified end-to-end ping across all client terminals.
- **Result:** Full database access was restored within 15 minutes. The accounting team submitted all VAT filings on time with 100% data integrity.'

Q16: 'Describe your Helious Tracker project and how it improved service desk operations.'

STAR Response:

- **Situation:** At Grand Infotech, we handled 30+ hardware and software repair jobs weekly. Manual paper logs and phone calls caused customer follow-up delays averaging 4 hours, creating communication bottlenecks.
- **Task:** Digitize repair workflow tracking and automate real-time status updates to clients.
- **Action:** I developed **Helious Tracker**, an IT Service Operations web platform integrated with the WhatsApp Business API. When technicians updated ticket statuses (Diagnostics -> In Progress -> Ready for Pickup), the system dispatched automated WhatsApp notifications with invoice estimates and pickup pins directly to customers.
- **Result:** Completely eliminated paper logbooks across 500+ customer tickets, reduced customer inquiry response time from 4 hours to under 30 minutes, and maintained a 100% follow-up rate.'

PART 7: STRATEGIC QUESTIONS YOU SHOULD ASK THE INTERVIEWER

Asking sharp, informed questions at the end of the interview demonstrates initiative and professionalism:

1. 'What is the current setup of your Windows Server and Active Directory domain infrastructure, and are there plans for infrastructure upgrades this year•'
2. 'What ticketing system and remote monitoring/management (RMM) platform does your IT team currently utilize (e.g. ManageEngine, ServiceNow, Datto)•'
3. 'What are the primary technical milestones or deployment projects you would like the incoming IT Support Engineer to accomplish in the first 90 days•'

4+ Years Hands-on IT Experience	CCNA Certified Cisco ID: CSC015240575	500+ Tickets Sub-24h Resolution SLA	Nexus Prime 82% Setup Time Reduction	Immediate In Abu Dhabi, UAE
---	---	---	--	---------------------------------------