# MILITARY SPECIFICATION

## SIMULATOR, TARGET: 10558244

This Amendment forms a part of Military Specification MIL-S-50347(MU) dated 10 November 1969, and is approved for use by all Departments and Agencies of the Department of Defense.

TABLE I: Delete in its entirety and substitute new Table I, attached.

Paragraph 4.5.2.2: Item 2, Description: Delete "5Vdc ± 0.3" and substitute "6 Vdc ± 0.3."

Item 4, Description: Delete in its entirety and substitute: "positive pulse, 0 V to no less than 15 Vdc, 0.2 to 0.6 μsec pulse width at the 50% points, rise time of 40 nsec max. into 50 Ω as measured between 10% and 90% points, 20 kHz ± 10% PRF."

Item 5, Description: Add: "and have an adjustable delay from SYNC SIGNAL to OUTPUT SIGNAL 0 to 20 μsec MIN."

Paragraph 4.6.1.1: After 4.9.1.3 does not apply, add: "The frequency and amplitude limits of paragraph 3.3.1 of this specification shall be used."

Paragraph 4.6.1.4.2: Delete: "-40°F" and "4.6.2" and substitute: "+32°F" and "4.6.2.2."

Paragraph 4.6.3.1(b): Delete: "2 to 10 μsec with adjustment of R1" and substitute: "not more than 2 to not more than 16 μsec with the adjustment of R1."

Paragraph 4.6.3.1(e): Delete: "10 ± 1.0 μsec to 20 ± 1.0 μsec" and substitute: "not more than 11 to not more than 26 μsec."

Paragraph 4.6.3.1(h): Delete: "20 ± 1.0 μsec to 30 ± 1.0 μsec" and substitute: "not more than 19 to not more than 34 μsec."

Paragraph 4.6.3.2(b): Delete: "not less than 3 volts P-P in phase when R1 is CCW and out of phase when R1 is CW" and substitute: "not less than 3 volts P-P in phase when R1 is CW and out of phase when R1 is CCW."

CUSTODIAN:

Army - MU

PREPARING ACTIVITY:

Army - MU

Project No. 4931-A127

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T20:22Z
Check the source to verify that this is the current version before use.

TABLE I - INPUT AND OUTPUT CHARACTERISTICS

| REQUIREMENT | CHARACTERISTICS | TERMINALS |
|---|---|---|
| Input power | 6.0 ± 0.3 Vdc regulated, ac ripple not greater than 50 mV peak-to-peak 300 mA capacity. | P1-30, 31, 32(+) and P1-24, 25, 26 (Ret) |
| | 33 ± 1 Vdc, ac ripple not greater than 0.1V peak-to-peak, 10 mA capacity. | P1-5(-) P1-25 (Ret) |
| INPUT SIGNALS | | |
| Signal #1 | positive pulse from zero volts to not less than 15 Vdc, 0.2 to 0.6 µsec pulse width at the 50% points, rise time of 40 nsec max into 50 Ω as measured between 10% and 90% points, 20 kHz ± 10% PRF. | P1-19 and P1-18 (Ret) |
| Signal #2 | positive pulse from 0 V to 3.0 Vdc, 0.35 ± 0.05 µsec pulse width, delayed 15.0 ± 3 µsec after signal #1. | P1-20 and P1-22 (Ret) |
| OUTPUT SIGNALS | | |
| Simulated Target | 0.2 ± 0.1 µsec positive pulse from 0 V to not less than +3 Vdc, delayed 2 to not more than 34 µsec from Signal #1. Delay controlled by resistance between J1-42 and J1-47 and proper switching between J1-33 through J1-38. | P1-16 and P1-14 (Ret) |
| Sum Doppler | 2.5 kHz 10% square wave from 0 V to not less than +3 Vdc. | P1-9 and P1-10 (Ret) |
| Difference Doppler | 2.5 kHz 10% square wave, from 0 V to not less than + 3 Vdc out of phase with the sum doppler when simulated target appears before Signal #2. | P1-12 and P1-8 (Ret) |



Source: https://assist.dla.mil -- Downloaded: 2026-10-22T20:22Z
Check the source to verify that this is the current version before use.