MILITARY SPECIFICATION

COMPUTER SET, LOFT BOMB RELEASE AN/AJB-3

This specification has been approved by
the Naval Air Systems Command, Department of the Navy.

1. SCOPE

1.1 Scope - The equipment covered by this specification shall provide the functions of an all-attitude flight reference system plus a correlated loft bomb release system.

1.2 Classification - The AN/AJB-3 Loft Bomb Release Computer Set shall consist of the items listed in 6.8.

2. APPLICABLE DOCUMENTS

2.1 General - The documents listed in 6.10 of the issue in effect on the date of invitation for bids form a part of this specification to the extent specified herein.

3. REQUIREMENTS

*3.1 Preproduction - This specification makes provision for preproduction testing.

*3.2 Parts and Materials - In the selection of parts and materials, fulfillment of major design objectives shall be the prime consideration. In so doing the following shall govern:

(1) Microelectronic items shall conform to requirements specified herein.

(2) Other parts and materials requirements shall conform to Specification MIL-E-5400.

(3) Nonrepairable subassemblies, as outlined in Specification MIL-E-5400, shall be used when practicable. The general size of the subassembly and the amount of circuitry to be included therein shall be approved by the procuring activity. Nonrepairable subassemblies must be reliable. (See 6.4)

(4) When previously produced models of this equipment did not use nonrepairable subassemblies, the design shall not be changed to employ nonrepairable assemblies without the approval of the procuring activity.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

3.2.1 Nonstandard Parts and Materials Approval - Approval for the use of nonstandard parts and materials shall be obtained as outlined in Specification MIL-E-5400. Microelectronic Devices shall be approved as outlined in WR-98.

3.2.2 Microelectronic Modular Assemblies - When used, Microelectronic Modular Assemblies shall meet the requirements of WR-98.

3.2.3 Modules, Maintenance - The electronic portions of the equipment shall be divided into maintenance modules (see Specification MIL-S-23603). Maintenance modules shall normally be considered repairable.

3.2.4 Microelectronic Interchangeability - The interchangeability provisions of WR-98 shall govern microelectronic interchangeability.

3.3 Design and Construction - The equipment shall conform with all the applicable requirements of Specification MIL-E-5400 for design, construction and workmanship, except as otherwise specified herein.

*3.3.1 Total Weight - The total weight of the equipment, excluding cables, shall be a minimum consistent with good design and shall not exceed 66.5 pounds.

3.3.2 Reliability

*3.3.2.1 Operational Stability - The equipment shall operate with satisfactory performance, continuously or intermittently for a period of at least 20 hours without the necessity for readjustment of any controls which are inaccessible to the operator during normal use.

*3.3.2.2 Operating Life - The equipment shall have a total operating life of 5000 hours with reasonable servicing and replacement of parts. Parts requiring scheduled replacement shall be specified by the contractor.

*3.3.2.3 Reliability in Mean Time Between Failures (MTBF) - The equipment shall have 200 hours of mean (operating) time between failures when tested and accepted as outlined under the requirements of 4.4.3. The MTBF of individual items shall be as specified in 6.8.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.3.2.4 Time Totalizing Meter - The equipment shall contain time totalizing meters in accordance with Specification MIL-M-7793. Meters shall be included in the following units:

(1) Adapter-Compensator, Compass MX-2488A/AJB-3
(2) Amplifier-Power Supply AM-1931/AJB-3
(3) Gyroscope Assembly, Displacement CN-494A/AJB-3

3.3.3 Cabling and Connections

*3.3.3.1 Cables and Connectors - The equipment shall provide for the use of cables and connectors in accordance with Specification MIL-E-5400.

*3.3.3.2 Interconnection Cabling - The equipment shall be capable of satisfactory operation using external wiring in accordance with the applicable requirements of Specification MIL-W-5088. The external wiring shall be unshielded, except that a minimum number of the individual wires may be shielded when demonstrated as necessary to meet interference control requirements and provided the assembly of the cable to its plugs may be easily accomplished. External cables and that portion of the connectors attached to the cables shall not be supplied as part of the equipment.

*3.3.4 Interchangeability of Reordered Equipment - For reordered equipment, interchangeability shall exist between units and all replaceable assemblies, subassemblies, and parts of a designated model of any previously manufactured equipment, supplied or designated by the procuring activity.

*3.3.5 Interference Control - The generation of radio interference by the equipment and the vulnerability of the equipment to radio interference shall be controlled within the limits of Specification MIL-I-6181.

*3.3.6 Maintenance Provisions and Field Testing - Provisions for maintenance shall be as specified in Specification MIL-E-5400. Specific test points and test facilities shall be provided to the greatest extent practicable for ease of field testing and maintenance.

3.3.7 Nomenclature and Nameplates - Nomenclature assignment and nameplate approval for equipment identification shall be in accordance with Specification MIL-N-18307.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.3.8 Standard Conditions - The following conditions shall be used to establish normal performance characteristics under standard conditions and for making laboratory bench tests.

Temperature	Room ambient (25°C ±5°C)
Altitude	Normal Ground
Vibration	None
Humidity	Room ambient up to 90% relative humidity
Input Power Voltage	115 ±1.0V AC, 400 ±5 cps and 27.5 ±0.5V DC

3.3.9 Service Conditions - The equipment shall operate satisfactorily under any of the environmental service conditions or reasonable combination of these conditions as specified in Specification MIL-E-5400 for Class 2 equipment, except as modified herein:

*3.3.9.1 Vibration - Each item of the equipment shall operate satisfactorily when subjected to the vibration requirements of Curve III of Specification MIL-E-5400, except the following items which shall operate satisfactorily when subjected to vibration requirements specified.

Unit	Requirement
Indicator-Programmer ID-695A/AJB-3	Proc. V, MIL-E-5272
Controller, Compass System C-2499A/AJB-3	Proc. V, MIL-E-5272
Indicator, Attitude-Director ID-694/AJB-3	Proc. V, MIL-E-5272
Gyroscope Assembly, Displacement CN-494A/AJB-3	Curve II, MIL-E-5400

3.10 Warm-Up Time - The time required for the equipment to warm-up prior to operation shall be kept to a minimum and shall not exceed 1 minute under standard conditions and 5 minutes at extreme service conditions.

3.11 Primary Input Power Requirements - The equipment shall meet all applicable requirements of MIL-STD-704 and shall give specified performance from the following power sources with characteristics as defined in MIL-STD-704 having limits as specified therein. The power required shall not exceed the specified amounts.

(1) AC Power (Three Phase) 115/200V, Category "B", 200 VA

(2) DC Power 28V, Category "B", 1.5 Amps.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.3.11.1 Degraded Performance - Degraded performance will be permitted for voltage transients not exceeding 0.5 seconds during normal electric system operation. Operation shall return to normal with no resulting damage to the equipment.

*3.3.12 Dielectric Strength - The materials used and the design shall be such that the resistance between isolated circuits and between each circuit and the case or connector shall be at least 50 megohms when a potential of 500V DC is applied for a period of 10 seconds.

*3.3.13 Control Panels - All rack or console mounted control panels shall conform to the applicable requirements of Specification MIL-C-6781. The configuration of all control panels must be approved by the procuring activity prior to preproduction testing.

3.4 Performance - Unless otherwise specified, values set forth to establish the requirements for satisfactory performance apply to performance under both standard and extreme service conditions. When reduced performance under the extreme conditions is acceptable, tolerances or values setting forth acceptable variations from the performance under the standard conditions will be specified.

*3.4.1 Operation - The Loft Bomb Release Computer Set shall provide the functions of an all-attitude flight reference system plus a correlated loft bomb release system. When operating as an all-attitude flight reference system, the system shall provide a continuous display of aircraft attitude through 360 degrees in roll, pitch and azimuth.
Roll, pitch, and heading outputs shall also be provided for use by other systems.

The heading portion of the system shall have the following modes of operation:

(1) Slaved - providing gyro-stabilized heading referenced to magnetic north as established by the associated compass transmitter.

(2) Free - providing gyro-stabilized heading referenced to a grid system established by the operator.

When operating in the loft bomb release mode, the system shall provide an additional display to direct the pilot through the proper maneuver. The display shall include an indication of aircraft normal acceleration and an acceleration command to direct the pilot throught a pull-up maneuver to a 4g loop up to the point of bomb release. The system shall also provide a signal to produce an aural warning tone and a tone indicating start of the pull-up maneuver, provide a signal to initiate bomb release at a preselected pitch angle, and cancel the bomb maneuver if excessive aircraft yaw occurs.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

Means shall also be provided for the pilot to select the desired time delay between inititation of the bomb run and pull-up and to select either a preset low angle (less than 90°) or a preset high angle bomb release.

*3.4.1.1 Conditions - The system shall provide the performance specified when the components and associated equipment are interconnected and power is applied in accordance with Figure 1. Unless otherwise specified, the deviation compensation of the compass adapter shall be adjusted to compensate for heading errors and the roll and pitch trim of the attitude indicator shall be adjusted for zero trim.

*3.4.2 Erection and Synchronization - Within 88 seconds after initial application of power, the OFF flag in the attitude indicator shall disappear from view. Within 3.0 minutes after initial application of power, the pitch and roll indication shall be within ±2.0° of the position of the displacement gyroscope relative to local gravity vertical. Within 10 minutes after initial application of power and with the system operating in the SLAVED mode, the heading indication shall agree with the compass transmitter heading within ±3.5° and the needle of the SYNC IND on the controller shall be within $\frac{1}{4}$ of the arc from the center to the end of the scale.

*3.4.2.1 Erection Rates - With the spin axis of the vertical gyro deflected 10° from local gravity vertical in roll, the low erection rate in roll shall be 1.3 ±0.7 degrees per minute. With the spin axis of the vertical gyro deflected 20° from local gravity vertical in pitch, the low erection rate in pitch shall be 1.3 ±0.7 degrees per minute.

*3.4.3 Azimuth Operation - Operating the PUSH TO SYNC button when in the SLAVED mode shall cause the heading indication to synchronize to within ±4.0° of the compass transmitter heading. Within 5 seconds after the heading indication has stabilized, the needle of the SYNC IND meter shall be within 3/4 of the arc from the center to the end of the scale.

*3.4.3.1 Set Heading - With the system operating in the FREE mode, operation of the PUSH TO TURN control shall cause the heading indication to change at a rate approximately proportional to the degree of rotation of the control. Rotation to the right (R) shall cause the heading indication to increase and rotation to the left (L) shall cause the indication to decrease. When the PUSH TO TURN control is released, the heading indication shall stop changing.

*3.4.3.2 Slaving Rate - With the system in the SLAVED mode and a heading error of approximately 30°, the heading indication on the attitude indicator shall slave at a rate of 1 to 2 degrees per minute.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.4.4 Attitude Indication - The attitude indicator sphere shall follow displacement gyro rotation through 360° in roll, pitch and azimuth smoothly and shall not jump greater than 0.5° in any axis except at 90° climb and 90° dive, a larger jump or transient in roll is permissible.

*3.4.4.1 Servo Sensitivity - Perceptible movement of the attitude indicator sphere in the corresponding axis shall result from displacement gyro movements of ±0.5° about each axis.

*3.4.5 Yaw Rate Switching - Within 35 seconds after a turn rate of 15° per minute is applied to the rate switching gyro, the synchronizing function shall become disabled and roll erection voltage to the displacement gyro shall be removed. Within 20 seconds after the turn rate is reduced to zero, the synchronizing function and roll erection voltage shall be restored.

*3.4.6 Latitude Compensation - With the system in FREE mode, the TRIM and BIAS voltages in the compass adapter set to the value stenciled on the displacement gyro, and the LATITUDE setting on the controller set at the local latitude, the heading indication shall not change by more than 3° in one hour of operation.

*3.4.7 Bombing Functions

*3.4.7.1 Acceleration Display - The indicator of the indicator-programmer shall indicate constant accelerations from 1 to 5g applied along its longitudinal axis toward the bottom of the indicator within ± .15g.

*3.4.7.2 G Program - With the system externally connected for LOW ANGLE bomb mode and a bomb run initiated, the programmer shall move from the 1 g to the 4 g position smoothly within 1.8 to 2.2 seconds.

*3.4.7.3 Timed Low Angle Release - With the system externally connected for LOW ANGLE bomb mode, initiation of a bomb run shall cause a short duration audio signal to exist at the tone output 1 ±0.1 seconds before the end of the timer interval. At the end of the timer interval, the tone output signal shall become continuous, the horizontal pointer on the attitude indicator shall start rundown (upward movement), and any pitch trim in the attitude indicator shall disappear. With these conditions existing rotation of the displacement gyro in climb shall cause a bomb release within ±1° of the low release angle setting. Bomb release shall be evidenced by the appearance of a 28V DC release signal, the tone output shutting off, the horizontal pointer returning to its initial position, and indicator pitch trim reappearing.

*3.4.7.4 Timed High Angle Release - With the system externally connected for TIMED HIGH ANGLE bomb mode, the operation shall be the same as in 3.4.8.3 except that bomb release shall occur at the high release angle setting ±1.0°.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.4.7.5 Instantaneous High Angle Release - With the system externally connected for INSTANTANEOUS HIGH ANGLE, initiation of a bomb run shall immediately cause the steady tone signal to appear, the horizontal pointer on the attitude indicator to start rundown, and indicator pitch trim to disappear. With these conditions existing, rotation of the displacement gyro in climb shall cause bomb release within ±1° of the high release angle setting.

*3.4.7.6 Roll Error Signal - With the system externally connected for a bomb mode, a bomb run initiated, the displacement gyro at 0° pitch and the timer interval elapsed, it shall be possible to adjust the ROLL potentiometer in the amplifier-power supply such that a roll of the displacement gyro in either direction shall cause a corresponding amount of roll in the same direction to appear on the attitude indicator. The indicator roll in each direction shall be equal within 2.5 degrees for 10 degrees roll of the gyroscope.

*3.4.7.7 Yaw Error Signal - With the system externally connected for a bomb mode, a bomb run initiated, the displacement gyro at 0° pitch and the timer interval elapsed, it shall be possible to adjust the YAW potentiometer in the amplifier-power supply over a sufficient range such that 3° azimuth change of the displacement gyro in either direction shall cause the attitude indicator to show from 3° roll to 12° roll in the corresponding direction (e.g. right turn gives right roll). The amount of indicator roll shall be equal within 2.5° for the setting which gives a 12° indication for 3° gyro roll.

*3.4.7.8 Bomb Cancel - With the system externally connected for a bomb mode, a bomb run initiated, the displacement gyroscope at 0° pitch, and the timer interval elapsed, rotation of the displacement gyro in azimuth shall cause bomb cancel to be effected with less than 30° rotation. Bomb cancel shall be evidenced by shutting off the continuous tone signal, the horizontal pointer on the attitude indicator returning to its center position, pitch trim being reactivated, and the system returning to all-attitude mode.

*3.4.8 Performance at Temperature Extremes - The equipment shall perform as specified herein at temperature extremes except as follows:

*3.4.8.1 Erection and Synchronization - The OFF Flag shall disappear from view within 114 seconds. Within 10 minutes the heading indication shall be within 4.5° of the compass transmitter heading.

*3.4.8.2 Erection Rates - The roll and pitch slow erection rates shall be 1.5 ±1.0 degrees per minute.

*3.4.8.3 Slaving Rate - The slaving rate shall be 0.5 to 2.5 degrees per minute.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.4.7.5 Yaw Rate Switching - Within 25 seconds after the turn rate is reduced to zero, the synchronizing function and roll erection voltage shall be restored.

*3.4.8.5 Latitude Compensation - The heading indication shall not change more than 4° in one hour of operation.

*3.4.9.6 G Program Adjustment - The run-down time shall be 2.0 ±0.2 seconds without readjusting the setting of 3.4.8.2.

*3.4.8.7 Roll Error Signal - Roll indications shall be equal within 3.0 degrees for 10 degrees roll of the gyroscope.

*3.4.8.8 Yaw Error Signal - Roll indications shall be equal within 4.0 degrees for 12° yaw of the gyroscope.

*3.5 Detail Requirements -

*3.5.1 Adapter-Compensator, Compass MX-2488A/AJB-3 - The Compass Adapter-Compensator shall meet the following requirements:

*3.5.1.1 Function - The Compass Adapter-Compensator shall provide azimuth heading outputs using basic input signals from a ML-1 Compass Transmitter per MIL-T-19576, a Displacement Gyroscope Assembly CN-494A/AJB-3 and a Compass System Controller C-2499A/AJB-3 or equals. It shall operate in the slaved or free mode to develop gyro stabilized magnetic or free gyro data for navigation, radar, fire control, autopilot and related equipment.

*3.5.1.2 Form Factor - The Compass Adapter-Compensator shall be enclosed in a case conforming to the general requirements of MIL-C-172. The outline dimensions of the case shall conform to MS-17377.

*3.5.1.3 Case - The case of the Compass Adapter-Compensator shall be made of non-ferrous, low density metal, uniform in texture and having a smooth surface. The case shall be finished with a lusterless black material, Color No. 37038 of FED-STD-595.

*3.5.1.4 Contents - The Compass Adapter-Compensator shall contain the following circuits and components.

(a) Servo System
(b) Gyro Slaving Amplifier
(c) Heading Data Synchro Transmitters
(d) Heading Data Differential Synchro Transmitter
(e) 24 pt. Mechanical Cam Compensator
(f) Compass Control Transformer
(g) Slewing System
(h) Power Supply
(i) Relays

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.1.4.1 Servo System - The Servo System shall consist of the following components:

(a) Differentially Mounted Synchro Control Transformer

(b) Servo Motor-Generator

(c) Angle Data Shaft

(d) Servo Amplifier

*3.5.1.4.1.1 Differentially Mounted Synchro Control Transformer - The rotor of the control transformer shall be geared to the servo angle data shaft and the stator shall be geared to the slewing system. The control transformer characteristics shall be such that the servo performance requirements herein are satisfied. Nominal input characteristics of the control transformer shall be as follows:

Input voltage, line to line	11.1 V, 400 cps
Input current, maximum	40 ma
Input Impedance (Rotor open circuit)	79 + j350 ohms

*3.5.1.4.1.2 Servo Motor-Generator - The motor-generator characteristics shall be such that the servo performance requirements specified herein are satisfied.

*3.5.1.4.1.3 Angle Data Shaft - The angle data shaft shall drive, through gearing, the heading synchro transmitters. The shaft position shall be controlled by the servo system. The shaft shall be coupled to the compass control transformer by means of the cam compensator.

*3.5.1.4.1.4 Servo Amplifier - The amplifier characteristics shall be such that the servo performance requirements specified herein are satisfied.

*3.5.1.4.2 Gyro Slaving Amplifier - The slaving amplifier shall operate from the output of the compass control transformer. The amplifier shall drive the slew motor during the fast synchronization cycle and shall supply slaving power for the CN-494A/AJB-3 Displacement Gyroscope.

*3.5.1.4.3 Heading Data Synchro Transmitters - Four heading data synchro transmitters shall be geared to the angle data shaft. Their rotors shall have a 1 to 1 rotational ratio with the rotor of the differentially mounted servo control transformer. Each transmitter shall be capable of operating, simultaneously, four Bendix type AY 500-5, or equivalent, control transformers.

The three output leads from each transmitter and the two rotor leads shall be connected to the pins of an external connector.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.1.4.4 Heading Data Differential Synchro Transmitter - The differential synchro transmitter rotor shall be geared to the slew motor. The transmitter shall have the following nominal characteristics:

Input current	100 ma
Z_{so}	28 + j114
Z_{ro}	38 + j122
Z_{rs}	47 + j13

The three input leads and the three output leads shall be connected to the pins of an external connector.

*3.5.1.4.5 24 Point Mechanical Cam Compensator - The compensator shall couple the angle data shaft to the rotor shaft of the compass synchro-control transformer. The unit shall provide 24 equally spaced compensation adjustments. The compensator shall be designed so that continuous rotation of the adjustment screws in either direction will not result in binding, jamming, or damage to the mechanism.

*3.5.1.4.6 Compass Control Transformer - The rotor of the control transformer shall be coupled to the angle data shaft by the cam compensator. The unit shall be capble of operating from the output of a ML type compass transmitter. Its output shall excite the slaving amplifier.

*3.5.1.4.7 Slewing System - The slewing system shall consist of a reversible AC motor and gearing between the differential synchro transmitter rotor and the stator of the servo control transformer. The gearing shall produce a 1 to 1 rotation radio between the two synchros.

*3.5.1.4.8 Power Supply - The power supply shall provide the operating power for the servo system, slewing system and excitation for the differential control transmitter and the compass control transformer. It shall also supply voltages for excitation of the latitude compensation potentiometer in the Compass Controller and excitation of the torquers in the Displacement Gyroscope for free and slaved modes of operation.

*3.5.1.4.9 Switching - Relays or solid-state switching shall be incorporated to provide fast synchronization and slaving cutout functions.

*3.5.1.5 Performance - The equipment shall meet the following performance requirements:

*3.5.1.5.1 Servo - When connected to a matching (See 3.5.1.4.1.1) synchro transmitter, the servo system shall provide the following performance.

Static Accuracy	$\pm 1.0^{\circ}$
Follow-up Rate, Minimum	50°/
Follow-up Lag, Maximum	-0125°/RPM

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.1.5.2 Slaving Amplifier - With the flux value simulator set at 150° and the output data shaft set at 0°, a current greater than 50 microamperes shall flow from pin R to pin P of J910 and there shall be an output of 5.6 ± 0.9V, 400 cps, pahse B + 90° at pin D of J910 with respect to J903 pin D.

Application of 28 ± 1 V DC between J910-S and J903-D (with - to J903-D) shall align the output data shaft to 150° ± 4° within 5 seconds, after alignment a current of 7.5 microamperes or less shall flow from pin R to pin P of J910.

*3.5.1.5.3 Heading Data Synchro Transmitters - The electrical error of the heading data transmitters shall not exceed 0.25°.

*3.5.1.5.4 Differential Synchro Transmitter - The CDX output signal error shall not exceed ± 0.25°.

*3.5.1.5.5 24 Point Mechanical Cam Compensator - Each point shall be adjustable ± 3.5°.

*3.5.1.5.6 Compass Control Transformer - The output signal error shall not exceed ± 0.75°.

*3.5.1.5.7 Slewing System - The slewing system shall drive the rotor of the differential control transmitter and the stator of the servo control transformer at a minimum rate of 50°/second.

*3.5.1.5.8 Power Supply - With 115/200 V ± 2%, 400 cps applied, the output voltages of the power supply shall be within the specified limits with the specified loads.

	Voltage	Load
(a)	7.0 ±0.28V, 400 cps, ØC-90°	237.5 +j0 +0.9%
(b)	12.0V minimum, 400 cps, ØC with TRIM full CW;6.0V maximum, 400 cps, ØC with TRIM full CCW	354 +j277 ±2%
(c)	22 to 28V, 400 cps, ØB	354 +j277 ±2%

*3.5.1.6 Performance at Temperature Extremes - When tested at environmental extremes, the compass adapter shall perform as specified above except as follows:

*3.5.1.6.1 Slaving Amplifier - The output shall be 5.6 ± 1.6V in lieu of 5.6 ± 0.9V.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.1.6.2 Power Supply - The output shall be 7.0 ± 1.0V in lieu of 7.0 ± 0.28V.

*3.5.1.7 Electrical Connections - Connections to external circuits shall be provided as shown in Figure 1.

*3.5.2 Amplifier-Power Supply AM-1931/AJB-3 - The amplifier power supply shall meet the following requirements:

*3.5.2.1 Function - The amplifier-power supply shall provide amplifiers, power supply, switching, and controls for the operation of associated displacement gyroscope, attitude indicator, and bomb release angle computer in the AN/AJB-3 and AN/AJB-3A Loft Bomb Release Computer Set.

*3.5.2.2 Form Factor - The amplifier-power supply shall be enclosed in a case conforming to the general requirements of MIL-C-172. The outline dimensions of the case shall conform to MS-17378.

*3.5.2.3 Case - The case of the amplifier-power supply shall be made of non-ferrous, low density metal, uniform in texture and shall have a smooth surface. The case shall be finished with a lusterless black material, Color No. 37038 of FED-STD-595.

*3.5.2.4 Contents - The amplifier-power supply shall contain the following circuits and controls.

(1) Power Supply - Develop power for motor and generator excitation, gyro erection systems, etc., incorporate the system start relay, gyro start relay and 12 and 60 sec. time delay relays.

(2) Servo Amplifier - Displacement gyro roll servo.

(3) Servo Amplifier - Displacement gyro pitch follow-up servo.

(4) Servo Amplifier - Displacement gyro leveling servo.

(5) Servo Amplifier - Bomb release angle computer servo.

(6) Servo Amplifier - Attitude indicator pitch servo.

(7) Servo Amplifier - Attitude indicator roll servo.

(8) Servo Amplifier - Attitude indicator azimuth servo.

(9) Relay Module - System switching relays.

(10) Controls - Roll/yaw signal mixing and "g" programmer speed adjust.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.2.4.1 Power Supply - The power supply shall perform as follows:

(1) Voltages - The following AC voltages shall be supplied and shall be within 9% of the nominal values with the specified loads.

60V @ 0.3 amp. Roll erection (12 to 60 sec.)
Pitch erection (1st 60 sec.)

34V @ 0.55 amp. Indicator Roll motor fixed Ø
Gyro leveling torquer fixed Ø
(after 12 sec.)

30V @ 0.2 amp. Bomb rel. angle computer gen. excitation
Bomb rel. angle computer motor fixed Ø

26V @ 0.6 amp. Indicator power failure flag motor excitation
Gyro roll gen. excitation
Gyro roll motor fixed Ø

21V @ .3 amp. Indicator pitch motor fixed Ø
Indicator azimuth motor fixed Ø

18V @ .85 amp. Roll erection (after 60 sec.)
Pitch erection (after 60 sec.)
Indicator gen. excitation
gyro pitch follow-up gen. excitation

(2) Relays - The 12 second and 60 second time delay relays shall accomplish the following system switching:

(a) 12 second relay - The relay contacts shall cause the operation of the gyro start relay during the first 12 seconds after system power is applied. The gyro start relay removes roll erection, opens the fixed phase to the leveling torquer and the indicator roll motor, opens phase A to the gyro rotor and adds 500 ohms in series with phase B to the gyro rotor. The tolerance for the 12 second period shall be ±5 seconds as the input voltage varies from 25 to 29VDC.

(b) 60 second relay - The relay contacts shall cause the energizing of the system start relay coil and the 12 second time delay relay coil during the first 60 seconds after system power is applied. Operation of the system start relay shall remove

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

ground from the indicator power failure flag, energize the cage relay, and increase the pitch and roll erection voltage to 60 VAC. The tolerance for the 60 second period shall be +12, -15 seconds as the input voltage varies from 25 to 29VDC.

*3.5.2.4.2 Displacement Gyro Roll Servo Amplifier - This amplifier shall have the following nominal characteristics and shall provide the performance specified when connected in an AN/AJB-3 system.

(1) Characteristics:

Input impedance	15K ohms minimum
Load impedance	43 +j63 ohms
Input (displacement)	0.1V AC, ØC
Output (displacement input)	15V leading gyro motor fixed Ø by 90°
Input (rate)	0.1V AC, ØC
Output (rate input)	11V leading gyro motor fixed Ø by 90°
Null output	3.0V AC maximum

(2) Performance:

Follow-up rate	225°/sec. minimum
Follow-up lag	0.5°/10°/sec. maximum
Positional accuracy	Roll angle ±1°
Hunting and jumping	±0.5° maximum at maximum rate

*3.5.2.4.3 Displacement Gyro Pitch Follow-up Servo Amplifier - This amplifier shall have the following nominal characteristics and shall provide the performance specified when connected in an AN/AJB-3 system.

(1) Characteristics:

Input impedance	15K ohms minimum
Load impedance	100 +j95 ohms.
Input at saturation	0.15V AC,ØC
Output at saturation	15V, leading gyro motor fixed Ø by 90°
Null output	3.0V AC maximum

(2) Performance:

Follow-up rate	200°/sec. minimum
Follow-up lag	1.0°/10°/sec. maximum
Positional accuracy	Pitch angle ±1.25°
Hunting and jumping	±0.5° maximum at maximum rate

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.2.4.4 Displacement Gyro Leveling Servo Amplifier - This amplifier shall have the following nominal characteristics and shall provide the performance specified when connected in an AN/AJB-3 system.

(1) Characteristics:

Input impedance	15K ohms minimum
Load impedance	530 +j700 ohms
Input at saturation	0.15V AC, ØC
Output at saturation	41V lagging torquer fixed phase by 90°
Null output	4V AC maximum

(2) Performance:

Leveling rate	
Initial	Shall level the gyro to within 1½ minutes after start
Normal	2° to 10°/minute
Leveling accuracy	The gyro spin axis shall be perpendicular to the azimuth axis within ±0.5°.

*3.5.2.4.5 Bomb Release Angle Computer Servo Amplifier - This amplifier shall have the following nominal characteristics and shall provide the performance specified when connected in an AN/AJB-3 system.

(1) Characteristics:

Input impedance	15K ohms minimum
Load impedance	82 +j143 ohms
Input at saturation	0.15V AC ØC
Output at saturation	20V AC leading motor fixed phase by 90°
	3.0V AC, maximum

(2) Performance:

Follow-up rate	300°/sec. minimum
Follow-up lag	0.4°/10°/sec. maximum
Positional accuracy	Pitch input signal ±0.5°
Hunting and jumping	±0.5° maximum at maximum rate 0.7

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.2.4.6 Attitude Indicator Pitch Servo Amplifier - This amplifier shall have the following nominal characteristics and shall provide the performance specified when connected in AN/AJB-3 system.

(1) Characteristics:

Input impedance	1K ohms. minimum
Load impedance	158 +j104 ohms
Input at saturation	0.6V AC, ØC in series with 20K ohms
Output at saturation	16V AC leading motor fixed phase by 90°
Null output	3.0V AC, maximum

(2) Performance:

Follow-up rate	300°/sec. minimum
Follow-up lag	0.5°/10°/sec. maximum
Positional accuracy	Pitch input signal ±1.0°
Hunting and jumping	±0.4° maximum at maximum rate
Damping factor	0.7

*3.5.2.4.7 Attitude Indicator Roll Servo Amplifier - This amplifier shall have the following nominal characteristics and shall provide the performance specified when connected in an AN/AJB-3 system.

(1) Characteristics

Input impedance	1K ohms minimum
Load impedance	87 +j109 ohms
Input at saturation	0.60V AC, ØC in series with 20K ohms
Output at saturation	15V AC leading motor fixed phase by 90°
Null output	3.0V AC, maximum

(2) Performance:

Follow-up rate	300°/sec. minimum
Follow-up lag	0.5°/10°/sec. maximum
Positional accuracy	Roll input signal ±1.0°
Hunting and jumping	±0.5° maximum at maximum rate
Damping factor	0.7

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.2.4.8 Attitude Indicator Azimuth Servo Amplifier - This amplifier shall have the following nominal characteristics and shall provide the performance specified when connected in an AN/AJB-3 system.

(1) Characteristics:

Input impedance	15K ohms minimum
Load impedance	158 +j104 ohms
Input at saturation	0.15V AC ØC
Output at saturation	16V AC leading motor fixed phase by 90°
Null output	3.0V AC maximum

(2) Performance:

Follow-up rate	300°/sec. minimum
Follow-up lag	0.4°/10°/sec. maximum
Positional accuracy	Azimuth input signal ±1.0°
Hunting and jumping	±0.5° maximum at maximum rate
Damping factor	0.7

*3.5.2.4.9 Relay Module - The relay module shall provide the following:

*3.5.2.4.9.1 Continuity - Continuity as specified by Table I below shall exist between designated pins. No power shall be applied.

TABLE I

FROM PIN NO.	TO PIN NO.	FROM PIN NO.	TO PIN NO.
J201-A	J202-Z	J202-V	J204-R
J201-B	J202-a	J202-S	J202-T
J201-C	J202-b	J202-P	J202-V
J201-D	J203-E	J202-U	J204-P
J201-E	J204-Y	J203-B	J204-A
J201-E	J205-F	J203-D	J203-R
J202-B	J202-U	J203-S	J204-D
J202-e	J204-W	J-203S	J204-S
J202-d	J204-U	J-204-g	J204-K
J202-f	J204-V	J204-Z	J205-a
J202-g	J202-G	J204-Z	J205-c
J202-g	J205-b	J205-A	J205-L
J202-h	J203-M	J205-B	J205-K
J201-D	J202-X	J205-F	J205-G
J202-L	J203-Z	J205-g	J205-M
		J202-M	J202-H

*3.5.2.4.9.2 Yaw Cancel - With a pickle signal applied, a yaw resolver signal of .75V shall cause yaw cancel to occur. This opens the bomb release signal circuit and reverts the system to all attitude. Cancel shall remain until the pickle voltage is interrupted.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.2.4.9.3 Pull-up - Application of a pull up signal shall provide the following functions:

a. Pitch erection cut-out
b. Roll erection cut-out
c. Leveling cut-out
d. Cage relay operated - This switches the displacement gyro roll servo amplifier input from inner roll to outer roll.
e. Locks the Indicator Azimuth servo loop.
f. Sums the yaw and roll resolver signal with indicator roll signal and displays the sum on the indicator roll axis. It shall always be possible to override the summed yaw-roll resolver signal with the indicator roll input signal.

*3.5.2.4.9.4 System Switching - The relay modules shall provide the following switching logic.

*3.5.2.4.9.4.1 Apply +28V DC to J205-c and J201-E. Continuity shall exist between the following pairs of pins:

1. J204-W and J202-d
2. J204-U and J202-e
3. J204-A and J203-A
4. J204-B and J203-B

*3.5.2.4.9.4.2 The open circuits described in 3.5.2.4.9.4.1 shall remain through the following sequence of operations.

1. Connect J202-N to ground
2. Move ground from J202-N to J202-H
3. Move ground from J202-H to J204-L
4. Connect J202-H and J204-L to ground
5. Move ground from J204-L to J202-N
6. Move ground from J202-H to J204-L

*3.5.2.4.9.9.3 The open circuits described in 3.5.2.4.9.4.1 shall become short circuits upon simultaneously ground J202-H, J204-L and J202-N. These short circuits shall remain through the following sequence of operations.

1. Remove ground from J204-L
2. Remove ground from J202-N
3. Remove ground from J202-H

*3.5.2.4.9.4.4 Simultaneously ground J202-N, J202-H and J204-L shall produce the closed circuits of Paragraph 3.5.2.4.9.4.3. These closed circuits shall remain after removing the ground from J202-N. The closed circuits shall remain after replacing the ground on J202-N and removing the ground from J202-H. Once again remove the ground from J202-N and with J204-L, only, grounded the closed circuits shall become open.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.2.4.9.4.5 Apply +28V DC to J204-g. Short pin J205-a to J204-K. Applied voltage shall not appear at J204-F. Ground pin J204-G. The applied DC voltage shall disappear at J204-K and shall appear at J204-F. Remove the ground connection to J204-C. The applied DC voltage shall remain at J204-F. Remove the short between J205-a and J204-K. The applied voltage shall remain at J204-F. Remove the power to J204-g. The DC voltage shall disappear at J204-F.

*3.5.2.4.9.4.6 Apply +28V DC to pin J205-a and ground J204-G. There shall be zero volts at J204-F. Remove ground from J204-G. There shall be continuity between J202-R and B.

*3.5.2.5 Controls - The amplifier-power supply shall contain "ROLL", "YAW", and "PROG SPEED" controls of the screw-drive adjustment type. When connected to an AN/AJB-3 system, they shall function as follows:

1. Roll - It shall be possible to adjust the roll portion of the roll/yaw signal to obtain a 0.5° to 2° roll deflection on the indicator for ° roll attitude change.

2. Yaw - It shall be possible to adjust the yaw portion of the roll/yaw signal to obtain a 2° to 6° roll deflection on the indicator for a 1° yaw attitude change.

3. Programmer Speed - A resistor variable from 0 to 250 ohms shall be provided for control of programmer speed.

*3.5.2.6 Performance at Temperature Extremes - The amplifier-power supply shall perform as specified herein at temperature extreme.

*3.5.2.7 Electrical Connections - Connections to external circuits shall be provided as shown in Figure 1.

*3.5.3 Computer, Bomb Release Angle, CP-410/AJB-3 - The bomb release angle computer shall meet the following requirements:

*3.5.3.1 Function - The bomb release angle computer shall receive pitch attitude signals from a displacement gyroscope and shall develop bomb release signals at pre-selected pitch angles, shall resolve gyro roll and yaw signals about pitch to provide aircraft roll and yaw signals, shall develop relay switching signals at pre-selected pitch angles, and shall develop a signal proportional to the error between aircraft dive angle and a pre-selected dive angle.

*3.5.3.2 Form Factor - The bomb release angle computer shall be enclosed in a case conforming to the general requirements of MIL-C-172. The outline dimensions of the case and mounting bracket shall confrom to MS-17379.

*3.5.3.3 Case - The case and mounting bracket shall be made of non-ferrous, low density metal, uniform in texture, and having a smooth surface. The case and mounting bracket shall be finished with a lusterless black material, Color No. 37038 of FED-STD-595. The case shall be pivoted in the mounting bracket so it may be positioned to facilitate adjustment and viewing of the dials.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.3.4 Contents - The bomb release angle computer shall contain the following:

*3.5.3.4.1 Servo Mechanism - The servo mechanism shall consist of a synchro control transformer, a servo motor-generator, and a gear train. The servo mechanism shall operate in conjunction with an external amplifier. Its components shall have the following characteristics:

(1) Control Transformer - The control transformer shall have the following nominal characteristics:

DC rotor resistance	347 ohms
DC stator resistance	64 ohms, line to line
Input voltage	11.8 V, line to line
Input current	33 ma, max.
Output voltage	26V, open circuit
Impedance	
Output, ZRO	470 +j1860 ohms
Input, ZSO	76 +j346 ohms
Accuracy	±7 minutes

(2) Motor - Generator - The motor-generator shall have the following nominal characteristics:

Motor -	
Input voltage	
Fixed phase	26V, 400 cps
Control phase	33V, 400 cps
Current	
Fixed phase	95 ma, max.
Control phase	72 ma, max.
Impedance	
Fixed phase	270 + j195
Control phase	460 + j320
Generator -	
Voltage	
Input	30V, 400 cps
Output	.2V/1000 rpm
Impedance	
Input	1450 +j950 ohms
Output	650 +j416 ohms
Input Current	22 ma, max.
Null Voltage	30 MV, max.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

(3) Gear Train - The gear train shall be designed to provide the specified follow-up rate and accuracy. The gear design shall eliminate detrimental play and backlash.

*3.5.3.4.2 Angle Data Shaft - The angle data shaft shall be driven by the servo gear train and shall drive the control transformer rotor, the dive synchro transmitter rotor, the resolver rotor, and the switch assembly. The design of the system shall be such that the shaft repeats the pitch attitude of the aircraft when the control transformer is driven by the pitch synchro transmitter in the CN-494A/AJB-3 Displacement Gyroscope Assembly.

*3.5.3.4.3 Resolver - The resolver shall consist of two stator windings and two rotor windings. The nominal electrical characteristics of the resolver shall be as follows:

(1) Stator, per winding -

Input Voltage	26V, mas.
Input Current	14 ma, max.
Impedance, Zso	475 +j2170
Input Power	.12 watt max.

(2) Rotor, per winding -

Impedance, ZRO	595 +j1900
Null Voltage	50 MV, max. open circuit

The two stator and two rotor windings shall be positioned 90 degrees in respect to each other.

(3) Output Voltages -

(a) From electrical 0° to 180° and CW rotation, the resolver output voltages shall vary in accordance with the following equations:

$$E_R\ 13 = 0.843\ E_S\ 42 \cos \theta$$
$$E_R\ 24 = 0.843\ E_S\ 42 \sin \theta$$
or
$$E_R\ 31 = 0.843\ E_S\ 31 \sin \theta$$
$$E_R\ 24 = 0.843\ E_S\ 31 \cos \theta$$

(b) From 180° to 360° the output voltages shall be equal to those specified in (a) above, but of reverse phase.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

(c) With both stator windings excited, the output voltages shall vary in accordance with the following equations:

$$E_R\ 13 = .843\ E_S\ 42 \cos \theta - .843\ E_S\ 31 \sin \theta$$
$$E_R\ 24 = .843\ E_S\ 31 \cos \theta + .843\ E_S\ 42 \sin \theta$$

NOTE: θ = stator to rotor displacement angle. Unit observations are made from the lead side.

*3.5.3.4.4 Dive Transmitter - The dive synchro transmitter shall have the following nominal electrical characteristics. The stator shall be adjustable from 0° to -100°.

DC rotor resistance	24 ohms
DC stator resistance, line to line	7.5 ohms
Input Voltage	26V, 400 cps, 1 Ø
Input Current	200 ma max.
Impedance	
Input, ZRO	32 +j150 ohms
Output, ZSO	7.3 + J26 ohms
Output Voltage line to line	11.8V, max.
Null Voltage	30 MV, max.
Accuracy	±7 minutes

*3.5.3.4.5 Switch Assembly - The switch assembly shall provide the following control signals:

(1) Low Angle Release - The low angle release switch shall be adjustable to produce continuity to DC ground at angles of 0° to 80°. The continuity shall remain through 10°. The same condition shall prevail at the selected angle plus 180°.

(2) High Angle Release - The high angle release switch shall be adjustable to produce continuity to DC ground at angles of 80° to 170°. The continuity shall remain through 10°. The same condition shall prevail at the selected angle plus 180°.

(3) +20° Switch - The +20° switch shall produce continuity to DC ground from 340° through 20° and from 160° through 200°.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.3.4.6 Dials - Precision dials shall be provided to enable accurate setting of the low and high bomb release angle switches and the dive synchro transmitter stator. A vernier scale shall be provided for each dial so that each dial may be adjusted to .1° setting.

*3.5.3.4.6.1 Dial Adjustment - The dials shall be settable by adjustment screws available from the exterior of the case and shall not lose adjustment or change setting during or after exposure to any of the specified environmental requirements.

*3.5.3.5 Performance - The equipment shall meet the detail performance requirements specified when connected to a test synchro transmitter and amplifier as specified below.

*3.5.3.5.1 Test Synchro Tranmitter - The test synchro transmitter shall be a Kearfott type R510-1A or equivalent and shall be connected as indicated below:

Synchro Transmitter	Connector Pins (J611)
X	Y
Z	X
Y	Z
H)	26V AC -
C)	400 cps

The rotor and stator leads H, C, X, Y, and Z shall be designated for 180° index reference and positive rotational reference per ARinc Synchro Manual. Positive rotation is designated as climb.

*3.5.3.5.2 Test Amplifier - The test amplifier shall have the nominal characteristics and shall be connected as specified below:

(1)	Input impedance	15K ohms min.
(2)	Load impedance	82 + J143 ohms
(3)	Input saturation E	0.15VAC, ØC
(4)	Output E at saturation	20VAC, leading motor fixed phase by 90°
(5)	Null output	3.0 V rms max.
(6)	Connections:	
	Input, low ---------- pin g	
	Input, High ---------- pin a	
	Output, High --------- pin L	
	Output, Low (case gnd) pin K	

*3.5.3.5.3 Servo - The servo performance shall be as follows:

(1)	Follow-up rate	150°/sec. min.
(2)	Follow-up error	-0.1°/10°/sec.
(3)	Overshooting	None at rates up to 150°/sec.
(4)	Static positional accuracy	±0.3°

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.3.5.4 Resolver - The voltage output across pins A and B shall be at a minimum and not greater than 130 mv (in phase) with the synchro test transmitter set at 30° ± 5° climb. The voltage output across pins V to W shall be 980 mv ± 10% and shall be in phase with the input to T to U. As the synchro test transmitter is advanced in climb, the voltage output across pins A to B shall increase and be in phase with the input to pins T to U. The voltage output across pins A and B shall be at a maximum and more than 550 mv with the synchro test transmitter set at 120° ± 5°. The A-B voltage shall be in phase with the input to T to U. Also, the output voltage across pins V to W shall be at a minimum and not greater than 130 mv in phase. As the synchro test transmitter is advanced, the voltage output across V to W shall be out of phase with the input voltage to T to U.

*3.5.3.5.5 Dive Transmitter - Electrical zero as described in MIL-S-16892 shall occur within ±1.5° of any dive angle set on the dive angle dial as the rotor is moved by the servo and synchro transmitter.

*3.5.3.5.6 Switching - The performance of the switches shall be as specified below:

(1) Low Angle Release Switch - Continuity to DC ground shall occur when the synchro transmitter is within +.1° - -.6° of the preset release angle and is being advanced from 0° at a rate equal to or less than 1 RPM.

(2) High Angle Release Switch - Performance shall be as specified for the low angle release switch.

(3) +20° Switch - Continuity to DC ground shall exist from 340 +2° through 20 ±2° and from 160 ±2° through 200 ±2°.

*3.5.3.5.7 Dials - The setting accuracy of the high and low angle release dials shall be ±0.1° and that of the dive transmitter dial shall be ±1.0°.

*3.5.3.6 Performance at Temperature Extremes - The bomb release angle computer shall perform as specified herein at temperature extremes except as follows:

*3.5.3.6.1 Servo Follow-up Error - The follow-up error shall not exceed 0.15°/10°/second in lieu of 0.1°/10°/second.

*3.5.3.6.2 Resolver - The resolver null shall not exceed 150 mv in lieu of 130 mv.

*3.5.3.7 Electrical Connections - Connections to external circuits shall be provided as shown in Figure 1.

*3.5.4 Controller, Compass System C-2499A/AJB-3 - The compass system controller shall meet the following requirements:

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.4.1 Function - The compass system controller shall provide the mode selection and controls for the operation of a directional gyro-magnetic compass heading system. It shall operate with the Adapter-Compensator, Compass MX-2488A/AJB-3.

*3.5.4.2 Form Factor - The compass system controller shall be enclosed in a case conforming to the general requirements of MIL-C-172. The outline dimensions of the case including the control knobs, shall conform to MS17380.

*3.5.4.3 Case - The case of the controller shall be made of non-ferrous, low density metal, uniform in texture, having a smooth surface. The case shall be finished with a lusterless black material, Color No. 37038 of Fed. Std. No. 595. Panel markings shall be in accordance with MS17380.

*3.5.4.4 Controls - The compass system controller shall provide the following controls as shown on MS17380:

*3.5.4.4.1 Mode Selector Switch - The mode selector switch shall provide for the selection of "SLAVED" directional gyro mode of operation or "FREE" directional gyro mode of operation.

*3.5.4.4.2 Set Heading Control - The set heading control shall be labeled "PUSH TO TURN", shall provide switching to de-couple the autopilot and to control the direction and rate of slewing the system to an azimuth heading when operating in the "FREE" mode.

*3.5.4.4.3 Synchronizing Switch - The synchronizing switch shall be labeled "PUSH TO SYNC" and shall provide for synchronization of the azimuth heading output to the magnetic compass when operating in the "SLAVED" mode.

*3.5.4.4.4 Latitude Control - The latitude control shall provide means to compensate for apparent drift of the gyroscope resulting from rotation of the earth.

*3.5.4.5 Synchronizing Indicator - The compass system controller shall include a synchronizing indicator to provide a visual indication of synchronization between the azimuth heading output and the magnetic compass.

*3.5.4.5.1 Dial Marking - The synchronizing indicator dial shall be marked as shown on MS17380. The "L" and "R" and zero index markings shall be lusterless black, Color No. 37038 of FED-STD-595 and the scale shall be lusterless white, Color No. 37875 of FED-STD-595.

*3.5.4.6 Electrical Connections - Connections to external circuits shall be provided as shown in Figure 1.

*3.5.4.7 Panel Illumination and Marking - The compass system controller shall contain a lighting plate conforming to Specification MIL-P-7788. The plate shall be marked in accordance with Specification MIL-C-18012.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.4.8 Performance Characteristics - The performance characteristics shall be as follows under standard conditions (3.3.8).

*3.5.4.8.1 Synchronizing Indicator - With the mode selector in the "SLAVED" position, 45 microamperes DC from pins P to R shall cause a minimum pointer deflection of 2/3 of full scale from its center position. Deflection shall be to the left when pin R is positive and to the right when pin P is positive.

*3.5.4.8.2 Mode Selector Switch - The specified resistance shall exist between the specified pins for the two switch positions.

Connector Pins (J801)	Slaved	Free
G - E	Less than 1 ohm	Over 50 megohms
G - C	Over 50 megohms	Less than 1 ohm
F - Y	Over 50 megohms	Less than 1 ohm
F - D	Less than 1 ohm	Over 50 megohms
M - V	Less than 1 ohm	Over 50 megohms
c - b	Over 50 megohms	Less than 1 ohm
a - b	Less than 1 ohm	Over 50 megohms

*3.5.4.8.3 Set Heading Control - The specified resistance shall exist between the specified connector pins for the two switch positions. The "PUSH TO TURN" knob shall not be rotated and the mode selector switch shall be in the "SLAVED" position.

Connector Pins (J801)	Normal	Depressed
G - E	Less than 1 ohm	Over 50 megohms
H - J	Over 50 megohms	500 ± 50 ohms
L - N	Less than 1 ohm	Over 50 megohms
W - X	Less than 1 ohm	Over 50 megohms

*3.5.4.8.3.1 With the "PUSH TO TURN" knob depressed; the resistance between J and H and K and H shall be equal within 60 ohms and rotation to the full CW position shall increase the resistance between H and J to 1000 + 100 ohms. Rotation to the full CCW position shall decrease the resistance between H and J to 30 ohms or less. In the full CW position the resistance between K and H shall be less than 30 ohms.

*3.5.4.8.3.2 With the "PUSH TO TURN" knob at its maximum CW or CCW position and with no axial pressure on the knob, the following resistances shall exist:

Connector Pins (J801)	Resistance
X - W	Over 50 megohms
L - N	Over 50 megohms

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.4.8.4 Synchronizing Switch - With the synchronizing switch in its normal position and the mode selector in the "SLAVED" position, the resistance between pins S and V of J801 shall be over 50 megohms. With the switch depressed, the resistance shall be less than 1 ohm.

*3.5.4.8.5 Latitude Control - The resistance between connector pins Y and A of J801 shall vary from 5 ohms or less at the 90°S setting to 237.5 ± 4 ohms at the 90°N setting. At the 0° setting the resistance between pins Y and A and Y and B shall be equal within 4 ohms.

*3.5.4.9 Performance at Temperature Extremes - The compass system controller shall perform as specified herein at temperature extremes except as follows:

*3.5.4.9.1 Set Heading Control - The resistance between pins H and J with the knob depressed shall be 500 ±80 ohms.

*3.5.4.9.1.1 With the "PUSH TO TURN" knob depressed; the resistance between J and H and K and H shall be equal within 80 ohms and rotation to the full CW position shall increase the resistance between H and J to 1000 ± 130 ohms.

*3.5.4.9.2 Latitude Control - The resistance between connector pins Y and A of J801 shall vary from 7 ohms or less at the 90°S setting to 237.5 ±6 ohms at the 90°N setting. At the 0° setting the resistance between Y and A and Y and B shall be equal within 6 ohms.

*3.5.5 Distribution Box J-1122/AJB-3A - The distribution box shall shall meet the following requirements.

*3.5.5.1 Function - The distribution box shall provide two functions, an AC-DC interlock and an aural tone generator. The AC-DC interlock shall interrupt both AC and DC power when the DC and/or one, two, or all three phases of the AC power is interrupted or drops below predetermined values. The aural tone generator shall generate a 400 cps warning burst when triggered by a DC ground signal pulse and shall generate a 400 cps steady tone when triggered by 28V DC.

*3.5.5.2 Form Factor - The distribution box shall be enclosed in a case conforming to the general requirements of MIL-C-172. The outline dimensions of the case shall conform to MS-17381.

*3.5.5.3 Case - The case of the distribution box shall be made of non-ferrous, low density metal, uniform in texture and shall have a smooth surface. The case shall be finished with a lusterless black material, Color No. 37038 of FED-STD-595.

*3.5.5.4 Contents - The distribution box shall contain the following circuits:

*3,5.5.4.1 AC-DC Interlock

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.5.4.1.1 Operation - With 115V ±3%, 400 cps ±2% from pins A to D, B to D and C to D of J1402 and 28 ±1V DC from E to D (-DC to D) of J1402, input AC power shall appear at pins A, B, and C of J1401 in respect to pin G.

*3.5.5.4.1.2 Drop-Out - Removal of AC power from A, B, or C of J1402 or removal of DC power from pin E of J1402 shall cause the output power at pins A, B, and C of J1401 to disappear within 7 seconds.

Reduction of the AC power to pins A, B, or C of J1402 to 70V shall cause the output power at pins A, B, and C of J1401 to disappear within 25 seconds.

*3.5.5.4.2 Tone Generator - The following performance requirements shall be met with 115V ±3%, 400 cps ±2%, 1 ØAC power applied between B and G of J1401 and a 600 ohm ±5%, 5W resistance load across T and G of J1401.

*3.5.5.4.2.1 Warning Tone Burst - With the volume control at maximum cw position, grounding of pin U of J1401 shall cause a 0.25 to 0.5 second, 400 cps ±2% signal burst of 100 mw minimum across pins G and T. With the volume control at maximum CCW position, the power of the burst shall be 10 mw maximum.

*3.5.5.4.2.2 Continuous Tone - With the volume control at maximum cw position, application of 28 ±1V DC to pin D with respect to pin G of J1401 shall cause a steady, 400 cps ±2% signal of 50 mw minimum across pins G and T. With the volume control at maximum ccw position, the signal power shall be 5 mw maximum. The tone shall remain until the DC power is removed from pin D.

*3.5.5.4.2.3 Power Ratio - For a given setting of the volume control, the power level of the warning tone burst shall be approximately twice that of the continuous tone.

*3.5.5.4.2.4 Tone Content - The tone generator shall utilize the 400 cps aircraft power as a tone source but shall introduce sufficient harmonic to distinguish the tone from normal 400 cps hum.

*3.5.5.5 Controls - A screw driver adjustable AURAL TONE VOLUME control shall be externally accessible.

*3.5.5.6 Electrical Connections - Connections to external circuits shall be provided as shown in Figure 1.

*3.5.5.7 Performance at Temperature Extremes - The performance of the distribution box shall be as specified herein at temperature extremes except as follows:

*3.5.5.7.1 Tone Level - Without readjustment, the output power of the tone generator shall be within +3 db of the value obtained under standard conditions (3.3.8).

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.6 Gyroscope Assembly, Displacement CN-494A/AJB-3 - The displacement gyroscope assembly shall meet the following requirements:

*3.5.6.1 Function - The displacement gyroscope assembly shall provide electrical signals representative of aircraft attitude through 360° of pitch, roll, and yaw. It shall consist of a vertical gyro and a directional gyro mounted in multiple gimbals with a common outer gimbal as described herein. The gimbal arrangement shall prevent gimbal lock and, with proper correction for signal phasing, the unit shall meet the detail performance requirements with the outer gimbal in its normal attitude or in a position 180° from the normal attitude.

*3.5.6.2 Form Factor - The displacement gyroscope assembly shall be enclosed in a case conforming to the general requirements of MIL-C-172. The outline dimensions of the case sahll conform to MS-17382.

*3.5.6.3 Case - The case of the gyroscope shall be made of non-ferrous, low density metal, uniform in texture, having a smooth surface and shall be hermetically sealed. The case shall be finished with a lusterless black material, Color No. 37038 of FED-STD-595. A white arrow labeled "direction of flight" shall be painted on the case as shown on MS-17382.

*3.5.6.3.1 Hermitic Sealing - The case shall provide a hermetically sealed enclosure for all of the mechanism. The case shall be so constructed that it may be opened, the mechanism removed and replaced and the case re-sealed at least three times. This shall be possible without the use of any special tool, jig or fixture, unless such device is specifically approved by the procuring activity. The sealing of the case shall not be dependent upon any material which will be adversely affected by any atmosphere to which the instrument may be subjected in normal use in military aircraft.

*3.5.6.3.2 Filling Medium - The filling medium shall be either a mixture of 90% nitrogen and 10% helium or 95% helium and 5% carbon dioxide. The nitrogen used shall be in accordance with Specification BB-N-411, Type I, Class I, Grace C. The filling medium shall contain not more than 0.006 milligram of water vapor per liter (dew point -65°C) at the filling pressure. The absolute pressure of the filling medium in the case shall be 1 +0.1 atmosphere.

*3.5.6.3.3 Leak Rate - The gas or mixture of gases in the case, adjusted to a pressure differential of one atmosphere, shall not have a leakage from the case that would permit more than 10 per cent contaimination of the filling medium after 1000 hours.

*3.5.6.4 Electronical Connections - Connections to external circuits shall be provided as shown in Figure 1.

*3.5.6.5 Installation Mounting - Installation shall be with the mounting feet down and with the "direction of flight" arrow pointing forward.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.6.6 Contents - The displacement gyroscope assembly shall consist of a vertical gyro and a directional gyro mounted in multiple gimbals with a common outer gimbal.

*3.5.6.6.1 Vertical Gyro - The vertical gyro shall have sufficient angular momentum and be of such design so as to provide the performance specified herein when operated throughout the temperature, vibration, and acceleration ranges specified.

*3.5.6.6.1.1 Gimbal System - The vertical gyro shall be suspended in a gimbal system which has two free inner gimbals and a servo driven outer gimbal to eliminate gimbal lock of the gyro. The outer gimbal shall be used in common with the directional gyro.

*3.5.6.6.1.1.1 First Gimbal - The first gimbal shall be the gyro rotor housing. It shall be stabilized by the inertia of the gyro.

*3.5.6.6.1.1.2 Second Gimbal - The second gimbal shall be the next gimbal outward from the first gimbal. It shall be stabilized in pitch by the gyro.

*3.5.6.6.1.1.3 Third Gimbal - The third gimbal shall be the outer gimbal. It shall be servo driven to maintain a fixed relation between the first and second gimbal except for certain conditions specified herein.

*3.5.6.6.1.2 Axes of Freedom - The vertical gyro shall have three axes of freedom. Each axis shall be a signal axis.

*3.5.6.6.1.2.1 First Axis of Freedom - The first axis of freedom shall be between the first and second gimbal. This axis shall be maintained in the horizontal plane and be aligned with the orthogonal horizontal projection of the fore and aft axis of the gyroscope under normal conditions. A minimum freedom of ±80 degrees shall be provided about this axis. An angular displacement about this axis shall provide an indication which changes from roll to yaw as the pitch angle changes from zero pitch to ±90 degrees pitch. Stops shall be incorporated on this axis which produce a pitch precession when the freedom is exceeded and no damage shall result under this condition.

*3.5.6.6.1.2.2 Second Axis of Freedom - The second axis of freedom shall be between the second gimbal and the third (servo driven) gimbal. This axis shall be perpendicular to the first axis of freedom and shall be maintained in the horizontal plane under normal conditions. Unlimited freedome shall be provided about this axis. An angular displacement about this axis shall be a measurement of the pitch angle.

*3.5.6.6.1.2.3 Third Axis of Freedom - The third axis of freedom shall be between the third gimbal and the instrument frame or case. This axis shall be perpendicular to the second axis of freedom and shall coincide with the fore and aft axis of the instrument. Unlimited freedom shall be provided about this axis.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

An angular displacement about this axis shall be a measurement of the roll angle. This axis shall have a pre-assembled slip ring and brush-block capsule having redundant circuits for all output signal leads. Individual slip ring circuit assignments shall be made to minimize the voltage differential between adjacent slip rings.

*3.5.6.6.1.3 Gimbal Actuation - The inner two gimbals are maintained in a fixed relation to the apparent gravity verticaly by the erection system. The outer gimbal is actuated by a servo mechanism and is driven so as to maintain the spin axis of the vertical gyro and the pitch axis in a 90-degree relation to each other except for certain transient conditions. The response of the servo of the outer gimbal shall be usch that this 90-degree relation will be maintained during roll rates from zero through 360 degrees per second with no lag, over-shooting, oscillation, hunting, or jumping or such a magnitude and frequency which will effect the performance of a high performance autopilot. The servo loop shall be sufficiently tight such that in normal operation during loop maneuvers, the third gimbal is rotated when the third gimbal axis passes through the vertical in order to keep proper sensing of the servo drive. The servomechanism shall be designed to meet specified performance requirements when connected to a servo amplifier as specified in paragraph 3.5.6.7.3(c).

*3.5.6.6.1.4 Erection - Means shall be incorporated for erection of the gyro to apparent gravity vertical from any attitude. The pitch and bank erection systems shall be separate and controllable individually.

*3.5.6.6.1.5 Synchro Outputs - Two transmitting synchros shall be mounted on the outer roll and on the pitch gimbals. One transmitting synchro shall be mounted on the inner roll gimbal. The inner roll synchro and one each of the two pitch and outer roll synchros shall be excited internally. The rotor leads of the other synchros shall be brought out to the connector for external excitation. The stator leads of all five synchros shall be brought out to the connector. The output signal from each synchro shall have a one-to-one ratio with the movement of the corresponding gimbal.

*3.5.6.6.1.5.1 Synchro Characteristics - The VG pitch synchro (opposite the pitch servo CX) and the outer roll synchro (DG end) shall have the following nominal characteristics:

(1)	Input Voltage	115v, 400cps
(2)	Input current, open stator	40 ma
(3)	Input power, open stator	1.1 watts
(4)	Input impedance, open stator	820 + J3240
(5)	Rotor resistance, DC	226 ohms
(6)	Stator output voltage, line-to-line	12.65 ± 0.25v
(7)	Stator resistance, DC, between leads	4.5 ohms
(8)	Null voltage, maximum	25 mv
(9)	Accuracy: Pitch	± 8 min.
	Roll	± 15 min.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

3.5.6.6.1.5.2 Synchro Characteristics - The remaining synchros shall have the following nominal characteristics:

(1)	Input voltage	115v, 400 cps
(2)	Input current, open sator	38 ma
(3)	Input power, open stator	.90 watts
(4)	Input impedance, open stator	810 + J3500
(5)	Rotor resistance, DC	235 ohms
(6)	Stator output voltage, line-to-line	11.8 ± 0.25v
(7)	Stator resistance, DC, between leads	4.5 ohms
(8)	Null voltage, maximum	25 mv
(9)	Accuracy: 2 Azimuth	± 8 min.
	1 Roll, 1 Pitch	± 15 min.

3.5.6.6.1.5.3 Synchro Loading - Each synchro shall be capable of operating up to eight high impedance control transformers of the Eclipse-Pioneer AY500-5 type or equal simultaneously when the control transformers are loaded with 10,000 ohm loads.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

Each synchro shall be capable of operating up to eight high impedance control transformers of the Eclipse-Pioneer AY500-5 type or equal simultaneously when the control transformers are loaded with 10,000 ohm loads.

*3.5.6.6.1.6 Roll Switch - A segment switch shall be incorporated to sense an inverted outer roll gimbal condition.

*3.5.6.6.1.7 Pitch Switch - A segment switch shall be incorporated to sense the relation between the pitch gimbal and outer roll gimbal positions.

*3.5.6.6.1.8 Power-Off Freedom - When power is removed momentarily, the vertical gyro shall still have freedom about its first and second gimbal axes and shall not be displaced from the vertical at +70° pitch and bank angles. Re-erection shall be ½° of vertical subsequent to restarts because of power off to the gyro.

*3.5.6.6.2 Directional Gyro - The directional gyro shall have sufficient angular momentum and be of such design so as to provide the performance specified herein when operated throughout the temperature, vibration, and acceleration range specified herein.

*3.5.6.6.2.1 Gimbal System - The directional gyro shallbe suspended in a gimbal system of which the outer gimbal is the third (servoed) gimbal of the vertical gyro. The directional gyro shall have three other gimbals contained in the outer gimbal.

*3.5.6.6.2.1.1 First Gimbal - The first (inner) directional gyro gimbal (gyro wheel housing) shall be stabilized by the inertial of the gyro. Its pivot axis shall be the first directional gyro axis of freedom and shall be perpendicular to the spin axis of the gyro and shall normally lie in the horizontal plane. The slaving torquer shall be mounted on this axis. This gimbal shall have a minimum of ±80 degrees of freedom from normal.

*3.5.6.6.2.1.2 Second Gimbal - The second directional gyro gimbal shall be stabilized by the inertia of the gyro. Its pivot axis shall be the second directional gyro axis of freedom and shall be normally aligned with the vertical. The azimuth output synchros and the leveling torquer shall be mounted on this axis. This gimbal shall be capable of continuous rotation about its axis.

*3.5.6.6.2.1.3 Third Gimbal - The third directional gyro gimbal (pitch) shall be servo driven such that it follows the vertical gyro second gimbal (Pitch) at a maximum rate of not less than 200° per second. Its pivot axis shall be the third directional gyro axis of freedom and shall be parallel to the vertical gyro second axis (pitch) of freedom. This gimbal shall be capable of continuous rotation about its axis. The servo mechanism shall be designed to meet specified performance requirements when connected to the servo amplifier specified in paragraph 3.5.6.7.3(a). This axis shall have a pre-assembled slip ring and brushblock capsule having redundant circuits for all output signal leads. Individual slip ring circuit assignments shall be made to minimize the voltage differential between adjacent slip rings.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.6.6.2.2 Leveling - Means shall be incorporated to maintain the spin axis perpendicular to the azimuth axis. The leveling shall be controlled by a non-pendulous sensor and shall utilize the amplifier specified in paragraph 3.5.6.7.3(b).

*3.5.6.6.2.3 Slaving - Means shall be incorporated to slave the azimuth gimbal to any desired heading.

*3.5.6.6.2.4 Latitude Compensation Calibration - Data necessary to provide compensation for directional gyro drift shall be provided as follows:

(a) Bias and trim voltages, necessary to compensate for directional gyro drift due to random drift and earth's rate, shall be calibrated for each gyro assembly and shall be displayed (in voltage values) on the connector end of the case. These voltages shall determine the "Bias" and "Trim" potentiometer settings on the specification MIL-A-23717, Compass Adapter-Compensator MA-2488R/AJB-3 (or equal) only, as used in the Loft Bomb Release Computer Set AN/AJB-3 only.

(b) Also, the directional gyro random drift in degrees per hour shall be displayed on the connector end of the case. This value shall determine the setting of the "bias/deg/hr" potentiometer on the Compass Adapter-Compensator MX-2826A/AJB-3A only, as used in the Loft Bomb Release Computer Set AN/AJB-3A only.

*3.5.6.6.2.5 Synchro Outputs - Two transmitting synchros shall be mounted on the azimuth gimbal. The rotor leads of both synchros shall be brought out to the connector for external excitation (however, one synchro may have one lead tied to AC neutral internally). The stator leads of both synchros shall be brought out to the connector. The output signal from each synchro shall have a one-to-one ration with the movement of the gimbal.

*3.5.6.6.2.5.1 Synchro Characteristics - The synchro characteristics shall be identical to those of thevertical gyro synchros. See paragraph 3.5.6.6.1.5.1.

*3.5.6.7 Performance Characteristics - The performance characteristics shall be as follows under standard conditions (3.3.8).

*3.5.6.7.1 Vertical Gyro -

*3.5.6.7.1.1 Erection - When the gyro is displaced about one axis but erected in the other, the gyro shall not deviate more than 1.5° from the erected position while the displaced gimbal is being erected. Application of 60V rms to both the pitch and roll erection systems shall cause erection of the gimbals at a minimum rate of 15° per minute. Application of 18V rms to both the pitch and roll erection systems shall cause erection of the gimbals at a rate of 0.8 to 1.8° per minute.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.6.7.1.1.1 Initial Erection - With the gyro rotor at a standstill and the spin axis in any random position, application of rotor power and high erection voltage to both the pitch and roll erection systems shall cause erection of the gyro to a position within 1° of apparent gravity vertical in 1 minute or less.

*3.5.6.7.1.1.2 Final Erection - After completion of the initial erection cycle, application of low erection voltage shall cause erection of the gyro to a position within 0.25° of vertical in 2 minutes or less.

*3.5.6.7.1.2 Synchro Outputs -

*3.5.6.7.1.2.1 Outer Roll - The phase of the outer roll synchro output signals shall be as specified below:

(a) Externally Excited Synchro - When terminals W and H are connected to AC neutral and terminal J to Ø C, the voltage measured across U and V shall be at a minimum and the voltage measured betwwen U or V and J shall be less than the excitation voltage when the gimbal is at zero displacement. Applying right roll to the reference shall cause the voltage across U and W to increase before decreasing and the voltage across V and W to decrease before increasing. Referenced terminals are on J361.

(b) Internally Excited Synchro - When terminal Z is connected to AC neutral, the voltage measured across X and Y shall be at minimum and the voltage measured between X or Y and D of J362 shall be less than the excitation voltage when the gimbal is at zero displacement. Applying right roll to the reference shall cause the voltage across X and Z to increase before decreasing and the voltage across Y and Z to decrease before increasing. Referenced terminals are on J361.

(c) In each of the above, the outer roll gimbal shall be stabilized as the reference is rolled.

*3.5.6.7.1.2.2 Pitch - The outputs of the pitch synchros shall be as specified below.

(a) Externally Excited Synchro - When terminals c and K are connected to AC neutral and terminal L to Ø C, the voltage measured across a and b shall be at minimum and the voltage measured between a or b and L shall be less than the excitation voltage when the gimbal is at zero displacement. Applying climb to the reference shall cause the voltage a and c to increase before decreasing and the voltage across b and c to decrease before increasing. Terminals are on J361.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

(b) Internally Excited Synchro - When terminal f is connected to AC neutral, the voltage across d and e shall be at minimum and the voltage measured between d or e and D of J362 shall be less than the excitation voltage when the gimbal is at zero displacement. Applying climb to the reference shall cause the voltage across d and f to increase before decreasing and the voltage across e and f to decrease before increasing. Referenced terminals are on J361. The maximum tracking and alignment error spread shall be 1° and the difference between the errors at identical angles as the gyro is rotated from 0° to 180° in climb with the outer roll gimbal inverted and norma shall not exceed 0.4°.

*3.5.6.7.1.2.2.1 Pitch Synchro Correction Chart - A pitch synchro correction chart shall be derived from the synchro error data taken between 0° and 180° climb at pins d, o, and f of J361 in 5° steps. This chart shall be found on the side of the unit.

*3.5.6.7.1.2.3 Inner Roll - The output of the inner roll synchro shall be as specified below.

When terminal j is connected to AC neutral, the voltage across g and h shall be a minimum and the voltage measured between g or h and D of J362 shall be less than the excitation voltage when the gimbal is at zero displacement. Applying right roll to the reference shall cause the voltage across g and j to increase before decreasing and the voltage across h and j to decrease before increasing. Referenced terminals are on J361.

*3.5.6.7.1.2.4 Electrical Zero Accuracy - With the gimbals fully erected, the synchro signals shall be at electrical zero within the tolerances specified below:

(a) Outer Roll - ±0.75°
(b) Pitch - ±0.5°
(c) Inner Roll - ±0.5°

*3.5.6.7.1.3 Drift - The maximum free drift, noted after compensation for earth's rotation effect, shall not be greater than 0.25° per minute with the gyro spin axis either tilted 20° or vertical.

*3.5.6.7.1.4 Roll Switch - The roll switch shall connect terminal D to AC neutral from ±90° through 180° to 270° where zero roll is the initial zero position as defined in paragraph 3.5.6.7.1.2.1. The circuit shall be open for the remaining 180° of roll. Referenced terminals are on J361.

*3.5.6.7.1.5 Outer Roll Servo - The performance of the roll servo shall satisfy the design requirements as specified in paragraph 3.5.6.6.1.3 when connected to an amplifier whose characteristics are equal to those of the roll serve test amplifier as specified in 3.5.6.7.3(c).

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.6.7.2 Directional Gyro -

*3.5.6.7.2.1 Leveling - Using an amplifier whose characteristics are equal to those of the leveling test amplifier as specified in 3.5.6.7.3(b) and a fixed phase voltage of 30V rms on the torquor, the leveling rate shall be 2 to 10° per minute. The leveling system shall level the gyro within 1½ minutes after application of starting power.

*3.5.6.7.2.2 Slaving - Application of 5.6V rms of slaving power to the slaving torquer shall torque the gyro about its azimuth axis at a rate of 1 to 2 degrees per minute.

*3.5.6.7.2.3 Pitch Follow-Up - The pitch follow-up servo shall drive the pitch follow-up gimbal at a maximum rate of not less than 200°/sec when connected to an amplifier whose characteristics are equal to those of the pitch follow-up test amplifier as specified in 3.5.6.7.3(a).

*3.5.6.7.2.4 Synchro Outputs - The outputs of the azimuth synchros shall be as specified below.

(a) Internally Excited Synchro - When terminal T is connected to AC neutral, the voltage across R and S shall be a minimum and the voltage measured between R or S and E shall be greater than excitation voltage when the spin axis is aligned with the fore and aft axis of the reference. Applying right turn to the reference shall cause the voltage across R and T to increase before decreasing and the voltage across S and T to decrease before increasing. Connect E to Ø C for this test. Referenced terminals are on J361.

(b) Externally Excited Synchro - When terminals P and F are connected to AC neutral and G is connected to Ø C, the voltage across M and N shall be at minimum and the voltage measured between M or N and G shall be greater than the excitation voltage when the spin axis is aligned with the fore and aft axis of the reference. Applying right turn to the reference shall cause the voltage across M and P to increase before decreasing and the voltage across N and P to decrease before increasing. Referenced terminals are on J361.

*3.5.6.7.2.5 Random Drift - The random drift, noted after compensation for earth's rotation effect, shall not exceed 4° per hour.

*3.5.6.7.3 Test Amplifiers - Amplifiers with the following characteristics shall be connected to the pins indicated during all performance tests. The amplifiers shall be energized with Ø C power.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

(a) Pitch Follow-Up Servo Amplifier

J362-h	input, low
J362-W	input, high
J362-m	output

Connect

J361-e to J362-Y
J361-d to J362-k
J361-f to J362-s
J362-X to J362-Z

Amplifier Characteristics Nominal

Input impedance	25K ohms
Lead impedance	100 + J95 ohms
Input saturation E	0.15 VAC
Output E at saturation	15 ±2 vac, 180° out-of-phase
Null output	3.0V rms, Maximum

(b) Leveling Amplifier

J362-i	input, low
J362-j	input, high
J362-H	output

Amplifier Characteristics, Nominal

Input impedance	25K ohms
Load impedance	530 + J700 ohms
Input saturation E	0.15 VAC
Output E at saturation	41 ±4 vac, k80° out-of-phase
Null output	4.5V rms, Maximum

(c) Roll Servo Amplifier

J361-g	input, high
J362-g	rate, input, low
J362-f	rate, input, high
J361-h	input, low
J362-q	output

Amplifier Characteristics, Nominal

Input impedance	25Kohms
Load impedance	43 + J63 ohms
Input saturation E	0.1 VAC
Output E at saturation	15 ±2 vac, 180° out-of-phase, with input to J361-g. 11 ±2 vac, 180° out-of-phase, with input to J362-f.
Null output	2.0V rms, Maximum

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

(d) When specified, J361-Y shall be connected to the input, high, in place of J361-g and J361-X shall be connected to the input, low, in place of J361-h in Section (c) above.

*3.5.7 Gyroscope, Rate Switching CN-495A/AJB-3 - The rate switching gyroscope shall meet the following requirements.

*3.5.7.1 Function - The rate switching gyroscope shall provide a single pole, double throw switching function within specified time intervals both after application of specified turn rates and after the return to zero turn rate from specified turn rates.

*3.5.7.2 Form Factor - The rate switching gyroscope shall be enclosed in a case conforming to the general requirements of MIL-C-172. The outline dimensions of the case shall conform to MS17384.

*3.5.7.3 Case - The case of the gyroscope shall be made of non-ferrous, low density metal, uniform in texture, having a smooth surface and shall be hermetically sealed. The case shall be finished with a lusterless black material, Color No. 37038 of Fed. Std. No. 595. A white line labeled "line of flight" shall be painted on the case as shown on MS17384.

*3.5.7.3.1 Hermetic Sealing - The case shall provide a hermetically sealed enclosure for all of the mechanism. The case shall be so constructed that it may be opened, the mechanism removed and replaced and the rate switching gyroscope case resealed at least three times. This shall be possible without the use of any special tool, jig or fixture, unless such device is specifically approved by the procuring activity. The sealing of the case shall not be dependent upon any material which will be adversely affected by any atmosphere to which the instrument may be subjected in normal use in military aircraft.

*3.5.7.3.2 Filling Medium - The filling medium shall be either a mixture of 90% nitrogen and 10% helium or 95% helium and 5% carbon dioxide. The nitrogen used shall be in accordance with Specification BB-N-441, Type I, Class I, Grade C. The filling medium shall contain not more than 0.006 milligram of water vapor per liter (dew point -65°C) at the filling pressure. The absolute pressure of the filling medium in the case shall be 1 ±0.1 atmosphere.

*3.5.7.3.3 Leak Rate - The gas or mixture of gases in the case, adjusted to a pressure differential of one atmosphere, shall not have a leakage from the case that would permit more than 10 per cent contaimination of the filling medium after 1000 hours.

*3.5.7.4 Electrical Connections - Connections to external circuits shall be provided as shown in Figure 1.

*3.5.7.5 Installation Mounting - Installation shall be with the mounting feet down and the "line of flight" line on the case parallel to the longitudinal axis of the aircraft.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.7.6 Contact Rating - The rating of the switching contacts shall not be less than 2 amps at 115V when operating into a resistive load.

*3.5.7.7 Performance Characteristics - The performance characteristics shall be as follows under standard conditions (3.3.8).

*3.5.7.7.1 Switching - The rate switching gyroscope shall operate to close the internal circuit between terminals D and E and to open the circuit between terminals C and D within the time specified after application of the following turn rates about the axis perpendicular to the plane of the mounting feet.

Turn Rate	Time	Turn Rate	Time
180° per minute	4 seconds	20° per minute	20 seconds
45° per minute	8 seconds	15° per minute	35 seconds

When the turn rate is reduced to zero, the circuit between terminals D and E shall open and the circuit between terminals C and D shall close within 20 seconds.

*3.5.7.7.2 Yaw Oscillation - With zero turn rate applied, yaw oscillations of plus and minus one degree with a 2 second period and yaw oscillations of plus and minus 2 degrees with an 8 second period shall not cause switching to occur. With the one degree oscillation superimposed on a 30 degree per minute rate of turn, switching shall occur within 30 seconds.

*3.5.7.7.3 Power Failure - Removal of power from the gyroscope shall immediately cause the circuit between terminals D and E to open and remain open and the circuit between terminals C and D to close and remain closed.

*3.5.7.8 Performance at Temperature Extremes - The rate switching gyroscope shall perform as specified herein at temperature extremes except as follows:

*3.5.7.8.1 Switching - When the turn rate is reduced to zero, the circuit between terminals D and E shall open and the circuit between terminals C and D shall close within 25 seconds.

*3.5.8 Indicator, Attitude ID-694/AJB-3 - The attitude indicator shall meet the following requirements:

*3.5.8.1 Function - The attitude indicator shall provide a continuous and unambiguous display of aircraft attitude for 360° of roll, pitch, and azimuth and a power failure indication.

*3.5.8.2 Form Factor - The attitude indicator shall be enclosed in a case conforming to the general requirements of MIL-C-172. The outline dimensions of the case shall conform to MS17385.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.8.3 Case - The case of the indicator shall be made of non-ferrous, low density metal, uniform in texture, having a smooth surface and shall be hermetically sealed. The case shall be finished with a lusterless black material, Color No. 37038 of Fed. Std. No. 595.

*3.5.8.3.1 Hermetic Sealing - The case shall provide a hermetically sealed enclosure for all of the mechanism. The case shall be so constructed that it may be opened, the mechanism removed and replaced and the indicator case resealed at least three times. This shall be possible without the use of any special tool, jig or fixture, unless such device is specifically approved by the procuring activity. The sealing of the case shall not be dependent upon any material which will be adversely affected by any atmosphere to which the instrument may be subjected in normal use in military aircraft.

*3.5.8.3.2 Filling Medium - The filling medium shall be either a mixture of 90% nitrogen and 10% helium or 95% helium and 5% carbon dioxide. The nitrogen used shall be in accordance with Specification BB-N-411, Type I, Class I, Grade C. The filling medium shall contain not more than 0.006 milligram of water vapor per liter (dew point -65°C) at the filling pressure. The absolute pressure of the filling medium in thecase shall be 1 ±0.1 atmosphere.

*3.5.8.3.3 Leak Rate - The gas or mixture of gases in the case, adjusted to a pressure differential of one atmosphere, shall not have a leakage from the case that would permit more than 10 per cent contamination of the filling medium after 1000 hours.

*3.5.8.3.4 Mounting - A flange shall be provided for panel mounting. The flange and panel cutout dimensions shall be in accordance with MS-33545 (ASG).

*3.5.8.4 Contents - The attitude indicator shall contain assemblies, subassemblies, and circuits to provide the following displays.

*3.5.8.4.1 Attitude Display - The attitude display shall basically consist of a bank angle dial and scale, dial masks, mechanism mask, bank indices, a miniature airplane, and a sphere background which is supported and rotated about three servo driven gimbal axes. The overall arrangement of the attitude display shall be in accordance with Figure 2.

*3.5.8.4.1.1 Bank Index - The markings and coloring on the bank index shall be in accordance with Figure 3.

*3.5.8.4.1.2 Miniature Airplane - The markings and coloring on the miniature airplane shall be in accordance with Figure 4.

*3.5.8.4.1.3 Sphere Markings and Colorings -

*3.5.8.4.1.3.1 Top Half - The markings and coloring on the top half sphere shall be in accordance with Figure 5.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.8.4.1.3.2 Bottom Half - The markings and coloring on the bottom half sphere shall be in accordance with Figure 6.

*3.5.8.4.1.4 Bank Scale - The markings and coloring on the bank scale shall be in accordance with Figure 7.

*3.5.8.4.1.5 Power Failure Indicator - The markings and coloring on the power failure indicator shall be in accordance with Figure 8.

*3.5.8.4.1.6 Gimbal System - The gimbal system shall consist of three gimbals whose axes are mutually perpendicular.

*3.5.8.4.1.6.1 Roll Gimbal - The roll gimbal shall be the outer gimbal and shall be capable of rotating 360. The axis of the gimbal shall be perpendicular to the face of the indicator and in line with the center of the sphere. The gimbal shall be driven by the roll servo mechanism. The gimbal shall be designed to mount the bank scale and pitch gimbal.

*3.5.8.4.1.6.2 Pitch Gimbal - The pitch gimbal shall be suspended in the roll gimbal. The axis of the gimbal shall be at right angles to the roll gimbal. axis and in line with the center of the sphere. The gimbal shall be driven by the pitch servo mechanism. The azimuth mechanism shall be mounted on the pitch gimbal.

*3.5.8.4.1.6.3 Azimuth Mechanism - The azimuth mechanism shall consist of a shaft and the azimuth servo mechanism. The shaft shall be mounted so that it is perpendicular to the pitch gimbal axis. The shaft shall support the two sphere halves at their centers. The shaft shall be driven by the azimuth servo mechanism.

*3.5.8.4.1.7 Servo Mechanism -

*3.5.8.4.1.7.1 Roll - The roll servo system shall consist of a synchro control transformer, a servo motor-generator and a gear train. The rotor of the control transformer shall have a 1 to 1 rotation ratio with the roll gimbal. The servo system shall meet the performance requirements herein when connected to the specified roll servo test amplifier.

(a) Control Transformer - The control transformer shall be a Bendix AY-500-5 or equivalent.

(b) Motor Generator - The motor-generator shall be a Bendix FV-123-5-A1 or equivalent.

(c) Gear Train - The gear train shall be designed to provide the specified follow-up rate and accuracy. The gear design shall eliminate noticeable play and backlash.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.8.4.1.7.2 Pitch - The pitch servo system shall consist of a synchro control transormer, a servo motor-generator, and a gear train. The rotor of the control transformer shall have a 1 to 1 rotation ratio with the pitch gimbal. The servo system shall meet the performance requirements herein when connected to the specified pitch servo test amplifier.

(a) Control Transformer - The control transformer shall be a Bendix AY-300-38-A1 or equivalent.

(b) Motor-Generator - The motor-generator shall be a Bendix FV-112-11-A1 or equivalent.

(c) Gear Train - The gear train shall be designed to provide the specified follow-up rate and accuracy. The gear design shall eliminate noticeable play and backlash.

*3.5.8.4.1.7.3 Azimuth - The azimuth servo system shall consist of a synchro control transformer, a servo motor-generator, and a gear train. The rotor of the control transformer shall have a 1 to 1 rotation ratio with the azimuth shaft. The servo system shall meet the performance requirements specified herein when connected to the specified azimuth test amplifier.

(a) Control Transformer - The control transformer shall be identical to the pitch servo control transformer.

(b) Motor-Generator - The motor-generator shall be identical to the pitch servo motor-generator.

(c) Gear Train - The gear train shall be designed to provide the specified follow-up rate and accuracy. The gear design shall eliminate noticeable play and backlash.

*3.5.8.4.2 Pitch Trim - Means shall be incorporated to adjust the position of the sphere in pitch. The adjustment shall be made by a knob on the front panel as in Figure 2. The knob marking the index dot shall be in accordance with Figure 9.

*3.5.8.4.3 Pitch Trim Fade - Means shall be incorporated to fade out the pitch trim as the pitch angle approaches 90° and 270° and to re-insert the trim at inverted and level flight.

*3.5.8.4.4 Roll Trim - Means shall be incorporated to adjust the position of the sphere in roll. The control shall be located on the indicator case.

*3.5.8.4.5 Obliteration of Bank Indices - The bank scale minor indices shall be obliterated as the pitch attitude departs from level and inverted flight.

*3.5.8.4.6 Power Off Warning - A warning flag and an actuating mechanism shall be incorporated to provide front panel warning of AC power interruption or failure. The flag shall be located in accordance with Figure 2.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.8.4.7 Indicator-Programmer Connector - An electrical connector incorporating power and control leads for the Indicator-Programmer ID-695A/AJB-3 shall be mounted on the front of the attitude indicator as shown on MS-17385. An Indicator-Programmer Mounting Adapter per MS-17387 shall be permanetly attached to the front of the indicator.

*3.5.8.4.8 Integral Lighting - The attitude indicator shall be provided with integral lighting in accordance with MIL-L-25467.

*3.5.8.4.8.1 Lamps - The lamps shall be located within the case. Lamps conforming to MS-24367-680 or MS-24515-1 may be used in lieu of, or in addition to, the lamps specified in MIL-L-25467.

*3.5.8.4.9 Cover Glass - The cover glass shall be free from defects which interfere with normal reading of the indicator.

*3.5.8.4.10 Numerals and Letters - Numerals and letters shall be in accordance with Drawing MS33558.

*3.5.8.5 Performance Characteristics - The performance characteristics shall be as follows under standard conditions:

*3.5.8.5.1 Gimbal Freedom - The sphere shall have unlimited freedom in roll, pitch, and azimuth. The bank scale shall have unlimited freedom in roll. There shall be no interference between gimbals and associated mechanisms.

*3.5.8.5.2 Roll Servo - The roll servo performance shall be as follows when connected to the amplifier and voltages specified below:

(a)	Follow-up rate	300°/sec., minimum
(b)	Follow-up error	.4°/RPM
(c)	Overshooting	No overshooting at rates less than 180°/sec.
(d)	Static positional accuracy	
	At 0° and 180°	±0.5°
	Other roll attitudes	±1°

Quadrature stripper - amplifier characteristics, nominal:

(a)	Input impedance	25K ohms
(b)	Load impedance	87 +J109 ohms
(c)	Input saturation E	0.15V rms
(d)	Output E at saturation	15V rms
(e)	Quadrature rejection ratio	16:1
(f)	Null output	3.0V rms, max.
(g)	Input power	115V, Phase C

Voltages, nominal:

(a)	Motor fixed phase	34V, Phase C
(b)	Generator fixed phase	18V, Phase C

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

Synchro Transmitter:

The roll servo synchro control transformer shall be driven by a Kearfott type R510-1A, or equivalent, synchro transmitter.

*3.5.8.5.3 Pitch Servo - The pitch servo performance shall be as follows when connected to the amplifier and voltages specified below:

(a)	Follow-up rate	300°/sec., minimum
(b)	Follow-up accuracy	-0.25°/RPM
(c)	Overshooting	No overshooting at rates less than 180°/sec.
(d)	Static positional accuracy	
	At 0° and 180°	±0.5°
	Other pitch attitudes	±1°

Quadrature stripper - amplifier characteristics, nominal:

(a)	Input impedance	25K ohms
(b)	Load impedance	158 +J104 ohms
(c)	Input saturation E	0.15V, RMS
(d)	Output E at saturation	16V, RMS
(e)	Quadrature rejection ratio	16:1
(f)	Null output	3.5V RMS, max.
(g)	Input power	115V, Phase C

Voltages, nominal:

(a)	Motor fixed phase	21V, Phase C
(b)	Generator fixed phase	18V, Phase C

Synchro Transmitter:

The pitch servo control transformer shall be driven by a Kearfott type R510-1A, or equivalent, synchro transmitter.

*3.5.8.5.4 Azimuth Servo - The azimuth servo performance shall be as follows when connected to the amplifier and voltages specified below:

(a)	Follow-up rate	300°/sec., minimum
(b)	Follow-up accuracy	-0.25°/RPM
(c)	Overshooting	No overshooting at rates less than 180°/sec.
(d)	Static positional accuracy	±1°, any heading

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

Amplifier characteristics, nominal:

(a)	Input impedance	25K ohms
(b)	Load impedance	158 +J104 ohms
(c)	Input saturation E	0.15V, RMS
(d)	Output E at saturation	16V, RMS
(e)	Null output	3.0V RMS, max.
(f)	Input power	115V, Phase C

Voltages, nominal:

(a)	Motor fixed phase	21 V, Ø C ∠90°
(b)	Generator fixed phase	18 V, Ø C

Synchro Transmitter:

The azimuth servo control transformer shall be driven by a Kearfott R510-1A, or equivalent, synchro transmitter.

*3.5.8.5.5 Sensitivity - With zero roll and pitch trim applied, application of 0.25°, from the synchro transmitter, of right and left bank; climb and dive; and left and right turn shall cause perceptible movements of the sphere and bank scale.

*3.5.8.5.6 Pitch Trim - With the synchro transmitter at 0°, rotation of the pitch trim knob to maximum CW position shall cause a 20° (minimum) dive deflection of the sphere and rotation of the knob to maximum CCW position shall cause a 6° (minimum) climb deflection of the sphere. With the pitch trim knob arrow aligned within the edges of the index dot, the horizon line shall be in coincidence with the miniature airplane wings within ½ the width of the horizon line. 18 V, Ø C shall be applied to the fade potentiometer.

*3.5.8.5.7 Pitch Trim Fade - Pitch trim shall start to decrease as the pitch attitude reaches 20° ∠ 10° from 0°. The trim shall completely fade out at 75° ∠ 10°. Zero trim condition exists until 105 ∠ 10° is reached. Trim shall increase until it reaches maximum at 160° 10°. The trim shall remain maximum to 200 ∠ 10°. The trim shall fade out completely when 255 ∠ 10° is reached. Zero trim condition shall exist until 285 ∠ 10° is reached. Trim shall increase until it reaches maximum at 340 ∠ 10° and shall remain maximum back to 0 ∠ 10°, 18 V, Ø C shall be applied to the fade potentiometer.

*3.5.8.5.8 Roll Trim - With the synchro transmitter at 0°, rotation of the roll trim control shaft to its extreme CW and CCW positions shall cause a 3° (minimum) right and left bank, respectively, deflection of the sphere. 18 V, Ø C shall be applied to the primary of the roll trim transformer.

*3.5.8.5.9 Bank Indice Obliteration - As the sphere is rotated in pitch starting at 0° and 180°, the minor roll indices on the bank scale shall be obliterated in the range of ∠35° to ∠75° from the starting point.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.8.5.10 Power Off Warning - Application of 26 V, Ø C to the fixed phase of the actuating motor and 26 V, Ø C ∠90°, to the control phase and grounding the other ends of the winding shall cause the warning flag to disappear within 1 second after application of power. Removal of power shall cause the flag to appear within 1 second.

*3.5.8.5.11 Bombing Mode Relay - The following conditions shall exist without input power applied to the unit.

Prog.-Ind. Connector (J599)	Condition	Rear Connector (J598)	Condition	Rear Connector (J598)
A	50 X	N		
G	50 K	J		
C	1 ohm	J & K		
B	1 ohm	N		
		H	7 ∠3 ohms	K

With 25-29 VDC applied across U and K, dc ground to K, the following conditions shall exist.

(J599)	Condition	(J598)	Condition	(J598)
A	1 ohm	N		
G	1 ohm	J		
C	50 K	J & K		
B	50 K	N		
		H	25 ∠5 ohms	K

*3.5.8.6 Performance at Temperature Extremes - The attitude indicator shall perform as specified herein at temperature extremes except as follows:

*3.5.8.6.1 Sensitivity - The sensitivity with zero trim applied shall be 0.5° in lieu of 0.25°.

*3.5.8.7 Electrical Connections - Connections to external circuits shall be provided as shown in Figure 1.

*3.5.9. Indicator - Programmer ID-695A/AJB-3 - The indicator-programmer shall meet the following requirements:

*3.5.9.1 Function - The indicator-programmer shall provide a visual indication of the positive normal acceleration of an aircraft and a command pointer to provide information for a programmed LABS maneuver as a component of the AN/AJB-3 Loft Bomb Release Computer Set.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.9.2 Form Factor - The indicator-programmer shall be enclosed in a case conforming to the general requirements of MIL-C-172. The outline dimensions of the case shall conform to MS17386.

*3.5.9.3 Case - The case of the indicator-programmer shall be made of non-ferrous, low density metal, uniform in texture, shall have a smooth surface and shall be hermetically sealed. The case shall be finished with a lusterless black material, Color No. 37038 of FED-STD-595.

*3.5.9.3.1 Hermetic Sealing - The case shall provide a hermetically sealed enclosure for all of the mechanism. The case shall be so constructed that it may be opened, the mechanism removed and replaced and the case resealed at least three times. This shall be possible without the use of any special tool, jig or fixture, unless such device is specifically approved by the procuring activity. The sealing of the case shall not be dependent upon any material which will be adversely affected by any atmosphere to which the indicator-programmer may be subjected in normal use in military aircraft.

*3.5.9.3.2 Filling Medium - The filling medium shall be a mixture of 90 percent nitrogen and ten percent helium or 95 percent helium and 5 percent carbon dioxide. The nitrogen used shall be in accordance with Specification BB-N-411, Type I, Class I, Grade C. The filling medium shall contain not more than 0.006 milligram of water vapor per liter (dew point -65°C) at the filling pressure. The absolute pressure of the filling medium in the case shall be 1 ±0.1 atmosphere.

*3.5.9.3.3 Leak Rate - The gas or mixture of gases in the case, adjusted to a pressure differential of one atmosphere, shall not have a leakage from the case that would permit more than 10 percent contamination of the filling medium after 1000 hours.

*3.5.9.3.4 Mounting - The indicator-programmer shall mount to the front of the Attitude Indicator ID-694/AJB-3.

*3.5.9.4 Contents - The indicator-programmer shall contain an indicator and a programmer.

*3.5.9.4.1 Indicator - The indicator shall consist of a bobbin suspended on a spring inside a tube. The tube shall be calibrated from 1 to 5 g in increments of 1 g. The bobbin shall have an index ring which is normally aligned with the 1 g graduation.

*3.5.9.4.1.1 Accuracy - The indicator shall indicate constant accelerations from 1 to 5 g applied along its longitudinal axis toward the bottom of the indicator within ±.15 g.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.9.4.1.2 Transient Response - With a step input from 5 to 1 g accomplished in 0.15 second or less, the indicator shall indicate, within 0/1 g, 1 g within 1.5 seconds after initiation of the step input.

*3.5.9.4.2 Programmer - The programmer shall consist of an index, reversible driving motor and associated mechanism. The index shall move in front of the tube and its ravel shall be between the 1 and 4 g positions. The index shall have an index mark which is normally aligned with the 1 g graduation. The index shall move smoothly at a constant rate.

*3.5.9.4.2.1 Run Down Time - With a 2 mfd, 100 V capacitor connected between pins A and B and 26 V, 400 cps applied to pin A and AC neutral to Pin G, the index shall move from the 1 g to the 4 g position smoothly within 1.8 to 2.2 seconds. The index shall stop at the 4 g graduation within ± .075 g.

*3.5.9.4.2.2 Return Time - Connection of 26 V, 400 cps, to pin B instead of pin A as in paragraph 3.5.1.4.2.1 shall cause the index to return to the 1 g position within 1.8 to 2.2 seconds.

*3.5.9.5 Integral Lighting - The indicator-programmer shall be provided with integral lighting in accordance with Specification MIL-L-25467.

*3.5.9.5.1 Lamps - The lamps shall be located within the indicator-programmer case. Lamps conforming to MS24367-680 or MS24515-1 may be used in lieu of, or in addition to, the lamps specified in Specification MIL-L-25467.

*3.5.9.6 Dial - The dial (consisting of the tube, the bobbin, and the programmer index) shall be as shown on MS17386. The calibration marks on the tube, the index ring on the bobbin, and the programmer index shall be lusterless white, Color No. 37875, of FED-STD-595. The body of the bobbing and the inside of the indicator-programmer case shall be lusterless black, Color No. 37038, of FED-STD-595.

*3.5.9.6.1 Visibility of Dial - All specified markings on the dial shall be visible from any point within the frustum of a cone whose side makes an angle of 30 degrees with a perpendicular to the dial and whose small diameter is the aperture of the indicator-programmer case.

*3.5.9.6.2 Dial Marking - The dial shall be marked as shown on MS17386. Unless otherwise specified, all visible portions of the dial shall be lusterless Black Color No. 37038 of FED-STD-595 and all markings on the dial shall be lusterless white Color No. 37875 of FED-STD-595. All markings shall be durable to withstand usage encountered in service. The form of the numerals and letters shall be in accordance with MS33558. Numerals shall distinctly indicate the graduation to which each applies.

*3.5.9.7 Performance at Temperature Extremes - The indicator-programmer shall perform as specified herein at temperature extremes.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.9.8 Electrical Connections - Connections to external circuits shall be provided by a connector which mates with the connector on Attitude Indicator ID-694/AJB-3.

*3.5.10 Timer, Interval TD-236A/AJB-3 - The Interval Timer shall meet the following requirements:

*3.5.10.1 Function - The interval timer shall provide a speed governed 28 volt DC motor, associated switching mechanisms, a digital time display, and a knob for setting time intervals in flight and shall provide accurately timed electrical signals for the AN/AJB-3 or AN/AJB-3A Loft Bomb Release Computer Set.

*3.5.10.2 Form Factor - The interval timer shall be enclosed in a case conforming to the general requirements of MIL-C-172. The outline dimensions of the case shall conform to MS-17388.

*3.5.10.3 Case - The case of the interval timer shall be made of non-ferrous, low density metal, uniform in texture, having a smooth surface and shall be hermetically sealed. The case shall be finished with a lusterless black material, Color No. 37038 of FED-STD-595.

*3.5.10.3.1 Hermetic Sealing - The case shall provide a hermetically sealed enclosure for all of the mechanism. The case shall be so constructed that it may be opened, the mechanism removed and replaced and the interval timer case resealed at least three times. This shall be possible without the use of any special tool, jig or fixture, unless such device is specifically approved by the procuring activity. The sealing of the case shall not be dependent upon any material which will be adversely affected by any atmosphere to which the instrument may be subjected in normal use in military aircraft.

*3.5.10.3.2 Filling Medium - The filling medium shall be either a mixture of 90% nitrogen and 10% helium or 95% helium and 5% carbon dioxide. The nitrogen used shall be in accordance with Specification BB-N-411, Type I, Class I, Grade C. The filling medium shall contain not more than 0.006 milligram of water vapor per liter (dew point -65°C) at the filling pressure. The absolute pressure of the filling medium in the case shall be 1 $\pm$0.1 atmosphere.

*3.5.10.3.3 Leak Rate - The gas or mixture of gases in the case, adjusted to a pressure differential of one atmosphere, shall not have a leakage from the case that would permit more than 10 per cent contamination of the filling medium after 1000 hours.

*3.5.10.4 Contents - The interval timer shall contain a speed governed DC motor, associated switching mechanisms, a digital time display and a control knob.

*3.5.10.4.1 Output Signals - The unit shall provide output signals as follows:

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*3.5.10.4.1.1 One Second Warning - The one second warning signal shall consist of a DC ground occuring 1.0 ±0.2 seconds before the end of the selected time cycle. The signal shall remain until the unit is reset.

*3.5.10.4.1.2 Time-Out - The time-out signal shall be the input DC voltage occuring at the end of the selected interval within ±0.1 second or 1% of the interval, whichever is greater. The signal shall remain until the unit is reset.

*3.5.10.4.1.3 Circuit Loads - The output signal circuits shall be capable of supplying a minimum of 1 ampere to a resistive load.

*3.5.10.4.2 Function Initiation - The time interval shall be initiated by the application of 25-29 volts DC. The motor shall stop at the end of the time interval and the timing mechanism shall reset upon removal of time interval initiation DC.

*3.5.10.4.3 Range of Operation - The time interval shall be settable to time intervals of 0.1 to 30 seconds in 0.1 second increments. The time settable shall not be greater than 30.9 seconds and not less than 0.1 second.

*3.5.10.4.3.1 Time Interval Selection - A control knob which can be adjusted in flight shall be provided to select the time interval. Positive detent action shall be provided at the 0.1 second increments throughout the adjustment range.

*3.5.10.4.4 Interval Display - The interval display shall be digital and shall display all intervals specified in 3.5.10.4.3. The display shall be visible from any point within the frustum of a cone whose side makes an angle of 30° with a perpendicular to the dial and whose small diameter is the aperture of the case.

*3.5.10.4.4.1 Integral Lighting - The interval timer shall be provided with integral lighting in accordance with MIL-L-25467.

*3.5.10.4.4.2 Dial Marking - The dial shall be marked as shown on MS-17388. All visible portions of the dial shall be lusterless black; Color No. 37038 of FED-STD-595, and all markings on the dial shall be lusterless while; Color No. 37875 of FED-STD-595.

*3.5.10.5 Performance at Temperature Extremes - The performance of the interval timer at temperature extremes shall be as specified herein.

*3.5.10.6 Electrical Connections - Connections to external circuits shall be provided as shown in Figure 1.

*3.6 Design Data - No data is required by this specification (other than reports accompanying samples submitted for testing) or by applicable documents, unless specified in the contract or order (See paragraph 6.7).

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

4. QUALITY ASSURANCE PROVISIONS

*4.1 Responsibility for Inspection - Unless otherwise specified in the contract or purchase order, the supplier is responsible for the performance of all inspection requirements as specified herein. Except as otherwise specified, the supplier may utilize his own facilities or any commercial laboratory acceptable to the Government. The Government reserves the right to perform any of the inspections set forth in the specification where such inspections are deemed necessary to assure supplies and services conform to prescribed requirements.

*4.1.1 Classification of Tests - Items covered by this specification shall be subjected to the following tests to determine compliance with all applicable requirements:

(1) Preproduction Tests
(2) Initial Production Tests
(3) Acceptance Tests
(4) Life Tests

*4.2 Preproduction Tests - Preproduction tests shall be made on an equipment representative of the production equipments to be supplied under the contract. Preproduction tests shall be accomplished under the responsibility of the contractor and shall be conducted in accordance with the approved test procedure of 4.6. The Government inspector and the procuring activity shall be advised when tests are to be conducted so that a representative may be designated to witness or supervise the tests when so desired. Contractors not having adequate facilities to conduct all required tests shall obtain the services of a commercial testing laboratory acceptable to the Government.

*4.2.1 Preproduction Test Data - The contractor shall submit all data collected in conducting these tests to the procuring agency for review and approval. On first production contracts this data shall include a list of all electrical and electronic parts giving their specified voltage, current and temperature rating and the applied circuit voltage, current and ambient and surface temperatures. The ambient and surface temperature shall be obtained under the extreme high temperature operating condition.

*4.2.2 Scope of Tests - Preproduction tests shall include all tests deemed necessary by the procuring activity to determine that the equipmeets all the requirements of this specification and the contract. Preproduction tests shall include environmental tests in accordance with the procedures of Specification MIL-T-5422 and interference tests in accordance with Specification MIL-I-6181.

*4.2.3 Preproduction Approval - Approval of the preproduction sample shall be by the procuring activity upon satisfactory completion of all tests. No production equipments shall be delivered prior to the approval of the preproduction sample. Prefabrication of production equipment prior to

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

the approval of the preproduction sample is at the contractor's own risk. The approved preproduction sample shall be retained by the contractor for his use in the fabrication and testing of equipment to be submitted for acceptance. The preproduction sample shall not be considered as one of the equipments under the contract.

*4.2.4 Production Equipments - Equipments supplied under the contract shall in all respects, including design, construction, workmanship, performance and quality, be equivalent to the approved preproduction sample. Each equipment shall be capable of successfully passing the same tests as imposed on the preproduction sample. Evidence of non-compliance with the above shall constitute cause for rejection and for equipment already accepted by the Government, it shall be the obligation of the contractor to make necessary corrections as approved by the procuring activity.

*4.3 Initial Production Tests - One of the first ten production equipments shall be selected and sent at the contractor's expense to a designated Government laboratory for tests. This equipment shall be selected by the procuring activity after the equipment has successfully passed all individual tests. The preproduction sample shall not be selected for this test.

*4.3.1 Scope of Tests - This equipment may be subjected to any and all tests the procuring activity deems necessary to assure that the production equipment is equivalent to the previously approved preproduction sample in design, construction, workmanship, performance and quality and that it meets all applicable requirements.

*4.3.2 Accessory Material - In addition to the complete equipment submitted for Initial Production Tests the contractor shall also submit such accessory material and data necessary to test the equipment.

*4.3.3 Initial Production Sample Approval - Approval of the Initial Production Sample shall be by the procuring activity upon satisfactory completion of all tests. Any design, material or performance defect made evident during this test shall be corrected by the contractor to the satisfaction of the procuring activity. Failure of the Initial Production Sample to pass any of the tests shall be cause for deliveries of equipment under the contract to cease until proper corrective action is approved and accomplished. Correction action shall also be accomplished on equipment previously accepted when requested by the procuring activity.

*4.3.4 Reconditioning of Initial Production Test Sample - On completion of the initial production test the equipment shall be reworked by the contractor by replacing all wear or damaged items. After reworking, the contractor shall resubmit the equipment for acceptance.

Source: https://assist.dla.mil - Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*4.4 Acceptance Tests - The contractor shall furnish all samples and shall be responsible for accomplishing the acceptance tests. All inspection and testing shall be under the supervision of the government inspector. Contractors not having testing facilities satisfactory to the procuring activity shall engage the service of a commercial testing laboratory acceptable to the procuring activity. The contractor shall furnish test reports showing quantitative results for all acceptance tests. Such reports shall be signed by an authorized representative of the contractor or laboratory, as applicable. Acceptance or approval of material during the course of manufacture shall not be construed as a guarantee of the acceptance of the finished product. Acceptance tests shall consist of the following:

(1) Individual Tests
(2) Sampling Tests
(3) Reliability Assurance Tests
(4) Special Tests

*4.4.1 Individual Tests - Each equipment submitted for acceptance shall be subjected to the individual tests. These tests shall be adequate to determine compliance with the requirements of material, workmanship, operational adequacy and reliability. As a minimum, each equipment accepted shall have passed the following tests:

(1) Examination of Product
(2) Operational Test
(3) Manufacturing Run In Test

*4.4.1.1 Examination of Product - Each equipment shall be examined carefully to determine that the material and workmanship requirements have been met.

*4.4.1.2 Operational Test - Each equipment shall be operated long enough to permit the equipment temperature to stabilize and to check sufficient characteristics and record adequate data to assure satisfactory equipment operation.

*4.4.1.3 Manufacturing Run In Test - Each equipment shall be operated under the conditions specified herein for a period of 6 hours without failure. A failure shall be defined as anything which causes malfunctioning of the equipment. Only those adjustments will be permitted which can be made by using such controls and adjustments that are accessible to the operator during the normal use of the equipment.

Temperature	Ambient room
Humidity	Ambient room
Vibration	Any selected frequency within the range of 20 to 30 cps (excluding resonant points) and a minimum amplitude of ±3 g's except the Displacement Gyroscope Assembly and the

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

Attitude-Director Indicator which shall be at a minimum amplitude of 0.5g's and 1.0g respectively.

The equipment shall be vibrated (without vibration isolators) for a period of 10 minutes prior to the beginning of the 6-hour period of operation. Where feasible, the equipment shall be operated during this vibration period of the purpose of detecting flaws and imperfect workmanship. Operation within the specified limits of satisfactory performance is not necessarily required during the vibration period. The direction of vibration should be vertical to the normal mounting plane for 5 minutes and lateral to the plane for 5 minutes. Where it is not feasible to vibrate the equipment in 2 directions the vertical direction shall be used. During the 6-hour period of operation following the 10-minute vibration period, the equipment shall be mechanically cycled periodically through its various phases of operation. Should a failure occur, it should be repaired and the test started over, except that the 10-minute vibration period need not be repeated when it is certain the failure was not a result of the vibration. Should repetitive failures occur, corrective action shall be taken to eliminate this defect from future equipment. A record shall be kept of all failures. The 6-hour period specified above may be composed of two 3-hour periods to conform with standard working hours.

*4.4.2 Sampling Tests - Equipments selected for sampling tests shall first have passed the individual tests. Equipments shall be selected for sampling tests by the government inspector in accordance with the following: (Sampling tests shall not be conducted unless Reliability Assurance Tests of 4.4.3 are deleted by contractual action.)

Quantity of Equipments Offered for Acceptance	Quantity to be Selected For Sampling Test
First 10	0*
Next 50	1
Next 75	1
Next 100	1
	1 for each additional 200 or fraction thereof

* NOTE: If by contract action the Initial Production Test (4.3) is deleted, then a Sample Test shall be conducted on one equipment from the first 10 produced.

*4.4.2.1 Scope of Tests - As a minimum, each equipment selected for sampling tests shall be subjected to the following tests:

(1) Complete operational test at ambient room conditions, making all necessary measurements to assure that all applicable specification requirements have been met.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

4.4.3 Reliability Assurance Tests - Reliability Assurance Tests shall be conducted using MIL-STD-781. Tests as required by both the Qualification Phase and the Sampling Phase shall be conducted.

4.4.3.1 Qualification Phase - Prior to the acceptance of equipments under the contract or order, minimum of three (3) equipments shall be tested as outlined in MIL-STD-781, under the section entitled "Qualification Phase of Production Reliability Tests". The maximum number of equipments to be used shall be those listed in Table 5 of MIL-STD-781.

4.4.3.2 Reliability Sampling Phase Tests - Samples of the equipment shall be tested as outlined in MIL-STD-781, under the section entitled "Sampling Phase of Production Reliability Tests".

4.4.3.3 Test Level - The test levels for the Qualification Phase and the Reliability Sampling Phase shall be as follows:

Except for the initial temperature cycle of +71°C (+160°F) followed by -54°C (-65°F), the high temperature shall be +55°C (+130°F) and the low temperature shall be -40°C (-40°F). The initial temperature cycle shall be conducted at the start of each system and on each unit thereafter upon repair or replacement. The length of each cycle shall not exceed 24 hours nor shall either of the high or low temperature conditions be less than 4 hours. The equipment shall be vibrated at ½g at a non-resonant frequency between 20 and 60 cps for 10 minutes at each extreme temperature. No unit shall be subjected to temperature or vibration conditions exceeding the unit specification requirements.

4.4.3.3.1 Duty Cycle - Upon receipt of the equipment, following operational tests (or debugging) the system shall be placed in a chamber at +71°C (+160°F) and operated for 4 hours using nominal voltage. The system shall be tested by Scorsby motion during this test (at least ±5°). The system shall then be tested at -54°C (-65°F).after a 4-hour soak at -54°C (-65°F). The system shall then be tested as follows:

The system shall be operated for 2½ hours at nominal voltage and shall be de-energized for ½ hour. This duty cycle shall be conducted at least eight times each day. Time counted toward the reliability tests shall be the sum of all 2½ hour running periods.

Following the initial hot and cold tests of the one temperature cycle (see 4.4.3.3), the tests shall continue at -40°C (-40°F) to +55°C (+130°F). At all times when power is applied during the Reliability test, including heat and cold (except for a period including the starting cycle on each start and not to exceed 5 minutes) the displacement gyro, the rate switching gyro, and the proportional rate gyro shall be on a Scorsby table operating at between 5 and 7 cycles per minute and at an angle sufficient to cause positive switching of the rate switching gyro.

*4.4.3.4 Lot Size for Sampling Phase - To evaluate whether the contracted MTBF is being met, the entire contract quantity (with the exception of those equipments used in the Qualification Phase) shall be considered one lot.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

The test program shall start the first month after the Qualification Phase has been completed Samples of each month's production shall be selected and placed on test in the same manner as though one month's production was a lot. The samples shall be tested until an accept or reject decision is reached. In the meantime, other equipments constructed shall be shipped. The test results shall be summarized monthly for the procuring activity. The procuring activity reserves the right to stop the acceptance of equipment at any time after one or more reject decisions have been reached, pending a review of the contractor's efforts to improve the equipment, the equipment parts, the equipment quality control etc., so that the entire contract quantity will show an accept decision.

4.4.3.5 Test Details - The test details such as the length of the Test cycle, the length of the heat portion of the cycle, the performance characteristics to be measured, special failure criteria, preventive maintenance to be allowed during the test etc., shall be part of the test procedures to be submitted and approved by the procuring activity prior to the beginning of the Qualification Test Phase of the Reliability Assurance Tests.

*4.4.3.6 Accept-Reject Criteria - Test plan III of MIL-STD-781 shall be used to determine the accept-reject criteria for the Reliability Qualification Test Plan. Test plan IV of MIL-STD-781 shall be used to determine the accept-reject criteria for Reliability Sampling Test Plan.

*4.4.3.7 Performance Characteristics to be Measured - The performance characteristics to be measured shall be as specified in 6.9.

*4.4.3.8 Failure Criteria - In addition to the requirements of MIL-STD-781, the following requirements shall be used to determine when a failure has occurred during the test:

(1) Whenever performance characteristics fall below the acceptance requirement (paragraph 4.4.3.7) at least one failure has occurred. If subsequent analysis reveals that several parts have deteriorated, each shall be counted a failure, unless one caused the other parts to fail.

*4.4.3.9 Preventive Maintenance - During the test no preventive maintenance, other than simple adjustments normally performed on the equipment by the operator, shall be permitted. However, a log of all such adjustments shall be kept. The procuring activity may weight these adjustments and if it feels justified assign excessive ones as failures.

*4.4.3.10 Additional Requirements - The procedure set forth herein requires a complete system or a suitable simulation of the system loads and sequencing when the test is applied for the item specified.

*4.4.4 Special Tests - Special tests shall be conducted on a quantity of equipments for the purpose of checking the effect of any design or material change on the performance of the equipment and to assure adequate quality control. The equipment selected for special tests may be selected from equipments previously subjected to the sampling or reliability assurance tests.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*4.4.4.1 Special Test Schedule - Selection of equipments for special tests shall be made as follows:

(1) On an early equipment after an engineering or material change.

(2) Whenever failure reports of other information indicate additional tests are required. (This will be determined by the procuring activity.)

*4.4.4.2 Scope of Tests - Special tests shall consist of such tests as approved by the procuring activity. Test procedures previously approved for the preproduction tests shall be used where applicable. When not applicable, the contractor shall prepare a test procedure and submit it to the procuring activity for approval prior to conducting the tests.

*4.4.5 Equipment Failure - Should a failure occur during either the sampling, reliability assurance or special tests, the following action shall be taken:

(1) Determine the cause of failure.

(2) Determine if the failure is an isolated case or design defect.

(3) Submit to the procuring activity for approval, proposed corrective action intended to reduce the possibility of the same failure(s) occurring in future tests.

(4) Where practical, include a test in the individual test to check all equipment for this requirement until reasonable assurance is obtained that the defect has been satisfactorily corrected.

*4.5 Life Test - The contractor shall furnish all samples and shall be responsible for accomplishing the life test. The test shall be of 1000 hour duration and shall be conducted on equipments that have passed the individual test. The life test shall be performed under the conditions specified in 4.5.1. The life test sample shall be selected by the government inspector in accordance with the following. (Equipments which have successfully passed the Initial Production Test, Sampling Tests, Reliability Tests, or Special Tests may be selected for life tests.) When reliability tests are conducted, the life test may be omitted if, during the reliability tests, a quantity of equipments equal to, or more than, that listed below receive at least 1000 hours each of test time on samples and all parts.

Quantity of Equipments Offered for Acceptance	Quantity to be Selected for Life Test
First 25	1
Next 175	1
Next 300	1
	1 for each additional 500 or fraction thereof

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*4.5.1 Test Conditions - The life test shall be conducted under the following simulated service conditions:

Temperature	Normal room
Altitude	Normal ground (0 - 5000 ft.)
Humidity	Room ambient
A. C. Voltage	115 ± 5 volts (at lowest applicable frequency)
D. C. Voltage	27.0 ± 2.0 volts

*4.5.2 Test Periods - The test may be run continuously or intermittently. Any period of operation shall be of sufficient duration to permit the equipment temperature to stabilize. Periodically, the equipment shall be turned on and off several times and put through its various phases of operation.

*4.5.3 Performance Check - At approximately 8-hour intervals during the test, a limited performance check shall be made. The performance check proposed by the contractor shall be subject to approval by the procuring activity.

*4.5.4 Test Data - The contractor shall keep a daily record of the performance of the equipment, making particular note of any deficiencies or failures. In the event of part failures, the defective part shall be replaced and the operation resumed for the balance of the test period. A record shall be kept of all failures throughout the test, including all tube failures. This record shall indicate the following:

(1) Part type number
(2) The circuit reference symbol number
(3) The part function
(4) Name of the manufacturer
(5) Nature of the failure
(6) The number of hours which the part operated prior to failure

*4.5.4.1 Failure Report - In the event of a failure, the government inspector shall be notified immediately. A report shall be submitted to the procuring activity upon completion of the test. In this report, the contractor shall propose suitable and adequate design or material corrections for all failures which occurred. The procuring activity will review such proposals and determine whether they are acceptable.

*4.5.5 Reconditioning of the Life Test Samples - An equipment which has been subjected to the life test shall be reconditioned as follows:

(1) On completion of the life test, the equipment shall be reworked by the contractor by replacing all "wear" items. The "wear" items shall be determined by agreement between the contractor and the procuring activity.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

(2) After reworking, the contractor shall resubmit the equipment for acceptance.

*4.6 Test Procedures - The procedures used for conducting preproduction tests, acceptance tests and life tests shall be prepared by the contractor and submitted to the procuring activity for review and approval. The right is reserved by the procuring activity or the government inspector to modify the tests or require any additional tests deemed necessary to determine compliance with the requirements of this specification or the contract. Specification MIL-T-18303 shall be used as a guide for preparation of test procedures. When approved test procedures are available from previous contracts such procedures will be provided and may be used when their use is approved by the procuring activity. However, the right is reserved by the procuring activity to require modification of such procedures, including additional tests, when deemed necessary.

*4.7 Reconditioning of Tested Equipment - Equipment which has been subjected to acceptance and life tests shall be reconditioned by the contractor by replacing all wear or damaged items. After reworking the contractor shall resubmit the equipment for acceptance.

*4.8 Presubmission Testing - No item, part or complete equipment shall be submitted by the contractor until it has been previously tested and inspected by the contractor and found to comply, to the best of his knowledge and belief, with all applicable requirements.

*4.9 Rejection and Retest - Equipment which has been rejected may be reworked or have parts replaced to correct the defects and resubmitted for acceptance. Before resubmitting, full particulars concerning previous rejection and the action taken to correct the defects found in the original shall be furnished the government inspector.

5. PREPARATION FOR DELIVERY

*5.1 General - All major units and parts of the equipment shall be preserved, packaged, packed and marked for the level of shipment specified in the contractor or order in accordance with Specification MIL-E-17555.

6. NOTES

6.1 Intended Use - The equipment covered by this specification is intended for use in aircraft to provide an all-attitude flight reference system plus a correlated loft bomb release system providing flight director and bomb release information for either high or low angle loft bomb release maneuvers.

*6.2 Test Values - Normal and limiting values of performance data shall be determined at input voltages of 27.5 ± 0.5 V DC and 115 ± 1.0 V AC as applicable. These data are to be used in testing the equipment at installation points for compliance with minimum acceptance standard of performance.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*6.3 Performance Objectives - Minimum size and weight, simplicity of operation, ease of maintenance, and an improvement in the performance and reliability of the specific functions beyond the requirements of this specification are objectives which shall be considered in the production of this equipment. Where it appears a substantial reduction in size and weight or improvement in simplicity of design, performance, ease of maintenance or reliability will result from the use of materials, parts and processes other than those specified in Specification MIL-E-5400, it is desired their use be investigated. When investigation shows advantages can be realized, a request for approval shall be submitted to the procuring activity for consideration. Each request shall be accompanied by complete supporting information.

*6.4 As a general rule non-repairable subassemblies should be encapsulated or hermetically-sealed. The number of connections internal to the subassembly should be held to a minimum. Detail parts tolerances and ratings should be so selected that the life of the subassembly is greater than that of a similar repairable one. With few exceptions (such as high voltage power supplies), the non-repairable subassembly should evidence a Mean-Time-to-Failure greater than 5000 hours, and for many applications this figure must be nearer 50,000 hours.

*6.5 Precedence of Documents - When the requirements of the contract, this specification, or applicable subsidiary specifications are in conflict, the following precedence shall apply:

(1) Contract - The contract shall have precedence over any specification.

(2) This Specification - This specification shall have precedence over all applicable subsidiary specifications. Any deviation from this specification, or from subsidiary specifications where applicable, shall be specifically approved in writing by the procuring activity.

(3) Referenced Specifications - Any referenced specification shall have precedence over all applicable subsidiary specifications referenced therein. All referenced specifications shall apply to the extent specified.

6.6 Ordering Data - Purchasers should exercise any desired options offered herein, and procurement documents should specify the following:

(1) Title, number and date of this specification.
(2) Selection of applicable levels of packaging and packing (see 5.1).
(3) Data requirements (see 3.6).

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

6.7 Asterisk - In specification revisions and superseding amendments an asterisk "*" preceding a paragraph number denotes paragraphs in which changes have been made from the previous issue. This has been done as a convenience only and the government assumes no liability whatsoever for any inaccuracies in these notations. Bidders and contractors are cautioned to evaluate the requirements of this document based on the entire content as written, irrespective of the asterisk notations and relationship to the last previous issue.

*6.8 Items of Equipment - The equipment covered by this specification shall consist of the following items:

Item	Type Designation	Applicable Paragraph	MTBF
Adapter-Compensator, Compass	MX-2488A/AJB-3	3.5.1	800
Amplifier-Power Supply	AM-1931/AJB-3	3.5.2	1000
Computer, Bomb Release, Angle	CP-410/AJB-3	3.5.3	1500
Controller, Compass System	C-2499A/AJB-3	3.5.4	2000
Distribution Box	J-1122/AJB-3A	3.5.5	2500
Gyroscope Assembly, Displacement	CN-494A/AJB-3	3.5.6	600
Gyroscope, Rate Switching	CN-495A/AJB-3	3.5.7	1000
Indicator, Attitude	ID-694/AJB-3	3.5.8	1000
Indicator-Programmer	ID-695A/AJB-3	3.5.9	2500
Timer, Interval	TD-236A/AJB-3	3.5.10	2000

*6.8.1 Associated Equipment - The equipment shall operate with the following associated equipment:

Equipment
Transmitter, Remote Compass, Thin Wing,
Type ML-1 (unstabilized)
ID-663 BDHI (2 units thru size 11 CDX synchro)
AFCS (12.4 ± 1/4) voltage output

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

*6.9 Performance Characteristics to be Measured - Tests necessary to determine failures in performance characteristics (listed below) shall be conducted at least once every 24 hours. If operation is extended over a weekend, the tests may be conducted on the day prior to and the day following the weekend in lieu of the 24-hour tests for the weekend. A failure shall be defined to be any of the following conditions:

1. Any failure which prevents the presentation of accurate roll, pitch, or azimuth information (±2 degrees) to the observer.

2. Any intermittent condition which causes jumping in the roll, pitch, or azimuth indication. Disqualifying jumping shall be jumping of 3 degrees or more.

3. Any failure which interferes with the ability to "drop" bombs in the normal manner.

4. Any draft rate of the vertical gyro which exceeds 45 degrees per hour, when the erection circuits are de-energized.

5. Any azimuth drift which exceeds 12 degrees per hour, after correction for earth rate effects. Azimuth compensating circuits are to be ineffective during this test.

6. Any azimuth drift exceeding 9 degrees per hour, uncorrected for earth rate effects and compensated by the proper compensating circuits.

*6.10 Applicable Documents -

SPECIFICATIONS

Federal

BB-N-411	Nitrogen

Military

MIL-C-172	Cases; Bases, Mounting; and Mounts, Vibration (for use with Electronic Equipment in aircraft)

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

MIL-W-5088	Wiring; Aircraft, Installation of
MIL-E-5400	Electronic Equipment, Aircraft, General Specification for
MIL-T-5422	Testing, Environmental, Aircraft Electronic Equipment
MIL-I-6181	Interference Control Requirements, Aircraft Equipment
MIL-C-6781	Control Panel: Aircraft Equipment, Rack or Console Mounted
MIL-P-7788	Plate, Plastic Lighting
MIL-M-7793	Meter; Time Totalizing
MIL-S-16892	Synchros, 400 Cycle
MIL-E-17555	Electronic and Electrical Equipment and Associated Repair Parts, Preparation for Delivery of
MIL-T-18303	Test Procedures; Preproduction and Inspection, For Aircraft Electronic Equipment, Format for
MIL-N-18307	Nomenclature and Nameplates for Aeronautical Electronic and Associated Equipment
MIL-T-19576	Transmitter, Remote Compass, Thin Wing, Type ML-1 (unstabilized)
MIL-L-25467	Lighting, Integral, Instrument, General Specification for
JAN-F-675	Anti-Reflective Coatings

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.

STANDARDS

Federal

FED-STD-595	Colors

Military

MIL-STD-704	Electric Power, Aircraft, Characteristics and Utilization of
MIL-STD-781	Reliability Tests Exponential Distribution
MS-17378	Amplifier-Power Supply AM-1931/AJB-3
MS-17379	Computer, Bomb Release, Angle CP-410/AJB-3
MS-17381	Distribution Box J-1122/AJB-3A
MS-17382	Gyroscope Assembly, Displacement CN-494A/AJB-3
MS-17384	Gyroscope, Rate Switching CN-495A/AJB-3
MS-17388	Timer, Interval TD-236A/AJB-3
MS-17386	Indicator-Programmer ID-695A/AJB-3
MS-17377	Adapter-Compensator, Compass MX-2488A/AJB-3
MS-24515	Lamp - Sub Miniature
MS-17380	Controller, Compass System C-2499A/AJB-3
MS-17385	Indicator, Attitude ID-694/AJB-3
MS-17387	Adapter Kit, Indicator-Programmer Mounting
MS-24367	Lamp, Incandescent-Miniature Integral Lighting
MS-33545	Case - Instrument, 5 X 5 ¾, Standard Dimensions for
MS-33558	Numerals and Letters, Aircraft Instrument Dial, Standard Form of

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:42Z
Check the source to verify that this is the current version before use.