MILITARY SPECIFICATION

REGULATOR CONTROL PANEL, AIRCRAFT DIRECT
CURRENT GENERATOR, 28 VOLT

This amendment forms a part of Military Specification
Sheet MIL-R-23761/1A(AS) dated 30 June 1977.

Page 1

Control Panel Drawing: Delete "CONCEALED VOLTAGE ADJ. SEE REQ. 27." Also delete drawing markings associated with above note.

Page 2

Control Panel Connection Diagram: Add "P/N M6106/30-1" after line contactor and "P/N M6162/1-2" after starter-generator, and label right-hand component, shown in dotted lines, as "CONTROL PANEL."

Page 3

REQUIREMENT 4: Delete and substitute the following: "Voltage Adjustment - No adjustment on the control panel shall be accessable when the control panel is installed." The voltage setting of the control panel during manufacture shall be fixed at 27.75 ± 0.25 volts at 10,000 rpm generator speed and 200 amperes load. The voltage adjustment shall not change as a result of shock and vibration."

REQUIREMENT 5: Add the following: "The equalizer circuit shall be closed when the potential at the point of regulation is 24 ± 1 volts, the generator switch is in the ON position and the field relay is closed. The equalizer circuit shall be opened when the panel is tripped, the generator control switch OFF, or the potential at the point of regulation drops to 19 ± 1 volts."

REQUIREMENT 10: Add the following: "When the generator is energized with a fault on its feeder, the control panel shall de-energize the generator before 0.5 volt appears across the generator equalizer."

REQUIREMENT 11: Delete the three sentences and substitute the following: "The control panel shall include and overvoltage protective function. The overvoltage device shall selectively trip the faulty generator

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:48Z
Check the source to verify that this is the current version before use.

system and shall not cause nuisance tripping of other systems on the line. The time intervals corresponding to overvoltage values on bus shall meet the requirements of MIL-STD-704. The maximum time required for the control panel to open the field of the generator shall be in accordance with the following table."

Page 5

REQUIREMENT 27: Delete and substitute the following: "Self-Excitation - When the control panel is reset, the control panel shall provide less than 0.2 ohm resistance in series with the field circuit during self-excitation of the generator."

TESTS, 1: Delete "MIL-G-6162" and substitute "MIL-R-23761."

TESTS, 2: Delete and substitute the following: "Acceptance Tests -The acceptance tests specified in MIL-R-23761 shall be performed to the requirements specified therein or as modified herein using an M6162/1-2 generator."

Preparing Activity:
Navy - AS
Project No. 6110-N223

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T17:48Z
Check the source to verify that this is the current version before use.