INCH-POUND

MIL-M-28787/152A
AMENDMENT 2
30 September 1992
SUPERSEDING
AMENDMENT 1
15 August 1985

MILITARY SPECIFICATION

MODULES, STANDARD ELECTRONIC

DRIVER, LAMP/RELAY, DIGITAL, KEY CODE ABF

This amendment forms a part of Military Specification MIL-M-28787/152A(EC), dated 15 June 1982, and is approved for use by all Departments and Agencies of the Department of Defense.

PAGE 2

*4.4.2: Delete and substitute the following:

"4.4.2 Order of testing. Test conditions A through N shall be performed in any order with the following exceptions. Test conditions A, B, and L are stress tests and shall be performed only at 25 ± 5°C. If test conditions A, B, or L are part of a sequence of tests, the order of testing shall be as follows: L, A, and B where applicable, followed by the remaining tests in the sequence."

PAGE 4

TABLE I, Test conditions A1-A8, Parameter column: Delete "Static output current (50 V)" and substitute "Static input current (50 V)".

TABLE I, Test conditions B1-B4, Parameter column: Delete "Collector to emitter current (50 V)" and substitute "Collector to emitter leakage current (50 V)".

PAGE 5

*TABLE I, Test conditions L1 and L2, Test type columns: Delete "Q" (two places) and substitute "S" (two places).

DISTRIBUTION STATEMENT A. Approved for public release; distribution is unlimited.

Source: https://assist.dla.mil -- Downloaded: 2026-10-20T16:18Z
Check the source to verify that this is the current version before use.

PAGE 6

*4.5.1, fifth and sixth lines: Delete "C through L, and N" and substitute "C through K, M, and N".

PAGE 26

TABLE VIII: Delete and substitute new table VIII as printed on page 3 of this amendment.

PAGE 34

*FIGURE 14, Item R06 box: Delete "100 ± 10 Vdc" and substitute "See note 3".

*FIGURE 14, NOTES: Add a new note 3 as follows: "3. For L1, use 100 ± 10 Vdc.
For L2, use 30 ± 3 Vdc."

NOTE: The margins of this amendment are marked with an asterisk or vertical lines to indicate where changes (additions, modifications, corrections, deletions) from the previous amendment were made. This was done as a convenience only and the Government assumes no liability whatsoever for any inaccuracies in these notations. Bidders and contractors are cautioned to evaluate the requirements of this document based on the entire content irrespective of the marginal notations and relationship to the last previous amendment.

Custodians:
Army - ER
Navy - SH
Air Force - 85

Review activities:
Army - AT
Navy - AS, MC
Air Force - 13, 19
DLA - ES

Preparing activity:
Navy - NW

(Project 5963-0146)

Source: https://assist.dla.mil -- Downloaded: 2026-10-20T16:18Z
Check the source to verify that this is the current version before use.

TABLE VIII. Input threshold voltages (low-level and high-level) test.

Test cond	ABF input	Logic level	Vcc voltage (± 1%) 1/	Acceptance requirements 25°C ± 5°C ambient temperature 1/		0°C to 60°C 1/ Operating temperature	
				Initial	End-of-life	Initial	End-of-life
F1-F12	A and B	Low	4.5 V	0.8	1.1	1.0	1.3
F13-F16	E	Low	4.5 V	1.5	1.7	1.6	1.9
F17-F24	A and B	Low	22.5 V	12.0	13.3	13.3	14.5
F25-F28	E	Low	22.5 V	12.5	13.8	13.8	15.0
G1-G4	ALL	High	5.5 V	3.5	3.7	3.9	4.0
G5-G8	ALL	High	27.5 V	25.5	25.7	25.9	26.0
		High	Vcc	Vcc -2.0V	Vcc -1.8V	Vcc -1.6V	Vcc -1.5V

1/ When performing tables VI, VII, and figures 9 and 10 tests, adjust item P01-1 voltage (V_{CC}) as specified in the V_{CC} column and adjust item P01-2 voltage (V_{IN}) as specified in this table.

Source: https://assist.dla.mil -- Downloaded: 2026-10-20T16:18Z
Check the source to verify that this is the current version before use.