inspection requirements as specified herein. Except as otherwise specified in the contract or order, the contractor may use his own or any other facilities suitable for the performance of the inspection requirements specified herein, unless disapproved by the Government. The Government reserves the right to perform any of the inspections set forth in the specification where such inspections are deemed necessary to assure supplies and services conform to prescribed requirements.

4.1.1 Dissassembly inspection. Failure of any test by the preproduction model shall be cause for disassembly, in the presence of a Government representative, of the preproduction model to the extent necessary to determine the cause of failure. Each disassembled part shall be examined in detail for compliance with this specification and referenced drawings in regard to materials, dimensions, tolerances, and workmanship. Parts not complying with such requirements shall be rejected.

4.2 Classification of inspections. Inspections shall be classified as follows:

a. Preproduction inspection (see 4.3).
b. Quality conformance inspection (see 4.4).
c. Inspection of packaging (see 4.6).

4.3 Preproduction inspection.

4.3.1 Examination. The preproduction inverter assembly shall be examined as specified in 4.5.1. Presence of one or more defects shall be cause for rejection.

4.3.2 Tests. The inverter assembly shall be subjected to the tests marked "X" in column 1 of table I. Failure of any test shall be cause for performing the inspection specified in 4.1.1.

4.4 Quality conformance inspection.

4.4.1 Sampling. Sampling for examination and tests shall be in accordance with MIL-STD-105, Inspection Level S-3.

4.4.2 Examination. Samples selected in accordance with 4.4.1 shall be examined as specified in 4.5.1. AQL shall be 4.0 percent defective.

4.4.3 Tests.

4.4.3.1 Individual. Each inverter assembly shall be subjected to the tests marked "X" in column 2 of table I. Failure of any test shall be cause for rejection.

4.4.3.2 Samples. Samples selected in accordance with 4.4.1 shall be subjected to the tests marked "X" in column 3 of table I. Failure of any test shall be cause for rejection.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T21:15Z
Check the source to verify that this is the current version before use.

4.5 Inspection procedures.

4.5.1 Examination. The inverter assembly shall be examined as specified herein for the following defects:

Major

101. Dimensions not as specified.
102. Absence of parts or components.
103. Misalignment of parts or components.
104. Materials or components not as specified.
105. Dials not legible.
106. Wiring and connections not as specified.
107. Treatment and painting not as specified.
108. Identification markings not as specified.
109. Workmanship not as specified.
110. Fungus and moisture resistance not as specified.

4.5.2 Test schedule. Tests shall be in accordance with table I. Tests shall be conducted in the sequence listed.

TABLE I. Test schedule.

Preproduction model	Quality conformance		Test	Test paragraph	Requirement paragraph
	Indiv.	Sample			
1	2	3	4	5	6
X	X	-	Operation.	4.5.2.1.1	3.4
X	-	-	Shock.	4.5.2.1.2	3.4.1
X	-	-	Vibration.	4.5.2.1.3	3.4.1
X	-	-	Temperature and humidity.	4.5.2.1.4	3.5
X	-	-	Waterproofing.	4.5.2.1.5	3.6
X	-	X	Operational reliability.	4.5.2.1.6	3.7

4.5.2.1 Test procedures. Voltage, current, and frequency shall be measured by laboratory-type, direct-reading meters which have been calibrated within 30 days prior to the start of testing and at intervals not more than 6 months during the test period. The voltage and current meters shall have at least 1 percent accuracy and shall be connected to indicate in the most accurate portion of the range.

4.5.2.1.1 Operation. The inverter assembly shall be operated for not less than 1 hour with each input as specified in 3.4 and its output voltage, current, and frequency recorded by means of laboratory-type direct-reading meters (see 4.5.2.1). Failure of the inverter assembly to supply rated current (see 6.4.2),

Source: https://assist.dla.mil -- Downloaded: 202610-22T21:15Z
Check the source to verify that this is the currentversion before use.

voltage, and frequency under each input condition specified in 3.4, failure of the voltage control, or any evidence of damage shall constitute failure of this test.

4.5.2.1.2 Shock. The inverter assembly shall be tested as specified in MIL-STD-202, Method 213, Test Condition A. Upon completion of the shock test, perform the test specified in 4.5.2.1.1. Failure to operate under any input condition or evidence of damage shall constitute failure of this test.

4.5.2.1.3 Vibration. The inverter assembly shall be tested as specified in MIL-STD-202, Method 201. Upon completion of the vibration test, perform the test specified in 4.5.2.1.1. Failure to operate under any input condition or evidence of damage shall constitute failure of this test.

4.5.2.1.4 Temperature and humidity. The temperature in the test chamber shall be maintained within 4° F of test temperature throughout the test.

4.5.2.1.4.1 Low temperature. Place the inverter assembly in a test chamber and expose it to a temperature of minus 65° F for 12 hours. With input connected to a source of 24 volts dc and its output set at 120 volts, operate the inverter assembly connected to rated load (see 6.4.2) for 2 hours. Failure to operate or any evidence of damage shall constitute failure of this test.

4.5.2.1.5 Waterproofing. Immerse the inverter assembly for 1 hour under 3 feet of salt water having a specific gravity of 1.04 at 75° F plus or minus 5° F. Within 3 minutes after removal from the salt water, test the inverter assembly as specified in 4.5.2.1.1. Evidence of water in the inverter assembly or failure to operate with any input condition shall constitute failure of this test.

4.5.2.1.6 Operational reliability. Subject the inverter assembly to the test specified in 4.5.2.1.1 at input voltages of 24 volts dc, 120 volts, 60 Hertz, and 120 volts, 400 Hertz. The duration of operation with each input condition shall be 10 hours. Repeat this test four times. Inabilitiy of the inverter assembly to operate for a total of 40 hours with each input condition shall constitute failure of this test.

4.6 Inspection of packaging.

4.6.1 Quality conformance inspection of pack.

4.6.1.1 Unit of product. For the purpose of inspection, a completed pack prepared for shipment shall be considered a unit of product.

4.6.1.2 Sampling Sampling for examination shall be in accordance with MIL-STD-105.

4.6.1.3 Examination. Samples selected in accordance with 4.6.1.2 shall be examined for the following defects. AQL shall be 2.5 percent defective.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T21:15Z
Check the source to verify that this is the current version before use.

111. Materials, methods, and containers not as specified for level A or B.
112. Contents not cushioned as specified for level A.
113. Box closure not as specified for level A.
114. Gross weight exceeds that specified for level A.
115. Gross weight or size exceeds the limitations of the box specification for level B.
116. Marking missing, illegible, incorrect, or incomplete for level A, B, or commercial.

5. PACKAGING

5.1 Preservation. Preservation shall be level A, or commercial, as specified (see 6.2).

5.1.1 Level A. Each complete inverter assembly shall be contained in a close fitting box conforming to PPP-B-636, W6c, style optional. The contents shall be cushioned to prevent damage and free movement within the box. The box shall be closed and secured in accordance with method V of the appendix to the box specification.

5.1.2 Commercial. Each complete inverter assembly shall be preserved in accordance with MIL-STD-1188.

5.2 Packing. Packing shall be level A, B, or commercial, as specified (see 6.2).

5.2.1 Level A. The inverter assemblies preserved as specified in 5.1 shall be packed together in close-fitting boxes conforming to PPP-B-601, Overseas Type, style optional, in quantities not to exceed 250 pounds gross weight. Box closure and strapping shall be in accordance with the appendix to the box specification.

5.2.2 Level B. The inverter assemblies preserved as specified in 5.1 shall be packed together in close-fitting boxes conforming to PPP-B-636, V3c, style optional or PPP-B-640, Class 2, style optional. The gross weight or size of each box shall not exceed the limitations of the applicable box specification. Box closure and strapping shall be in accordance with the appendix to the applicable box specification.

5.2.3 Commercial. The inverter assemblies shall be packed in accordance with MIL-STD-1188.

5.3 Marking.

5.3.1 Military. Marking for military levels of protection (level A or B) shall be in accordance with MIL-STD-129.

5.3.2 Commercial. Marking for commercial packaging shall be in accordance with MIL-STD-1188.

Source: https://assist.dla.mil -- Downloaded: 202640-22T21:15Z
Check the source to verify that this is the currenversion before use.

6. NOTES

6.1 Intended use. These inverter assemblies are intended to supply auxiliary power for Light Assembly, Marker conforming to MIL-L-52292.

6.2 Ordering data. Procurement documents should specify the following:

a. Title, number, and date of this specification.
b. Date of issue of DoDISS applicable and exceptions thereto (see 2.1.1).
c. When a preproduction model is not required (see 3.2).
d. Time frame required for submission of the preproduction model when applicable (see 3.2).
e. When treatment, painting or color shall be other than as specified (see 3.8).
f. Degree of preservation and packing required (see 5.1 and 5.2).

6.3 Preproduction model. Any changes or deviations of production inverter assemblies from the approved preproduction model during production will be subject to the approval of the contracting officer. Approval of the preproduction model will not relieve the contractor of his obligation to furnish inverter assemblies conforming to this specification.

6.4 Definitions.

6.4.1 Damage. Damage is deformation, loosening, breakage, corrosion, or change of fit of any component or part, or any condition resulting in noncompliance of any requirement in this specification.

6.4.2 Rated load. Rated load is 60 volt-amperes at 120 volts.

Custodian:
Army - ME

Review activities:
Army - ER, CR

Preparing activity:
Army - ME

Project 6230-A263

Source: https://assist.dla.mil -- Downloaded: 202640-22T21:15Z
Check the source to verify that this is the current version before use.

Source: https://assist.dla.mil -- Downloaded: 202610-22T21:15Z
Check the source to verify that this is the current version before use.

STANDARDIZATION DOCUMENT IMPROVEMENT PROPOSAL

INSTRUCTIONS: This form is provided to solicit beneficial comments which may improve this document and enhance its use. DoD contractors, government activities, manufacturers, vendors, or other prospective users of the document are invited to submit comments to the government. Fold on lines on reverse side, staple in corner, and send to preparing activity. Attach any pertinent data which may be of use in improving this document. If there are additional papers, attach to form and place both in an envelope addressed to preparing activity. A response will be provided to the submitter, when name and address is provided, within 30 days indicating that the 1426 was received and when any appropriate action on it will be completed.

NOTE: This form shall not be used to submit requests for waivers, deviations or clarification of specification requirements on current contracts. Comments submitted on this form do not constitute or imply authorization to waive any portion of the referenced document(s) or to amend contractual requirements.

DOCUMENT IDENTIFIER *(Number)* AND TITLE MIL-I-52358B(ME) Inverter Assembly for Light Set, Marker, Landing and Drop Zone

NAME OF ORGANIZATION AND ADDRESS OF SUBMITTER

☐ VENDOR ☐ USER ☐ MANUFACTURER

1. ☐ HAS ANY PART OF THE DOCUMENT CREATED PROBLEMS OR REQUIRED INTERPRETATION IN PROCUREMENT USE? ☐ IS ANY PART OF IT TOO RIGID, RESTRICTIVE, LOOSE OR AMBIGUOUS? PLEASE EXPLAIN BELOW.

A. GIVE PARAGRAPH NUMBER AND WORDING

B. RECOMMENDED WORDING CHANGE

C. REASON FOR RECOMMENDED CHANGE(S)

2. REMARKS

SUBMITTED BY *(Printed or typed name and address — Optional)*

TELEPHONE NO.

DATE

DD FORM 1 OCT 76 1426 EDITION OF 1 JAN 72 WILL BE USED UNTIL EXHAUSTED.

Source: https://assist.dla.mil -- Downloaded: 202610-22T21:15Z
Check the source to verify that this is the current version before use.

FOLD

DEPARTMENT OF THE ARMY

OFFICIAL BUSINESS
PENALTY FOR PRIVATE USE $300

NO POSTAGE
NECESSARY
IF MAILED
IN THE
UNITED STATES

BUSINESS REPLY CARD

FIRST CLASS PERMIT NO. 12062 WASHINGTON D. C.

POSTAGE WILL BE PAID BY THE DEPARTMENT OF THE ARMY

COMMANDER
US ARMY MOBILITY EQUIPMENT RESEARCH
AND DEVELOPMENT COMMAND
ATTN: DRDME-DS
FORT BELVOIR, VA 22060

FOLD

Source: https://assist.dla.mil -- Downloaded: 202610-22T21:15Z
Check the source to verify that this is the current version before use.