METRIC

A-A-59003/7
31 May 1995
SUPERSEDING
MIL-A-21577/7
15 August 1968

COMMERCIAL ITEM DESCRIPTION

AMPLIFIER-CONTROL GROUP AN/SIA-119

The General Services Administration has authorized the use of this commercial item description as a replacement for MIL-A-21577/7B which is canceled.

1. **Scope**. This commercial item description covers the detailed requirements for an audio amplifier control group AN/SIA-119.

2. **Salient characteristics**.

2.1 **General**. Amplifier-control group AN/SIA-119 shall be in accordance with the applicable paragraphs of A-A-59003 and as specified herein. Whenever a requirement of A-A-59003 conflicts with a requirement of this specification, the requirement of this specification shall govern.

2.2 **Equipment**. Equipment complement shall consist of one microphone preamplifier assembly, six power amplifiers, and one common power supply in a common bulkhead mounted enclosure. No amplifier-oscillator assemblies are required. One of the six power amplifiers is considered a spare.

2.3 **Forced air cooling**. Forced air cooling is not permitted.

2.4 **Output power**. The rated output power for the individual power amplifier assemblies shall be 20 watts, minimum rating.

2.5 **Input facilities**. Amplifier-control group AN/SIA-119 shall have input facilities for two local microphone jackboxes, type IC/MJB.

2.6 **Output facilities**. Facilities shall be provided for transferring the associated loudspeaker load from the output of a remote amplifier to the output of the AN/SIA-119 amplifier. This transfer shall occur when the press-to-talk push button on either of the two local microphones is depressed. When amplifier AN/SIA-119 is used as a booster amplifier, manual provisions shall be included to transfer the local loudspeaker group from its own output to the output of the remote amplifier upon failure of local power supply or plate voltage supply.

2.7 **Input circuit**. Additional facilities shall be provided in the control rack for attenuating a 70-volt signal transmitted from a remote amplifier for injection into the input of the amplifier assembly. This attenuator shall be resistive, and shall appear as a load not exceeding 1 watt.

2.8 **Alarm signal priorities**. When used as a booster or emergency amplifier with local microphone input facilities, alarm signals transmitted from the remote amplifier shall have priority over all features of the amplifier assembly.

AMSC N/A

FSC 6320

DISTRIBUTION STATEMENT A. Approved for public release; distribution is unlimited.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T10:01Z
Check the source to verify that this is the current version before use.

2.9 **Speech priorities**. When used as an emergency amplifier, either of the local microphones shall have priority over all transmissions except alarm signals arriving from the remote amplifier.

2.10 **Microphone press-to-talk switches**. The operation of a microphone press-to-talk switch at either of the two local microphone stations shall:

(a) Connect the microphone audio circuit at that station to the input of the preamplifier assembly.

(b) Energize the busy indicator lamp at the other microphone station.

(c) Place the amplifier channel in the "ready" condition.

(d) Disconnect the adjacent loudspeaker circuit associated with that microphone circuit.

2.11 **Busy indicator circuits**. Busy indicator circuits shall be provided for the two local microphone stations so that when either microphone station is in use the busy indicator lamp of the other station will be energized.

2.12 **Local loudspeaker cut-out circuit**. Local loudspeaker cut-out circuits shall be provided for each of the two local microphone stations.

2.13 **Power amplifier assembly outputs**. Each individual power amplifier shall have its output brought to separate output terminals.

2.14 **Frequency response**. Frequency response at the power amplifiers shall be measured in accordance with A-A-59003 except that the amplifier shall be delivering 10 decibels (db)below rated output at 1000 cycles per second.

2.15 **Distortion**. Distortion of the power amplifier shall be measured in accordance with A-A-59003, except that at 200 and 6000 cycles the measurement shall be made at 6db below rated output.

2.16 **Module mounting**. Modules shall be mounted in a vertical position to facilitate the unrestricted flow of air.

2.17 **Test facilities**. A common voltmeter with switching facilities shall be provided on the control rack to determine proper power supply voltage for amplifiers and preamplifiers. The meter calibration and circuit component values shall be such that the operating condition of amplifiers can be determined directly from the meter without reference to tables and charts.

3. **Quality assurance**. Sampling, examination and tests shall be in accordance with A-A-59003.

4. **Packaging**. Packaging shall be in A-A-59003.

5. **Notes**.

5.1 **Intended use**. Amplifier-control group AN/SIA-119 is intended for use.

5.2 **Notes**. The notes of A-A-59003 are applicable to this document.

Preparing activity:
Navy - SH
(Project 6320-N0053)

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T10:01Z
Check the source to verify that this is the current version before use.