The documentation and process conversion measures necessary to comply with this revision shall be completed by 22 March 2001.

INCH-POUND

MIL-PRF-19500/428D
AMENDMENT 1
22 February 2001

PERFORMANCE SPECIFICATION

SEMICONDUCTOR DEVICE, FIELD-EFFECT TRANSISTOR, N-CHANNEL SILICON,
TYPE 2N4416A
JAN, JANTX, JANTXV AND JANS

This amendment forms a part of MIL-PRF-19500/428D, dated 30 August 2000, and is approved for use by all Departments and Agencies of the Department of Defense.

PAGE 6

TABLE I, subgroup 4, delete and substitute:
"

Inspection 1/	MIL-STD-750		Symbol	Limits		Unit
	Method	Conditions		Min	Max	
Subgroup 4						
Magnitude of small-signal, common-source short-circuit forward transfer admittance	3455	V_{DS} = 15 V dc; V_{GS} = 0 V dc; f = 1 kHz; pulse width = 100 ms; duty cycle = 10 percent	$\|y_{fs}\|_2$	4.5	7.5	mS
Small-signal, common-source short-circuit input capacitance	3431	V_{DS} = 15 V dc; V_{GS} = 0 V dc; 100 kHz ≤ f ≤ 1 MHz	C_{iss}		4	pF
Small-signal, common-source short-circuit reverse transfer capacitance		V_{DS} = 15 V dc; V_{GS} = 0 V dc; 100 kHz ≤ f ≤ 1 MHz	C_{rss}		0.8	pF
Small-signal, common-source short-circuit output capacitance		V_{DS} = 15 V dc; V_{GS} = 0 V dc; 100 kHz ≤ f ≤ 1 MHz (see 4.5.6)	C_{oss}		2	pF

DISTRIBUTION STATEMENT A. Approved for public release; distribution is unlimited.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T01:44Z
Check the source to verify that this is the current version before use.

Inspection 1/	MIL-STD-750		Symbol	Limits		Unit
	Method	Conditions		Min	Max	
Subgroup 4 - continued						
Small-signal, common-source short-circuit input susceptance		V_{DS} = 15 V dc; V_{GS} = 0 V dc; (see 4.5.3) f = 100 MHz	b_{is}		2.5	mS
Small-signal, common-source short-circuit output susceptance		V_{DS} = 15 V dc; V_{GS} = 0 V dc; (see 4.5.3) f = 100 MHz	b_{os}		1	mS
Small-signal, common-source short-circuit input conductance		V_{DS} = 15 V dc; V_{GS} = 0 V dc; (see 4.5.3) f = 100 MHz	g_{is}		0.3	mS
Small-signal, common-source short-circuit output conductance		V_{DS} = 15 V dc; V_{GS} = 0 V dc; (see 4.5.3) f = 100 MHz	g_{os}		75	µS
Small signal, common source insertion power gain		V_{DS} = 15 Vdc; ID = 5 mA dc; R_G = 1 kΩ (see 4.5.5) f = 100 MHz			18	dB
Common source spot capacitance		f = 100 MHz			2	dB

"

Custodians:
Navy - EC
Air Force - 11
DLA - CC

Review activities:
Navy - MC
Air Force - 19

Preparing activity:
DLA - CC

(Project 5961-2448)

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T01:44Z
Check the source to verify that this is the current version before use.