23 July 1974
SUPERSEDING
(See Section 6)

MILITARY SPECIFICATION

CONTROLLER, WEAPONS-GUN SPEED

AND LAUNCHER BRAKE, RH

This specification is approved for use by all Departments and Agencies of the Department of Defense.

1. SCOPE

1.1 This specification covers one type of weapons controller for installation in the right hand position of the M28A1 Armament Subsystem. The right weapons controller contains the required circuitry to control firing speed of the right machine gun, M134 or the drive and brake of the M129 Grenade Launcher.

2. APPLICABLE DOCUMENTS

2.1 The following documents, of the issue in effect on date of invitation for bids or request for proposal, form a part of this specification to the extent specified herein.

SPECIFICATIONS

Military		
MIL-W-13855	-	Weapons, Small Arms and Aircraft Armament Subsystems, General Specification for.
MIL-P-14232	-	Parts, Equipment and Tools for Army Materiel, Packaging and Packing of.
MIL-I-45607	-	Inspection Equipment, Acquisition, Maintenance and Disposition of.
MIL-A-45967	-	Armament Subsystem Helicopter: M28A1

FSC 1090

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T04:27Z
Check the source to verify that this is the current version before use.

STANDARDS

Military

MIL-STD-105	-	Sampling Procedures and Tables for Inspection by Attributes.
MIL-STD-109	-	Quality Assurance Terms and Definitions.

DRAWINGS

U.S. Army Weapons Command

F11688532	-	Controller, Weapons-Gun Speed and Launcher Brake, (RH).
IEL11688532	-	Inspection Equipment List.

(Product drawings referenced in this specification form a part of F11688532; acceptance inspection and test equipment drawings form a part of IEL11688532.)

PUBLICATIONS

U.S. Army Weapons Command

P11688532	-	Packaging Data Sheet for Controller, Weapons-Gun Speed and Launcher Brake, (RH).

(Copies of specifications, standards, drawings, and publications required by suppliers in connection with specific procurement functions should be obtained from the procuring activity or as directed by the contracting officer.)

3. REQUIREMENTS

3.1 First article. Requirements for submission of first article shall be as specified in the contract (see 6.2). Unless otherwise specified (see 6.2), the first article shall include a pilot pack (see 5.1).

3.2 Materials, construction and design. Controllers shall conform to the material, construction and design requirements specified herein, on Drawing F11688532, and in MIL-W-13855.

3.2.1 Weight. The weight of the controller shall not exceed 8.5 pounds.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T04:27Z
Check the source to verify that this is the current version before use.

3.3 Functional requirements.

3.3.1 Power input. The controller shall be capable of meeting the requirements specified herein, when supplied with 22 to 30 volts direct current (vdc) and a maximum current of 3.5 amperes (amps).

3.3.2 Weapon clearing (7.62mm). The weapon clearing function shall be performed utilizing the following relays:

A6K1	Time delay relay (7.62mm)
A6K3	Unclear relay
A6K6	Gate relay
A6K7	7.62mm Low speed relay
A6K8	Clear/Unclear Memory relay
A6K9	7.62mm High/Low speed relay.

Relays A6K10, A6K12, connector A6J3 and pin U of connector A6J1 shall be energized when 22-30 vdc is applied to pins A, R and U of connector A6J1. Any reference to a circuit being energized shall assume the grounded (negative) side of the power supply is connected to pin V of connectors A6J1 and A6J2.

3.3.2.1 Unclear mode (7.62mm). Relay A6K3 shall be energized when 22-30 vdc is applied to pin N of connector A6J1, thereby actuating all A6K3A and A6K3B contacts. Applying 22-30 vdc to pin C of connector A6J1, relays A6K1, A6K7, A6K8 (clear memory coil) and A6K9 (low speed coil X1X2) shall be energized through the normally closed contacts A6K11A and A6K12B. Once relay A6K1 is energized, relays A6K6 and A6K8 (unclear memory coil) shall become energized through A6K1 contacts and power from pin U of connector A6J1. Relay A6K8 will stay latched in the clear memory position, contact A6K8B will be open and no voltage shall exist at pin P of connector A6J1. At this time, voltage shall exist at pin C of connector A6P1 and continuity shall exist between pins D and E of connector A6P1. Upon removal of power at pin C of connector A6J1, relays A6K7 and A6K8 (clear memory coil), and A6K9 (low speed coil X1X2) shall immediately deenergize. Relay A6K7 and A6K9 (low speed coil X1X2) contacts shall open removing power from pin C of connector A6P1 and cause an open circuit between pins D and E of connector A6P1. Relay A6K6 and the unclear memory coil of relay A6K8 shall remain energized from power applied to pin U of connector A6J1 and by the time delay action of relay A6K1 for a period of 250 + 40 milliseconds. Upon completion of the time delay period, relay A6K6 and A6K8 (unclear memory coil) shall be deenergized. Because of the latching action, relay A6K8 shall remain in the unclear memory position. Relay contact A6K8B shall be closed at the time power is removed from pin C of connector A6J1. (Power applied to pin P of connector A6J1 from 22-30 vdc on

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T04:27Z
Check the source to verify that this is the current version before use.

pin R of connector A6J1 and diode CR12). A6K6A contacts shall remain closed during the time relay A6K1 is closed, and during the delay period. Continuity shall exist between pins E and F of connector A6J1.

3.3.2.2 Clear mode (7.62mm). Relay A6K3 shall not be energized (A6K3 contacts set in normal position) when 22-30 vdc is applied to pin C of connector A6J1, thereby energizing relays A6K1, A6K6 and A6K8 (unclear memory coil). When relay A6K1 becomes energized, relays A6K7, A6K8 (clear memory coil), and A6K9 (low speed coil X1X2) shall become energized through relay contacts A6K1A with power on pin U of A6J1. Relay A6K8 will stay locked in the unclear memory position, contact A6K8B shall close, thereby applying power to pin P of A6J1 from pin R of A6J1. Contact A6K6A shall close when power is applied to pin C of A6J1 resulting in continuity between pins E and F of A6J1. Pin C of A6P1 shall be energized from A6J3 through A6K9A1, A6K9A2,and A6K7A contacts. Continuity shall exist between pins D and E of A6P1. When power is removed from pin C of A6J1, relay A6K6 and A6K8 (unclear memory coil) shall deenergize. This will latch relay A6K8 in the clear memory position where it shall remain energized for completion of the time delay of relay A6K1. Relay A6K1 (time delay) shall maintain contact with A6K1A (closed for a period of 250 + 40 milliseconds), thereby providing energy to relays A6K7 and A6K9 (low speed coil X1X2), and the clear memory coil of relay A6K8 until completion of the time delay period of relay A6K1. Upon completion of the time delay period, relay A6K8 shall remain in the clear memory position due to latching action. Contacts A6K8B shall be open, and there shall be no voltage on pin P of A6J1 from pin R of A6J1.

3.3.3 Low speed operation (7.62mm). This function shall be performed by the following relays:

A6K1	Time delay relay (7.62mm)
A6K6	Gate relay
A6K7	7.62mm Fire relay
A6K9	7.62mm High/Low speed relay.

For the low speed operation function, power shall be applied to the same pins as required in the weapon clearing functions (see 3.3.2). The same relay functions shall apply in either the clear or unclear memory condition. When 22-30 vdc is applied to pin C of A6J1, relays A6K7 and A6K9 (low speed coil) shall be energized. Contacts A6K7 (A1-A2), A6K9 (A1-A2) and A6K9 (B1-B2) shall close. Contacts A6K7 (A1-A2) and A6K9 (A1-A2) shall cause a redundant current path from A6J3 to pin C of A6P1. Contacts A6K9 (B1-B2) shall cause a current path from pin D to pin E of A6P1. Contacts A6K6A shall close to provide continuity between pin E and pin F of A6J1.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T04:27Z
Check the source to verify that this is the current version before use.

3.3.4 High speed operation (7.62mm). This function shall be performed by the following relays:

A6K1	Time delay relay (7.62mm clear)
A6K6	Gate relay
A6K7	7.62mm Fire relay
A6K9	7.62mm High/Low speed relay
A6K11	7.62mm High speed relay.

For the high speed operation function, power shall be applied to the same pins as required in the weapon clearing functions (see 3.3.2). The same relay functions shall apply in either the clear or unclear memory condition. When 22-30 vdc is applied to pin D of A6J1 all relay functions shall remain the same except that relay A6K11A contacts shall be open and relay A6K9 (low speed coil) shall not be energized. Relay A6K9 (high speed coil) shall be energized from power on pin D of A6J1 through A6K12A contacts. With relay A6K9 (high speed coil) energized, A6K9 contacts A3, A4, B3 and B4 shall be closed, allowing a current path between pin E and pin F and between pin C and pin D of A6P1. Relay A6K7A contacts shall remian closed and a current path shall exist between A6J3 and pin C of A6P1.

3.3.5 Weapon enable. The weapon enable relay shall be energized by applying 22-30 vdc to pin A of A6J1. Relay contact A6K10A shall close providing a circuit to relay A6K1 and associated relays, to provide power to either the high or low speed coils or relay A6K9. This shall close relay A6K9A or A6K9B contacts and provide a current path from A6J3 to pin C of A6P1, and pin D and pin E of A6P1, or between pin C and pin D and between pin E and pin F of A6P1. Relay contact A6K10B shall open to provide an open circuit between pin B and X of relay A6J1. Prior to energizing relay A6K10, a closed circuit existed from pin B to pin X of A6J1 through the A6K10B contacts and diode CR13. There shall be a closed circuit between pin B of A6J1 and pin B of A6J2. Relay contacts A6K10C shall close to provide power from pin M of A6J1 to relay A6K2 and A6K5 (relay coil). Relay contacts A6K10D shall be closed and continuity shall exist between pins T and W of A6J1.

3.3.6 40mm Gun drive. This function shall be performed by the following relays:

A6K2	Time delay relay (40mm clear)
A6K5	Drive latch relay
A6K9	40mm Drive brake relay

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T04:27Z
Check the source to verify that this is the current version before use.

The 40mm gun drive function shall require 22-30 vdc applied to pins K, A and U of A6J1 and to A6J3. Power at pin A shall energize relay A6K10 which shall close contact A6K10C. 22-30 vdc applied to pin M of A6J1 shall energize relay A6K2 through contact A6K10C. Relay A6K5 shall become energized after contact A6K2A closes in the ground side of the A6K5 relay coil and power is applied on the plus side of the coil from pin M of A6J1, contact A6K10C and CR3. The A6K5A contacts shall close when relay coil A6K5 is energized forming a holding current for relay A6K5 when power is applied to pin K of A6J1. (Power in pin K is supplied from the 40mm magnetic brake sensor in the turret of the M28 subsystem). Contact A6K2B shall close upon energizing relay A6K2 and the power shall be supplied to pin G of A6P1. Contacts A6K5B1 and A6K5B2 shall close when relay A6K5 is energized, thus applying power to relay A6K9 (40mm drive coil) through the normally closed contact A6K12B. Relay A6K9 brake coil shall be deenergized since contacts A6K5B2, A6K5B3 are open. This will result in relay A6K9 being latched in the drive position with a current path from A6J3 to pin C of A6P1. Pin C of A6P1 shall be energized and continuity shall exist between pins D and E of A6P1 through contacts A6K9B1 and A6K9B2. With relay A6K9 latched in the drive position, power shall be applied to the A6K9 relay brake coil through A6K9A1, A6K9A2 contacts, CR8 diode, A6K12C(2-3), and A6K12A (2-3). Relay A6K9 shall remain in the drive position since the drive coil was energized before the brake coil. Continuity shall exist between pin C of A6P1 and pin A of A6P2 and between pin F of A6P1 and pin D of A6P2.

3.3.7 40mm Gun braking. This function shall be performed by the following relays:

A6K2	Time delay relay (40mm clear)
A6K5	Drive latch relay
A6K9	40mm Drive brake relay

The 40mm gun braking function shall require 22-30 vdc applied to pins A, K and U of A6J1 and to A6J3. Power to pin A shall energize relay A6K10 which will close contact A6K10C. When power is removed from pin M of A6J1, relay A6K2 will remain energized for 500 ± 50 milliseconds. All relays shall remain in the drive condition for 500(ms) unless power is removed from pin K of A6J1. If power is removed from pin K, relay A6K5 will drop out of the drive condition immediately. At the end of the 500(ms) period or when power is removed from pin K of A6J1, relay A6K5 shall be deenergized. Removing power from the drive coil of relay A6K9 through the A6K5B1 and A6K5B2 contact openings will allow relay A6K9 to latch in the brake position for a period of 15(ms) or less.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T04:27Z
Check the source to verify that this is the current version before use.

Relay A6K9 (brake coil) has been previously energized from A6J3, contacts A6K9A1, A6K9A2, diode CR 8, A6K12A and A6K12C normally closed contacts. Relay A6K9 brake coil shall be held in the brake position from power applied through relay contacts A6K5B2, A6K5B3 and pin U of A6J1. Power shall then be removed from pin G of A6P1 500 ± 50(ms) after relay A6K2 is deenergized. The action of relay A6K9 changing from the drive position to the brake position shall cause contacts A6K9A1, A6K9A2, A6K9B1 and A6K9B2 to open while contacts A6K9A3, A6K9A4, A6K9B3 and A6K9B4 close in 15(ms) or less. Diode CR9 connected from pin G to pin F shall absorb the reverse voltage caused by the motor shunt field collapsing. Diode CR10 shall be connected from pins E to C of A6P1 to absorb the energy from the back EMF generated while the motor armature is being dynamically braked.

3.3.8 Diodes. Diodes reverse connected across A6K3, A6K6, A6K7, A6K10, A6K11 and A6K12 relay coils shall absorb the induced voltage generated in the collapsing relay coil field.

3.3.9 Condensers. The condenser connected across relay A6K1 shall absorb external switching voltage transients on pin C of A6J1, preventing relay A6K1 from being inadvertently energized.

3.3.10 Feed through circuits. Continuity shall exist between the following pins of A6J1 and A6J2:

A6J1		A6J2	A6J1		A6J2
Pin A	to	Pin S	Pin E	to	Pin F
B		B	W		W
P		P	J		R
A		A	G		G
D		D	C		C
N		N	V		V
M		M	L		L
H		H	U		E

3.4 Reliability. When specified in the contract (see 6.2), the controller shall have a minimum acceptable Mean-Mission-Between-Failure (MMBF) of not less than 1427 missions with a desired and specified MMBF of 2141 missions. A mission is defined as those functions of the controller necessary to simulate the expenditure of 4,000 rounds of 7.62mm ammunition and 265 rounds of 40mm ammunition during a two hour flight. A failure will be defined as a nonoccurrence of the appropriate event when power is applied and the required control switches are actuated. Testing for the weapons controller shall be in accordance with 4.4 and 4.6.2.

3.4.1 Reliability criteria. The above reliability requirements are based on a minimum acceptable Mean-Time-Between-Failure (MTBF) of 2855 hours.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T04:27Z
Check the source to verify that this is the current version before use.

3.5 Environmental conditions. When specified in the contract (see 6.2), the weapons controller shall be capable of satisfying the environmental conditions in accordance with MIL-A-45967 for the system. When subjected to the environmental conditions, the controller shall not exhibit any detrimental damage or deterioration which would prevent acceptable performance. Testing for environmental shall be in accordance with 4.4.

3.6 Electromagnetic interference (EMI). When specified in the contract (see 6.2), the weapons controller shall be capable of satisfying the EMI requirements in accordance with MIL-A-45967 for the system. When subjected to the EMI, the weapons controller shall not exhibit any detrimental damage or deterioration which would prevent acceptable performance. Testing for EMI shall be in accordance with 4.4.

3.7 Marking. Controllers shall be marked in accordance with the applicable drawing and MIL-W-13855. Serial numbers shall be assigned by the procuring activity (see 6.2).

3.8 Workmanship. Workmanship shall be in accordance with MIL-W-13855.

4. QUALITY ASSURANCE PROVISIONS

4.1 Responsibility for inspection. Unless otherwise specified in the contract or purchase order, the supplier is responsible for the performance of all inspection requirements specified herein. Except as otherwise specified in the contract or order, the supplier may use his own or any other facilities suitable for the performance of the inspection requirements specified herein unless disapproved by the Government. The Government reserves the right to perform any of the inspections set forth in the specification where such inspections are deemed necessary to assure supplies and services conform to prescribed requirements.

4.2 Quality assurance terms and definitions. Quality assurance terms and definitions used herein are in accordance with MIL-STD-109.

4.3 Classification of inspection. The inspection requirements specified herein are classified as follows:

a. First article inspection (see 4.4).
b. Quality conformance inspection (see 4.5).

4.4 First article inspection. The first article (initial production unit(s) shall be submitted for inspection in accordance with contract requirements (see 6.2). The first article shall be representative of the production processes used during quantity production. The first article shall be subjected to quality conformance inspection specified herein, and when specified in the contract, the reliability test (see 3.4 and 4.6.2), environmental test (see 3.5), electromagnetic interference (EMI) test (see 3.6), and such other inspection as is necessary

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T04:27Z
Check the source to verify that this is the current version before use.

to determine compliance with the requirements of the contract.

4.5 Quality conformance inspection.

4.5.1 Examination.

4.5.1.1 Component parts and concurrent repair parts. Examination of parts shall be performed in accordance with the criteria specified in the contract (see 6.2). Examination of parts shall be accomplished prior to their assembly into the end items or submission for acceptance as repair parts.

4.5.1.2 Inspection methods. The following provisions shall be applicable to the prescribed inspection methods. Request for a method other than that specified shall be submitted to the Government for approval.

a. Where "Visual" is specified as the inspection method for functioning assembly requirements, the assembly shall be visually examined for completeness and manually operated for functioning requirement.
b. Where "SMTE" (Standard Measuring and Test Equipment) is specified as the method of inspection, the contractor may use any type of industry developed, commercially available, multi-usage equipment or special inspection and/or testing equipment approved by the Government.
c. Examination for workmanship shall include examination for missing operations and the presence of nicks, cracks, burs, scratches, toolmarks, deformations or other signs of poor workmanship. Controllers shall be carefully compared with a specimen of known acceptable quality and conform to the requirements of 3.8.

4.5.1.3 Controllers. Each controller shall be examined as specified below. The examination provisions should be applied at the earliest practical point in manufacture at which it is feasible to inspect for acceptance without risk of change in the characteristics by subsequent operations. Reinspection of these characteristics is not required provided assurance exist that the characteristic has not been changed, degraded or damaged by subsequent manufacturing, assembly or handling and that adequate inspection records are maintained. Controllers failing to meet these requirements shall be rejected.

	Characteristic	Requirement	Inspection Method
a.	Missing, damaged, or incorrectly assembled component parts.	3.2	Visual

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T04:27Z
Check the source to verify that this is the current version before use.

Characteristic	Requirement	Inspection Method
b. Diodes and condensers connected across relay coils for proper installation and for electrical conductance while in the forward position and nonconductance while in the reserve position.	3.3.8 and 3.3.9	SMTE
c. Illegible, incorrect or missing product markings, identification plates and serial numbers.	3.7	Visual
d. Workmanship.	3.8	Visual

4.5.1.3.1 Weight. The first 3 controllers produced shall be examined as specified in 3.2.1 for weight requirements.

4.5.2 Testing.

4.5.2.1 Failure data. Unless otherwise specified herein, all tests shall be conducted on a complete controller. If test requirements cited herein are not met, acceptance of the controller shall be deferred and the contractor shall accomplish as applicable, the following actions:

a. Conduct a failure analysis study performing a dimensional physical and visual examination of the components which are suspected to be the cause of failure or malfunction.
b. Evaluate and correct the applicable production processes and procedures to prevent recurrence of the same defect(s) in future production.
c. Examine controllers, partially assembled controllers and components (including components and subassemblies at in-process or final assembly) to insure that material containing the same defect is purged from the inventory and not presented to the Government for acceptance.
d. Submit the results of the failure analysis and the corrective actions taken to the Government for review and approval prior to submitting a reconditioned lot or reconditioned controller for retest.

4.5.2.2 Functional testing. Each controller shall be function tested (see 3.3) using the test method specified in 4.6.1. Controllers failing to meet the functional requirements shall be rejected and the contractor shall perform the corrective action specified in 4.5.2.1.

4.5.2.3 Component parts and concurrent repair parts testing. Raw material testing, part testing, and certification shall be performed in accordance with the criteria specified in the contract (see 6.2). This will include chemical analysis and physical tests of materials, tests

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T04:27Z
Check the source to verify that this is the current version before use.

of protective finish, heat treatment, bonding, and function of parts as applicable. The contractor shall accomplish these tests prior to assembly of parts into the end item.

4.5.3 Packaging examination and testing. Unless otherwise specified (see 6.2), the packaging examination and testing shall be in accordance with MIL-P-14232.

4.5.4 Inspection equipment.

4.5.4.1 Acquisition, maintenance and disposition. Unless otherwise specified, (see 6.2) responsibility for acquisition, maintenance and disposition of acceptance and test equipment prescribed on the List of Inspection Equipment IEL11688532 and for all other inspection equipment required to perform inspection prescribed by applicable specifications, shall be in accordance with MIL-I-45607.

4.5.4.2 Accuracy of standard measuring equipment. When commercial and modified commercial inspection and test equipment is used, it must be capable of repetitive measurements to an accuracy of 10 percent of the total tolerance of the characteristic being inspected.

4.6 Test methods.

4.6.1 Function test. Controllers shall be tested in accordance with the test procedure specified on IEL11688532 (ref. Drawing 11836855).

4.6.2 Reliability test. The reliability test shall be performed by repeating the test cycle defined in 4.6.2.1 to determine compliance with 3.4. For each test cycle, the failure versus test cycles data shall be cumulatively plotted. Testing shall be terminated whenever a decision point as defined in Figure 1 has been reached.

4.6.2.1 Reliability test cycle. One test cycle (representing the functions necessary to perform two missions) shall be completed by performing the following test methods contained in the functional test procedure, specified in IEL11688532 (Ref Functional Test Procedure 11836855), for the number of repetitions stated.

4.6.6.2 The contractor shall provide replacement parts as required to complete the test.

4.6.2.3 At the option of the contractor, the test may be interrupted during, or at the end of, a cycle and the test restarted later at the point at which it was interrupted.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T04:27Z
Check the source to verify that this is the current version before use.

Functional Test Procedure Paragraph Number	Number of Repetitions
5.1	Initial only
5.2	Initial only
5.3	7
5.4	9
5.5	5
5.6	2
5.7	5
5.8	5
5.9	1
5.10	1
5.11	1
5.12	5
5.13	1
5.14	1
5.15	2
5.16	2
5.17	1
5.18	1

4.6.2.4 Complete, accurate records shall be kept for each reliability test, showing each failure and part replacement, including an indication of when each failure occurred. In addition, complete, accurate records shall be kept for all time losses attributable to weapons controller, including the time for each stoppage.

5. PREPARATION FOR DELIVERY

5.1 Pilot pack. The pilot pack shall consist of a complete controller packaged in accordance with Packaging Data Sheet P11688532 for the level of protection specified in the contract (see 6.2), packed level C and forwarded in accordance with 3.1.

5.2 Preservation, packaging, packing and marking. Controllers shall be preserved, packaged, packed and marked in accordance with Packaging Data Sheet P11688532 for the level of protection specified in the contract (see 6.2).

5.3 Repair parts. Repair parts shall be preserved, packaged, packed and marked in accordance with the Packaging Data Sheet or other requirements for the level of protection specified in the contract (see 6.2).

6. NOTES

6.1 Intended use. The controller is intended for use on, but not limited to the M28A1 Helicopter Armament Subsystem.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T04:27Z
Check the source to verify that this is the current version before use.

6.2 Ordering data. Procurement documents should specify the following:

6.2.1 Procurement requirements.

a. Title, number and date of this specification.
b. List of drawings and specifications pertinent to the controller showing applicable revision dates.
c. Requirements for and number of controllers to be submitted for first article by the contractor (see 3.1 and 4.4 and 5.1).
d. Reliability, environmental and electromagnetic interference, when required (see 3.4, 3.5, 3.6 and 4.4).
e. Block of serial numbers required (see 3.7).
f. Criteria for examination and testing of component parts and concurrent repair parts (see 4.5.1.1 and 4.5.2.3).
g. Packaging examination and testing, if different see 4.5.3)..
h. List of inspection equipment, responsibilities for acquisition, maintenance, and disposition of, if other than as specified (see 4.5.4.1).
i. Selection of applicable levels of preservation, packaging and packing (see 5.2).
j. Packaging instructions for repair parts (see 5.3).

6.2.2 Management control systems requirement. When warranted, the contract should specify the application of MIL-Q-9858 or MIL-I-45208 on the Management Control Systems Summary List, DD Form 1660.

6.2.3 Unless otherwise specified (see 6.1.1 h), the contract should specify the application of MIL-I-45607 and MIL-C-45662 on the Management Control Systems Summmary List, DD Form 1660.

6.3 Relay functions. The following descfibes the general functions of relays specified in section 3.

Symbol	Type	Function
A6K1	Time Delay	Machine gun clearing - The time delay relay A6K1 (7.62mm clear) shall provide for continued operation of the machine gun and accessories for a period of 250 milliseconds upon release of the trigger. The delay shall permit expenditure of rounds already in the weapon at the time of trigger release. Trigger release also results in loss of energy in the gate solenoid thereby interrupting ammo feed to the weapon during the delay period.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T04:27Z
Check the source to verify that this is the current version before use.

Symbol	Type	Function
A6K2	Time Delay	Grenade launcher clearance - The time delay relay A6K2 (40mm clear) shall provide continued operation of the grenade launcher and accessories upon release of the trigger for a period of time sufficient to clear the weapon chamber of ammunition.
A6K3	Switching	Unclear relay - Operation controlled by a switch on the gunner control panel. The contact action provides an option to the gunner to automatically clear or not to clear the rounds from the machine gun and feed mechanism upon release of the trigger (see A6K8). The contact action with relay energized, shall provide for actuation of the gate solenoid on the machine gun and the unclear weapon indicator light on the control panel. The contact action, with the relay not energized, shall provide for clearing of the weapon by means of time delay relay A6K1 and firing relays A6K7 and A6K9 as well as by closure of the entrance to the machine gun chamber by loss of energy in the gate solenoid coil.
A6K5	Switching	Energized by 40mm trigger, in turn energizing "drive" coil of A6K9. Upon release of trigger, A6K5 is held energized by grenade launcher magnetic recoil sensor until next recoil occurs. A6K5 then deenergizes and thereby energizes "brake" coil of A6K9, dynamically braking weapon.
A6K6	Switching	Gate relay - This relay shall introduce the 22-30 vdc battery busbar power to the coil of the gate solenoid thereby clearing the entrance to the machine gun chamber.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T04:27Z
Check the source to verify that this is the current version before use.

Symbol	Type	Function
A6K7	Switching	7.62mm Firing relay - This relay shall be actuated by the 7.62mm trigger and shall provide the primary firing contact for the machine gun at high speed with a 100 ampere steady state inductive current rating.
A6K8	Switching	Clear/Unclear memory relay. Following release of the trigger, the contacts of this relay shall magnetically remain in the position determined by A6K3. The contacts of this relay shall provide current to the weapon unclear indicator light on the gunner control panel when the weapon was not cleared and will interrupt this current the next time the weapon is cleared.
A6K9	Switching	40mm Brake/Drive relay or 7.62mm High/Low speed relay - This relay shall be energized either by action of relay A6K5 or by 7.62mm trigger action. With a 40mm weapon installed, A6K9 provides contact action which will introduce the 22-30 vdc battery busbar power directly into the grenade launcher drive motor. The contact action of this relay shall result in either starting or braking of the grenade launcher assembly and accessories. With a 7.62mm weapon installed, the 7.62mm trigger and A6K11 provide the switching necessary for A6K9 coils, either directly or through A6K1 contacts to achieve low speed, and directly as well as by action of A6K11 contacts to achieve high speed. The contacts of this relay switch the 7.62mm drive motor armatures to either a parallel or series configuration, providing high and low speeds. These contacts should have a 50 ampere steady state inductive current rating. Relay A6K12 determines whether A6K9 acts as a 40mm or 7.62mm firing relay.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T04:27Z
Check the source to verify that this is the current version before use.

Symbol	Type	Function
A6K10	Switching	Weapon enable relay - This relay shall be energized by the weapon select switches on the gunner sight and pilot control panel. The contact action shall place the controller in a standby condition which will permit armament operation upon actuation of the trigger. This relay prevents firing of an unselected weapon.
A6K11	Switching	7.62mm High speed relay - The second detent of the 7.62mm trigger shall actuate this relay, while at the same time energizing the high speed coil of A6K9. The contacts of this relay shall interrupt the current to the low speed coil of A6K9 allowing the gun to fire at high rate of speed.
A6K12	Switching	7.62mm Weapon installed relay - When a 7.62mm weapon is installed, this relay shall be energized off the turret power bus through a jumper wire in the 7.62mm chorting connector (A3A1P2 or A3A2P2). The contacts of this relay shall be used as an interlock between the 7.62mm and the 40mm firing circuits by setting up the coil circuits of A6K9 to receive 7.62mm or 40mm trigger signals.

6.4 Firing interlock. With the 7.62mm weapon installed, relay A7K12 shall be energized by 22-30 vdc applied to pin R of A6P1. The contacts of this relay provide for an interlock between the 7.62mm and 40mm firing circuits to prevent the firing of the unselected weapon.

6.5 Supersession data. This specification includes the requirements of U.S. Army Weapons Command Purchase Description, USAWECOMPD-31, Amendment 1, dated 31 March 1972.

Custodian:
Army - WC

Preparing activity:
Army - WC

Project number:
1010-A066

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T04:27Z
Check the source to verify that this is the current version before use.

STANDARDIZATION DOCUMENT IMPROVEMENT PROPOSAL

OMB Approval No. 22-R255

INSTRUCTIONS: The purpose of this form is to solicit beneficial comments which will help achieve procurement of suitable products at reasonable cost and minimum delay, or will otherwise enhance use of the document. DoD contractors, government activities, or manufacturers/ vendors who are prospective suppliers of the product are invited to submit comments to the government. Fold on lines on reverse side, staple in corner, and send to preparing activity. Comments submitted on this form do not constitute or imply authorization to waive any portion of the referenced document(s) or to amend contractual requirements. Attach any pertinent data which may be of use in improving this document. If there are additional papers, attach to form and place both in an envelope addressed to preparing activity.

DOCUMENT IDENTIFIER AND TITLE

MIL-C-45954(WC); Controller, Weapons-Gun Speed and Launcher Brake, RH

NAME OF ORGANIZATION AND ADDRESS

CONTRACT NUMBER

MATERIAL PROCURED UNDER A

☐ DIRECT GOVERNMENT CONTRACT ☐ SUBCONTRACT

1. HAS ANY PART OF THE DOCUMENT CREATED PROBLEMS OR REQUIRED INTERPRETATION IN PROCUREMENT USE?

A. GIVE PARAGRAPH NUMBER AND WORDING.

B. RECOMMENDATIONS FOR CORRECTING THE DEFICIENCIES

2. COMMENTS ON ANY DOCUMENT REQUIREMENT CONSIDERED TOO RIGID

3. IS THE DOCUMENT RESTRICTIVE?

☐ YES ☐ NO *(If "Yes", in what way?)*

4. REMARKS

SUBMITTED BY *(Printed or typed name and address - Optional)*

TELEPHONE NO.

DATE

DD FORM 1 JAN 72 1426

REPLACES EDITION OF 1 JAN 66 WHICH MAY BE USED

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T04:27Z
Check the source to verify that this is the current version before use.

FOLD

POSTAGE AND FEES PAID
DEPARTMENT OF THE ARMY
DOD – 314

OFFICIAL BUSINESS
PENALTY FOR PRIVATE USE $300

Commander
Rock Island Arsenal
ATTN: SARRI-LE-S
Rock Island, Illinois 61201

FOLD

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T04:27Z
Check the source to verify that this is the current version before use.