MILITARY SPECIFICATION

MODULES, STANDARD ELECTRONIC

MEMORY, RANDOM ACCESS, DIGITAL, KEY CODE GYB

This amendment forms a part of Military Specification MIL-M-28787/141B(EC), dated 23 August 1983, and is approved for use by the Space and Naval Warfare Systems Command, Department of the Navy, and is available for use by all Departments and Agencies of the Department of Defense.

PAGE 8

4.4.2, delete and substitute the following:

"4.4.2 Order of testing. Test conditions A through Y shall be performed in any order with the following exceptions. Test conditions A, B, and D are stress tests and will be performed at 25°C ±5°C. If test conditions A, B, or D are part of a sequence of tests, the order of testing shall be as follows: A, B, D where applicable, followed by the remaining tests in the sequence."

PAGE 9

6.4, Input capacitance, D0-D3, data, delete "15 pF maximum" and substitute "17 pF maximum". WE, write enable, delete "45 pF maximum" and substitute "50 pF maximum".

PAGE 44

TABLE XV, footnote 3/, delete and substitute the following:

3/ A program that fulfills the walking-zero test pattern would be as follows:

(a) Write "highs" in all memory address locations.
(b) Read "highs" in all memory address locations.
(c) Write a "low" in memory output "Q0" at address location "0".
(d) Read "high" in all other memory bit locations.
(e) Read a "low" in memory output "Q0" at address location "0".
(f) Write a "high" in memory output "Q0" at address location "0".
(g) Write a "low" in memory output "Q1" at address location "0".
(h) Read a "high" in all other memory bit locations.
(i) Read a "low" in memory output "Q1" at address location "0".
(j) Write a "high" in memory output "Q1" at address location "0".
(k) Write a "low" in memory output "Q2" at address location "0".
(l) Read a "high" in all other memory bit locations.
(m) Read a "low" in memory output "Q2" at address location "0".
(n) Write a "high" in memory output "Q2" at address location "0".
(o) Write a "low" in memory output "Q3" at address location "0".
(p) Read a "high" in all other memory bit locations.
(q) Read a "low" in memory output "Q3" at address location "0".
(r) Write a "high" in memory output "Q3" at address location "0".
(s) Write a "low" in memory output "Q0" at address location "1".
(t) Read a "high" in all other memory bit locations.
(u) Continue the pattern until a "low" has been walked through every memory bit location.

Agent:
DLA - ES

Preparing activity:
Navy - EC

(Project 5963-N664)

FSC 5963

DISTRIBUTION STATEMENT A. Approved for public release; distribution is unlimited.

Notice: https://assist.dla.mil - Downloaded: 2020-10-20T16:16Z
Check the source to verify that this is the current version before use.