1 OCTOBER 1963
SUPERSEDING
FA(FC)-PD-184
6 MAY 1963

MILITARY SPECIFICATION

INTERCONNECTING BOX: 8932942

1. SCOPE

1.1 This specification covers one type of interconnecting box which is part of Fire Direction Set, Rocket, Aircraft: 5S00965. Electrical connections between the fire direction set assemblies are made through the interconnecting box (see 6.1).

2. APPLICABLE DOCUMENTS

2.1 The following documents, of the issue in effect on date of invitation for bids or request for proposal, form a part of this specification to the extent specified herein:

SPECIFICATIONS

MILITARY

MIL-T-152 – Treatment Moisture- and Fungus-Resistant, of Communications, Electronic and Associated Electrical Equipment

MIL-F-13926 – Fire control Materiel; General Specification Governing the Manufacture and inspection of

MIL-P-14232 – Parts, Equipment and Tools for Ordnance Materiel; Packaging of

MIL-I-45208 – Inspection Requirements, General Specification for

STANDARDS

MILITARY

MIL-STD-105 – Sampling Procedures and Tables for Inspection by Attributes

MIL-STD-109 – Quality Assurance Terms and Definitions

DRAWINGS

U. S. ARMY Munition COMMAND

F8932942 – Interconnecting Box: 8932942

PACKAGING DATA SHEET

MIL-P-14232/P8932942 – Packaging of Interconnecting Box: 8932942

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T05:49Z
Check the source to verify that this is the current version before use.

(Copies of specifications, standards, drawings, and publications required by suppliers in connection with specific procurement functions should be obtained from the procuring activity **or as** *directed by the contracting officer.)* " '

3. REQUIREMENTS

3.1 Fabrication. The interconnecting box shall be manufactured in accordance with Drawing F8932942 and drawings pertaining thereto.

3.2 General specification. The interconnecting box shall meet the requirements of Specification MIL-F-18926, as specified below. Should any conflict exist between the general specification and this specification, this specification shall take precedence,

(a) **Order of precedence.**

(b) *Dimensions and tolerances.*

(c) *Inorganic protective surface . finishes.*

(d) *Part identification and 'marking.*

(e) Workmanship,

3.3 Wires. Wires shall be free of nicks.

3.4 Dressing. Wire shall not be dresssed so that it touches resistors of two watts or over.

3.5 Environmental service conditions.

3.5.1 ***Vibration.*** The interconnecting box shall withstand a vibration of a simple harmonic motion having an amplitude of 0.015 inch (0.03 inch total excursion). The frequency shall be varied uniformly between the limits of 10 to 55 cycles per second (cps) and return to 10 cycles. This cycle shall be traversed in 8 minutes & 15 seconds. The motion shall be applied for a period of 20 minutes in each of the three mutually perpendicular directions (total of 60 minutes). During vibration the interconnecting box shall meet the requirements of 3.6.

3.5.2 Shock. The interconnecting box shall withstand 3 shock impulses in each of the three mutually perpendicular directions. . The acceleration of the shock impulses shall be 20 gravity units (G's). Pulse duration of each shock impulse shall be 11 $\pm$ 1 milliseconds. Subsequent to shock the interconnecting box shall meet the requirements of 3.6,

3.5.3 ***Temperature.***

3.5.3.1 Operating. The interconnecting box shall *meet the* requirements of 3.6 when thermally *stabilized at ambient temperatures of –30°F and + 145°F.*

3.5.3.2 storage. The interconnecting box shall meet the requirements of 3.6 at an ambient temperature of between 60°F to 90°F after having been thermally stabilized at ambient temperatures of —65 OF and -f- 165°F.

3.5.4 ***Humudity.*** The interconnecting box shall meet the requirements of 3.6, after being subjected to five 12-hour 'relative humidity (RH) cycles; each cycle consisting of the following conditions:

(a) Water shall have **a** PH factor of between 6.6 and 7.5 at 77°F.

(b) Exposure of 6 hours at 95% RH; *4 1/2 hours of which shall be at an ambient temperature of 115°F.*

(c) A variation once each hour during last 6 hours of $\pm$ 9°F at an ambient temperature of 80°F',

(d) A variation once each hour during last 6 hours from 95$% RH to 100% RH with condensation. (Duration at 100% RH optional and need not coincide with

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T05:49Z
Check the source to verify that this is the current version before use.

hourly phase temperature variation.)

3.5.5 Moisture - ***Fungus resistanee.*** The interconnecting box shall be treated per Type II for moisture - and fungus-resistance in accordance with Specification MIL-T-152.

3.6 Performance. The application of 28 volts, direct current (Vdc) to pins A, B, C, and D of J4 shall prevail for all requirements of 3.6 excepting 3.6.9. Pins A and B shall be polarized positive; pins C and D shall be polarized negative. All symbols referred to are those shown on Drawing E8932945.

3.6.1 ***Reset button.*** With the reset button depressed, the zero indication lamp shall light and 28 Vdc shall exist between pins S and T of Jl, when the stepping switch is in the zero position.

3.6.2 ***Relays K25*** *and K30* ***operation.*** With pins B of J7, F of J7, and A of J1 electrically connected together, the following shall be exhibited:

(a) *28* ***Vdc shall exist between —***

(1) A and L of J8

(2) *B and* L of J8.

(3) A and K of J8.

(4) B and K of J8.

(5) B and G of J?.

(6) D and G of J?.

(7) E and G of J?.

(8) F and G of J7.

(9) H and T of J1.

(10) K and T of J1.

(11) B and f of J1.

(12) Z and f of J1.

(b) No voltage **shall exist at** D, B, or C of **J6.**

3.6.2.1 ***Stepping switch zero position.*** With the relays K25 and K30 energized (B and F of J? shorted) and the stepping switch in the zero position, the zero indication lamp shall light and 28 Vdc shall exist between pins S and T of J1.

3.6.3 ***Relay*** K26 (arm-relay ***operation.*** With relays K25 and K30 energized, and pins **Z** and G of J1 shorted, the following shall be exhibited:

(a) 28 Vdc shall exist between pins L and *T of J1.*

(b) 28 Vdc shall no longer exist between pins K and T of J1 (see 3.6.2(a) (10)).

3.6.4 ***Relay K2Y firing relay operation).*** With relays K25, K30 and K26 energized, and pins Z and X or A and B **of** J1 shorted, 28 Vdc shall exist —

(a) at the wiper arm of the stepping switch.

(b) between pins R and T of J1.

(c) between J and L or K *of* J8.

3.6.5 ***Step switch operation.*** With **the** existing conditions of 3.6.4 and pins L, **J** and M of J1 shorted the following shall be exhibited:

(a) The wiper-arm of the stepping switch shall move from the zero to number one firing position, energizing relay K1.

(b) The zero indication lamp shall not be illuminated.

(c) The normally closed contacts of relay Kl, shunted across **the** normally open contacts of Kl,

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T05:49Z
Check the source to verify that this is the current version before use.

shall open removing the double ground from i of J2 and J3.

(d) 28 Vdc shall exist between pins **A** and j of J2 and between pins F and j of J3 (voltage drop across normally open contacts leading to squibs).

3.6.5.1 SS coil and *interrupter operation.* Each time. the 28 Volt-supply between pins L, J and M of J1 is interrupted and reapplied, the wiper arm of the stepping switch shall move to the next firing position applying 28 Vdc to the respective firing relay and pins of J2 and J3.

3.6.5.2 *Typical sequential firing operation.* The operation specified in 3.6,5.1 shall be typical for all 24 firing relays and associated pins for J2 and J3 During the sequential firing, the zero indication lamp shall remain deenergized. The normally closed contacts, shunted across the normally open contacts of the respective relay being energized for firing, shall open removing the double ground from j of J2 and J3.

3.6.5.3 ***Reset to zero.*** Upon completion of the sequential firing operation, the wiper arm of the stepping switch shall be capable of being reset to the zero position, at which time the zero indication lamp shall be illuminated.

3.6.6 *Explosive - bolt operation.* With 28 Vdc applied at pin C of J7, 28 Vdc shall exist at the following pins:

(a) D and *f* of J&

(b) H and f of J5.

(c) K and ***f*** of J&

(d) S and *f* of J5,

3.6.6.1 ***Time delay.*** one-tenth (0.1) second ± 2 milliseconds after the 28 Vdc is exhibited at pins specified above (3.6.6), 28 Vdc shall appear at pins:

(a) B and *f* of J5.

(b) F **and** *f* **of J5.**

(c) P and *f* **of J6.**

(d) M and **f** of J5.

3.6.7 ***Relay*** *K28* ***operation.*** With 28 Vdc applied to E and D of J1 the following shall prevail:

(a) 28 Vdc shall exist at H of J6 and U of J1.

(b) No voltage shall be present at V of J1.

3.6.7.1 When 28 Vdc is applied to pin C of Jl, 28 Vdc shall be present at pin E of J6 and pin W of J1.

3.6.8 Diode CR86. When pin B of J7 and pin G of J6 are electrically connected together, CR36 shall conduct and 28 Vdc shall be present at pin E of J7.

3.6.9 *Continuity.* Continuity between pins specified below shall be less than 0.1 ohm:

(a) F (J6) and D (Jl).

(b) E (J6) and W (Jl).

(c) II (J6) and U (Jl).

3.7 Weight. The interconnecting box shall not exceed 35.5 & 0.6 pounds.

4, QUALITY ASSURANCE PROVISIONS

4.1 Responsibility for inspection. The supplier is responsible for the performance of all inspection requirements as specified herein. Except as otherwise specified, the

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T05:49Z
Check the source to verify that this is the current version before use.

supplier may utilize his own or any other inspection facilities and services acceptable to the Government. Inspection records of the examinations and tests shall be kept complete and available to the Government as specified in the contract or order. The Government reserves the right to perform any of the inspections set forth in the specification where such inspections are deemed necessary to assure supplies and services conform to prescribed requirements.

4.1.1 General provisions. The quality assurance provisions of this specification and of other documents referenced herein form the basis for inspection to be performed by the supplier. Inspection shall be in accordance with the requirements of Specification MIL-I-45208 and the component inspection requirements of Specification MIL-F-13926. Definitions of inspection terms not otherwise defined herein shall be as listed in Standard MIL-STD-109.

4.2 Inspection provisions.

4.2.1 *Inspection lot,* Unless otherwise specified by the contracting officer, inspection lot size, formation, and presentation of lots shall be in accordance with "Presentation of Lots and Drawing of Samples" specified in Standard MIL-STD-105.

4.2.2 *Examination and tests.* Components and subassemblies shall be inspected in accordance with the inspection provisions contained in Specification MIL-F-13926. Examinations and tests related to Section 3 herein shall be performed on a defect (individual characteristic) basis in accordance with Standard MIL-STD-105, and the inspection level and sampling plans specified in Table I titled "Classification of Defects". Examinations and tests for Packaging, Packing and Marking shall be in accordance with Specification MIL-P-14232 and Section 5 herein. The tabulated classification of defects shall constitute the minimum inspection to be performed by the supplier prior to Government acceptance or rejection by lot. The Government reserves the right to inspect for any applicable requirement, and to reject individual non-conforming items.

TABLE I. Classification of defects

Use Inspection Level II of Table III-A with Sampling Plan Table XV-A of Standard MIL-STD-106

Critical: None.

Major: *AQL 1.0% Defective.*

		Requirement	*Test procedure*
101.	Reset *button operation*	8.6.1	4.6.2.1
102.	*Relay K 25 & K 30 operation*	3.6.2	4.5.22
103.	*Zero position*	3.6.2.1	4.5.2.4.1
104.	*Relay K26 operation*	3.6.9	4.5.2.8
105.	*Relay K27 operation*	8.6.4	4.5.2.4
106.	*Stepping Switch operation*	3.6.5	4.6.2.4.2
107.	*Stepping switch coil and interrupter operation*	3.6.5.1	4.6.2.6
108.	*Sequential firing operation*	3.6.2	4.6.2.5
109.	*Zero reset*	3.6.5.3	4.6.2.6

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T05:49Z
Check the source to verify that this is the current version before use.

TABLE 1—Continued.

Major: AQL 1.0% Defective.	Requirement	Test procedure
110. Explosive bolt operation	3.6.6	4.5.2.6
111. Time delay action	3.6.6.1	4.5.2.6.1
112. Relay K28 operation	3.6.7	4.5.2.7
118. Diode CR 36	3.6.8	4.6.2.8
114. Continuity	3.6.9	4.5.2.9
115. VVeight	3.7	Spring Scale
116. Vibration	3.5.1	4.6.1.1
Minor: None.		

4.2.3 ***Disposition of non-conf orming product.*** Rejected lots shall be screened for all defective characteristics. Removal or ***correction*** of defective units and resubmittance of rejected lots shall be in accordance with "Disposition of Non-conforming Product" specified in Standard MIL-STD-105,

4.3 Control tests. Three interconnecting boxes shall be selected at random from each 100 produced, or from each months production, whichever occurs first. Control samples shall have successfully met all acceptance tests specified herein prior to conducting **the** following examinations and tests:

Control test	Requirment	Test procedure
Fabrication	3.1	Visual — Per drawings & Specifications
General Specification	3.2	Visual MIL-F-13926
Wires	3.3	Visual MIL-F-13926

4.3.1 ***Additional control sampling.*** Three additional samples shall be selected from the production quantities from which the above sampling was selected and all six samples shall then be subjected to the tests outlined below prior to determining compliance with 3.6. This inspection and examination shall be conducted by the contractor under the surveillance of the Government representative at the contractors facility or Government approved laboratory using test equipment authorized for use by the contractor or otherwise approved by the contracting officer.

(a) Shock,

(b) Temperature.

(c) Moisture-Fungus **Resistance.**

(d) Humidity.

4.3.1.1 Control ***test failure.*** Should the control test sample fail to meet the specified test requirement, acceptance of the product will be suspended by the Government until necessary corrections have been made by the contractor and the resubmitted samples have been approved.

4.4 **Inspection equipment.** Except as otherwise provided for by the contrac$ the contractor shall furnish and maintain all required measuring and testing equipment in accordance with the "Inspection Equipment" requirement of Specification MIL-1-45208. The Government reserves the right to use the test equipment for its own independent inspections to the extent that

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T05:49Z
Check the source to verify that this is the current version before use.

such use will not unduly interfere with the contractor's delivery schedule.

4.4.1 Contractor design. The contractor shall design and supply inspection equipment compatible with the "Test Methods and Procedures" specified in 4.5, and with the "Component Inspection" requirements of Specification MIL-F-13926. Concept, construction, materials, dimensions, and tolerances used in design of test equipment shall be so selected and controlled as to insure that the test equipment will permit positive rejection of a product which exceeds the prescribed tolerance limit, and will reliably indicate acceptability of a product which does not exceed 90~0 of the prescribed tolerance limit. Construction shall be such as to facilitate routine calibration of the equipment.

4.4.1.1 ***Devices used for environmental testing.*** All environmental testing devices used to determine conformance of the environmental requirements (listed below) shall conform to the "Test Facilities" requirements outlined in Specification MIL F-13926; except Moisture-Fungus Resistance (see MIL-T-152).

(a) Vibration.

(b) Shock.

(c) Temperature.

(d) Humidity.

(e) Moisture-Fungus Resistance.

4.4.1.2 In addition to the above mentioned requirements the following test equipment accuracies shall also apply.

Item	*Accuracy*
(1) Power supply 0-50V dc	Min. Amperage - 5 amps. Positive & Negative terminals required. Voltage accuracy (output) 5%.
(2) Voltmeter 0-50 V	all meter readings taken during the inspection shall fall within 30 to 80% of the scale range. The overall scale range shall have an accuracy of plus or minus 2 percent.
(3) Continuity checker	.02 ohms to 5000 megohms.
(4) Oscilloscope	Dual channel fast sweep 1 U sec\cm sensitivity 10 MV\C31.
(5) Switches	Standard type push button On and Off for operating within a voltage range between 5 to 28 V dc, 17 amps.

4.5 Test methods and procedures.

4.5.1 ***Environmental tests.***

4.5.1.1 Vibration. This test shall be the first test performed prior to performing the remaining acceptance inspection tests (see Classification of Defects, Table I) and the cover shall be removed prior to performing this test. The test conditions specified in **3.5.1** shall apply. At the conclusion of this test the interconnecting box shall be visually inspected as outlined below prior to being subjected to the remaining acceptance tests.

4.5.1.2 ***Post vibration.*** Subsequent to vibration, the interconnecting box shall be thoroughly inspected for physical defects resulting from poor workmanship and ma-

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T05:49Z
Check the source to verify that this is the current version before use.

terials. A visual examination shall be made for missing, damaged and loose internal mechanical and electronic parts. Any one defect shall be cause for rejection unless separate defects per hundred type sampling plans have been established and approved by the Government as part of the contractors inspection system. Interconnecting boxes which have passed this examination shall be subjected to the following tests prior to determining conformance with 3.6.

4.5.1.3 Shock. This test shall be performed as outlined in 8.5.2 and Procedure I of Specification MIL-F-13926. At the conclusion of this test the panel shall meet the requirements of 3.5.2.

4.5.1.4 *Temperature tests.*

4.5.1.4.1 *Operating temperature.* With the interconnecting box placed in the test equipment (4.4.1.1. (c)), the requirements of 3.6 shall be met at each of the temperatures specified in 8.6.3.1. Raising and lowering to the specified temperatures shall be done gradually to avoid thermal shock The temperature tolerances shall be in conformance with the "Test facilities" requirements of Specification MIL-F-13926, including the conditions specified for testing.

4.5.1.4.2 Storage temperature. This test shall be performed in accordance with the conditions and temperatures specified in 3.5.3.2. At the conclusion of this test procedure the interconnecting box shall be tested for conformance with the requirements of 3.6 at standard ambient temperature.

4.5.1.5 *Moisture-Fungus resistance. This* test shall be performed in accordance with the Moisture-Fungus Resistance tests outlined in Specification MIL-T-162 (Type II) to determine compliance with 8.6.5.

4.5.1.6 *Humidity. This* test shall be performed as outlined in Procedure I of Specification MIL-F-13926, however, the time limits specified in 3.5.4 shall apply.

4.5.2 *Electrical test.*

4.5.2.1 Reset button. When 28 Vdc is applied by means of item 1 of 4.4.1.2 to pins A B C & D of J4 as specified in 3.6, and the reset button is depressed, the zero indicator lamp shall be energized when the stepping switch is in the zero position and a voltage reading is taken between pins S and T of J1. This reading shall be within the limits specified in 3.6.1. Should the indicator fail to energize apply pressure on the lens. Should the indicator become energized, the switch is to be considered defective. Should the indicator fail to energize when the lens is depressed the bulb is defective. Should the indicator become energized, check for continuity between pins B of J4 and S of J1 and between pins L and K of J8 when the reset button is depressed. Lack of continuity indicates a defective switch.

4.5.2.2 *Operation of Relays K25 and K30.* Prior to applying voltages specified in 3.6 by means of item 1 of 4.4.1.2, connect a jumper between pin B-F of J7 and A of J1. Energize the pins specified in 3.6. by means of item 1 of 4,4.1.2. Voltage readings shall be taken (using item 2 of 4.4.1.2) at the pins specified in 3.6.2. The voltage reading shall conform to the values specified in 3.6.2 (a) and 3.6.2 (b).

4.5.2.3 Operation *of Relay K26.* Prior to applying the voltage to the pins outlined in 3.6, by means of item 1 of 4.4.1.2, connect a jumper between pins Z and G of J1. This jumper is in addition to that jumper specified in 4.5.2, Apply the voltage to the pins specified in 3.6 and measure the voltage (using item 2 of 4.4.1.2) between the pins listed in 3.6.3 (a) and 3.6.3 (b).

4.5.2.4 *Operation of Relay K27, zero petitioning and operation of stepping* switch. Prior to applying the voltage out lined in 3.6 (using item 1 of 4.4.1.2), connect a jumper between the pins of either Z and X of J1 or A and B of J1. This

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T05:49Z
Check the source to verify that this is the current version before use.

jumper is in addition to the jumper outlined in 4.5.2.3. With all jumpers in place, apply the voltage to the pins outlined in 3.6. A voltage reading (using item 2 of 4.4.1.2) shall be taken between pins R and T of J1. This voltage reading shall be within the limits specified in 3.6.4 (b). A voltage reading shall be taken between pins L or K and pin J. This voltage reading shall be within the limits of 3.6.4 (c). Repeat procedure above using alternate pins specified herein.

4.5.2.4.1 When the stepping switch is in the zero position, no voltage shall be present (using item 2 of 4.4.1.2) between pin j and any other pins of J2 and J3, in order to assure conformance with 3.6.5 (c). Continuity (item 3 of 4.4.1.2) shall be present between pin j and any other pin on J2 and J3, and no continuity shall exist between the pins of J2 and J3 with respect to pin J of J8. The indicator light shall be energized,

4.5.2.4.2 Remove the voltage from pins J1 and connect a jumper between pins M-J and L of J1. This jumper must contain a push button switch located between pins L and J; this jumper is in addition to those specified in 4.5.2.4. Closing the switch, the Zero indicator light shall be deenergized as specified in 3.6.5 (b), and a voltage reading shall be taken between pins j and F of J3 and between j and A of J2. A voltage reading indicates conformance with the requirements outlined in 3.6.4 (a), 3.6.6 (a), and 3.6.5 (d) ; and the normallY open contacts of K1 are closed and the normally closed contacts of K1 are open as outlined in 3.6.5 (C) .

4.%2.4.3 Failure *to obtain a voltage reading between pins j and A of J2, and j and F of J3.* Failure to obtain a voltage reading on the specified pins will require opening and reclosing the switch between pins L and J of J1 to move the wiper arm to firing position #2. With the wiper arm in this position, a voltage reading shall be obtained between the common ground j and B of J2 and E of J3 as specified in 3.6.5(a). *Obtaining a voltage reading at the second position* indicates a defective K1 system. Failure to obtain a voltage reading in firing position #2, will require opening and reclosing the switch in the jumper between pins L and J of J1. A voltage reading shall be taken between the common ground j and pin C of J2 and pin D of J3. Failure to obtain a voltage at firing position #3 indicates defective K27 Relay operation.

4.5.2.5 ***Operation of stepping switch coil, interrupter firing sequence and reset.*** Without disturbing the electrical connections outlined in 4,5.2.4, continue opening and reclosing the switch in the jumper located between pins L and J of J1. When the voltage is transferred from one pin of J2 and J3 to the next pin of J2 and J3, after each reclosing of the switch, the stepping switch coil and interrupter are in accordance with 3.6.5.1. Continue this opening and reclosing the switch until all 24 firing relays have been energized while simultaneously recording the voltage reading, using item 2 of 4.4.1.2 and noting their sequence, Both shall conform to the requirement outlined in 3.6.5.2. After the last firing relay has been energized, continue to open and reclose the switch specified above, eight (8) more times. On the ninth reclosing of the switch, the reset indicator shall be energized as specified in 3.6.5.3.

4.5.2.6 ***Explosive blot operation.*** Prior to performing any test, determine that continuity exists (using item 3 of 4.4.1.2) between the common ground ***f*** and the remaining pins of J5. There shall be no continuity between either pin A or B of J4, and all pins of J5.

4.5.2.6.1 ***Voltage and time check.*** Connect a jumper with a push button switch between pin C and B of J7. This jumper is in addition to the previously specified jumpers. The actual test is performed by connecting one channel of an oscilloscope

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T05:49Z
Check the source to verify that this is the current version before use.

(item 4 of 4.4.1.2) to pins F and common ground *f* of J5. Connect pin H and common ground f of J5 to the scope's second channel. When the push button switch is closed a voltage from pin H shall appear on the scope, and a second voltage from pin F shall appear on the scope. The voltages and time lag between voltages recorded on the scope shall conform to the requirement of 3.6.6 and 3.6.6.1. Repeat this procedure substituting pin S for II and pin M for F on J5.

4.5.2.7 ***Relay*** *K28* ***Operation.*** Prior to determining proper operation of Relay K28, observe that continuity (using item 2 of 4.4.1.2) does not exist between the following pins: E of J1 and H of J6, E and U of Jl, C and W of J1 and between C of J1 and E of J6. Next check for continuity between V of J1 and F of J6. Place a jumper between pins B of J7 and E of J1 Energize the pins of J1 as outlined in 3.6 (item 1 of 4.4.1.2), and measure the voltage between pins H of J6 and G of J7, and between U of J1 and G of J7. This voltage reading shall be within the limits specified in 3.6.7(a). Place jumper between pins F and H of J6. Zero voltage shall be recorded between pins G of J7 and V of J1 as specified in 3.6.7(b). Remove jumper from pin E of J1 and connect it to pin C of J1. Measure the voltage between pins E of J6 and G of J? and between G of J7 and W of J1. This voltage reading must be within the limits outlined in 3.6.7.1.

4.5.2.8 ***Diode CR*** *96. Remove all previously mentioned jumpers and connect a jumper between pin B of J7 and G of J6. Apply the voltage by using item 1 of 4.4.1.2 to the pins of J4 as specified in 3.6. Measure the voltage (using item 2 of 4.4.1.2) between pins G and E of J7. This voltage must conform to the limits outlined in 3.6.8.*

Custodian:

Army-MU

4.5.2.9 ***Continuity.*** Remove all power and jumpers and by means of a continuity checker (item 3 of 4.4.1.2), determine that continuity exists between the pins outlined in 3.6.9 within the limits specified.

5. PREPARATION FOR DELIVERY

5.1 Packaging, packing and marking. Packaging, packing and marking shall be in accordance with Specification MIL-P-14232 and Packaging Data Sheet MIL-P-14232/P8932942. The level of protection shall be as specified in the procurement document.

6. NOTES

6.1 Intended use. The interconnecting box is intended to:

(a) Provide for the electrical connection between the system components.

(b) Provide for resetting the stepping switch to the zero position.

(c) Provide visual indication, when the stepping switch is in the zero position.

6.2 Ordering data. Procurement documents should specify the following:

(a) Title, number and date of this specification.

(b) Selection of applicable levels of preservation, packaging and packing.

(c) Applicable stock number.

Preparing activity:

Army—MU

Project No. 1270-A002Y

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T05:49Z
Check the source to verify that this is the current version before use.