MIL-R-46388(MU)
17 September 1963
SUPERSEDING
FA(FC)-PD-183
17 April 1963

MILITARY SPECIFICATION

ROCKET ARMAMENT PANEL: 8933209

1. SCOPE

1.1 This specification covers one type of rocket armament panel, part of Fire Direction Set, Rocket, Aircraft: 5800965. The rocket armament panel consists of two sections; the rocket armament and jettison.

2. APPLICABLE DOCUMENTS

2.1 The following documents, of the issue in effect on date of invitation for bids or request for proposal, form a part of this specification to the extent specified herein:

SPECIFICATIONS

Military

MIL-T-152	Treatment Moisture-and Fungus-Resistant, of Communications, Electronic and Associated Electrical Equipment
MIL-F-13926	Fire Control Materiel; General Specification Governing the Manufacture and Inspection of
MIL-P-14232	Parts, Equipment and Tools for Ordnance Materiel; Packaging of
MIL-I-45208	Inspection Requirements, General Specification for

STANDARDS

Military

MIL-STD-105	Sampling Procedures and Tables for Inspection by Attributes
MIL-STD-109	Quality Assurance Terms and Definitions

FSC 1270

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T05:48Z
Check the source to verify that this is the current version before use.

DRAWINGS

U.S. Army Munitions Command

C8932941	Main Stepping Switch Assembly
D8933209	Rocket Armament Panel: 8933209

PACKAGING DATA SHEET

MIL-P-14232/P8933209	Packaging of Rocket Armament Panel: 8933209

(Copies of specifications, standards, drawings, and publications required by suppliers in connection with specific procurement functions should be obtained from the procuring activity or as directed by the contracting officer.)

3. REQUIREMENTS

3.1 Fabrication.- The rocket armament panel shall be manufactured in accordance with Drawing D8933209 and drawings pertaining thereto.

3.2 General specification.- The rocket armament panel shall meet the requirements of Specification MIL-F-13926, as specified below. Should any conflict exist between the general specification and this specification, this specification shall take precedence.

a. Order of precedence
b. Dimensions and tolerances
c. Inorganic protective surface finishes
d. Part identification and marking
e. Workmanship

3.3 Transistors.- Each assembly that is procured with transistors shall be furnished with the same transistors used when the assembly is tested.

3.4 Wires.- Wires shall be free of nicks.

3.5 Dressing.- Wire shall not be dressed so that it touches resistors of two watts or over.

3.6 Environmental service conditions.

3.6.1 Vibration.- The rocket armament panel shall withstand a vibration of a simple harmonic motion having an amplitude of 0.015 inch (0.03 inch total excursion). The frequency shall be

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T05:48Z
Check the source to verify that this is the current version before use.

varied uniformly between the limits of 10 to 55 cycles per second (cps) and return to 10 cycles. The cycle shall be traversed in approximately 1 minute. The motion shall be applied for a period of 10 minutes in each of the three mutually perpendicular directions (total of 30 minutes). During vibration the rocket armament panel shall meet the requirements of 3.7 except 3.7.2.2.1 and 3.7.2.6.1.

3.6.2 Shock.- The rocket armament panel shall withstand 3 shock impulses in each of the three mutually perpendicular directions. The acceleration of the shock impulses shall be 20 gravity units (G's). Pulse duration of each shock impulse shall be 11 ± 1 milliseconds. Subsequent to shock the rocket armament panel shall meet the requirements of 3.7.

3.6.3 Temperature.

3.6.3.1 Operating.- The rocket armament panel shall meet the requirements of 3.7 when thermally stabilized at ambient temperatures of -30°F and +145°F.

3.6.3.2 Storage.- The rocket armament panel shall meet the requirements of 3.7 at an ambient temperature of between 60°F to 90°F after having been thermally stabilized at ambient temperatures of -65°F and +165°F.

3.6.4 Humidity.- The rocket armament panel shall meet the requirements of 3.7 after being subjected to five 12-hour relative humidity (RH) cycles; each cycle consisting of the following conditions:

a. Water shall have a pH factor of between 6.5 and 7.5 at 77°F.

b. Exposure of 6 hours at 95% RH; 4-1/2 hours of which shall be at an ambient temperature of 115°F.

c. A variation once each hour during last 6 hours of ±9°F at an ambient temperature of 80°F.

d. A variation once each hour during last 6 hours from 95% RH to 100% RH with condensation. (Duration at 100% RH optional and need not coincide with hourly phase temperature variation).

3.6.5 Moisture - fungus resistance.- The rocket armament panel shall be treated per Type II for moisture - and fungus-resistance in accordance with Specification MIL-T-152.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T05:48Z
Check the source to verify that this is the current version before use.

3.7 Performance.- The functional characteristics, inclusive of 3.7 shall be exhibited with the following prevalent conditions:

a. +28 volts, direct-current (Vdc) applied between pins B and G of J1 (jack of jettison section), with ground return at pin G

b. Pins A, D and F of J1 shorted together

c. Pin B of J1 and pin B of J2 (jack of rocket armament section) shorted together

d. Pin L of J2 and G of J1 shorted together

NOTE: All symbols referred to herein, are those shown on Drawing D8933210.

3.7.1 SYSTEM POWER ON and JETTISON COMPLETE indicators.- The SYSTEM POWER ON and JETTISON COMPLETE indicators shall be energized at all times, when the POWER switch is in the ON position.

3.7.1.1 When the POWER switch is in the OFF position, the 28 Vdc power shall be disconnected from all circuits and all indicators shall be deenergized except the JETTISON POWER ON indicator.

3.7.2 Rocket armament section.

3.7.2.1 Output.- The output of the rocket armament section, when in coincidence with Stepping Switch 8932941 or equal, shall consist of 28 Vdc pulses at a rate of 6 ± 1 pulses per second (pps).

3.7.2.2 ARM-SAFE switch.- The spring-lock, 2-position type toggle switch shall appropriately arm or disarm the firing circuits when in the ARM or SAFE positions.

3.7.2.2.1 Switch actuation.- The pressure required to actuate the spring-loaded toggle switch to either of the two positions shall be between 4 and 6 pounds.

3.7.2.3 SAFE indicator.- The ARM-SAFE switch, when in the SAFE position, shall illuminate the SAFE indicator.

3.7.2.4 ZERO indicator.- The ZERO indicator shall be illuminated by the application of 28 Vdc.

3.7.2.5 ARM indicator.- The ARM-SAFE switch, when in the ARM position, shall illuminate the ARM indicator.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T05:48Z
Check the source to verify that this is the current version before use.

3.7.2.6 Rocket-burst selector switch.- The rocket-burst selector switch shall select a predetermined number of rocket pairs to energize the appropriate firing circuits. The predetermined number of firing circuits to be energized shall be in sequential pairs (ripples) of 1 through 6 (excepting 5) and 24, (a pair shall be defined as one rocket from each of the two pods).

3.7.2.6.1 Torque.- The snap-detent type positioning selector switch shall have a torque of between 12 and 16 ounce-inches from detent to detent.

3.7.2.7 Timing circuit.- The timing circuit employing the double-base diode (unijunction transistor) and resistive-capacitive (RC) network shall be controlled by the position of the rocket-burst selector switch.

3.7.2.8 Digital counter.- The digital counter actuated by a 28 Vdc pulse through the relay network shall indicate the number of rocket pairs which have been fired.

3.7.2.8.1 Total count.- The counter shall be capable of recording up to a minimum of 24 rocket pairs that have been fired.

3.7.2.8.2 Reset-button.- The reset-button of the digital counter shall be capable of nullifying any number of rocket pairs that have been registered as being fired.

3.7.3 Jettison section.

3.7.3.1 JETTISON switch.- The JETTISON switch, when in the firing or up position, shall supply 28 Vdc to be utilized in the explosive-bolt squibs' circuitry. With the JETTISON switch in the non-firing or down position and the SYSTEM POWER ON switch in the ON position, the JETTISON COMPLETE indicator shall light and the relay contacts of K3 (between pin C of [illegible]1 and the JETTISON switch) shall open.

3.7.3.2 JETTISON POWER ON indicator.- The JETTISON POWER ON indicator shall be illuminated at all times when a +28 Vdc main power source voltage is applied to the rocket armament panel.

3.7.4 Indicator failures.- The PRESS TO TEST method of the indicators shall signify whether the indicator lamps are defective or the circuitry is not functioning properly.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T05:48Z
Check the source to verify that this is the current version before use.

3.7.5 Indicator illumination.- The indicators when illuminated shall have sufficient illumination to be distinguishable by normal eye vision between a lighted and a non-lighted indicator from a minimum distance of 5 feet, when exposed to normal daylight without the direct rays of the sun focused on the indicators.

3.8 Weight.- The rocket armament panel shall be 3.5 ± 0.5 pounds.

4. QUALITY ASSURANCE PROVISIONS

4.1 Responsibility for inspection.- The supplier is responsible for the performance of all inspection requirements as specified herein. Except as otherwise specified, the supplier may utilize his own or any other inspection facilities and services acceptable to the Government. Inspection records of the examinations and tests shall be kept complete and available to the Government as specified in the contract or order. The Government reserves the right to perform any of the inspections set forth in the specification where such inspections are deemed necessary to assure supplies and services conform to prescribed requirements.

4.1.1 General provisions.- The quality assurance provisions of this specification and of other documents referenced herein form the basis for inspection to be performed by the supplier. Inspection shall be in accordance with the requirements of Specification MIL-I-45208 and the component inspection requirements of Specification MIL-F-13926. Definitions of inspection terms not otherwise defined herein shall be as listed in Standard MIL-STD-109.

4.2 Inspection provisions.

4.2.1 Inspection lot.- Unless otherwise specified by the contracting officer, inspection lot size, formation, and presentation of lots shall be in accordance with "Presentation of Lots and Drawing of Samples" specified in Standard MIL-STD-105.

4.2.2 Examination and tests.- Components and subassemblies shall be inspected in accordance with the inspection provisions contained in Specification MIL-F-13926. Examinations and tests related to Section 3 herein shall be performed on a defect (individual characteristic) basis in accordance with Standard MIL-STD-105, and the inspection level and sampling plans specified in Table I Title "Classification of Defects". Examination and tests for Packaging, Packing and Marking shall be in accordance with Specification MIL-P-14232 and Section 5 herein. The tabulated classification of defects shall constitute the minimum inspection to be performed by the supplier prior to Government acceptance or rejection by lot. The Government reserves the right to inspect

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T05:48Z
Check the source to verify that this is the current version before use.

for any applicable requirement, and to reject individual non-conforming items.

TABLE I - CLASSIFICATION OF DEFECTS

Use Inspection Level II of Table III-A with Sampling Plan Table IV-A of Standard MIL-STD-105

CRITICAL: NONE		REQUIREMENT	TEST PROCEDURE
MAJOR: AQL 1.5% Defective			
101.	Improper function of power indicator (on)	3.7.1	4.5.2.2
102.	Improper function of power indicator (off)	3.7.1.1	4.5.2.2
103.	Improper output	3.7.2.1	4.5.2.7
104.	Improper action arm-safe switch	3.7.2.2. 3.7.2.3	4.5.2.3 4.5.2.3.
105.	Improper zero indicator	3.7.2.4.	4.5.2.5
106.	Improper arm indicator	3.7.2.5	4.5.2.3
107.	Improper burst selection switch	3.7.2.6	4.5.2.8
108.	Improper timing circuit	3.7.2.7	4.5.2.9
109.	Improper function of digital counter	3.7.2.8	4.5.2.10
110.	Improper function of jettison switch	3.7.3.1	4.5.3
111.	Improper jettison power-on indication	3.7.3.2	4.5.3
112.	Improper indicator action	3.7.4	4.5.2.2
113.	Improper indicator illumination	3.7.5	4.5.4
MINOR: AQL 4.0% Defective			
201.	Improper switch actuation	3.7.2.2.1	4.5.2.4
202.	Improper burst selection switch torque	3.7.2.6.1	4.5.2.6

4.2.3 Disposition of non-conforming product.- Rejected lots shall be screened for all defective characteristics. Removal or correction of defective units and resubmittance of rejected lots shall be in accordance with "Disposition on Non-conforming Product" specified in Standard MIL-STD-105.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T05:48Z
Check the source to verify that this is the current version before use.

4.3 Control tests.- Three panels shall be selected at random from each 100 produced, or from each months production, whichever occurs first. Control samples shall have successfully met all acceptance tests specified herein prior to conducting the following examinations and tests:

CONTROL TEST	REQUIREMENT	TEST PROCEDURE
Fabrication	3.1	Per Dwgs.
General Specification	3.2	Visual & MIL-F-13926
Wires	3.4	Visual - MIL-F-13926
Dressing	3.5	Visual - MIL-F-13926

4.3.1 Additional control sampling.- Three additional samples shall be selected from the production quantities from which the above sampling was selected and all six samples shall then be subjected to the test outlined in 4.5.1 to determine compliance with 3.6. This inspection and examination shall be conducted by the contractor under the serveillance of the Government representative at the contractors facility on Government approved laboratory using test equipment authorized for use by the contractor or otherwise approved by the contracting officer.

4.3.1.1 Control test failure.- Should the control test sample fail to meet the specified test requirements, acceptance of the product will be suspended by the Government until necessary corrections have been made by the contractor and the resubmitted samples have been approved.

4.4 Inspection equipment.- Except as otherwise provided for by the contract, the contractor shall furnish and maintain all required measuring and testing equipment in accordance with the "Inspection Equipment" requirement of Specification MIL-I-45208. The Government reserves the right to use the test equipment for its own independent inspections to the extent that such use will not unduly interfere with the contractor's delivery schedule.

4.4.1 Contractor design.- The contractor shall design and supply inspection equipment compatible with the "Test Methods and Procedures" specified in 4.5, and with the "Component Inspection" requirements of Specification MIL-F-13926. Concept, construction, materials, dimensions, and tolerances used in design of test equipment shall be so selected and controlled as to insure that the test equipment will permit positive rejection of a product which exceeds the prescribed tolerance limit, and will reliably indicate acceptability of a product which does not exceed 90% of the prescribed tolerance limit. Construction shall be such as to facilitate routine calibration of the equipment.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T05:48Z
Check the source to verify that this is the current version before use.

4.4.1.1 Devices used for environmental testing.- All environmental testing devices used to determine conformance of the environmental requirements (except Fungus Resistance) shall conform to the "Test Facilities" requirements outlined in Specification MIL-F-13926. The accuracy for Fungus Resistance shall be as specified in MIL-T-152.

a. Vibration
b. Shock
c. Temperature
d. Fungus Resistance

4.4.1.2 In addition to the above mentioned requirements the following test equipment accuracy shall also apply:

	Item	Accuracy
(1)	Volt Meter 0-50 Volts D.C.	All meter readings taken during inspection shall fall within 30 to 80 percent of the scale range. The overall scale range shall have an accuracy of plus or minus 2 percent.
(2)	Power Supply 0-50 Volts D.C.	.05 to 20 v/cm.
(3)	Switch	Standard type push button on-for operating voltage, voltage between 5 and 50 V.D.C.
(4)	Stepping Switch	Operating voltage 26-32 Vdc 3 level nonbridging wiper self cycling operation Positive Position speed approx 65 steps/sec. Double trim-nondouble load.
(5)	Oscilloscope	1 U Sec/CM Slowest, .5 Sec/CM sensitivity 10 MV/CM

4.5. Test Methods and procedures.

4.5.1 Environmental tests.

4.5.1.1 Vibration.- This test shall be performed as outlined in Procedure I Condition D of Specification MIL-F-13926, however,

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T05:48Z
Check the source to verify that this is the current version before use.

the time duration specified in 3.6.1 shall apply. During vibration the rocket armament panel shall be tested as outlined, herein for conformance to the requirements of 3.6.1.

4.5.1.2 Post vibration.- Subsequent to vibration, the panel shall be thoroughly inspected for physical defects resulting from poor workmanship and materials to determine compliance with 3.6.1 prior to being subjected to the remaining tests specified herein. A visual examination shall be made for missing or damaged parts prior to being subjected to the remaining tests. An audible examination shall be made by holding the panel close to the ear and shaking it by hand to detect loose internal mechanical and electronic parts. Any one defect shall be cause for rejection unless separate defects perhundred type sampling plans have been established and approved by the Government as part of the contractors inspection system. Panels which have passed this examination shall be subjected to the following test to determine conformance with 3.7.

4.5.1.3 Shock.- This test shall be performed as outlined in 3.6.2 and Procedure I of Specification MIL-F-13926. At the conclusion of this test the panel shall meet the requirements outlined in 3.6.2.

4.5.1.4 Temperature tests.

4.5.1.4.1 Operating temperature.- With the panel placed in the test equipment (4.4.1.1.(c)), the requirements of 3.7 shall be met at each of the temperatures specified in 3.6.3.1. Raising and lowering to the specified temperatures shall be done gradually to avoid thermal shock. The temperature tolerances shall be in conformance with the "Test facilities" requirements of Specification MIL-F-13926, including the conditions specified for testing.

4.5.1.4.2 Storage temperature.- This test shall be performed as outlined in Procedure II of Specification MIL-F-13926, however, the temperatures specified in 3.6.3.2 shall apply. At the conclusion of this test procedure the panel shall be tested for conformance with the requirements of 3.7 at standard ambient temperature.

4.5.1.5 Moisture-Fungus resistance.- This test shall be performed as outlined in Specification MIL-T-152(Type II). At the conclusion of the test, the panel shall meet the requirements outlined in 3.7.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T05:48Z
Check the source to verify that this is the current version before use.

4.5.1.6 Humidity.- This test shall be performed as outlined in Procedure I of Specification MIL-F-13926, however, the time limits specified in 3.6.4 shall apply. At the conclusion of the test the panel shall meet the requirements of 3.7 at standard ambient temperatures.

4.5.2 Electrical test.

4.5.2.1 Performance.- Prior to performing the electrical test, the panel shall be energized as specified in 3.7.

4.5.2.2 System power ON and system failure.- When the voltage specified in 3.7 is applied, all indicators shall be energized in conformance with 3.7.1 when the power switch is in the ON position and 28 Vdc shall be present between pins F and G, D and G and A and G of J1. When the switch is in the OFF position voltage shall be removed from the above mentioned pins; all lights except the JETTISION POWER-ON indicator shall be de-energized as specified in 3.7.1.1. With the switch in the OFF position, all indicators mentioned in 3.7.4 shall be energized by exerting pressure on the indicators except JETTISON POWER-ON. Remove 28 Vdc from pin B of J1 and apply to pin B of J2 JETTISON POWER-ON indicator will de-energize and will be energized when pressure is applied to the JETTISON POWER-ON indicator.

4.5.2.3 Arm-Safe Switch and Indicators.- Prior to applying voltage outlined in 3.7 set ARM-SAFE switch in the SAFE position; place a jumper between pins B-F, and C-D of J-2. The SAFE Indicator shall be energized as specified in 3.7.2.3. Connect a jumper between pins G-F of J-2 to energize oscillator relay KI, SAFE indicator shall be de-energized. Place a jumper between pins A-E of J-2 and set ARM-SAFE switch to the ARM position. ARM indicator shall be energized as specified in 3.7.2.5 and the numerical counter shall register one count for each oscillating cycle of relay K-I. Return ARM-SAFE switch to SAFE position; ARM and SAFE indicators shall be de-energized. Return ARM-SAFE switch to ARM position; ARM indicator shall be energized and the numerical counter shall register an additional count. Return ARM-SAFE switch to SAFE position, ARM-SAFE indicators shall be de-energized. Remove jumper from pins G-F of J-2, the SAFE indicator shall be energized. When the racket armament panel conforms as outlined above, the ARM-SAFE switch complies with requirements of 3.7.2.2.

4.5.2.4 Switch torque.- By means of standard measurement equipment and an appropriate adapter, measure the pressure required to actuate the switches. This pressure must conform to the limits outlined in 3.7.2.2.1.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T05:48Z
Check the source to verify that this is the current version before use.

4.5.2.5 ZERO indicator.- With panel energized as outlined in 3.7 place a jumper between pins B and K of J2 to energize the indicator to determine compliance with 3.7.2.4. Remove jumper and apply pressure to the ZERO indicator lens. This should energize the indicator light and illuminate the lens in compliance with 3.7.4.

4.5.2.6 Torque selector switch.- By means of standard measuring equipment and an appropriate adapter, measure the torque required to move the switch from one position to another; the required torque shall conform to the limits outlined in 3.7.2.6.1.

4.5.2.7 Output.- The output (pulse rate) specified in 3.7.2.1 shall be measured after the following electrical connection have been made and are in addition to those outlined under 3.7.

a. Connect a jumper with a standard type ON-OFF push button switch between pins B and H of J2

b. Connect pins F and G of J2 to the interrupter contacts of the stepping switch listed as item 4 in paragraph 4.4.1.2.

c. Connect pin C of J2 to one end of the stepping switch coil. Connect the remaining end of coil to pin L of J-2.

d. Connect an oscilloscope between pins G and L of J-2.

4.5.2.7.1 The actual test is made when the voltage specified in 3.7 is applied, and the push button switch between pins B and H of J-2 is closed. The voltage (pulse rate) as read on the oscilloscope must conform with the requirement outlined in 3.7.2.1.

4.5.2.8 Rocket burst selector switch.- Proper setting of the rocket burst selector switch shall be determined after the following electrical connections have been made and are in addition to those outlined in 3.7:

a. Connect a jumper with a standard type ON-OFF push button switch between pins B and J of J-2

b. Connect a jumper between pins A and E of J-2

c. Set the ARM-SAFE switch in ARM position

d. Connect pins C and L of J-2 to the coil contacts of the stepping switch, item 4 in paragraph 4.4.1.2

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T05:48Z
Check the source to verify that this is the current version before use.

e. Connect one lead of the relay (item 4) to pin G of J-2

f. Connect a lead of the moveable contact (item 4) to pin F of J-2

g. Connect an oscilloscope between the remaining contact of the relay and pin L of J-2

h. Place the selector switch on #1 position

4.5.2.8.1 When 28 Vdc is applied, the pulse (voltage) shall appear on the oscilloscope when the push button switch between pins B and J of J2 is depressed. For each pulse shown on the oscilloscope one count shall be recorded on the counter. Repeat this procedure for each setting of the selector switch. The number of pulses shall conform to the requirements of 3.7.2.6.

4.5.2.9 Timing circuit.- With the electrical set-up specified in 4.5.2.8, operation and control of the timing circuit shall be determined by observing the number of pulses appearing on the scope and the numerical count recorded on the counter. Both must be compatible with the pre-determined selection set by the selector switch as specified in 3.7.2.7.

4.5.2.10 Digital counter.- With the electrical set-up described in 4.5.2.8, the digital counter and relay network shall operate as specified in 3.7.2.8.1 when the voltage specified in 3.7.2.8 is applied. Depression of the reset button on the counter shall nullify the count shown on the counter as specified in 3.7.2.8.2.

4.5.3 JETTISON switch.- Positive action of the JETTISON switch shall be determined after the electrical connections outlined in 3.7 have been made.

4.5.3.1 With the system energized as outlined in 3.7, the JETTISON POWER indicator shall be energized and no voltage shall be recorded on the voltmeter connected between pins AG and CG of J1 when the JETTISON switch is open. When this switch is closed, Relay K3 is energized, and a voltage will be present between pins C and G of J1; and no voltage shall be recorded between pins A-G of J-1.

4.5.3.1.1 Open the JETTISON switch, close the power switch. All indicators shall be energized as specified in 3.7.3.2 and a voltage shall not be recorded between C-G of J-1; indicating the relay contacts of K-3 are open as specified in 3.7.3.1.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T05:48Z
Check the source to verify that this is the current version before use.

4.5.4 Indicator illumination.- When the indicators are energized, the amount of illumination shall conform to requirements of 3.7.5. This inspection shall be performed under lighting conditions specified in 3.7.5.

5. PREPARATION FOR DELIVERY

5.1 Packaging, packing and marking.- Packaging, packing and marking shall be in accordance with Specification MIL-P-14232 and Packaging Data Sheet MIL-P-14232/P8933209. The level of protection shall be as specified in the procurement document.

6. NOTES

6.1 Intended use.- The rocket armament panel is intended to:

a. Select the number of rounds to be fired in a ripple or ripples

b. Provide 28 Vdc pulses at a burst-rate of 6 ± 1 pulses per second to arm the firing circuits

c. Record the number of pairs of rounds fired during a mission

d. Provide for the jettisoning of the pod assemblies in the event of emergencies

e. Indicate the appropriate functions of the controls and related circuitry

6.2 Ordering data.- Procurement documents should specify the following:

a. Title, number and date of this specification

b. Selection of applicable levels of preservation, packaging and packing

c. Applicable stock number

Custodian:

Army-MU

Preparing activity:

Army - MU

Project No. 1270-A001Y

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T05:48Z
Check the source to verify that this is the current version before use.