MIL-C-49144 (CR)
AMENDMENT 3
15 January 1988
SUPERSEDING
AMENDMENT 2
16 April 1985

MILITARY SPECIFICATION

Charger, Battery, PP-7286/U

This amendment forms a part of Military Specification MIL-C-49144(ER), dated 5 August 1982, and is approved for use by the Communications-Electronics Command, Department of the Army, and is available for use by all Departments and Agencies of the Department of Defense.

Page 6

Paragraph 3.11 Delete and substitute:

"3.11 Burn-in. (See 4.6) Each equipment on order shall be subjected to a burn-in of a minimum of 48 hours with the last 24 hours failure free. The equipment shall be capable of meeting the requirements herein after subjection to the burn-in of 4.6. Upon completion of the burn-in, the equipment shall be calibrated (See 4.6.3.)."

Page 8

Table I Delete Item 7, Test paragraph, and substitute:

"Item 7	Group D Reliability	Test 4.5.4.5"

Page 9

Paragraph 4.5 Delete and substitute:

"4.5 Quality conformance inspection of equipment before packaging. The contractor shall perform the inspection specified in 4.4 and 4.5.1 through 4.6. This does not relieve the contractor of his responsibility for performing any additional inspection which is necessary to control the quality of the product and to assure compliance with all specification requirements."

AMSC N/A
DISTRIBUTION STATEMENT A. Approved for public release; distribution is unlimited.

FSC 6130

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T19:52Z
Check the source to verify that this is the current version before use.

Paragraph 4.5.1 Delete and substitute:

"4.5.1 Group A inspection. Each unit on contract shall be inspected for conformance to the inspections specified in Table II. Discrete losts shall be formed from units that pass this inspection. Factors of lot composition not defined herein, or in the contract, shall be in accordance with MIL-STD-105, using the general inspection levels and AQL's indicated in Table II. Calibration of the equipment shall be performed at the contractor's facility prior to Group A testing (see 4.6.3)."

Paragraph 4.5.2 Delete and substitute:

"4.5.2 Group B inspection. Group B inspection shall be performed on samples selected from units that have been subjected to and met Group A inspection. Upon completion of Group B testing, staking compound shall be applied to the TB1-R12 adjustment potentiometer used to calibrate the equipment. This inspection shall conform to Table III herein and to the special inspection levels of Table I of MIL-STD-105."

Page 11

Table V Delete and substitute:

"Table V, Group D Inspection

Inspection	Req. Para.	Insp. Para.
Reliability	3.10	4.5.4.5"

Page 12

Paragraph 4.5.4.2 Delete and substitute:

"4.5.4.2 Performance measurements. At least once daily the performance parameters shall be measured with the equipment stabilized at the high temperature and the absolute value on all channels adjusted to 150 ma. If the value of this parameter does not stay within tolerence of 3 ma., a failure shall be recorded and the required action shall be taken. The failure shall be presumed to have occurred immediately after the last successful measurement of the same parameter."

Page 13

Paragraph 4.5.4.5 Delete and substitute:

"4.5.4.5. Quality Conformance (Group D) Reliability Test. The equipment shall be tested in accordance with test plan XXIC of MIL-STD-781 to demonstrate a lower test MTBF (0_1) of 2000 hrs. The environmental conditions shall be the same as Burn-In."

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T19:52Z
Check the source to verify that this is the current version before use.

Paragraph 4.6.1 Delete and substitute:

"Chamber temperature: 100 ± 5°F

Line Voltage: 1st 24 hours at 115 ± 0.5V, 2nd 24 hours at 230 ± 1.0V

Load: Short circuit on all channels, current meter set to 150 ± 2ma. on all channels.

Vibration: 22Hz, 2.2g. non-operating, 30 minutes/day"

Add: 4.6.3 Calibration procedure.

"a. Using a heavy rubberband, fasten interlock switch in closed position.

b. Set INPUT VOLTAGE switch to 115V.

c. Connect power cable to a 115 VAC source.

d. Set BATTERY SELECT switch to 3.

e. Set all CURRENT SET switches to the 200 MA position.

f. Connect positive lead of digital multimeter (HP 3465B or equiv.) to red REMOTE BATTERY terminal of channel 3 and negative lead to black terminal of channel 3.

g. Set to a scale that will conveniently read 100 mA.

h. Set POWER switch to ON.

i. Set SET CHARGE TIME control 01.0; press START TIME switch.

j. Using a small bladed screw driver, adjust CURRENT SET FINE ADJ control for channel 3 so that the multimeter reads 100 ±0.10 mA.

k. Adjust TB1-R12 potentiometer so that the panel meter reads 100 mA."

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T19:52Z
Check the source to verify that this is the current version before use.

Paragraph 6.7.1 Delete and substitute:

"6.7.1 Equipment failure. Equipment failure is defined as the inabiltiy of the PP-7286/U Battery Charger to perform its function as specified herein to include damage resulting from improper operation. Damage which results from abuse is not a failure nor is the need for adjustment of the operator's controls. The need for calibration of the equipment is not considered to be a failure."

Custodian:
Army - CR

Preparing activity:
Army - CR

(Project 6130-A292)

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T19:52Z
Check the source to verify that this is the current version before use.