MILITARY SPECIFICATION SHEET

GENERATOR SET, DIESEL ENGINE DRIVEN,

100 KILOWATT, 400 HERTZ, PRECISE, (TACTICAL)

This specification sheet is approved for use by all Departments and Agencies of the Department of Defense.

The complete requirements for procuring the generator set described herein shall consist of this document and the issue in effect of Specification MIL-G-52884/GEN.

1. SCOPE

1.1 Scope. This specification sheet covers the detail requirements for Type I (Tactical) Generator Sets, Size 100 KW, Mode II (400 Hz) Class 1 (Precise), Model MEP-116A, NSN 6115-00-133-9103.

2. APPLICABLE DOCUMENTS

DRAWINGS

TA 30554-70-11c	- Generator Set, Diesel Engine, 100 KW, 400 Hz, Tactical Precise, Mode II, Class 1.

3. REQUIREMENTS

3.1 Requirements. Requirements shall be in accordance with MIL-G-52884/GEN and as specified herein.

3.2 Description. The set shall be in accordance with Top Assembly TA 30554-70-11c and as specified herein.

3.2.1 Reliability. The set shall have a reliability of 380 hours (minimum acceptable) Mean-Time-Between-Failure (MTBF).

3.3 Operating speeds. Operating (rated) speed shall be 2000 rpm.

3.4 Maximum power. The maximum power in kilowatts of the set shall be not less than 125 KW.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T21:38Z
Check the source to verify that this is the current version before use.

3.5 Engine.

3.5.1 Engine horsepower. The minimum continuous brake horsepower of the engine shall be 168 bhp at 1800 rpm.

3.5.2 Engine safety devices. The trip points for engine safety devices shall be as specified in the general specification. The low lubricating oil pressure device shall trip at 15 plus or minus 3 psi.

3.6 Governing system. The electric governing system shall be adjusted such that the set will meet the performance requirements herein.

3.6.1 Frequency regulation. The system shall provide isochronous operation, i.e., for every load change (including rated load) the frequency regulation shall not exceed 1/4 of 1 percent of rated frequency.

3.6.2 Short term stability (30 seconds). At every constant load from no-load to rated load, the system shall maintain frequency within a bandwidth equal to 1/2 of 1 percent of rated frequency. The system shall not permit repetitive periodic frequency variations, commonly called "hunting", even though within the allowable 1/2 of 1 percent band.

3.6.3 Long term stability (4 hours). At constant ambient temperature, constant barometric pressure, constant voltage and any constant load from no-load to rated load, the system shall maintain frequency within a bandwidth equal to 1 percent of rated frequency in a 4 hour operation period.

3.6.4 Transient performance. Following a sudden increase or decrease in load up to and including rated load, the governing system shall reestablish stable engine operating conditions within 2 seconds. The maximum transient frequency change above or below the new steady-state frequency shall be not more than 4 percent of rated frequency.

3.6.5 Frequency adjustment. By means of the potentiometer on the control cubicle, it shall be possible to adjust the frequency (when the set is operating at any constant load) as follows:

- Between 390 and 420 Hz but not below 370 Hz nor above 430 Hz.

It shall not be possible to adjust frequency to a value which will actuate the overspeed protective device.

Source: https://assist.dla.mil -- Downloaded: 202610-22T21:38Z
Check the source to verify that this is the currentversion before use.

3.7 Generator and excitation system.

3.7.1 Transient reactance, rated voltage. The direct axis transient reactance shall be not more than 16 percent.

3.7.2 Negative sequence impedance. The negative sequence impedance shall be not more than 15 percent.

3.7.3 Voltage regulation. The voltage regulation from no-load to rated load and from rated load to no-load shall be not more than 1 percent of rated voltage.

3.7.4 Short term stability (30 seconds). At every constant load from no-load to rated load, the voltage at the set terminals shall remain within a bandwidth equal to 1 percent of rated voltage.

3.7.5 Long term stability (4 hours). At constant ambient temperature, constant barometric pressure, constant frequency and any constant load from no-load to rated load, the voltage shall remain within a bandwidth of 2 percent of rated voltage in a 4 hour operation period.

3.7.6 Transient performance. Performance of the set under transient conditions (as measured by a magnetic oscillograph) shall be as follows (reactive droop compensation of the voltage regulator being inoperative):

(a) With the set initially operating at no-load, rated voltage, and rated frequency the rms terminal voltage of the set shall not drop to less than 75 percent of no-load voltage (rated voltage) when a balanced 3-phase 0.4 pf (or less, lagging), static load having an impedance of 0.5 per unit is suddenly applied to the output terminals of the set. When connected to the specified load, the generator shall recover to a minimum of 95 percent rated voltage within 0.7 seconds and shall stabilize at or above this voltage. The above specified voltage dip shall not be exceeded when a fully-loaded induction motor of the above specified impedance is used in place of a static load, and no reactions shall be set up to prevent full acceleration of the motor with rated torque applied to its shaft.

(b) When the set is initially operating at rated frequency, rated voltage, and following any sudden change in load from no-load to full load, the instantaneous rms voltage shall not drop to less than 88 percent of rated voltage and shall reach stable conditions within 0.5 seconds; no overshoot or undershoot of the final voltage may exceed the initial voltage transient in amplitude. The above requirements shall also apply when load is suddenly changed from full load to no-load, except that the initial voltage transient shall not exceed 112 percent of rated voltage.

Source: https://assist.dla.mil -- Downloaded: 202610-22T21:38Z
Check the source to verify that this is the current version before use.

(c) The generator set shall be capable of across-the-line starting a motor rated at 1 horsepower per kW.

3.7.7 Voltage operating range. The set shall operate at any loads between no-load and rated load at the following line-to-line voltages:

(a) Between 395 and 458 volts for the 240/416 volt connection and between 197 and 229 volts for the 120/208 volt connection.

3.8 Parallel operation. With their governor and voltage regulator paralleling circuits properly interconnected; with the voltage across Pins A and B of the respective parallel receptacles initially adjusted to an equal value between 4 and 6 volts, at rated load, three sets of the same mode and size be capable of operating in parallel and dividing load in accordance with the following as system load at rated power factor is varied between zero and 100 percent (and vice versa) of the combined rating of the connected sets:

(a) Real power division. At no time shall the difference between the average individual kilowatt outputs of the sets, when supplying the system load, be greater than 10 percent of the kilowatt rating of one set.

(b) Power exchange. At any constant system load up to the combined rating of the sets in parallel, power exchange between the sets shall not exceed 10 percent of the kW rating of one set. Power exchange is the difference between the maximum and minimum power output delivered by one set, for constant system load conditions, as determined from oscillographic measurements.

(c) Reactive power division. At no time shall the difference in average reactive kVA supplied by the sets differ by more than 10 percent of the reactive kVA rating of one set. For the above requirements, the initial system load shall be equally divided between the sets, both as to active and reactive components; thereafter, there shall be no adjustments to governors, voltage regulators, or any other component as system load is changed.

3.9 Protective devices.

3.9.1 Underfrequency. This device shall operate when the frequency drops below 370 plus or minus 5 Hz. The device shall not permit closure of the set output circuit interrupter at frequencies below those specified above.

3.9.2 Permissive parallel relay. This device shall actuate when the signal voltage exceeds 8 plus or minus 1.0 volts rms.

Source: https://assist.dla.mil -- Downloaded: 202610-22T21:38Z
Check the source to verify that this is the currentversion before use.

3.9.3 Undervoltage. This device shall operate instantaneously when the voltage drops below 48 volts. It shall not operate instantaneously at voltages above 65 volts. In addition, the device shall operate in 6 plus or minus 2 seconds after the voltage has fallen to and remained at not more than 99 plus or minus 4 volts.

3.10 Audio noise. The audio noise sound pressure levels shall not exceed the band pressure levels listed in Table "A". Measurements shall be taken with the set operating at any load up to and including rated load. The microphone(s) shall be located 5 feet, 8 inches above ground at positions 25 feet from the perimeter of the set at the center of each side and at each corner of the set (8 positions).

Table "A"
Commercial Frequencies

Octave Band Limits (Hz)	Center Frequency (Hz)	Noise Limit
37.5-75	53	86
75-150	106	95
150-300	212	82
300-600	425	83
600-1200	850	82
1200-2400	1700	80
2400-4800	3400	75
4800-9600	6800	70

Custodians:

Army - ME
Navy - YD
Air Force - 80

Preparing activity:

Army - ME

Project No. 6115-0175/12

Source: https://assist.dla.mil -- Downloaded: 202610-22T21:38Z
Check the source to verify that this is the current version before use.

STANDARDIZATION DOCUMENT IMPROVEMENT PROPOSAL

OMB Approval
No. 22-R255

INSTRUCTIONS: The purpose of this form is to solicit beneficial comments which will help achieve procurement of suitable products at reasonable cost and minimum delay, or will otherwise enhance use of the document. DoD contractors, government activities, or manufacturers/vendors who are prospective suppliers of the product are invited to submit comments to the government. Fold on lines on reverse side, staple in corner, and send to preparing activity. Comments submitted on this form do not constitute or imply authorization to waive any portion of the referenced document(s) or to amend contractual requirements. Attach any pertinent data which may be of use in improving this document. If there are additional papers, attach to form and place both in an envelope addressed to preparing activity.

DOCUMENT IDENTIFIER AND TITLE MIL-G-52884/12 Generator Set, Diesel Engine Driven, 100 Kilowatt, 400 Hertz, Precise, (Tactical)

NAME OF ORGANIZATION AND ADDRESS

CONTRACT NUMBER

MATERIAL PROCURED UNDER A

☐ DIRECT GOVERNMENT CONTRACT ☐ SUBCONTRACT

1. HAS ANY PART OF THE DOCUMENT CREATED PROBLEMS OR REQUIRED INTERPRETATION IN PROCUREMENT USE?

A. GIVE PARAGRAPH NUMBER AND WORDING

B. RECOMMENDATIONS FOR CORRECTING THE DEFICIENCIES

2. COMMENTS ON ANY DOCUMENT REQUIREMENT CONSIDERED TOO RIGID

3. IS THE DOCUMENT RESTRICTIVE?

☐ YES ☐ NO (If "Yes", in what way?)

4. REMARKS

SUBMITTED BY (Printed or typed name and address - Optional)

TELEPHONE NO.

DATE

DD FORM 1 JAN 72 1426

REPLACES EDITION OF 1 JAN 68 WHICH MAY BE USED

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T21:38Z
Check the source to verify that this is the current version before use.

FOLD

POSTAGE AND FEES PAID
DEPARTMENT OF THE ARMY
DOD – 314

OFFICIAL BUSINESS
PENALTY FOR PRIVATE USE $300

Commander
US Army Mobility Equipment Research and
Development Command
ATTN: DRXFB-DS
Fort Belvoir, VA 22060

FOLD

Source: https://assist.dla.mil -- Downloaded: 202610-22T21:38Z
Check the source to verify that this is the current version before use.