INCH-POUND
MIL-DTL-53133/5B
15 April 2002
SUPERSEDING
MIL-DTL-0053133/5A(ME)
26 July 1996
And MIL-G-53133/5
30 August 1993

DETAIL SPECIFICATION SHEET

GENERATOR SETS, SKID MOUNTED, TACTICAL, QUIET,

DIESEL ENGINE DRIVEN, ALTERNATING CURRENT

15 KILOWATTS, 50/60 HERTZ

Inactive for new design after 11 August 1997.

This specification is approved for use by all Departments and Agencies of the Department of Defense.

The requirements for acquiring the product described herein shall consist of this specification sheet and the issue of MIL-DTL-53133 listed in that issue of the Department of Defense Index of Specifications and Standards (DoDISS) specified in the solicitation.

1. SCOPE

1.1 Scope. This specification sheet covers the detail requirements for tactical generator sets, size 15 kW, mode I (50/60 Hz), model MEP-804A, NSN 6115-01-274-7388.

2. APPLICABLE DOCUMENTS

2.1 Government drawings. The following Government drawings form a part of this specification sheet to the extent specified herein. Unless otherwise specified, the issues are those cited in the solicitation.

AMSC N/A FSC 6115
DISTRIBUTION STATEMENT A. Approved for public release; distribution is unlimited.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T22:12Z
Check the source to verify that this is the current version before use.

DRAWINGS

TA 30554-88-804 - Generator Set, Tactical, Quiet, 15 kW, 50/60 Hz.

(Copies of drawings required by contractors in connection with specific acquisition functions should be obtained from the US Army Communications-Electronics Command, ATTN: AMSEL-LC-ED-BG, 10115 Gridley Road, Ste 201, Fort Belvoir, VA 22060-5849.)

3. REQUIREMENTS

3.1 Requirements. Requirements for acquiring the product described herein shall consist of this document and MIL-DTL-53133.

3.2 Description. The set shall be in accordance with TA 30554-88-804 and as specified herein.

3.3 Reliability. The minimum acceptable mean time between failure (MTBF for the set shall be 538 hours with a 80 percent lower confidence limit.

3.4 Size and weight. The maximum operating set dimensions with control panel doors closed and the total operational weight shall not exceed the following:

Parameter	Dimension
Length	1760 mm (69.3 inches)
Width	897 mm (35.3 inches)
Height	1374 mm (54.1 inches)
Weight	963.4 kg (2124 pounds)

3.5 Fuel consumption. Fuel consumption, at all loads up to and including rated load, shall not be more than 5.69 l/h (1.50 gallons per hour [GPH]) when the set is operating on referee grade diesel fuel conforming to MIL-F-46162.

3.6 Parallel operation. With their governor and voltage regulator paralleling circuits interconnected, two sets of the same mode and size operated in parallel shall divide load in accordance with the following as system load (at rated power factor) is varied between zero and 100 percent (and vice versa) of the combined rating of the connected sets:

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T22:12Z
Check the source to verify that this is the current version before use.

a. Real power division. At no time shall difference between the average individual kilowatt outputs of the set, when supplying the system load, be greater than 10 percent of the kilowatt rating of one set.

b. Power exchange. At all constant system loads up to the combined rating of the sets in parallel, power exchange between the sets shall not exceed 20 percent of the kilowatt rating on one set. Power exchange is the difference between the maximum and minimum power output delivered by one set for constant system load conditions, as determined from oscillographic measurements.

c. Reactive power division. At no time shall the difference in average reactive kilovolt-ampere (kVA) supplied by any two set differ by more than 10 percent of the reactive kVA rating on one set.

For the above requirements, the initial system load shall be equally divided between the sets, both as to activate and reactivate components; thereafter, there shall be no adjustments to governors, voltage regulators, or any other components as system load is changed.

3.7 Frequency regulation. The governing system shall provide isochronous operation of the set; i.e., (including rated load) the frequency regulation shall not exceed 0.25 percent of rated frequency.

3.8 Frequency short-term stability (30 seconds). At every constant load from no load to rated load, the system shall maintain frequency within a bandwidth equal to 0.5 percent of rated frequency. The system shall not permit repetitive frequency variations, commonly called "hunting", even though within the allowable 0.5 percent band.

3.9 Frequency long-term stability (4 hours). At constant ambient temperature, constant barometric pressure, constant voltage, and any constant load from no load to rated load, the system shall maintain frequency within a bandwidth equal to 1 percent of rated frequency in a 4-hour operation period.

3.10 Frequency drift. With the set operating at constant load and voltage, a change in ambient temperature of up to 33 C° (60 F°) in an 8-hour period shall not cause the frequency to change by more than 0.5 percent, set temperature stabilization being accomplished at both the initial and final ambient temperature conditions.

3.11 Frequency transient performance. Following a sudden increase or decrease in load, up to and including rated load, the governing system shall re-establish stable engine operating conditions within 2 seconds. The maximum transient frequency

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T22:12Z
Check the source to verify that this is the current version before use.

change above and below the new steady-state frequency (undershoot) shall be not more than 4 percent of rated frequency.

3.12 Frequency adjustment. By means of the frequency adjust device, it shall be possible to adjust the frequency, (when the set is operating at any constant load) as follows:

- Between 58 and 62 but not above 65 Hz for the 60 Hz operating condition.

- Between 48 and 52 but not below 45 Hz for the 50 Hz operating condition.

It shall not be possible to adjust the frequency for operation within the 48 to 52 Hz range when the frequency selector switch is in the 60 Hz position; and it shall not be possible to adjust for operation in the 58 to 62 Hz range when the frequency selector switch is in the 50 Hz position. Further, it shall not be possible to adjust frequency to a value which will actuate the overspeed protective device.

3.13 Voltage waveform. The deviation factor for the line-to-line and line-to-neutral voltage waveform for each voltage connection shall be not more than 5 percent, nor shall any single voltage harmonic be more than 2 percent. In addition, there shall be no evident discontinuities, spikes, or notches in the waveform when viewed on an oscilloscope having a bandwidth of DC to 1.5 MHz and usable viewing screen of 8 x 10 cm. The oscilloscope gain shall be adjusted such that one cycle of voltage wave covers approximately the entire viewing screen.

3.14 Voltage unbalance. Maximum difference between line-to-line voltages shall be not more than 5 percent of rated voltage for the 240/416-volt connection under the conditions of a single phase, line-to-line unity pf-load of 25 percent rated current and no other load on the generator.

3.15 Phase balance voltage. With the set operating at rated voltage and frequency and no load, maximum difference in the three line-to-neutral voltages shall be not more than 1 percent of the rated line-to-neutral voltage. The maximum difference between the voltage of the 120-volt windings of any phase shall not exceed 1 volt.

3.16 Voltage modulation. The voltage modulation of the output voltage for any load up to and including rated load shall not exceed 1 percent. This requirements shall apply to all line-to-line and line-to-neutral voltages.

3.17 Voltage regulation. The voltage regulation from no load to rated load and from rated load to no load shall be not more than 1 percent of the rated voltage for all voltage connections throughout the voltage ranges specified in 3.22.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T22:12Z
Check the source to verify that this is the current version before use.

3.18 Voltage short-term stability (30 seconds). At every constant load from no load to rated load, the voltage at the set terminals shall remain within a bandwidth equal to 1 percent of rated voltage.

3.19 Voltage long-term stability (4 hours). At constant ambient temperature, constant barometric pressure, constant frequency and any constant load from no load to rated load, the voltage shall remain within a bandwidth of 2 percent of rated voltage in a 4-hour operating period.

3.20 Voltage drift. With the set operating at constant load and frequency, a change in ambient temperature up to 33 C° (60 F°) in an 8-hour period shall not cause the voltage to change by more than 1 percent, set temperature stabilization being accomplished at both the initial and final ambient temperature conditions.

3.21 Voltage transient performance. Performance of the set under transient conditions (as measured by an oscillograph) shall be as follows (reactive droop compensation of the voltage regulator being inoperative):

a. With the set initially operating at no load, rated voltage, and rated frequency, the terminal voltage of the set shall not drop to less than 70 percent of no load voltage when a balanced 3-phase, 0.4 pf (or less) lagging, static load having an impedance of 0.5 per unit, is suddenly applied to the output terminals of the set. When connected to the specified load, the output voltage shall recover to a minimum of 95 percent of rated voltage within 0.7 seconds and shall stabilize at or above this voltage. The above specified voltage dip shall not be exceeded when a fully-loaded induction motor of the above specified impedance is used in place of a static load, and no reactions shall be set up to prevent full acceleration of the motor with rated torque applied to its shaft.

b. When the set is initially operating at rated frequency, rated voltage, and following any sudden change in load from no load to rated load, the instantaneous voltage shall not drop to less than 85 percent of rated voltage and shall reach stable conditions within 0.5 seconds; no overshoot or undershoot of the final voltage shall not exceed the initial voltage transient in amplitude. The above requirements shall also apply when the load is suddenly changed from rated load to no load, except that the initial voltage transient shall not exceed 112 percent of rated voltage.

c. The generator set shall be capable of across-the-line starting a motor rated at 1 horsepower per kW of set kW rating. The starting current rating of the motor shall be NEMA Code F and the motor shall be loaded with a flywheel having an inertia equal to that of the motor rotor.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T22:12Z
Check the source to verify that this is the current version before use.

3.22 Voltage adjustment range. The minimum voltage adjustment range shall be:

Voltage Connection	Range
120/208 V	197 to 229 volts
240/416 V	395 to 458 volts

This voltage adjustment range shall apply for all loads between no load and rated kW, rated power factor at rated frequency under all environmental conditions. It shall not be possible to adjust the voltage of a value which activates the overvoltage protective device.

3.23 Endurance. The set shall operate for 6,000 hours without critical failure at all loads, continuous and intermittent, up to and including rated load under all of the individual or combination of conditions specified in 3.9.1 of the general specification.

3.24 Exciter field current. With the generator temperature stabilized at normal ambient conditions, the exciter field current shall not exceed .91 amperes for rated load at 60 Hz operation.

3.25 Generator efficiency. With the generator in the 120/208 V connection, the rated load efficiency of the generator shall be equal to or greater than 86 percent.

Custodians:
Army – CR4
Navy – MC
Air Force - 99

Preparing activity:
Army – CR4

Project 6115-0730

Review activity:
DLA - GS

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T22:12Z
Check the source to verify that this is the current version before use.