MIL-R-25544(USAF)
AMENDMENT 2
20 June 1957

Superseding
AMENDMENT 1
21 December 1956

MILITARY SPECIFICATION

RECEIVING SET, RADIO AN/ARN-32
BENCH, PREFLIGHT, AND FLIGHT TESTS OF

This amendment forms a part of Military Specification
MIL-R-25544(USAF) dated 11 April 1956

Page 2, paragraph 3.2: Add the following: "Audio Oscillator TS-382( )/U or equal."

Page 2, paragraph 3.3.3: Delete and substitute:

"3.3.3 Receiver Sensitivity and Output Check.- Adjust the signal generator, (AN/USM-44) for 30 percent modulation at 400 cycles per second, with the radio frequency attenuator at minimum. Advance the radio-frequency attenuator; the indicator lamp should light at 1500 microvolts, plus or minus 10 percent. Ground pin No. 1 on the receiver; the indicator lamp should light at 500 microvolts plus or minus 10 percent. With the indicator light operating at either 1500 or 500 microvolts radio frequency input, the power output meter should read 1 milliwatt, plus or minus 10 percent. Modulate the signal generator with audio oscillator TS-382 and repeat these steps with the modulation adjusted for 1300 cycles per second and again at 3000 cycles per second. Failure of the indicator lamp to operate indicates a malfunction of the receiver or the test equipment used. Adjustment of the radio frequency sensitivity controls and the audio output controls in the receiver when the light fails to operate within the specified limits is permissible and shall be done in the following manner.

a. Adjust R8 until the lamp lights at 1500 microvolts rf input.

b. Ground pin No. 1 and adjust R9 until the lamp lights at 500 microvolts rf input.

c. Adjust R27 for 1 microvolt output with the lamp lit.

NOTE: These adjustments shall be made using 400 cycle modulation only; the power output limit does not apply using 1300 or 3000 cycle modulation."

WCINS-3
LV/dm

FSC 5826

GPO 804814

Source: https://assist.dla.mil -- Downloaded: 202610-20T06:39Z
Check the source to verify that this is the current version before use.