MIL-R-16620A(SHIPS)
AMENDMENT - 4
11 July 1957
SUPERSEDING
Amendment - 3
20 August 1956

MILITARY SPECIFICATION

RECEIVING SET, RADIO, AN/URR-35( )

This amendment forms a part of Military Specification MIL-R-16620A(SHIPS), 27 May 1954.

Page 1, paragraph 2.1: Under "Military Specifications" delete reference to "MIL-C-3608" and "MIL-M-17952" and add:

"MIL-T-27 - Transformers and Inductors (Audio, Power, and Pulse)."

Page 2, paragraph 2.1: Under "DRAWINGS" delete reference to "RE49AA399" and add:

"RE10C727 - Protective Cover for Preselector Unit of Radio Receivers AN/URR-27, 13, 13A, 13B, 35A, and 35B."

Page 2, paragraph 2.1: Under "PUBLICATIONS" delete reference to "NAVSHIPS-91906" and "NAVSHIPS-92022" and add:

"NAVSHIPS-92676 - Instruction Book for Radio Receiving Set AN/URR-35C."

Page 3, paragraph 3.2.5.1, lines 1 and 2: Delete "as described in Specification MIL-M-17952" and substitute "except a Winchester electronics type plug and receptacle, or equivalent, shall be used".

Page 3: Add the following paragraph:

"3.2.8 Protective covers. - Protective covers shall be in accordance with Drawing RE10C727."

Page 3, paragraph 3.3, item (g), lines 5 and 6: Delete.

Page 5, paragraphs 3.4.4 and 3.4.9: Delete.

Page 6, paragraph 3.4.18: Delete and substitute:

"3.4.18 Maximum undistorted output. - Maximum undistorted output shall be the output, for increasing a.f. output levels, at which the total harmonic distortion is 7 percent. A constant modulated input shall be used in obtaining the maximum undistorted output."

Page 7, paragraph 3.5, lines 20 and 21: Delete "(1) for broad band output at the frequency of the first i.f. amplifier for connection of a panoramic adaptor;" and substitute "for".

Page 8, paragraph 3.7.1, last sentence: Delete.

Page 8, paragraph 3.7.5: Delete.

Page 10, paragraph 3.7.14, last sentence: Delete.

Page 10, paragraph 3.7.15, third sentence: Delete.

FSC 5820

Source: https://assist.dla.mil -- Downloaded: 2026-10-18T09:15Z
Check the source to verify that this is the current version before use.

Page 10, paragraph 3.7.19, line 3: Delete "500,000" and substitute "50,000".

Pages 12 and 13, paragraph 3.8, items (d) and (l): Delete.

Page 13, paragraphs 3.8.1 and 3.9.1.1: Delete.

Page 16, paragraph 3.9.3.1.2.1, last two sentences: Delete and substitute "Connection to the appropriate terminal shall be effected by soldering and shall be factory connected for 115-volt operation."

Page 20, paragraph 3.9.5.1, item (b): Delete.

Page 20, paragraph 3.9.5.3: Delete.

Page 21, paragraph 3.11: Delete and substitute:

"3.11 Government furnished sample. - Except as specified herein, the AN/URR-35( ) covered by this specification shall be substantially the same as the sample equipment which will be loaned to the contractor by the bureau or agency concerned. All parts and subassemblies shall be electrically and mechanically interchangeable with corresponding parts and subassemblies of the sample equipment. The power transformer T-301, a.f. transformer T-209, and filter L-301 shall be constructed with class B insulation (see Specification MIL-T-27). In the event of any conflicts between the requirements of the preceding sentences and the performance requirements of this specification, the performance requirements of this specification shall govern. The contractor shall immediately notify the bureau or agency concerned, of such conflicts."

Page 21, paragraph 4.2, line 1: After "prototype", insert "(preproduction)".

Page 21, paragraph 4.2, line 23: Delete.

Page 23, paragraph 4.4, item (f): Delete.

Page 25, paragraphs 4.5.3, 4.5.3.1, and 4.5.3.2: Delete.

Page 26, paragraph 4.5.4.2: Delete and substitute:

"4.5.4.2 Method of test. -

(a) Adjust generator output to 100 microvolts unmodulated, and tune generator for maximum input meter reading on the AN/URR-35( ).
(b) Read and record the voltage at test jack specified in 3.9.1.3 (g).
(c) Increase signal generator output to 2 times the value of (a), and tune generator each side of resonance until the same voltage as in (b) is read. Measure and record the generator frequencies as the 6-db bandpass.
(d) Increase signal generator output to 1000 times the value of (a), and tune the generator each side of resonance until the same voltage as in (b) is read. Measure and record the generator frequencies as the 60-db bandpass."

Page 26, paragraph 4.5.5.2, item (d), line 1: Delete "scan channel output" and substitute "test jack in the output circuit of the first mixer".

Page 27, paragraph 4.5.6.2, item (b), line 1: Delete "scan channel" and substitute "test jack in the output circuit of the first mixer".

Page 28, paragraph 4.5.7.2, item (d), line 1: Delete "scan channel" and substitute "test jack in the output circuit of the first mixer".

Page 32, paragraph 4.5.18.1, item (a), line 2: Before "jack", insert "test".

Preparing activity:
Navy - Bureau of Ships



Source: https://assist.dla.mil -- Downloaded: 2026-10-18T09:15Z
Check the source to verify that this is the current version before use.