DATA ITEM DESCRIPTION

Form Approved
OMB No. 0704-0188

2. TITLE	1. IDENTIFICATION NUMBER
Polychlorinated Biphenyl Risk Assessment	DI-SAFT-80495

3. DESCRIPTION/PURPOSE

3.1 This assessment is used for the determination of risks involved with equipment containing polychlorinated biphenyl (PCB). Information from this report will be used to plan the removal of all PCB containing equipment at government installations.

4. APPROVAL DATE (YYMMDD)	5. OFFICE OF PRIMARY RESPONSIBILITY (OPR)	6a. DTIC REQUIRED	6b. GIDEP REQUIRED
871208	F/HQ AFSPACECOM-DEPV		

7. APPLICATION/INTERRELATIONSHIP

7.1 This data item description contains the format and content preparation instructions for the data product generated by the specific and discrete task requirement as delineated in the contract.

7.2 This item is applicable to contracts that provide for the use, handling and storage of electrical equipment containing PCB fluid.

8. APPROVAL LIMITATION	9a. APPLICABLE FORMS	9b. AMSC NUMBER
		F4275

10. PREPARATION INSTRUCTIONS

10.1 Format and content. A PCB Risk Assessment shall contain the data shown in the sample format shown at figure 1. The data entries are self explanatory and upon completion shall provide a numerical rating which can be applied to planning and programming replacement of the equipment. The sample format shown at figure 1 may be locally reproduced.

(Continued on page 2)

11. DISTRIBUTION STATEMENT

DISTRIBUTION STATEMENT A. Approved for public release; distribution is unlimited.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T10:37Z
Check the source to verify that this is the current version before use.

10. Preparation Instructions (continued)

PCB RISK ASSESSMENT

POINTS ASSESSED: _____

Nameplate Information

Name of Installation_____

Location (Facility Bldg. No., Room No.) _____

Manufacturer _____ Electrical Rating (KVA) _____

Fluid Trade Name _____ PCB Fluid Volume (Gal) _____

Serial Number _____ Component Weight (Kg) _____

Points Assessed	Risk Factor	
		I. EQUIPMENT TYPE
_____	0	Non-PCB filled (determined by analysis)
	1	PCB Contaminated Liquid (identified by nameplate or analysis)
	2	PCB Filled (identified by nameplate or analysis)
	3	Contents unknown
		II. LABELING
_____	0	No label required (non-PCB)
	1	Properly labeled
	2	Requires label but not present
		III. QUANTITY
		A. PCB Dielectric Fluid Level of Item, if applicable
_____	1	Fluid level full
	2	3/4 full
	3	Less than half full
		B. PCB Dielectric Fluid Volume in Item:
_____	1	Less than 10 gallons
	2	More than 10 but less than 100 gallons
	15	More than 100 but less than 500 gallons
	20	More than 500 but less than 1,000 gallons

FIGURE 1. Sample PCB Risk Assessment

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T10:37Z
Check the source to verify that this is the current version before use.

10. Preparation Instructions (continued)

Points Assessed	Risk Factor	
		IV. LOCATION
		A. General Location
_____	1	Located in isolated area
	2	Open area occasionally visited or used by people
	3	Outdoors in equipment vault
	4	Outdoors on pad
	5	Outdoors in underground vault
	6	Outdoors on pole
	7	Inside vault of occupied building
	8	In basement of occupied building
	135	Inside upper floor of building, or on roof
	150	Shutdown of the item will significantly degrade unit mission
		B. Result of Loss of Entire PCB Item's Contents by Spill
_____	1	Be contained or confined
	2	Contaminate pad and exterior of item only
	105	Contaminate nearby soil, gravel, or other materials
	120	Contaminate occupied areas
	150	Contaminate water drains, ditches, sewers, etc.
	180	Migration of fluid will cause extensive contamination including contamination of bodies of water located nearby
		C. Susceptability to Damage
_____	1	Not susceptible to damage
	2	Moderate. Unit has some protection (ie., fence or curb) but runaway vehicles could cause damage
	3	Unit is fenced or has light-weight guard posts, but machinery or vehicles are operated close by
	4	Unit is not protected and vehicles or machinery are operated nearby.
	5	Unit is accessible to non-authorized personnel
		D. Vent System, if applicable
_____	1	Vents located outside in area away from windows, air intakes, people, food, water
	2	Vents located outside near window, air intakes, people, food, water (high probability for contamination)
	3	Unit vents to inside of building where people are located
		V. CONDITION
		A. Containment
_____	0	Apparatus not leaking
	1	No active leak. However, old stains on casing or pad are present which indicate previous leaks
	200	New small stains noted mainly around bushings or gaskets
	300	Moderate active leak requiring control by drip pan or similar means
	400	Large leak needing immediate repair
	500	Active spill contaminating the item's pad and surrounding area

FIGURE 1. Sample PCB Risk Assessment - Continued

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T10:37Z
Check the source to verify that this is the current version before use.

10. Preparation Instructions (continued)

B. Transformer Pad or Similar Base Structure

_____	0	Equipment pad has no drain, cracks or open spaces around conduits or ground wire
	1	Pad has drain but no cracks
	2	Pad has drain but cracks and open spaces are present around conduits or ground wire
	3	Metal plates are present on pad where leaking PCBs would be difficult to remove
	4	Item located in porous concrete block or wood building
	5	Item located on wooden floor or pad
	6	Item located in underground vault with a sump-pump which could become contaminated by a PCB spill

C. Physical Surroundings

_____	0	Area around transformer is clean and clear of trash, with no extraneous equipment or materials present
	1	Fire suppression equipment readily available
	2	Tools and machinery nearby which may damage the item
	3	Area surrounding the item contains trash or is used to store tools or equipment which may damage the item
	3	No fire suppression equipment is available

D. Presence of Dikes or Curbs

_____	1	The item and pad or vault has dike or curb sufficient to contain spilled PCB
	2	Dike or curb is deteriorated or damaged
	100	No spill containment (dike or curb); apparatus located over or near water or food-handling areas
	105	Dike or curb insufficient to contain at least 10 percent of material if spill occurs
	125	No spill containment; apparatus located in occupied building

_____ TOTAL POINTS

RISK EVALUATION

Points	Risk Evaluation
300 and above	Extreme Hazard - Transformer requires immediate major corrective action
200 - 299	Potential Hazard - Requires minor repairs
100 - 199	Poor - Requires mainly spill containment, berm, dike, etc.
0 - 99	Good - Requires periodic inspections and normal maintenance

FIGURE 1. Sample PCB Risk Assessment - Continued

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T10:37Z
Check the source to verify that this is the current version before use.