MILITARY SPECIFICATION

MODULES, STANDARD ELECTRONIC

SHIFT REGISTER, DIGITAL, KEY CODE SJS

This amendment forms a part of MIL-M-28787/273A(EC), dated 23 August 1983, and is approved for use within the Space and Naval Warfare Systems Command, Department of the Navy, and is available for use by all Departments and Agencies of the Department of Defense.

PAGE 2

3.3, second line: Delete "0.164" and substitute "0.167".

3.3, third line: Delete "0.164" and substitute "0.399".

PAGE 4

TABLE I, test conditions G1-G32, class II, 85°C ±5°C, Max column: Delete "800" and substitute "400".

PAGE 5

TABLE I, test conditions Q1-Q32, class II, -55°C ±5°C, Max column: Delete "37" and substitute "42".

TABLE I, test conditions Q33-Q64, class II, -55°C ±5°C, Max column: Delete "47" and substitute "52".

PAGE 7

4.4.2, delete and substitute the following:

"4.4.2 Order of testing. Test conditions A through W shall be performed in any order with the following exceptions. Test conditions A, B, C, D, and F are stress tests and will be performed only at 25°C ±5°C. If test conditions A, B, C, D, or F are part of a sequence of tests, the order of testing shall be as follows: A, B, C, D, F where applicable, followed by the remaining tests in the sequence."

4.5.1, line five: Delete "D through W" and substitute "E and G through W".

4.5.3, line three: Delete "D through W" and substitute "E and G through W".

4.5.3, line six: Delete "D through X" and substitute "E and G through X".

DISTRIBUTION STATEMENT A. Approved for public release; distribution is unlimited.

Source: https://assist.dla.mil -- Downloaded: 2026-10-20T17:18Z
Check the source to verify that this is the current version before use.

PAGE 8

TABLE II, delete and substitute the following:

"TABLE II. Input to output relationship. 1/-6/

Inputs			Outputs		
Clear	Clock	Input	Q_A	Q_B	Q_P
L	X	X	L	L	L
H	L	X	Q_{A0}	Q_{B0}	Q_{P0}
H	↑	H	H	Q_{AN}	Q_{ON}
H	↑	L	L	Q_{AN}	Q_{ON}

1/ H = High level (steady state).
2/ L = Low level (steady state).
3/ X = Irrelevant (any input, including transitions).
4/ ↑ = Transition from low-to-high input.
5/ Q_{A0}, Q_{B0}, Q_{P0} = The level of Q_A, Q_B, or Q_P respectively, before the indicated steady state input conditions were established.
6/ Q_{AN}, Q_{ON} = The level of Q_A or Q_O before the most recent transition of the clock, indicates a one bit shift."

Agent:
DLA - ES

Preparing activity:
Navy - EC

(Project 5963-N689)

Source: https://assist.dla.mil -- Downloaded: 2026-10-20T17:18Z
Check the source to verify that this is the current version before use.